JAN. 20¢

# POPULAR SCIENCE



THE FORTRESS OF EUROPE? PG

# Here's Your BIG Opportunity in Industry—Now and After the War!



Learn Chemistry—in spare time at home through this Amazing, New, Low Cost SELF-STUDY COURSE:

# CHEMISTRY NADE EASY!

By CORNELIA T. SNELL, Ph.D., Consulting Chemist and FOSTER D. SNELL, Ph.D., Consulting Chemical Engineer

ERE is a brand-new way to study chemistry, designed especially for the man who must learn by himself, without teacher or laboratory. These entire 118 lesson chapters were prepared by authors possessing the most varied teaching and practical experience in plant and laboratory, in research and engineering. In each lesson they give you simple, straight from the shoulder instruction in plain English on a single chemical subject, with all necessary formulas, specially prepared diagrams, and then questions, to fix in your mind the knowledge you have gained. You get everything you need to master practical, Industrial chemistry by yourself-a complete course planned and organized so you can profit to the utmost from every minute of your spare time! And at the end of each volume you are given a complete final examination, with answers and a grading system, so that you can correct your own paper and check your progress.

#### Just a Hint of the Course's Fascinating Contents

Chemistry-the Study Symbols, Formulas Acids and Alkalies Nilrogen Compounds Why Gold Has to He Alloyed Radioactive Elements Colleids Sulphur Compounds Carbohydrates Sodium and Potassium Ammonium and Liblum Phenois and Their Compounds of Aluminum, Chromium and from Arsenic, Antimony and Tim Copper, Cadmium and Bismuth Lead, Silver, Gold and Mercury Petroleum Hydrocarbons Alcohola

A dehodes and Kelones Esters, Waxes and Ethers Organic Dyes Reduced Colors Natural Plant Products Alkaloids Natural Gums, Resins.

Simple experiments illustrate important industrial processes in chemistry,

Synthetic Reitns And Hundreds of other Subjects-All Explained in Simplest Terms by Practical Experts

and Ballama


See Free Examination Coupon on Facing Page

# TRAIN YOURSELF IN CHEMISTRY

Great new industries are arising from the war-time applications of Chemistry—synthetic rubbers, aluminum and steel alloys, the many-purpose plastics, magic new drugs, amazing new fibers, fabrics, methods—all vital to war, and destined to create thousands of after-war jobs for chemically-trained men and women! And now, at last, here is an EASY, LOW-PRICED, SELF-INSTRUCTION COURSE which will enable you to get a complete grasp of Chemistry now—and make some of these splendid opportunities yours!

## No Previous Training in Science Needed! Four Inexpensive Books Teach You From A to Z1

These books start from the most elementary facts and principles and build up your knowledge of modern, up-to-date chemistry on a sure foundation. The authors take no knowledge for granted on your part, and unfold to you a complete understanding of chemical science as it is used today in research and manufacturing. From the first page to the last the knowledge and training you get can be used as preparation for a job in any branch of the great and growing chemical industries.



how metals are produced from their ores, the uses of the pure metals and their alloys, their combinations with the non-metals. You will find not only chapters on tin, lead, nickel, chromium, iron, steel, etc., but also on chlorine, sulphur, phosphorus, exrbon, silicon, etc. This book covers the chemistry of alloys, pigments, insecticides, construction materials, sulphuric and other acids, and all the host of inorganic materials that are essential in industry.

complete picture of the chemical substances and compounds originating in living organisms. It covers the entire production of petroleum, natural and synthetic rubbers, resins, dyes, drugs, foods, sugars, starches, fats, waxes, alcohol, proteins and vitamins. This volume makes it easy for you to acquire by self-study a clearly-understood grasp of organic chemistry.

SOOK IV. Tells You All About the Chemicals of Commerce. You get full, practical reference data on many thousands of chemical materials—all carefully chosen for their commercial importance. You get the most important facts on each—composition, properties, uses, relative costs, etc. And to help you find, instantly, all the facts and figures in this great book, there is a remarkable SI-page index. Here is your indispensable source book of facts about commercial chemicals.

#### Examine the Complete Course FREE!

#### Send No Money-Just Mail the Coupon

Prove the value of these books for yourself in your own home—without spending a penny. Make certain that you can learn chemistry by yourself. See how skillfully these authors have simplified every topic for the man who must study without a teacher—see how readily you can use these questions and problems (with answers) to check your progress and to gain confidence. Send for these books on approval for 10 days' free examination. At the end of that time you are entirely free to return them to us for full credit unless you have proved to your utmost satisfaction that you can learn chemistry from their pages. If you keep them you need pay only \$1.95 within 10 days and \$2.00 a month for three months thereafter. Mail the coupon at once, as this offer may have to be withdrawn at any time.

D. VAN NOSTRAND COMPANY, INC. 250 FOURTH AVENUE NEW YORK 3, H. Y.

#### FREE EXAMINATION COUPON

D. Van Nostrand Company.

250 Fourth Ave., New York 3, N. Y.

Send me CHEMISTRY MADE EASY in 4 volumes. Within 10 days I will other return the books or send you \$1.95 as ford payment and \$2.00 per month for three months with the total price of \$2.95, plus a few cents postage, is paid. If you send \$7.90 payment in full with this order we will puy postage. Same return privilege.

Zone No. (if you know it) State

WANGE OF STREET AND THE STREET

Address
Popular Science 1-44

## POPULAR SCIENCE

FOUNDED 1872

MONTHLY

VOL. 144 NO. 1

#### Mechanics & Handicraft

A TECHNICAL JOURNAL OF SCIENCE AND INDUSTRY

## CONTENTS for JANUARY, 1944

Cover: Kodachrome by Hans Groenhoff

## News

41
49
55
62
64
68
76
84
89
90
92
97
103
107
108

## Automobiles

Keeping Car Upholstery Clean	118
Wood as a Wartime Motor Fuel?	120
Gus Clears Up a Case of Sabotage	122

## Home and Workshop

Candlesticks Turned from Pistons	127
Useful Cabinet Has Reeded Doors	134
Lenses Lend a Hand in the Shop	146
Steam Engine Without Castings	148
Transformer for Heavy Soldering	153
How Amplifier Circuits Work	158
Planning Your Photographs	162
Plowing Under Your Plow Troubles	170
Phosphorus-Element of Mystery	176

#### OUR NEW PRICE

BEGINNING with the February issue, your copy of POPULAR SCIENCE (if you buy it on the newsstand) will cost you 25 cents. This new price is made necessary by greatly increased costs of printing and paper. At the same time, bowever, we are giving our readers greater value than ever before through the extensive use of color. Starting with the present issue, POPULAR SCIENCE will contain many pages of color photographs and paintings, in a high quality of reproduction that makes them just perfect for pin-ups and for framing. See this new feature on bages \*3-96.


FOITORIAL ASSOCIATES: Fred O. Newman, news editor; Alden P. Armagnos, B. T. Richards, Marry Samuels, Michele de Santis, Dan Romero, Jack O'Écine, Jean Ackermann, Frank Rawsame, Jr., Carl W. Bertsch, Edward M. Callins, Ruth Westphal.

ART ASSOCIATES: Stewart Rouse, William Patrick, Samuel Dukler, Evelyn Cooper.

PHOTOGRAPHY, W. W. Morris, Robert F. Smith.

Published monthly at 10.3 Fourth Avenue, New York 10 N. Y. by Popular Science Publishing Co., Inc. Coeffrey Hammond, President and Treasurer; K. C. Wilson, Raymond J. Brown, Charles McLendon, risphen P. Gennem. Vice-Presidents; F. W. Sriggs, Secretary, fintered as accond-class matter Dec. 28, 19 18 of the Past Office at New York tabler the act of March 3. 1979; additional entry as second-rioss wester at feating, thin, Entered as second-class-Printed in U.S.A. Copyright, 1942, by Popular Science Publishing Co., Inc. All rights reserved to the I total states, Great Britain, and in all counthe participating in the International Copyright tententies and the Pan American Copyright Consention. Yearly subscriptions to United States and its passessions #2.480; Canada, \$2.500; foreign manufes, excepting Canada, \$5,00. Kulturrilla-re must mostly us of change of address four weeks in in some of the next publication date. He sure to give both old and mee addepse.

20



"He writes that he's signed up with I.C.S. Says he's going into training, too-that a trained man in industry is worth ten untrained, the same as in the service.

"First of all, he says, he wants to be a better fighter on the war production front. But helping win the war isn't all. He wants to help me win after the war, too.

"When we come back, he says, we're going to need seasoned leadership in industry and he aims to be one of those trained and ready. That's my Dad, all over!"

· You are beyond combat age? Qualifying as a trained man is the greatest contribution you can make to Victory and a Greater America. Mail the coupon for full information on L. C. S. Courses right now! Help your country while helping yourself and family.

## INTERNATIONAL CORRESPONDENCE SCHOOLS

BOX 7668-K, SCRANTON F, PENNA.

Without cost or obligation, please send me booklet and full particulars about the course before which I have marked X:

- Air Brake

  Air Conditioning

  Airplane Draftine Airplane Drafting Architectural Drafting Architecture Auto Engine Tone-up Aviation Aviation Mechanic Blumprint Reading Bollermaking
- Concrete Engineering Accounting Advectising Bookkeeping Business Management Cartocolog Civil Service

Advanced Dressmaking
Frods and Cookery

numbe rollinesavi

Civil Engineering

Chemistry Coal Mining

TECHNICAL AND
Contracting and Hubbing
Cotton Manufacturing
Dissel Engine
Electrical Drafting
Flucturian
Historical Maintenance
Flucturian
Historical Maintenance
Historical Hubbing
Highway Engineering
House Planning Management of Inventions
Marine Engines Mechanical Drafting Mechanical Engineering Mine Foreman
Mavigation | Patternmaking
Plastics | Pluming
Public Works Engineering Pulp and Paper Making Radio, General District Metallorer
Disconnective Engineer
Machinet Dissperior se l'innair, Radio Upersting BUSINESS COURSES

TECHNICAL AND INDUSTRIAL COURSES

- C First Year Collago

  Novemanship D Fress

  Good English

  High School

  Managing Mea at Work College Preparatory D French Commercial Commercial Illustrating C. P. Accounting HOME ECONOMICS COURSES

  District Designing of Designing
- Sanitary Engineering

  Bheet Metal Work

  Ship Drafting

  Shipfitting | Shop Practice Shipfitting [] Shop Practice Steam Electric [] Steam Engines Steam Fitting Structural Drafting Structural Engineering Surveying and Mapping Telegraphy | Telephony L'estile L'enlantine ☐ Radio Servicing ☐ Toolmaking ☐ Tool Dani ☐ R. R. Section Poyeman ☐ Welding, Gas and Electric ☐ R. R. Signalman ☐ Refrigeration ☐ Woolen Manufacturing Toulmaking | Tool Davies

SPECIAL

**TUITION RATES** FOR MEMBERS OF THE ARMED FORCES

- Salesmanship Railway Postal Clurk C Spanish Showcard and Sign Lettering
- Tes Room and Cafeteria Management, Catering

Slate Present Partition Canadian residents send coupon to International Correspondence Schools Canadian, Limited, Montreal, Canada British residents send coopen to L. C. S., 71 Kingsway, London, W. C. 2, England

Copyrighted misselful .



## Will You Be Ready to Enjoy THE COMING AIR AGE?

PREPARE now for the day when you'll fly your own Piper Cub. Take aviation subjects at night school, study aeronautics at home. Then, when peacetime comes, see your Piper Dealer and learn to fly. He can solo you with as little as 8 hours of dual instruction in a Piper Cub.

# Send Today for Your "HOW TO FLY" Booklet!

Prepared by certificated flight instructor. Clearly explains basic flight principles. Send 10c for booklet and Piper catalog to cover postage-handling. Piper Aircraft Corporation, Department PS 14, Lock Haven, Pennsylvania.

16mm. SOUND Film. The Construction of a Light Airplane." For distribution points, write: Supervisor, Audio-Visual Aids, Extension Services, Pennsylvania State College, State College, Pennsylvania.



### Coming Next Month

WHAT ABOUT GLIDERS? As a war weapon, are they just a substitute for planes, or can they do things that powered aircraft can't? How does the military glider differ from the peace-time sailplane in construction and handling? Alden P. Armagnac answers all the questions you have been asking yourself about this brandnew tool of warfare.

BURMA isn't all temple bells and romantic native maidens, according to American flyers who have been forced down among its dense jungles and inhospitable inhabitants. An interview with Col. Robert L. Scott, Jr., gives the low-down on the Road to Mandalay as it looks from a cockpit and an escape 'chute. Required reading for future members of Asiatic expeditionary forces.

A VOLTMETER is the only instrument you need for giving your car's electrical system a thorough check-up. Troubles that crop up in battery, ignition, or lights can be diagnosed easily with simple tests described by Ralph Rogers in an article that should find a place in your file of automotive reference material,

SOFTIES! That's what our young men are when they go up for induction, the officers in charge of the Army's physical-training program say. Turning these victims of easy living into tough fighters is the work of a streamlined conditioning course that crams months into weeks in preparing our soldiers for the rough-and-tumble business of modern war.

NO POSTWAR UNEMPLOYMENT looms ahead of the jeep, to judge by the flood of entries in our recent contest. We asked for suggestions on peacetime work for the bouncing buggies—and we got them! Next month we'll announce the names of the winners, with a word-and-picture digest of the ideas submitted.

CALLING THE PLUMBER for every little trouble can be an expensive proposition—and unpatriotic, too, in these days of scarce man-power. With a little knowledge, you can not only make the minor repairs yourself, but also forestall trouble in many cases by preventive measures. John Modroch tells you how to keep your pipes and drains working right.

Carrol Ind Indexil

# THE SEARCH THAT NEVER ENDS



In the industrial life of America, research has been of constantly increasing importance. And today it is a national resource, for the research of industrial and college laboratories is proving its value in War.

To the Bell System, research is an old idea, for the telephone itself was born in a laboratory. Behind its invention, sixty-nine years ago, were researches in electricity and acoustics and in speech and hearing.

And, ever since, there has been a laboratory where scientists have searched to know more about these subjects; and with their associated engineers have applied the new knowledge, fitting it with all the old, to make the telephone better and better.

Their fields of inquiry have broadened and deepened through these years; they inquire into all the sciences and engineering arts which have any promise of improving the telephone. Much has been learned but still more will be, because their search goes on. That is why the telephone laboratory grew to be Bell Telephone Laboratories, Incorporated, the largest industrial laboratory in the world. And it exists to improve telephone service.

Improvements in industry can be left to chance in the hope that some one, sometime, will think of something useful; that some good invention will turn up.

The other way to make improvements is to organize so that new knowledge shall always be coming from researches in the fundamental sciences and engineering arts on which the business is based. From that steady stream will arise inventions, new methods, and improved products.

This is the way of Bell Laboratories. Its search will never end. And as fast as it can the Laboratories will apply its new knowledge practically to the design of equipment and communication systems.

At present—and this started before Pearl Harbor—its trained scientists and engineers and all their skilled associates are concentrating on products of importance to our armed forces. But when this work is happily over they will be ready to continue their developments for the needs of peace.



#### BELL TELEPHONE SYSTEM

"Research is an effort of the mind to comprehend relationships no one has previously known; and it is practical as well as theoretical." . . . BELL TELEPHONE LABORATORIES

# This Christmas! GIVE THRILLING CASTLE HOME MOVIES!



# "NEWS PARADE OF THE YEAR" (1943)

Own this home movie digest of the entire year! Key moments of the entire year's history! The on-the-spot record of war on land, sea, and in the air! Mighty battles! Historic meetings! Victories for the Allies! A movie any projector owner will treasure! Own it! All this in one film:

- \* Franch Souttle Own Fleat!
- \* Normandia Raised! (U. S. S. Lafayetta) \* Battling the U-Beats!
- \* Allies lovade!
  - Africa ... Sicily . . . Italy!
- \* Russia's Night Actounds World!

\* Bambs Blast Germany !

- \* MacArthur's Swashing Offensives?
- Subject to change and addition of last minute releases



#### "CHRISTMAS CARTOON"

Delightful antics to make Christmas long remembered! Santa visits caninetown! Toy soldiers parade! Mice steal toy train! High jinks by kittens that bring tears of merriment and joy. Own and give this home movie!

FREE!

New DeLuxe Castle Films' Catalog describing 98 thrilling films you can give or own! Use it as your shopping guide. Send coupon now!

- ORDER FORM



# CASTLE

RCA MLDR., NEW YORK 20 FIELD DLDR., CHICAGO 3 RUSS DLDD., SAN FRANCISCO 4

Send Castle Films"	8 mm.		16 mm.		n.
Home Movies In- dicated in the size and length checked.	58 PL \$175	180 ft. 5550	100 ft. 5275	360 ft. 5 <u>8</u> 75	Sound 356 ft. \$1750
"Hous Parada of the Yeer" (1943)					
"'Christmas Cartson"					

		_
28 S. S. S. S.		
NAME		

ADDRESS

STATE

CITY

- INIE

Send Castle Films' FREE DeLuxe Catalog

amittages enclosed 🔲 Ship C. G. D. 🗍

# 

IN SERVICE ON EVERY FRONT



"We 'uns promised the blood bank a quart . . . reckon Paw has any?"

## GASOLINE DONORS CAN HELP, TOO!

Become a gasoline donor by giving your spark plugs a "Plug-Chek." Tests conducted by The American Automobile Association show Auto-Lite "Plug-Chek" Inspection Service can increase gas mileage as much as 12%!

As simple an operation as cleaning and regapping your present plugs may do the trick. A proved inspection service, "Plug-Chek" is exclusive with Auto-Lite Spark Plug Dealers.

Stop for a "Plug-Chek" today — and if new plugs should be installed, insist on Ignitian Engineered Auto-Lites!

THE ELECTRIC AUTO-LITE COMPANY TOLEDO, OHIO . Merchandising Division . SARNIA, ONT.



Color and condition tell if plugs are operating properly. Matching your plugs with those illustrated on the "Plug-Chak" is the first step in getting new life for "spark-weary" engines.





### Dear Bill:

### I'm the guy up front

This is the outfit for an old oyole fan! I thought I knew motorcycles, but the Army's teaching me plenty!

I'm riding an Indian -- as
usual. What a machine? Our operations course is plenty tough
but Indian's got the guts to
take it -- and for easy handling and safety, give me Indian
any day?

Incidentally, Indian's got some swell new improvements. It'll be a really great machine to ride when this war's over. Regards to the gang:

INDIAN MOTOCYCLE COMPANY, SPRINGFIELD, MASS.



BUY WAR BONDS NOW

\* \* TO BUY AN INDIAN LATER \* \*

# INTERNATIONAL CORRESPONDENCE SCHOOLS

Blueprint Reading Foundryman Heat Treatment of Mutals Muchinist Mechanical Drafting Mechanical Engineering Patternmeking Shop Practice Toolmaking Walding, Gus & Electric

#### OTHER TECHNICAL COURSES

#### Air Conditioning

Schools

Air Conditioning Heating Plumbing Refrigeration Steam Fitting

#### bemlitty Betschi

Chemistry, Analytical Chemistry, Mfg. Live and Staol Pharmacy Pulp and Paper Making

#### Civil, Architectural and Structural Engineering Schools

Architecture Architectural Drafting Bridge and

Building Foreman Bridge Engineering Building Fatimating Civil Engineering Concrete Engineering Concrete Engineering

Hudding
Highway Engineering
Ratad Lumberman
Structural Drafting
Structural
Engineering
Eurocying and

Manniag

#### Electrical Schools

Electrical Engineering
Electric Wirting
Gas and Electric
Welding
Industrial Electrician
Lighting Technician
Power House

Lighting Technician Power House Practical Telephony Ratio, General Ratio Operating Ratio Servicing Telegraph Engineering

### Engines Schools

Air Pilot
Automobile
Technician
Ariation
Diesel - Electric
Diesel Engines
Gas Engines

#### Mechanical Schools

Airplane Drafting
Foundry Work
Heat Treatment
of Metals
Inventing and
Patenting
Machine Shop
Practice
Mechanical
Engineering
Metal Pattern

Drafting

Mohl-loft Work
Reading Shop
Blueprints
Sheet Metal Worker
Ship Drafting
Ship Fitting
Ship Frietter
Steel Mill Workers
Tool Designing
Wood Pattern

#### Mailroad Courses

Mahitut

Foreman

Air Brake Car Inspector Locomotive Engineer Locomotive Freman Railroad Car Repairer Railroad Section

#### Bleam Engineering Schools

Boller Making Combustion Engineering Engine Running Marine Enginee Percelasion Retaining Plant Steam Plactric Steam Plactric Steam Plactric

#### Textile Cohools

Corton Manufacturing Testile Designing Woolen Manufacturing

#### BUSINESS AND ACADEMIC COURSES

#### Academic Schools

Arithmetic College Preparatory First Year College High School Higher Mathematics Bustrating

#### Business Schools

Accounting Advertising Bookkeeping
Business
Correspondence
Business
Management
Certified Public
Accounting
Commercial
Cost Accounting
Foremaskip
Salestantial
Stanography

Tax Accountant Traffic Managerouse

#### Civit Bervies Schools

City Letter Carrier Past Office Clerk Radway Postal Clerk

#### Language Schools

French Good English Spanish

INTERNATIONAL	CORRESPOND	ENCE	SCHOOLS
BOX 7447-K	SCRANTON	9, PEI	NNA.

Flease send me complete information on the following subject:

(Wette ab	ore Tech	nieut.	But	darw	00	General .	I dung-
finnel	Bub/cet	(W.R.	hick	THE REAL	arc	interested	1

Nome	
Home !ddress	

CHP	81#1e
de la	

Sandal Tuiffen Bates for Munices of the Armed Force

\_\_\_\_\_

Copyrighted relation

When the new man moves around you-



You remember the day Vince Benedict started in Factory Office. You remember his early weeks when you "broke him in." Today he's clearing off the old desk and moving into a job ahead of yours. You've been ten years longer with the company and you can't understand it.

Do some realistic checking up and you'll find that Benedict has been training himself for the demands and responsibilities of larger positions. It isn't too

late for you to do the same by taking an L. C. S. Shop Practice Course.

Thousands of successful Americans have acquired their all-important Shop Practice training from the world-famous International Correspondence Schools. The man who has moved around you quite possibly sent in this coupon once. And it wouldn't be surprising if the man who employs you both is a former I. C. S. student. Many employers are.

INTERNATIONAL CORRESPONDENCE SCHOOLS, BOX 7447-K, SCRANTON 9, PENNA.

MAIL THIS COUPON! It brings you full information on

I.C.S. advantages. It can be the turning point of your career!



#### Vital Jobs Like These Go To Men I Trained



# **Full Time Radio Jobs**

Here syour change to get a good job in a body worth of the two to a long by peacet included. There is a change it should be a like to Tree to another the Source to the temporal for a FRFE copy of my 64 peacet is Source to the Win Rich Rewards in Radio. It does not be made for a suppose of Rewards in Radio. It does not be made to a special for a suppose of Rewards to be with a least one to be bounded to the wind the contract of the suppose of Rewards to the wind post peacet and the response to the suppose of the KITS OF RADIO PARTS I soud'

#### There is a Shortage of Radio Technicians, Many Good Jobs are Open!

There's a lig shortage today of capable Radio Technicings and operate as F xere I at on pays better now than ever later. With new h. he wout of production, fixing add sets which were I have a traded in, adds greatly to to a stand number of servicing a ba-

Broadcasting Stations. As at on and Police Rudto and To be cans Rad manufact to the n w working on Govern nonterdes for half) carpoint employ trained of in The Covernment to no is buildeds of competent of an and worsen. You may not I see a first again was not will be so easy to get started in this fascinating field.

#### Be Ready to Cash in on Jobs Coming in Television, Electronics

Think of the NFW jobs that Television Frequency Modula the French ica and other Rada developments will open if the war for have a real opportunity. I will transit be really to cash in which Victors to cases the maximum article Radio developments for peacetime uses.

### You Build These and Other Radio Circuits with 6 Big Kits I Send!



SUPERHETERODYNE CIR-CUIT 'above' Preseles for, escalla or - maker-first detector, 1.1. stage, diode de tector-a.v.a. stage a dio stage. Bring in local and distant stations on his tircall you build yoursell'

MEASURING INSTRU-MENT bears you bad ears in Come U.e. in practical Rado work to make EXTRA money near tes AC DC and resistance recei er output



SIGNAL GEN-ERAIOR (3 ho e) B. dat aree' Proa deaper on il propies Gives variable practice.

By the time you've conducted 60 sets of Experiments with Radio Parts I supply, have made hundreds of measurements and adjustments, you'll have valuable PRACTICAL Radio experience for a good full or part time Radio job!

IND OUT ABO

# Technician

Than Ever Before

#### Many Beginners Soon Make \$5, \$10 a Week EXTRA in Spare Time

Right now, probably in your neighborh od, there's room for to the space and full time and Tabnicians. Many NRL St. lents make \$5. \$10 a was EXTLA to by fixing Radios in at the tree while searched I seek EXTLA MONEY JOS SHEETS that tell how to do it!

My 50 50 Method"—half belong and testing real Radio Circults, half learning from easy-to prime a rated assessed in a west to harm I at home a space take. This have much proceed apprenting to be by but it gother flapers to any Memoria learning to the flapers to any Memoria it and the second of the first of the second of the prime I start with a few mother you can be real at the parts I start. Within a few mother you can be real to the real and the parts I start. Within a few mother you can be real to the parts I start. Within a few mother you can be real to the parts I start with the Radio at your Invents and a sphere a prime flow.



#### Extra Pay in Army, Navy, Too

Men likely to go into military service soldiers salites marries sono diqua the Cuspon Son Learning Rango heaps Service men get exita

rank, extra presinge thate a eresting dates much higher par A no prepares for good Radio ,obs at er service ends. Over 1,00 Service of an now enrolled.

#### Find Out What N. R. I. Can Do For YOU

MAIL THE COUPON BELOW for my FREE 84-page book. It a maked with Ruder facts things you never knew about type than been in Bro-tenating, Radio Servicing, Government R Lo, and other Radio fields.

You'll read a description of my Course—"50-50 Method"—5
Pyperimental Kits—Extra Money Job Sheets, Tou'll see the
I sciout a this Radio offers and how YOU can train at
he ce. Not have no salesman will call, if you want to
J'MP YOUR PAY—Mail Coupon at once in an envelope or
pasted on penny postcard! J. E. SMITH, President, Dept.
4AP3, National Madio Institute, Washington S. D. C.



YOU meintenance men and in other capacities and pay well.



Bet Bervicing pays many NRI trained Rule of her a new Island a week Of sea had beek to see to a week fixed Radios in spare state

TRAINING MEN FOR VITAL RADIO JOBS

## Mail this to get 64 page book FREE

J. E. SMITH, President, Dept. 4AP2, National Redio Institute, Washington S, D. C.

Dear Mr. Smith: Mail me FREE, without obligation, your 64-page book, "Win Rich Rewards in Radio," which points out Radio's opportunities and tells how you train men at home to be Radio Technicians. (No salesman will call, Please write of print plainly.)

Age. ..

Name

Address

Clt

State

TO BETTER PAY



WITH EVERY COPY COMMANDO JIU-JITSU OF NEW COURSE ON COMMANDO JIU-JITSU

Latest, Newest — Clearly Explained in WORDS and PHOTOS by a Famous U.S. Marine Corps Instructor

EFENSE MANUAL OF . COMMANDO? MORE EMAN 150 HOLDS. THROWS, AND BLOWS ILLMETRATED WITH CLEAR MEW PHOTOS A DRAWINGS BY A FAMOUS W. S. e matricip

threatened by someone twice your aim and weight "surprise" Commando hold will enable you to use the bully's own strength to throw him vin-lently to his back Commando Jiu Jitau teaches how a little man can even knock a bully unconscious by a single blow with the edge of his band.

ONT fear bullleal When

This is the authentic course in Commando Jiu-Jilau with every old and new hold, blow and throw illustrated in more than

photographs. It takes the mystery out of Jin Jitau and makes it easy for anyone to learn quickly

you see pictured the form of attack with fist, knife, club or pistol. Second, the defense is likestrated with the surprise Disarm hold that makes the bully drop his weapon or suffer a broken arm or leg Third, the Throw that enables you to use the bully's own strength against him and stand on your feet unruilled while he struggles for breath 7.0

bunged head. FIRST TIME EVER PUBLISHED

New Choking Slick Technique learned from Savage Malay Jungle Pighters. Exact instructions fully illustrated for using the victous and deadly Malay Choking Stick. Defenses, holds, throws, and disabitus blows pever before put in published form, A

move with the Malay Choking Sick makes you master of any situation, Especially valuable for service men Plant Guards. Police, and Detective Officers.

#### MALAY AMERICA CHICKUTE STICK FREE to those who hurry

We have a limited supply of practice Choking Sticks-same type as used in Malay Jungle, and exactly the same as used for photographs in this Commando Course in Jits Jitsu. A practical, useful weapon that makes a one man "bitts in the hands of those who learn its use. NOTE Must not be placed in the hands of children or arresponsible persons. This is not a plaything, but a deadly weapon,

ON'T wait until the supply of Choking Blicks is gone, Send now Fill in the coupon, hend cash, money order, or check, and we will prepay postage. Or if you prefer put an X in the COD square and we will ship Commando Book AND Choking Stick, for \$1.95 plus COD charges and postage, Prepare now and be the "man of the hour" when the time comes.

FEW HOURS spent now A practicing Commando Jiu-Jitsu may save your life or your property when you are attacked—or may save you or your loved ones from

severe injury. The real heroes are not the men of brawn, but the ones who have the "know how"--men who can use their heads in a cool sure, swift, and knowing way when an emergency calls for someone to step forward and take the attuation in hand.

Etiak From of

WILCOX & FOLLETT CO., Dept. 31 1255 S. Wabash Ave., Chicago 5,

WILL	COX	A FOLI	4511	CO., Dep	4. 31	
1751	F 8.	Wales W	Aven	Chicago	(8),	AM.

Send the ABSOLUTELY FREE of FATRA CHARGE, one Jungle Choking 5t ch for practice with a copy of the New Reference Manual of Commando Jo Jivsu including more than 130 photographs and drawings of men and without and including the never before published blown to its and hours one made possible by use of the Jungle Choking 50ck. Total cost #1 08

I enclose remittance for 81 till You will propay produce.

Send above COD for \$1.98 to as COD fees and charges I will pay postmen

ADDRESS

STATE Orders from Canada must cartade full remittance in I' & Exchange.

YOU MURRY

The 97 Pound Weakling

-Who became "The World's Most Perfectly Developed Man"

# "I'll prove that YOU, too, can be a NEW MAN!"

Charles Cittas

KNOW, myself, what it means to have the kind of body that people pity! Of course, you wouldn't know it to look at me now, but I was once a skinny weaking who weighed only 97 lbs.! I was ashamed to strip for sports or undress for a swim. I was such a poor specimen of physical development that I was constantly self-conscious and embarrassed. And I felt only HALP-ALIVE

Then I discovered "Dynamic Tension." It gave me a body that won for me the title "World's Most Perfectly Developed Man."

When I say I can make you over into a man of grant power and energy, I know what I'm talking about. I've seen my new system, "Dynamic Tension," transform hundreds of weak, puny men into Atlas Champions.

## Only 15 Minutes a Day

Do you want big, broad shoulders—a fine, powerful chest—biceps like steel—arms and legs rippling with muscular strength—a stomach ridged with bands of sinewy muscle—and a build you can be proud of? Then just give me the opportunity to prove that "Dynamic Tension" is what you need.

No "ifs," "ands," or "maybes." Just tell me where you want handsome, powerful muscles. Are you fat and flabby? Or skinny and gawky? Are you short-winded, pepless? Do you hold back and let others walk off with the prettiest girls, best jobs, etc.? Then write for details about "Dynamic Tension" and learn how I can make you a healthy, confident, powerful HE MAN.

"Dynamic Tension" is an entirely NATURAL method. Only 15 minutes of your spare time daily is enough to show amazing results—and it's actually fun! "Dynamic Tension" does the work.

#### Send for FREE BOOK

Mail the coupon right now for full details and I'll send you my illustrated book, "Everlasting Health and Strength." Tells all about my "Dynamic Tension" method. Shows actual photos of men I've made into Atlas Champions. It's a valuable book! And it's FREE. Send for your copy today. Mail the coupon to me personally. CHARLES ATLAS,



# CHARLES ATLAS Dept. 1A. 115 End Tild Theet New York, 10, N. Y.

I want the proof that your system of a "Dynamic Tension" will help make a New I Man of me—give me a healthy husky body and big muscular development. Send me your I free book. Everlasting Health and Strength."

Name (Please print or write plainly)

Address. .....

City... State. State. Check here if under 16 for Booklet A

New York 10. N. Y.

Dept. 1A, 115 East 23rd St.,



### You Can Influence Others With Your Thinking

TRY IT SOME TIME. Concentrate intently upon another person seated in a room with you, without his noticing it. Observe him gradually become restless and finally turn and look in your direction. Simple—yet it is a positive demonstration that thought generates a mental energy which can be projected from your mind to the consciousness of another. Do you realize how much of your success and happiness in life depend upon your influencing others? Is it not important to you to have others understand your point of view -- to be receptive to your proposals?

How many times have you wished there were some way you could impress another favorably - get across to him or her your ideas? That thoughts can be transmitted, received, and understood by others is now scientifically demonstrable.

#### This FREE Book Points the Way

The tales of mireculous accomplishments of mind by the ancients are now known to be fact-not fable. The method whereby these things can be INTENTIONALLY. not accidentally, accomplished has been a secret long cherished by the Rosicruciansone of the schools of ancient wisdom existing throughout the world. Write for the free copy of the fascinating scaled book, "THE MASTERY OF LIFE," which explains how you may receive this unique wisdom and benefit by its application. Address: Scribe U. N. B.

#### The Rosicrucians San Jose, (AMORC) California

USE THIS COUPON
Scribe U. N. B.
The Resicrucians
San Jose, California
I am sincerely interested in an intel-
ligent method of attaining a mastership
of life bend me without obligation,
your FRFE Book which explains how
I may receive and use your age-old method.
Name
Address
City



#### 7-DAY FREE TRIAL EXAMINATION Amazing 3-VOLUME bound set

Complete Instructive Course



OCCUPATION

POR EXPERTS A DECIMINERS

> Compiled by practical machine shop experts—"Modern Mechine Shop Training"—shipped obse-lutely PREE for 7-day examination, Actual Losson Assignments, shop tested, with same training principles and instruction as given students in our huge Lee Angoles shops. Hundreds of illustrations, diagrams, charts, tables. Baginuars and experts need this proved Course. Mull Coupon at Brafting Lossons, Machinist's Die-

Mathine Tools helly described, demonstrated, Lessons in all kinds of hench work instructions to tool up, operate machines Numbereds of short Cars, and he was being the property from the part of the party of the pa tionary and 2 Shop Math. Texts.

TIONAL	<b>SCHOOL</b>	S, Las Angeles	497	j
		2 NO WAL		

MATIONAL SCHOOLS, Ownt. 1-L	Paste on Penny
4000 S. Figueroa St. Los Angeles 37 Calif	Postcard
Ship your 3 YOLL ME MODIEN MACHINE	SHOP TRAINING
Of RAE postpaid Within ? days after recul	TIME CONTACT AND
Bonus ( It I will elt ler return shipment and or if sat said 03.00 a	month until Intal
of \$12 57 is paid Sant payment \$3 54 You	may deduct \$1 25
If you enclose cash (\$11.25) with this Cou	por, Same return
wivilege.	

	Am section of the									
١	NAME		+ =	 			+		. 4	
Ì	ADDRESS.					* 1	 +	٠,		
i	CITY				STATE					

NOW Is the Time to PATENT and SELL Your Invention

Now, more than ever before, is the right time to patent your invention. Why? Because manufacturers everywhere presently engaged in war production are looking ahead to the future by buying up patent rights now, so they wish have new and attractive stems to make and sell for civilian consumption as soon as the war is over. This is what happened during and after the last war. Hence, the smart thing for you to do is to look ahead to the future too. Protect your invention by applying for a patent now, so you will be in position to each in on an outright sale, or on the royalties your invention will bring.

## Patent Guide Shows What To Do

Our "Patent Guide for the Inventor" answers many important questions concerning Patents that inventors constantly sak. It tells what facts, details, drawings, sketches, etc. are necessary to apply for a Patent; how to protect your invention through dated and witnessed disclosure; how to do this AT ONCE to exfeguard your rights; how Patent Office Records can be checked to determine whether the invention is probably patentable before filing fore need he paid; discusses costs involved and a practical way these can be paid as the application progresses. It tells how some inventors secured financial backing; how many simple inventions have proved large commercial successes; how Patents covering improvements also can be profitably utilized and marketed; tells countless other facts of interest.

## Why You Need Expert Assistance

The Patent Laws were enacted for your benefit—to give you protection for the features of your invention which are Patentable. But these features must be legally and concisely set forth in the form of "claims." This phase of the procedure is so complex that the Patent Office advises the Inventor to engage a competent Registered Patent Attorney. We maintain a large staff—carefully trained registered patent attorneys—expert draftsmen—experienced searchers—to serve you. We have been serving inventors for more than 20 years.

## Take First Step Now

With the Patent Guide you will receive also Free a "Record of Invention" form which will enable you at once to establish the data of your invention, before you file your Patent application. This step costs you nothing yet may be vital to your success. Remember—in Patent Matters, ACTION is IMPORTANT. Delay can be costly. Mail the coupon in an envelope, or pasts it on a penny postcard NOW.

#### CLARENCE A. G'BRIEN & HARVEY B. JACOBSON

Get That Begistered Patent Attersoys
42-A Adams Sudding Washington, D. C.

IMMEDIATELY MAIL COUPON TODAY!



### CLARENCE A. O'BRIEN & HARVEY B. JACOBSON

CLARENCE A. O'BRIEN & HARVEY B. JACOBSON Englatural Patent Attorneys belong the Bastol States Patent Office 42-A Adams Building, Weshington, D. C.

Please send me your 48-Page "Patent Guide for the Inventor" and your specially prepared "Record of Invention" form FREE, This request does not obligate me.

Name	<u> </u>
Address	
City	
	(Please write or print plainly.)



#### Wanna Blow an Ocarina No One Can Hear?

HERE is a contribution that can be extremely useful. It is possible for an



ocarina to be played without disturbing anyone. How, you ask? Simply by playing it inside a felt hat, Opposite edges of the brim are held together with a safety pin. Next, the ocarina is placed inside the hat. Then the hands go into the openings. As for the mouthplece, the most favorable method is to let it protrude

through a hole made in the top of the hat. I tested this arrangement with a soprano in G, and the loudest tones were almost completely blotted out. Any old felt hat should be large enough for most ocarinas.—R, J., Elgin, Ill.

#### Allow Us to Simplify a Simple Formula

Just received my November copy of P. S. M. and had quite a shock when I read what was supposed to be my letter to you with the formula for determining the distance of the visible horizon. Just try working out the formula for yourself and see how whoever was intrusted to print it got it all twisted. The formula I sent you was: Any intelligent officer of a ship knows that the square root of 1.5 times the height of his eye in feet is the distance from him in miles of the visible horizon. As printed in your Readers Say column, however, the formula would sure give a long distance to the horizon if a man was flying at 20,000 feet. Multiply that

height by 1.225 (the approximate square root of 1.5) and you get 24.500 miles. That's some distance to be able to see.—W. H., Cranbrook, B. C., Canada.

To clear up any possible ambiguity, allow us to explain that the distance of the virible horizon in miles is the square root of the product of 1.5 times the height of the eye in feet.—Ed

#### The Visibility Was Limited When We Checked This

In the quie on page 92 of your November issue, you ask what "CAVU" means as a weather symbol. The answer you give on page 94 is incorrect—unless the weather officers of the A. A. F. have been giving out false information. "CAVU" means ceiling and visibility unlimited, and not clouds and vapor unsafe, as you have indicated.—Lt. D. T., Selman Field, Monroe, La.

## Would Anyone Care to Tell Him How?

I would be very grateful if you or one of your readers would explain the process by which passes, identification cards, and other similar documents are coated with celluloid. I have several important papers that I would like to fix up in this manner. Is the celluloid likely to injure the papers, and, if so, how may this best be avoided?—J. F. McGarry, New York, N. Y.

## Mystery Cartoonist Exposed as a Clever Guy

Who is the guy that draws the cartoons for Readers Say? He's pretty darn clever.



How about more of them? Your Readers Say column is the first thing I read when my issue arrives, and again I say, "Congratulations to you, mystery-man cartoonist."—W, C., Baltimore, Md.

B. G. Scielstad is the man you're looking for. He also has a serious side—as you will note from

his drawings which appear frequently in other sections of the magazine.—Ed.



SICILIAN BEACH HEAD \* \* \*

Batteries furnish the power for portable radio communication the link between the fighting forces. Millions of Ray-O-Vac Batteries are delivering this vital power on all battlefronts right now. Millions more are coming! Your War Bond purchases help supply our fighting men's need.

RAY-D-VAC COMPANY . MADISON 4, WISCONSIN



TELEPHONE . LANTERN . MEAR SO AID . RADIO - 1041T10N



#### This Homemade Rifle Is A "Chuck-Hunter's Dream"

PERHAPS you will be interested in this photograph of a gun whose barrel was fashioned from an old truck axle that had been lying around in the sun for eight years. Designed by Chief Petty Officer Raphael G. Moss. shown holding the gun, the barrel was drilled and rifled by P. O. Ackley, gunsmith at the U. S. Arsenal at Ogden, Utah, who did the job in his basement shop. This .22 caliber gun is known as a "Varminter," and is said to be a "chuck-hunter's dream." It fires a .25 caliber shell that has been necked down to accommodate a .22 caliber jacketed bullet. With a heavy powder load behind it, the slug can attain a muzzle velocity of 4,000 feet per second, which is approximately twice as fast as the speed of a regulation Army bullet. With the exception of the barrel, the gun is a regulation Model 70 Winchester, and carries an eight-power scope.—D. H. M., Brigham City, Utah.

## Doctor and Soldier Prescribe More of the Same

The arrich entitled "What Do You Know About Your Ears?" that appeared in your November issue interested me greatly. The text is excellently written and most accurate. The drawings are good enough to be in a medical textbook. May I suggest that more articles of this nature would be most interesting to your readers, including myself.—Dr. E. H., Newport News, Va.

Your recent article on the human ear was most enlightening. It should prove helpful to flyers, for ear troubles are a constant danger to them. I have never before seen such clear-cut sectional drawings of the inner ear and its parts.—Pvt. M. K., Army Air Forces, San Bernadino, Calif.



## Look in a Mirror and You'll See

Die you know that no matter how hard you try, you can't by watching in a mirror, see

your own eyes move? Even if you turn them only slightly, you can never catch them in the act of moving. A person standing beside you and looking in the mirror, however, can easily see the movement of your eyes. From these and other facts it has been concluded that the eye does not when it is moving-

TRY TURNING YOUR HEAD WHILE LOOKING IN THE MIRROR!




that it is absolutely blind during the instant it is changing its focus—A. W., New York, N. Y.

A. W. has overlooked the fact that he naturally can't see his own eyes in a mirror until he is looking directly at their image in the glass.—Ed.

#### His Dad Developed the First Successful Airplane Engine

My attention has been called to a letter in the Readers Say column of your September issue concerning an article that you published some time ago on early airplane engines. The data given in that letter regarding the engine built by the late Charles M. Manly is substantially correct. This engine has been acknowledged by not only the Smithsonian Institution but by other eminent authorities, such as Charles L. Lawrence, as the first successful airplane engine. In fact, in 1930 the Langley medal, awarded only seven times for extreme achievement in the field of aviation, was awarded posthumously to Charles M. Manly. I, as the eldest son, was given the high honor of receiving the medal in my father's name. The engine developed by my father is on exhibit at the National Museum in Washington-C. W. M., Staff Engineer, Pan American Alrways, Miami, Fla.



## It All Adds Up To Subtracting Zeros

Today's apprentice gunner enters a deadly trade—defending American bombers against vicious attacks of Jap Zeros and other heavily armed enemy fighters.

To follow his trade and survive, the gunner first has to learn how to "polish 'em off around the clock." His training must be thorough and painstaking, and it must come within a hair's breadth of being the real thing. That's why Fairchild developed the GUNNER.

This advanced trainer has the essential characteristics of the bombers from which our student marksmen will soon shoot it out with Axis pursuits. From a power turret,

similar to one on a Flying Fortress, each fledgling is taught to pick off tiny targets while moving at better than 200 miles per hour. It's fast, tricky work and it takes a keen eye, steady nerves, precision equipment. It's the kind of training that pays off when the chips are down.

Fairchild's GUNNER, from which apprentice marksmen will step into bombers and then into action, is one of the largest, speediest training planes ordered by the Army Air Forces. Powered by two 12-cylinder, inverted, in-line, air-cooled Ranger engines, the GUNNER is a typical example of Fairchild's "touch of tomorrow in the planes of today."


BUY U.S. WAR BONDS AND STAMPS



ENGINE AND AIRPLANE CORPORATION
30 ROCKEFELLER PLAZA, NEW YORK

Ranger Aircraft Engines Division, Farmingdale, L.L. = Fairchild Aircraft Division, Hagerstown, Md. ..., Burlington, N. C. = Duramoid Division, New York, N.Y.

PREPARE FOR GOOD PEACE-TIME JOB THAT IS ESSENTIAL NOW!



Mail coupon today for details of my famous Coyne "Learn by Doing" method of practical shop training that prepares you for a good wartime job with a real future after the war- in Electricity, the big-pay field. Serve your country now by getting a training and at the same time you will be helping yourself by preparing for a peacetime future. Age or lack of money need not hold you back.

#### FINANCE YOUR TRAINING

Get training first; then take 12 months to complete small monthly tuition payments starting 60 days after your training period is over.

#### "LEARN-BY-DOING" AT COYNE

Coyne Training is practical training, easy to grasp . . . you learn quickly by doing actual Juba on real electrical machinery in my shops. Not by correspondence—you are trained right here in my big Chicago training shops. You don't need previous experience or advanced eduention. Expert instructors guide you every step of the way.



NOW! RADIO and ELECTRONICS INCLUDED AT NO EXTRA COST

Now I am including with my regular electrical training a special course in Radio and E retronics, at no added tultion cost. You can remain at Coyne after finishing your Electrical training. and take this extra course for extra apportunities now and after Victory.



Earn While Learning - Job Help When Trained

If you need part-time work to help with flying expenses white at C sync, we'll help PREE JOB BERVICE for you will be given

MEN with physical banicape we have facilities Ask for detaile!

#### MEN! WHETHER YOU ARE 16 OR UP TO 50—GET MY STORY

My FREE BOOK will interest any fellow who wants to get sheed even though he may have but very little money . . . Fill in the coupon today and mail it to me and you'll get my big FREE Catalog and all the facts.



E. C. COWER PROPERTY. COYNE ELECTRICAL SCHOOL CHICAGO 12 BLOF C. C. BOO S. PAULINA ST.

H G, LEWIS, President Co. Electrical School 500 S. Paulina Street, Dept. 14-71, Chicago 12, 111.

Send me, without obligation, your Big Free Book. Tell me about the extra RADIO. FTFCTROVICS COURSE included with Coyne Electrical Training and give details of "Pay-Tultion-Alter-Graduation" Offer.

NAME

ADDRESS

CITY

STATE

## TO GET AND KEEP



Do you want perfect 20 20 vision? Would you like to throw away your glasses? Great numbers of men. women and children have improved and strengthened their eyes by using the famous Ross-Rehner Method, a tested and proven system of home eye exercises for correcting nearsightedness, farsightedness, color blindness and astigmatism.

#### Get Better Eyesight—Without Glasses

Now you can get the entire system, profusely illustrated, including a complete Eye Testing Kit, with charts to show weekly improvement. If your book store does not have it, said one dollar Delivered postpaid, subject to return in 5 days if you are not satisfied. Order today

SAVE YOUR EYES



HALL PUBLISHING BLOOMFIELD HILLS 4, MICHIGAN

1564 n40 M w 28 \$ Jefferson CHICAGO & ILL SUPREME PUBLICATIONS 374

## ENGINEERI

With A Chartered Educational Institution Courses in EMS | MCERIMS | Mectalish | Cavit, Mechanical Drafting | Archametural Steam, Archamitical Radio Structural, Mining Industrial Mighway Fetraleum Martne Chamical | Moctalish Petroleum Letters; Courses in ANTS AND SCIENCES: Philosophy Education: Letters; Public Meetls Medical Jurisprudence Perchalogy; Boctalisty Physica, Chemistry; Occiding Pol Science Theology; Law Sustained Commerces Accounting Mathematics Statistics, Agriculture inglinitary-Reservett Interporated, 4810-SC, Cherisen Roof, Chicago 40

# Do you want

. to go to College?

or to enter a Profession?

(Buth as Accounting, Architectury Sursing, Dontistry, Teaching, Social Book this sporty Browty tulinec. Optometry, Embalming, Chirepody, Law, Medicine, ste )

### .. or get an Office Position?

To get anywhere, you provincelly MI ST finish High School FIRST You can complete our samplified High School Course To get anywhere, you printically MI MI notin risen person FIRMF Tou can complete our samplified Har. School Course in SPARE time at home at FAST as your time and abuilties permit. Equivalent to resident school work—prepares you for college, pre-professional examinations, bus ness, industry Standard tests furnished, Diptoma, tredit for H S subjects afteredy completed, Highe subjects if desired, Low tustion, easy terms. American School, Chicago est 1827 chicago by edgatora. Finish your high school education NOW Wrate TODAY

--------------

PROPERTY AND	real, La	PC, UL 100,	Distances Labor.	9d 20mi t	C., Camp	<b>alia</b> 94
Gentlemen	Bend to	e FREE	Infortantian	revering	gperial	train-
ing in subjec	to check	ed below.	No obligat	lon on m	y gart	

- O High School Course
  Cost Accounting for Cost Accounting for Mig. Arrhitecture and Quilding Automotive Engeneering
- Business Management Electrical Engineering
- Elec. and Ges Refriguration Air Conditioning
- Startway Training

Ulasel Engineering
Draiting and Design
for Men and Weman
Plastics
Private Secretary
Machaniant Contrast 50

ö	Aviation   Radio
_	Salesmaship
	Shiphunding

Some



Do you want action it is a marketal arriving war time industry . . . helping to their our fighting planes and jeeps and bombs and tanks? There s a big dein its for men and women plastics technicians to fill important war industry and diven state or the rig now-at home-you may qualify let a green test alparent the war program

#### LOOK TO THE FUTURE

Even more important is the question—what will you do when the war is over? Will you be among those tighting for jobs that may no longer exist? Or will you be well on your way to a permanently profitable career, or established in your own business, with

Build your perional post-war plans on a sound knowledge of plastics. This country is already to the Plastics Era. The forure of the plastics industry is so rich that some predictions seem exaggerated and funtation but the fact remains that plastics have proven themselves and are vital in the production of airplanes, auton, furniture, radios, trains, clothing, electrical appliances and equipment, machinery, tools, and hundreds of other Principle 15.

#### CHOOSE YOUR FIELD...Enter it thru PLASTICS

You should be able to see for yourself what plastics will mean in virtually every fieldthe possibilities that will be available to those trained in plastics. Now is the time to prepare for your chosen field, as a plastics technician.

#### LEARN AT HOME

Make your increased hours at home pay you dividends. You can easily fit Into your spare time your training for a career in plantics. You won't need to lose one minute from your present work . . . simply devote a few hours each week to enjoyable home study, like thousands of other men and women are doing who are helping their country while helping themselves. The Plastics Institute course it an easy, practical tested method which will help fit you for this promising and interesting field. . and if you are now working with plastics, it equips you for advancement. During the entire courte your training is supervised by men well known in the planter industry, in which they have been recognized as authorities for years.

#### TIME IS PRICELESS-ACT NOW!

Find out how the Plattics Institute can help YOU. Mail the coupon for your copy of the large FREE, illustrated booklet, the "World of Plastics." It is crammed with valuable information about plastics, tells about the new plastic airplanes and other uses for this revolutionary new material . . as well as about the opporturation for YOU in plastics. Decide NOW to let plastics point the way to YOUR success . . . send the coupon TODAY.

R.F.P.

#### TELHAKAL

AMERICA'S ORIGINAL PLASTICS SCHOOLS

1220-D Chanin Bldg. New York

STUDENTS REPORT

SUCCESS

I wish to acknowledge, with thanks, the receipt of my final

examination papers, my certifi-

care of graduation, and the les-

I have really enjoyed your ex-

cellent course of study, and the

triendly help and cooperation

you have given me, and feel that

the time and inoney expended


on my training has been well

son binders you sent me.

worthwhile "

626-D LaSalle-Wecker Bldg. Chicago

174 So. Afvarado St. Los Angeles



Plastics Industries Technical Institute 626-D to Saile-Wacker Bldg., Chicago


Gentlemen. Please send me the book let "World of Plastics" and information on your training program. I understand there is absolutely no obligation.

Name.

Street

City State.

Dept.1



#### HOW TO PROTECT, FINANCE and SELL YOUR INVENTION

Our FREE BOOK and other literature available to our clients—gives you complete details on how to "ready" your invention for money-making. It tells you how others did it—who they went to for finances—how they arranged partnerships—how they made contacts with manufacturers—how they dictated royalty arrangements—how much money they made—how you can find a market. Our new FREE BOOK discloses sources of guick revenue if your invention is patentable and sale-able with profit possibilities

#### THE FIRST STEP

The first step in getting your invention ready for market is to make a dated record of it on our "Invention Record" Form. This Form properly filled out and witnessed will be invaluable to you later in establishing the date of your invention should need for such evidence arise. We will be glad to send you our Invention Record" and have it witnessed in this office when you return it with declosure of your device. This service route you nothing—and it immediately puts you on record as the originator of your device. record as the originator of your device.

#### Protect Your Invention NOW!

We have many letters in our last last many requesting inventions Times a reason for the location is tremendous—added to by emergency needs. Frame your invention how with a U.S. Patent. By acting promptly you may prevent another inventor getting in shead of you at the Patent Office here in Wash agion. The first step is to make a sketch and description of your invention on our Invention Record have it witnessed and mail it to us We will then make a Search of the U.S. Patent Office files to ascertain whether we can get petent protection for you. This is a step you should make NOW—before another steps in a shead of you and walks away with a patent. sheed of you and walks away with a patent.

COUPOIL
MORROWABERM
PATENT ATTORNEYS  142-8 After Building, Washington E. D. C.
Bend me your NEW FREE Book "How to Protect, Flames and Sell Your invention." and specially prepared livent on Record form at mice. I understand that this request does not obligate me
HANE
ADDRESS
GRYV

#### LEARN AT HOME

Are you adult, alert, ambitious, willing to study? Investigate LAW! We guide you step by step-furnish all texts, in-cluding 14-volume Law Library. Training prepared by leading law professors and given by members of bar. Degree of LLB conferred. Low cost, easy terms. Send NOW for Free, 48-page "Law Training for Leadership."

LASALLE EXTENSION UNIVERSITY A CORRESPONDENCE INSTITUTION DEPT, 183-L CHICAGO



## RI-STATE COLLEGE

B. S. Degree in 27 Months

D stinguished for technical 24 -year courses in Civil. E certi al. Mechanical, them cal. Had a Accords ion, Engineering, B. s. ness Admin a trate in. Accounting and Bestellar a Science. MEN AND WOMEN 2 or high school students with good record ad-

matted. Special Preparatory Department Modern incorntories, latest equipment, Low to ton. Low living onto Postmopolatal student body atth year Enter Marth, June, September January, brate for culture.

514 College Ave.


ANGOLA, INDIANA

run as high as 868.-8100, weekly after a few weeks home training most medical or chiropody—many terms, no further capital meded, no goods to buy, 47th year, Write for free hooklet,

WANT a permanent business profession of your own Then become a foot men and women in this greatly needed profession

Stophonous System of Foot Correction, 62 Bock Bay, Boston, Muse.

**AUDELS** Carpenters and Builders Guides



for Carteen rate. Postation of an extent that the postation of an extent of a second of the control of the cont

Inside Trade Information Onl

Row to use the strel square-Row to file and set many-How to build lurn turn—How to use a more load-How to use the chalk line. How to use the chalk line. Carpen on turn and cause. How to make points—Carpen on himstony arrength of limbers—How to set girdets and sile.—How to rume houses and roots—How to artimate costs-Bow to build houses, barns, garages, bungalows, etc.-How to read and draw -Drawing up specifications - | | f | D-9| 50 cavate. How to use servings 12 13 and 17 on the steel square - Now to build houte and acaffolds shringh a "How to build starte-lige to put on interior team - How to hang doors -- How to lath -lay floors-How to point




THEO. AUDEL & CO., 43 W. 21rd St., New York City

Mak Andele Corporators and Budders Gordan & volu, on 7 days' free triel. If O X, well remay \$1 in 7 days, and \$1 m, nably anal \$6 m paid. Otherwise I will return them: No obligation unions I am national.

Mann-	,	* 17 +1+1+1+1+ A +	
Address		*** b ******	
Overgetten		71 7+ ++1+101+10+010(4)	,
Reference		200	





Here is the book aircraft workers and students have waited for -a new "tool" that helps speed work in every department. Whatever your aircraft job, the DATA BOOK is a complete reference library, with technical tables and formulae for engineers . . . charts, tables and other information to aid every man and women in the industry...plus a Dictionary of Aircraft Shop Terms.

Aero Tech is highly qualified to produce such a book, as their sole business for years has been the teaching of aircraft mechanics and engineering. Faculty editors ore eviction authorities, and other information was contributed by leading manufacturers.

Ask at your plant library for Aero Tech's AIRCRAFT DATA BOOK. If you want a copy of your own, ask for it at your factory store or mail the coupon below.

#### AERO INDUSTRIES TECHNICAL INSTITUTE

5247 W. San Fernando Road Los Angeles 26, California



5247

Here ere a few of the charts, tables and other information in your Duto Book

Dimensions and notes

Fits and tolerances Drill and ream notes Complete Air Corps Standard Sheen Plating formulae Production breakdown of typical airplane Waights of bor steels insulated were sizes Surface cutting speeds for pullametic screw mochines Welding torch tip and drell stress Rod size current volt loble Rod motion patternart welding

Set back chart for bending

Directory of protective coatings

Stondard calors for fluid line Identification

Dictionary of oircraft shop terms

Weight conversion chorts

Steel type and numbering chart

River code Threads tables

Standard gauges chort

Tansile strength of materials

AERO	INDUSTRIES	S TECHNICA	L INSTITUTE	
W. See	n Fernando	Bood, Los i	Annales 24.	Calif

Gentlemen: Enclared find \$1.50 (check, money-order) for my copy of AIRCRAFT@ATA BOOK, sent to me postpoid.


Street Address

Buy Wat Savings Bonds and Stemps regularly.

State

A-7-5

## MONEYat HOME! New, patented invention makes possible big earnings AT HOME. Replate auto-



553 N. Wells St., Chicago, III., Dept. 409

## Large Manufacturer Will Cash or Royalty for New Items

Here is your chance to cash in on your inventions for new products made of metal. These can include machine parts, new equipment, or production parts. Write fully, giving descriptions send sketches if needed-tell us your price. We wall arrange meeting if interested-or return your material. Write M.M.C., 11th Floor, 352 Fourth Ave., New York 10, New York.



BTUDY AT HE ME for PERSONAL SUCCESS and LANGER EARN NOW TO PERSONAL SUCCESS over 108 colt students encolled 13. 8 Degree awarned A. Iteats for banked has payments Send. for FRIE BOOK - Law and Executive Orldanes!

AMERICAN EXTENSION SCHOOL OF LAW Dept. 37 S. B Eest Huron 54., Chicago 11, III.

Find out your ability. Send name, age, occupation and address for Free Vocational Art Test.

ANT INSTRUCTION, OIC., 1144 Art Instruction Didg., Minneapolis, Mica. (Formerly Federal Schools, Inc.)

## **OUICK WA** TO LEARN MUSIC \_play any instrument

GET A REAL thrill out of music! Play the musical instrument you like best. Start right in with simple tunes. No tedious, old fashtoned drills and exercises

It's easy! Everything is in print and picture. You see every posi-tion and move. Thousands have been amazed at their progress in just a few short weeks. Now they re sought after guests for every party Don't miss out on the popularity that is rightfully yours



Mail coupon today for free illustrated Booklet and Print and Picture sample that show how easily and quickly you can learn music at home. Just check instrument that interests you in coupon below, U. S. School of Music, 81 Bronswick Bidg., New York 10, N. Y.

#### FREE PRINT and PICTURE SAMPLE

			-								
U. S.	School	of Mar	rie, All	Bruem	rick B	idq.,	Rew	York.	10, 1	N.	Y
Please	nend a	no Free	Book!	et and	Print	and !	Pictur	re Bar	aple.	I	would
like to	play is	wirume	est interp	ked bel	ow (I	d you	DATE	instr	umeo	£	
Piane		4.0	na felia m		Tenn	nak .		III Minus	Jelle		

a.mo	Acces 010m	Ţ
altar .	Secophone	Ť
leli n	M andolla	C

Orums & Traps Other Instrument enor Banje **Jeans** 

Name	(Picase Print)	
Street		
City	Ot at a	

#### AUDELS AIRCRAFT WORKER Answers Your Questions on 1-Aircraft Materia. Terms Part 2-Bideprints, Working Drawings 3-Ma second et. How to I tire 4-Layout & densing 5. Too 1 & May then b- 1, et. Boot Welding & Bints 7-Fabrication Angier etc. 3- 1, etc. bly Puse age, Wing & Fine-Lion to like Too 3 9- To - a & liaia, Symbols, Army & Navy Specifications, etc. 240 Pages Hum. AUDELS SMEETMETAL PATTERN LAYOUTS. \$4 Developed by Experts for Sheet Metal Workers Layout Men & Mechanica, A Practical Encyclopenta in 10 Sections and a 2-2125 Pages - 0 Lapour 1600 Harra tons Farts. Fully indexed for ready reference in a size og your a out problems, Covers all phases of sheet one a work methoding Pattern Cutting Pattern the exponent & Sup Proc. we AUDELS SHEETMETAL WORKERS HANDY BOOK..... Practical Incide information. Fundamentals of Sheet Metal Work 388 pages. Liustrated. 11 protions t carry writen besente & important facts, figures, pointers in everyony language. Ref. Jo. AUDELS WELDERS GUIDE. ... A concile, practical text un operat on & maintenance of a f w. markings for an mechanics. Over 400 pages a units out that an improved of electric soil and one we up a Incombing a space we have **AUDELS ANSWERS ON** BLUE PRINT READING... For Mechan of & Burklers, Covers all types of blue print reading including ship & at plane, 376 pages for y illustrated. AUDELS NEW MACHINIST & TOOLMAKERS HANDY BOOK...\$4 Covers modern mach me shop practice to all its begandes. A pier Liena books in I New from coner to cover. Teels how to set of A appointe la hea, acrew mile inti i g markunes, at april 16 a pre remail ai) of er mark no local. It so pages fully a see are a big E 2 Indetent to seek and 1—Morte in Markuse Moop I act in the Print Reading & Row in Draw 3—t along a long or mut en for Mark a etc. 4—Moop Physics 3—a on to big e Bisla Rute 40 char ers. Easy to read and uncerstand. A shop compan in that answers your questions AUDELS MATHEMATICS & CALCULATIONS FOR MECHANICS 52 Mathematics for home study or reference 788 pages, a 9 1 Practical materna ics from begain of How to flavor correctly

Rasy, correct methods entering a complete person. I de Judes à AUDELS AUTOMOBILE GUIDE. \$4 A practices quick result reference book for auto mechan es se sace tracts, our minus de deuter. Explained théory construction de les

A practical quick ready reference book for auto mechanics are save took, operation & dwaret haptened theory construction & for ing of matern motor cars, tracks bases in a to type theselves a track 100 pages, fully flux catch 35 chapters (independent Appendant Appendant to the flux catch 35 chapters (independent Appendant for mechanics). New Suid drare coursed.

AUDELS DIESEL ENGINE MANUAL, \$2. A practical, ensemble treat so with questions and answer on the theory operation and his ntenance of movem diesel on their clading Ceneral Minters 2 special Diesel. Dail pages forth that flexible training pocket a see All details plainly brought out, this hook is of excreme value to one neets, operators & students.

AUDELS RADIOMANS GUIDE \$4

A ker to the practical understanding of radio leads ing Prequency
Modulation, Terras on etc. Ass. at & Maxime Radio for raise
engineers, perticement, amateurs 172 pages, 400 1 instructions &
Disarrams, Photos, Res ew Questions & Answers, Reference Index
Aut. at the country.

PRACTICAL ELECTRICITY .... S

For maintenance and never, a settletans & all electrical works, 1440 Pages 2800 I tus Covers important electrical informs to handy form who as mg Marina Wiring, Radiu Price of Welding Indexed. A key composit culturelectrical agency at their

AUDELS CARPENTERS & BUILDERS
GUIDES-4 Vols. \$6

A practical illustrated trade assistant on modern construction for extractors joiners, business, more saids and all wood carbons and 1800 pages, 2004 such a constitute covers, buch as used pocket size. Bold separate y \$ 0 a voi

A Process. Trade Appletant & Bondy Reference Explains in part language & by clear illustrations, diagrams, charts graphs president principles of modern plumbing practice are last on the Pipe Fitting and Air Conditioning. 4 Year and 5 Pagester 42 Bingrams Each Vol. Pocket Size Sold Reporter 9 \$1.50 a Vol.

AUDELS WIRING DIAGRAMS

110 Pages. Discreted. Given practical facts on wiring of electrical apparatus. It explains clearly in simple language how to wire apparatus for practicalty all fieths of electricity. Each diagram is that place is relificated apparatus. Highly Endorsed Pothet Companion.

AUDELS ELECTRONIC DEVICES., \$Z. Tells What Toe Want to Know About Electric E. e. Eas by Universiting. Covers photo electric ests & their applications. Emplifiers it unimation, frequencies, voltage, photocell. Labet, Ohm & Jan waring diagrams, etc.

AUDEL, Publishers, 49 W. 23 St., N. Y. 10



#### AN AUDEL GUIDE IS A GOOD FRIEND!

Use the brains and experience of others in these Guides of the Trades. Save time and money with right methods, short cuts, lober saving ideas. CHECK NOW! You can look over any Audel Guide In your home. Start the Easy Payments if satisfied.

# MAILORDER

THEO. AUDEL & CO., 49 W. 23rd St., New York 10
Please mail me for 7 days' free examination the
books marked (X) below. I agree to mail \$1 in
7 days on each book or set ordered, and to further
mail \$1 s month on each book or set ordered until
I have paid purchase price.

If I am not satisfied with Guides I will return them. Audels PUMPS, HYDRAULICS & AIR COMPRESSORS \$4. Audels WELDERS GUIDE . Audels BLUE PRINT READING Audels SHEET METAL WORKERS Handy Book . Audels SHEET METAL PATTERN LAYOUTS Audels AIRCRAFT WORKER Audels MATHEMATICS and CALCULATIONS Audols MACHINISTS & TOOLMAKERS Handy Book Audil MARINE ENGINEERS HANDY BOOK Audols SHIPFITTERS Handy Book . 1. Audels MARINE Engineers Guide Guetha MECHANICAL DRAWING COURSE 3. Regers Mechanical DRAWING and Design .
Audels MILLWRIGHTS and Mechanics Guide Audels CARPENTERS and Builders Guides (4 vels.) Audols PLUMBERS and SteamStiere Guides (4 rols.) Audels MASONS and Builders Guides (4 vots.)
Mester PAINTER and DECORATOR Audels GARDENERS & GROWERS GUIDES (4 vols.) JAMES ENGINEERS and Mechanics Guidet Nos. 1, 2, 3, 4, 5, 6, 7 and 8 complets Audets Answers on Practical ENGINEERING 1. Audels Answers on REFRIGERATION . MARRIMA AIGS IN ENGINEERS EXAMINATION Rogers MACHINIST GUIDE Audole WIRING DIAGRAMS Audole Handy Book of PRACTICAL ELECTRICIT Audole ELECTRICAL POWER CALCULATIONS 2. I Hawkins ELECTRICAL Guides at SL each

Audols ELECTRONIC D		4			-		A 4		ı
Audels ELECTRIC Diet	prary			-				- 2	ı
Audels RADIOMANS G	UIDE		_	-			4 - 1 -	- 4	ı
Audels NEW ELECTRIC	LIBRA		at,	51.	54		rely	Lates.	
Vole, I, II, III, IV, V,	VI, VII, 1	ИЩ	, II	Κ,	ж,	жı,	X.		
Hame									
Address								-	
***************************************									
Occupation									
Acontación					-				١


Employed by ...

# . . War days are OPPORTUNITY DAYS for YOU in Accounting . . .

If you like to work with figures and are earnestly ambitious, accounting today offers you unparalleled opportunity—to serve your country and to profit.

For there just aren't enough bookkeepers and accountants to fill the needs of government and industry. There are thousands of new and vacant jobs. These jobs pay well and they are open to both men and women. Moreover, this need will continue through the war and the post-war adjustment period.

Ask us to prove this - and to show you how you can grasp this opportunity quickly.



Dept. 183-H I want to know what opportunity there is for me in Accounting now and how I can prepare for it Send-me your free booklet and any other pertinent unfor-

Name.	 181

Present Position

Address.....

GIVE 3-Monkey Cartoon Films SHOW



Always a FEATURE at Nome Movie Show Ideal CHRISTMAS gifts, GET THESE PEATURES.

SO FL SMM Beauty Shop

\$1.25 1201 A 1202 A

100 Ft. 16MM Ship Wrecked It gh & Dizzy

52 50 1268 A 1210 A

Always give and show Done d Duck Bosko Oswald Rabbit, Mickey Mouse Cartoon Home Movie fi.ms.

See At Your Photo Dealer or Order Direct. Chiefug and Prices on Request.

HOLLYWOOD FILM ENTERPRISES, Inc. Dept. 116, Hollywood 25, Calif.



Write for no Free Book How to Become Write for no Pres Blood How is Become at Papert Pollans in the shows what others have necessary mend by taking my Course. Landose 10. For me of my Paron to Pen Points and you halve with a cq. the fluid-T. M. TEVIS, Sex 258, Chillienthe, Me.

SERVICE MECHANICS COURSE CAPITAL RATION Learn at home—how to start your own repair shop on little capital No previous experience needed. Common school education take lent housed depropriently for older men. Prepare how for affect the war first fusicated booklet

MCCHANGS TRANSING SCHOOL, Dept. S. I., 4701 W. Pice, Les Avgeles S., Calif.





Now is the time to prepare for Essential War Work and a Brilliant Peacetime Career in Aviation, Ryan's tested methods of instruction will train you thoroughly vet quickly, in spare time. No higher education or experience necessary. A complete Aeronautical Drafting outlit is included with your training, at no extra cost

#### LIFETIME CAREER AT BIGGER PAY

The ameralt industry needs Draftsmen and Engineers Now and for the Big Tomorrow in Availion. Men who today hold ordinary foutine jobs will be important figures in the alternit plants toportunity To save time send a r mail.

Byan Aeronautical Institute,


415 Lindbergh Field, San Diego, California.

Gentlemen:

Please send me your FREE 24-page book. NEW ROBI ZONS OF OPPORTUNITY" and full information on R. A. L. including cost of training, and job opportunities.

Name		Age
STATES.		-1707
City	Rinte	

mation.



## RADIONICS-Radio Electronics 3 Big Fields in 1 (Television

was f in the Mall of the agency persty

#### MASTER ALL BRANCHES OF RADIO

D. DM 1 Table 19 Mary A Mary

National Radio Training with quarty just for a real future a good pay job, respond billy and marve one opportunity for advancement

#### LEARN AT HOME

NOW you can learn AT it. Mt. It your spare time. Notional a victory is aling plan appeals up your progress out i from the start, yet omits absolutely nothing vital to your preserve on.

#### FASCINATING WAY TO LEARN RADIO

Eliminating dry text books. Not enal a plan of rapid flume Training actually hither you the proved stop head of a creater methods that are in well by Noticeth a resident fra long theps. This training it a mpli field to that you can easily group flation step by step in a way that gr we in its four notice you gray prepared for a good todio on all excellent pay or may seture an ever radio business. Bear in mind that with the war time curtat input of rad o note there is a bugs increase in party co work. It homes that a manufacturing plants a bugs increase in party co work. It have been to bein produce the pull technic and to bein produce the bugs increase in party co work. It have been been to be a bug increase in party co work in the manufacturing plants. It was not the pull technic and to bein produce the bugs increase in party co work world into the area worth of mittery radio equipment. Enclosed area in all or other and ayateups. Electronics is grow in the produce of the pull that the produce is grow and houselds.

#### NATIONAL GRADUATES WIN GOOD POSITIONS

Thousands of graduates of Nell-nel Schools are em, aged throughout America and in thany parts of the World-strong testimontals of successful Training



"National Schools has done won descript work for the man who wants to get shead in life Your trained man can get a jub at a much higher salary."

O. K. Jeer, Washington D. C.



'Your schooling he ned me obtain a swell job Now in the Navy I am following the profession I resented in National It will be pury chances for taged advangement K Nekroeder, D. S. Navy



#### MEN WANTED

Ages 16-50

In Radio age is not a factor. The using is the main requirement the rade \$7 000 No. I ound Graduates.



## 2 FREE BOOKS

OPPORTUNITIES - TRIAL LESSON

REQUEST: FULL DETAILS

# PREPARE FOR

GET INTO



NOW!

For M years National Schools has trained ambittons men for Top Pay trades Squarety behind your Home Training are the modern, completely true peed Training Shools of Salasma, Schools where we develop and prove every Shop Method Assignment set to you I very phase of your less sing to personally superisted by an established For My of practical experienced instructors and end never They have do eloped progress venethods of testing you in your own home bosed in actual shop practice. In que training fact then give you flows Training lossed on Breidest School Shop or near a methods not available from one other fraction. Shop or near a methods not available from one other fraction.

#### KEEP PRESENT JOB WHILE LEARNING

Regardiese of previous education or age, you can Train for Radio, Continue your present job Earn while you leath. If subject to Military Service, all the more important that you get pre training.

MILITARY SERVICE

Prepare for Radio apportunties in 1. S. Gov. Service in Arms. Nave Mariar. All Corps. Uses found and other branches. Pre-induction preparation dives many. Not what productes prematuch and increased pay from the start. In addition the time you appead a military acretic further deve up your Radio technical ability so after the way your Radio technical ability so after the way your finest positive to be well you liked to handle the most remote that a Faper labor high paying jobs to the beaming Radio Indust v. Many man new in to thary secrice are today at east Martine Indust.

SPECIAL OFFER

So that you can demonstrate to yourself the case and re-plotly of years og Radion home. Not mel Schools at h historic to you the Camplifurnish Leanth free accum-panted by Opportunity Book of Facts and Sets is about all branches of Radio. See the Coupon, Mail It budge.

Chalify for These John Had a Fapert for adeasting At craft Ma time Indust tine Indust Flectron on Sludin Tech-polan God Service Re

## NATIONAL SCHOOLS

Los Angeles 1 California (STABUSHED 19

(Mail in anvelope or National Schools, Dept. 1-PS 4000 So. Figuresa, Las Angules 37, Calif. (Parts on penny postal)

Mail see FREE, without abligation, one Lesson and Opportunity Book, with full details about how I CAN become a RADIO Technician

AGE		

JANUARY, 1944

# tree T-Vay Offe REPAIR AMY MAKE MOTOR 5

Espiains Every Repair Job ou Every Model of AH These Cors — 1935 thraugh 1842 !

AUTO

American Bantam: Auburn Austra Buck; Cad. lac Chevrolet; Chrysler, Cord De-Boto Dodge Ford Boto Dudge Ford Oraham Hudson: Hapmobile Lafasette LaSaire Lincoln Line-coin Zephyr, Mermury; Nash Oldamob le Overland Packurd Bouth Ponting Res St debaker Te plate Wilys 200 000 Fucts Terra-

Charts 900 Photos, Draw ngs. Disgrams, Biss 8 4 x 11 in, Pub-lished by McTok, The Leading Astometry Business Magusine,

Total FREE 7-Day Office Malah's Truck Royale Managil 1400 pictures. 905 pages.
1400 pictures. Used by
100 000 Armed Folices
Birony Fabrikold Covers Brong Brabrikola Covers
Brong Brasil 1936-1942.
In 500 models Engines.
All DIESKLE manel
Fuel Institute of the second sec old, old

Heips EVERY Mechanic—ever experts—de repair jobs easier, nuicher

Explains every auto re-pair operation STEP-BY-STEP, Ensy-to-usel Hundireds of photographs, diagrams, drawings, show exact "bow to do it" of repuiss, adjustments, replacements. All joke on every model since 19351 Engine: E cetric Fuel. Couling, Lubrication Systems, Clutch, Transmission; Universals, Rear knd; Wheels, Brakes; Knee Action, Shock Absorbers, Springs, Body, Free Wheel Overdrive, Fluid Coupling!

#### BIS FACTORY BOOK! IN ORD.

Imagine a COMPLETE COLLECTION of ALL official shop procedure manuals, prepared by each car manufacturer's own engineers! That's what you GLT in this book! Open the manual to the car you want-you'll find everything to show the right way to do the job, This is the factory shop manual used by the U. S. Army, trade, techpicul and vocational schools,

#### SEMB NO MENEY

Simply fill out coupon below. Mail it today and a copy of MaToR's up-tothe-minute New Auto Repair Manual will be sent to you at once for 7 days Free Examination,

Malof Book D	at once: (check box opposite book you want)
- Mara	NA ARTO BEDALO BEARING CO.
sener de il	's Factory Shop Manual'), H O.K. I will 1 days, \$1 monthly for 4 months, plus 35c
book in 1	h final payment (#5 35 in all). Or i'il return
inoteR remit 3	in 7 days 42 monthly for 2 months, plus with final payment (18.35 in all), Or 1 li in 7 days. (Foreign, remit \$11 with order )
Name	was a sent (Lotester Lemys 215 Auff Older.)
Address	
City	State
Check	tere if enclosing full payment, WE pay 15c. Same 7 Day Return Privilege,

## don't WOR

Why put up with years of needless discomfort and worry? Try a Brooks Automatic Air Cushion. This marvelous appliance permuts the opening to close, yet holds reducible rupture securely, comfortably—day



and night. Thousands report amazing results. Light, neat-fitting. No hard pads or stiff springs to chale or gouge. Made for men, women and children. Durable, cheap, Sent on trief to prove it. Never sold in stores. Beware of imitations. Write for Free Book on Rupture, no-rock trial order plan, and proof of results. All correspondence confidential, BROOKS COMPANY, 168-C State St., Marshall, Mich.



Gueranteed Learn Easily Quickly step by step, Send for to-day for trial lessons, full details MODERN SCHOOL OF JIU-JITSU Dpl. B, S W, 52 St., N. Y. 19

# PRACTICAL



HANDY BOOK OF ELECTRICITY

For Engineers, Flectricians, Students and all inter-HANDY ested in Electricity. A quick, simplified, ready tence, giving complete instruction

1340 PAGES

to understand. A reliable au-thority and a handy helper that answers your questions.

#### . INSTDE TRADE INFORMATION ON

and practical information. Easy

The Rules and Laws of Electrics ity-Maintenance of Machinety-A. C. and D. C. Motors-Armature Wino og and RepareW te ing Diagrams - House Light ng-Power Wiring - Cable Spliting -Metera-Batter s-Transformers - Elevators - Electric Crancs -Raswaya ~ Bells ~ Sign F others ~ Telephone-lightton-Radio Principles-Refrigeration-Air Condi tioning-O l Burneri-Air Conpremore-Weiling, and many fern Applications explained so can understand. this assume for yourself, sumply

2600 ILLUS t and mail the FIRE COUPON below. THEO. AUDEL & Co., 49 West 23rd Street, New York.

Fitness and me. Audels Handy Buck of Practical Block trackets. For free examination it can factors & will redd on it in 5 days, then \$1 southers much \$4 to pass. Otherwise, 11 will return to. I will return to Name -

237 3
E 15 . 4
E. C. PISSE
4000
100000
- 3 411/2
BEAR FOR

PROFIT!

Accres Philosophia tares The beginning



• Leaders in science and industry have long been saying, "Keep your eye on Plastics." But now the time for action has arrived. The future of huge possibilities has already begun. Developments in Plastics for hundreds of wartime uses have set the pace for revolutionary changes in peacetime production of thousands of products.

## THIS IS YOUR .

Today there's a big need in vital war production for those who are trained in Plastics. From one to a hundred articles made of Plastics must be supplied for every man in our fighting forces. Start training now in Plastics Engineering, in spare

time in your own home. Fit yourself for a responsible, well-paid position. Help to win Victory. And at the same time you will be preparing for even greater opportunities when the war is over.

There is scarcely an industry in which these so-called "miracle materials" will not play an important part. After the war many old materials, methods and skills will be replaced. Acquire the all-important "know how." Be in a position to step into one of the key jobs.

#### YOU CAN LEARN WHILE YOU EARN

Turn at least part of your leisure time into money. Qualify at home for a larger income in an interesting career. Build greater security for your future in a vocation that looms large on the horizon of the new industrial era. Hours you might

otherwise waste can put you well on your way toward lasting success.

4 I

ပေျ

41

ac.

α,

It's easy to find out about Piastics training. To get details and outline of study prepared by specialists, and about the school that has helped thousands to success during the past 46 years, write us or check and mail the coupon. Send today. The

sooner you take this easy step, the sooner you will reach your goal and reap the rich rewards.

#### AMERICAN SCHOOL OFFERS COMPLETE TRAINING SERVICE IN MANY SUBJECTS

You who have not completed high school or have missed vocational training in college, and who cannot spare time to go away to school, can complete your education in your choice of many subjects. Several of these are listed in the coupon at right. Check the subject in which you are interested, fill in your name and address, also and mail the coupon today.

#### ME - STUDY TRAINING SINCE 1897

Take This First Easy Step

### CHECK, CLIP AND MAIL COUPON NOW

AMERICAN SCHOOL, Dept. 6-146, Dresse at 51th, Chicago 37, III.

Without obligation, Please send FREE and postpaid, builetin and details of the Subjects checked.

DPLASTICS ENG'R.

ORefrigeration

Oarchitecture

and Building

Obractical Plumbing

Automotive

Engineering

☐Aviation Drafting
☐Aviation
☐Besiers Mynmest
☐Rallway Training

Accounting and
C.P.A.
Door Accounting
for Manufacturing
Bookkeeping
Private Secretary
Diesel Engineering
Surveying & Topographical Drafting
Sheet Metal
Pattern Drafting
Slactrical Engineering

Drafting and Design
for Men and Women
ORadio
High School
Exir Conditioning
Oshipbusiding
Osherhanical Eng.
Oshop Management
UTool Making
Observer Foremanship
Operations

AMERICAN SCHOOL

Dept. 2-146 Draxet at 53th Street, Chicago 37

Address City

Name . .

State

Apr.

.. . Compation




#### YOU GET A DUAL-PURPOSE RADIO SET

The offer I make you here is the opportunity of a lifetime. It's your big chance to get ready for a wonderful future in the swiftly expanding field of Radio-Electron-

FULL RADIO SET

ics INCLUDING Radio, Television, Frequency Modulation, and Industrial Electronics. By Wise' NOW on the time to start. No previous experience is needed. I supply you with Radio Parts which you use to gain pre-experience in Repair work These same Parts are used for testing and for Signal Tracing etc.



. . . or Good Radio Jobs, Civilian or Military

The Sprayberry course starts right at the beginning of Radio. It gets the various subjects across in a clear, simple way, I make it easy for you to learn Radio Set Repair and Installation Work by practical proved time tested methods I teach you how to install and repair Liectronic Equipment Soon you if he quastted for a good paying job in one of the nation a Radio plants doing wer work OR, if you enter the Army, Navy, or Marines, my training will help you win higher rating and better pay.



MAIL COUPON

SPRA	YDERF	IY AÇA	DEMY (	OIGAN W
F. L.	Sprayb	erry, P	resident	
			Colora	
	_			

Please rush my FREE copies of 'HOW to TEST and RE-PAIR RADIO SETS Without METERS' and "HOW to MAKE MONEY in RADIO"

T-ENGINEER DAY OF THE		MLD4C			
Name			Age		
Address				+ + 1	 +
City	alela i	merilani.	 Stale	postent	 -



FREPARE TODAY FOR THE FUTURE THAT LIES AHEAD

Trained Artists Are Copable of Earning \$30-\$50-\$75 A WEEK

Use your spare time to prepare for a prefitable Art Career. Start training at home, new!

It's pleasant and interesting to study Art the N S A way COMMERCIAL ART, DE-BIGMING, CARFOONING at In ONE com-ing pourse Napres has Artexpertrage moces-sars we teach you step to step by our practi-cal mone study mathod well known since It 14. But tedar for he come has to IRFE BOOK ART F H F FAST RE ANT PROPETTY cells all about our course mai that form their nex-ter and reministers' opportunities for you in Art State age.

WASHINGTON SCHOOL OF ART Stadio 131K, 1115-15th St., N.W., Washington 5, B.C.

Why It Pays To LEARN PHOTOGRAPHY NOW Never before so many job and career

opportunities! Photographers needed in business, industry, science, NY I, graduates winning promotion, higher pay in Armed Forces Quanty of America's largest oldest school, Resident or home study FREE cata.og describes commercial, portrait, motion picture and color courses, Write today!

W. V. DESTRUTE of PHOTOGRAPHY, Dept. 5, 10 W. 33 St., New York 1, N. V.

LOW AS Correspondence Courses In

ELECTRICAL ENGINEERING Cot good grasp of wide electrical and Minters Very understandable. Theory made casy and casy and extenses Kates for course in red a, poblic address, photo electric work. Traine you to be super new et man, real various tube technician. Tutelos ONLY 126, either course. Deferred payment plan. Bervicemen needed baddy.

FREE Veste lot free course of school catalogs, atodent magazines etc., two courses of the course of school catalogs, atodent magazines etc., from every at Lincoln, Nebr., washington, O. C.

### ELECTRICIANS! RADIO MEN!



OVER Large Size Electrical and Radio Shop Prints -New to read and upo them

4 GREAT BOOKS IN ONE Course 2 500 Stop Prims 3. 1- lec

Radio Dictionary 4. Spare Time Jobs. FREE! Lyr Technical Courset by mail from COVNE staff, on trauble-shooting problems,

SEND NO MONEY! See offer below toy NE "Learn by Doing" Electrical School. Rush coupon now!

M. C. LEWIS, Press., Oopt, 14-4 COVME ELECTRICAL SCHOOL SOO S. Pauline SI., Chicago 12, M. COUPON Send, with a shipping charges paid rour new COVNE Elec- trained Raine Translet Shipping Manual Within 5 days after strilling if I either extern it or send 53, then 37 monthly until total of \$2.95 is paid, 1 Cash price II III years over 164)
Same day free trail and return pricings.
NAME

AJYMESS

STATE

П 



THAT WAS A GREAT HUNTING TOIP, BILL, ALL THE DUCKS WE WANT, BUT IT SEEMS A SHAME TO THROW AWAY THIS BEAUTIFUL

THAT'S JUST WHAT I'VE BEEN THINKING-JIM, I M GOING TO WRITE TO THE NORTHWESTERN SCHOOL OF TAXIDERMY AND SEE IF I CAN'T

WELL, I SEE YOU REALLY ARE TAKING UP TAX:DERMY IN EARNEST, BILL.

THAT'S RIGHT, JIM-AND I VE NEVER HAD SO MUCH FUN IN MY LIFE. I'VE ACTUALLY DOUBLED THE PLEASURE I GET FROM MY HUNTING AND REALLY





I'VE SOLD MANY BOOK-ENDS, LAMPS, ASHTRAYS, DIPE RACKS, AND SO ON TO SPORTSMEN FOR THEIR DENS -- I'VE LEARNED TO TAN FURS FOR CAPS, SCARES AND RUGS AND - BEST OF ALL-INSTEAD OF THROWING AWAY THOSE FOR BELTS, HARNESS AND STRAPS

COW-HIDES, I TAN THEM INTO LEATHER BUT WASN'T TAXIDERMY HARD TO LEARN, BILL?

HARD? NOT A BIT, AFTER YOU GET THE HANG OF IT WHY JIM, TO ME TAXIDERMY IS THE GRAND-EST HOBBY IN THE WORLD. LVE MADE AS HIGH AS \$75 PER MONTH IN MY SPARE TIME, MOUNTING TROPHIES FOR HUNTERS, WHY DON'T YOU TAKE IT UP?




asureand Pro EASILY, QUICKLY, BY MAIL IN SPARE

> Men, boys, women,-Study Taxidermy. Taught by Experts. ALL SECRETS revealed. It will amaze and delight you.



#### Hunters — Fisherman

den. Have a Musoum. Win fame to mount (stuff) expertity, Birds, Ani-That is Tandermy. You can be a Tuni-dermit Will you? Surely you are interested Mail Coupon right now for the artonlaking From Book.



#### Our Students Succeed

This old reliable school has graduated \$2.000 atom nate were uniform satisfaction, If we have taught that he is no most, you self-st agree t at we can teach YO also We offer you with t at we can teach YO also Fall I our we was to tan hing the west num-SEND COUPON TODAY FOR FREE BOOK.

#### Wild Game Not Needed

You can use common animals and birds; squirrels rath to I the close pup-plet it them signed even frogs Mount t em in human and humateurs groupe. Real Funj and pe ditable ton This is included in og Craft at Moretty tay deep it a socioled in og management of the Charlest and the school.

#### Is Taxidermy Profitable?

Websiteret at NO OTHER S. S. St SSoffers from 5 Al. 1150 A Ch THE ATTEND WONDERD EL SPRESTALIN HOS

#### Learn Tenning

Ten Reg harries, sale and chrome teathers me fact to be her or the gert Methods, easy bears of \$400 Make Morey turn of for a here Duck Sure Profits. The Free Book tells shout Rend cospon



## Coupon

Or a posteard will do. No obligation on your part. The beautiful Book, with hundreds of entrancing Pictures is Free. Do not must this wonderful epportunity to obtain the marrisons and valuable book FREE and PU-T-PAID. Write today, State your Age.

MOSTHWESTERN SCHOOL OF TAXIDERMY 3391 Elwood Bldg.

Northwestern School of Taxidermy, 3391 Elegad Bidgs, Ornaha Hous, Sano man and free atta to back How to 11 and same A of me now I may to "I ant same A of the new may been the factorating art assety and quickly bent

masi, No shiqai	iam, : lale pusi ega,	The same
Name		4

Omaka, Neb-

your own

Tiophies

## "YOU ARE UNDER ARREST"



There's a Thrill in Bringing a Crook to Justice Through Scientific

## ETECTION

I have taught thousands of men and women this exciting, profitable, pleasant profession. Let me teach you, too, in your own home. Prepare yourself in your leisure time to fill a responsible, steady, well-paid position in a very short time and at very small cost, What amora have done you, too, can do.

53% of all American Bureaus of



Employ I.A 8. students or graduates. "I will teach you Finger Print Identification-Firearms Identification-Police Photography-and Secret Service." That a what I told the men who now hendle jobs in Identification Bureaus throughout the nation.

And now I repeat. THIS time to YOU . . . Just give me a chance and I'll train you at home to fill an important position in the fascinating field of accentific crime detection. It is not expensive or difficult to learn Now is the time to start. War conditions make it necessary to guard against sabotage by enemy aliens. Finger Print identification is one of the recognised means of uncovering them. The need of more Finger Print experts is evident. Fit yourself now to help win the war and later on to hold down a fine job as a recognized expert in Crime Detection.

"BLUE BOOK OF CRIME" It's a thriller, fi.led from cover to

cover with exciting information on scientific trime detection. It tells about some of the most interesting crimes of modern times, and how the criminals were brought to justice through the very methods which you are taught at I.A S. The book will tell you, foo, how at a cost so low you shouldn't even think of it, you can get started on this important work without delay. Don't wait, Clip the coupon and send it along today

INSTITUTE OF APPLIED SCIENCE Dept. 1361, 1920 Sunwyside Ave. Chicago 40, Ill.

INSTITUTE OF APPLIED SCIENCE, 1820 Sunnysida Avg., Bupt. 1361, Chicago 40, III. Gentlemen: Without obligation, send me the Blue Book of Crime," and complete list of Identification Bureaus employing your students or graduates, together with your low prices and Easy Terms Offer. (Literature will be sent ONLY to persons stating their age.)

rolando de la Agranda de la Calenda de L

## BACKACHE, **LEG PAINS MAY** BE DANGER SIGN

Of Tired Kidneys

If backache and leg pains are making you miserable, don't just complain and do nothing about them Nature may be warning you that your kidneys need attention,

The kidneys are Nature's chief way of taking excess seids and poisonous waste out of the blood. They help most people pass about 3 pints a day.

If the 15 mues of kidney tubes and filters don't work well, poisonous waste matter stays in the blood, These poisons may start nagging backaches, rheumatic pains, leg pains, loss of pep and energy, getting up nights, swell-

ing, puffiness under the eyes, headaches and dizziness. Don't wait! Ask your druggist for Doan's Pills, used successfully by millions for over 40 years. They give happy relief and will belp the 15 miles of kidney tubes flush out poisonous waste from the blood, Get Doan's Pills.



THE TAMES AS ACCORDE OF DESIGNATURE TAIN R de H. dens Kins & C. by Mo.

WE BUY and put you in touch with other markets Catalog and copy of insurance life. Or aread the for Book to a second to the AMINI AN BMALL STOLE FAILURE. SUTOCOS ENTERPRISE CO., STEE.

SPECIAL FOR

AGENTS

UR CHART Sive Print 27" a 26" snaws how to find taught of any polygon 3 to 16 tides, read board foot and drace tables, ortagen scale caffee tables and many other v . Can be scaled down for model work as well as full scale to mann, Atas chart changing pitches to degrees for my with Right & Saws, Sond 50c in cole or money order. No Stampt of Chicks.

MASON & PARRIEM ENGINEERS.

2100 3 N. Bordick 54 Dept 71 R. I merrio M. ch gard OUR CHART

# EP AHEAD OF THE CROWD ROCKET YOUR AMBITIONS late reality

th age you want bon sh Fear solve problems quickly). Fascing he michous and experiments Write TODAY for storting FREE bruitlet and convincing FA TS or send B for a new received and a standard Quies Box 582 (c Harriete g Pd.

## **What Every Mason Wants**



We have Masome books and lodge supplies for Blue Lodge, Chapter, Commandery, Scottish Rite, and Shrine. OUR MITUALS ARE USED THE WORLD OVER

Send for free catalog of books and rituals for Masons, Odd Feliows. Knights of Pythias, Knights of Columbus Elks etc. EZRA A. COOK, Publisher, P. O. Box 796, SJ. Chicago 90, III.



Handreds of prospects near you specia-Hundreds of historic field you specially a produced at a contract war plants at a story of action demand their song warmin. Specially action demand their song warmin.

#### COMPLETE LINE

Leather and wool jackets, work shirts 2.0 shoe signer for own and women, Chera commissions Write today for FILES SALES OF TELL

MASON SHOE MFG. CO. Chippewa Falls, Wisc. Dept. M-235







## OITAIVA needs Trained men!

There is a constantly mounting demand for trained men in practically every branch of Aviation. And those who qualify for this vital work now, will be mady to go places in Aviation when it begins its tremendous peacetime commercial expansion. Here, at Embry-Riddle, you get thorough training which makes you a specialist in whatever branch you choost. If you really aspire to a bright future in Aviation, mail the coupon today Let us show you how easily and quickly you can be on your way to a real career. Now is the time to act!



and the second s
Dean of Encollments, Dept. V. Please send information on aviation training at Embry-Riddle  Auctiaft Engine Mechanic Course  Accepted Nechanic Course
Arceraft Deafting & Design  Arceraft Deafting & Production Illustration Radio Courses
Master Instrument Course Link Instructor's Course
Name Age
Address
City State



GENCIONE D. S. MARGAINS

O. D. Wood Blanchets (used \$2.25

U. B. Army Ration Sags (New) 48

U. S. Army Pup Yorks (used) 2 30

Slightly Used Army Colsson Wheels with
Axion 56 high, Wr., 222 his. 527 50

Othousands of other bargains in military
equidoor & sport goods for bunder farmer,
point Send The for 32 bags catalog veburned with first stder.

A. Mind N. R. P. P. Y. C. D.

6734 LESTER ST. Stickmond. VA.





NOW GET TOUGH DOUBLE-QUICK!

Learn how YOU can be dangerous. Lack brutes twice your size with only your bare bands, even when they are armed. This powerful fighting system is unbelievably efficient. You don't

offer and money-back guarantee, Hurry! Write today for FREB DETAILS. Nelson Co., 321 S. Wabash, Dept. A-503, Chicago

FIRE THIAL LESSON, Cash an on your sense of human AT HOME BY MAIL have fun Make money! No experience needed to start Write today for FILES LESSON AT ROME BY MAIL Have for percence needed to start Write tool ed postpaid. No obligation. Mosti Gag Carloon School, Bept. S. Argyle.



Tola new 128-page book, Blammering, Its Canne

and torresion describes the Bogne has Methon for actent the correct on it scanningly and as tering successful for it years flowing to Books, Deet, 1857, Carelo Tower, Indianapolis 4, Ind.



ENGINEERING, Broadcasting, Servlong Electronics, Aviation, Marine & Police Rad o taught thoraughly, sient to 3 years' college radio work School established 1874,

all expenses low Co-educational, Catalog free.

Dodge Institute. Dept. 503 Valparaise, Ind.



Will You West It and Show It to Friunds make band box time had 15° 1 17 1 17 BH 4 8 STONEFIELD 1330 W Marriage Drift A 821 Chicago

Bakers nake good money! Now Ith Industry in wages! Nearly trees proof New house at its Highest Course qual fire you. I drapper echaest estated on a contract if you're amb tous, and a first Fach. Fritting to destruct on to Baktus. Newtonet Eaking actions. 1125 Seightgare. Dept. 1262 Chicago.



temes from doctory claim or private; prober in pure t me a pendence and prepare pendence and prepare to by training at host o make good to can we hadety by training at house and quality my for 12 posses Abstract that tend at pure 12 possessed Book FREE Now! THE College of Buredish Manhage Deet 170. 1005. Ohio \$1. Checago 11.



# Mechanically Inclined Mon. HOME APPLIANCE REPAIRING Offers Big Money-Independence

America's War Made Industry

Restriction of manufacturing has meant that the men who know Home Appliance Repairing -fixing refrigerators, vacuum c caners, washing machines motors we ding a chel plating, etc. are resping a steady daily stream of do lars and building for themselves a permanent profitable business.

No Previous Experience Needed

The ability to build and use a tool plus an ambition to make money is all that you need to become a successful Repair Shop Owner

Full Time or Spare Time

Work as many hours as you want. \$5.00-\$5.00 an hour often

**New Course Tells All** 

Our new course on Home Appliance Repairing . . . profusely litustrated shows you in simple easy to understand language how to make all repairs build took you need end how to get husness to come to you. Price of course is so low that your savings on your own household repairs will quickly pay for it. Send today for complete FREE literature on how you too can get started.


#### CHRISTY SUPPLY CO.

2835 N. Central Ave.

Dapl. D-1201, Chicaga

## STUDY AT HOME

With A Chartered Educational Institution
Cotons in Engineering Electrical, Civil Mechanical Practing:
Architectural, Stram Associated Radio Structural, Mining Industrial Liginary Perole - Stating Chemical, Mining Industrial Liginary Perole - Stating Chemical, Mining Industrial Liginary Perole - Stating Chemical, Mining Industrial Liginary Peroles - Stating Physics:
Courses in ARTS AND SCIENCES Physics by Education, Letters:
Public Health, Redical Jurislymanance, Psychology Bocknings Physics:
Chemistry, Geology Polymonance, Psychology Law, Bustonia and
Communical Accounting; Mathematics Statinics: Agriculture,
McKinley Rodacecti Interporated 4610 AC Shoridae Wood, Chicago, 40



#### NEW FLUID DRIVE, HYDRAULIC SHIFT AND DIESEL ENGINES FULLY COVERED

Over 1500 pages—1540 illustrations showing itside views of modern cars, trucks and buses with instructions for all service jobs.

ASK TO SEE IT!—To dot This Assistance for Yourself Simply Fill in and Mail Coupon Today.

AUDEL, Publishers, 49 West 23rd St., New York, Man Audels new Auto Quide for free szammution, 1/0 K. I will send you \$1 in 7 days; then remit \$1 wanthly units price of \$4 is paid, Otherwise I will return it.

Names	 		
Address	 		
Occopation	 	+	1.6.5
Empleyed by	 		ir.s.m



#### TODAY'S INVENTIONS ARE KEYS TO THE FUTURE

Your IDEAS have a place in TODAY'S thinking—of war planners and peace planners. For it is to you that industry will turn for the time and labor saving devices—the new and improved products—that are NEEDED to bring about the marvels of tomorrow's world.

No matter what your idea is don't delay in

developing your invention. Once your patent is granted, it is yours, for 17 years—to sell or to license as you see fit. Many inventors are selling their patents NOW—to forward-thinking manufacturers who want to get into peacetime production as soon as the war ends.

WE'VE HELPED MEN LIKE YOU FOR NEARLY , INAME & BEFFERRY

Nearly all inventors take advantage of specialized Patent Attorney service. A competent staff is at your disposal—your application is pushed to a speedy conclusion—saving you time, money and trouble.



These two books give you all the information you need. They have helped many successful inventors—they can help you. Profusely film-traied, they outline clearly every after you benefit the give you take the tipe on here to brake team to vention practical; show detain of 115 fundamental mechanical movements. Also included with these two books—you get the "Evidence of Invention" form that will help establish your claim.

SEND FOR THEM TODAY—

**ЛИБТ МАШ ТИПЬ ЕЩИРОН** 

## VICTOR J. EVANS & Co.

SEGISTERED PATENT ATTORNEYS FOR NEARLY 50 YEARS SAO-A Mertin Building, Washington 6, D. C.

Please send me your books, "Patent Protection" and "When and How to Sell Your Invention "-also important "Evidence of Invention" form, wi hout cost or obligation

Name		 - 18181	77	
Address				
City and State				

#### It's YOUR future—Make the most of it!



#### Start now to earn the bigger pay in electrical repair

WAS there ever such an opportunity to get started

in electrical maintenance and repoly-and at top notch wages? Are you ready-with experience and ability to cash in on it? Others are getting just the sort of background needed-quick practical -to handle the great variety of electrical maintenance and repair work TODAY-from this well-known siectrical library. You can too!

#### OF ELECTRICAL THE LIBRARY MAINTENANCE AND REPAIR

5 vals., 1826 pages, 1724 Hestretions

Gives you the "know-how" to tackle any wiring or motor job. Pive books show you HOW-to install all types of motor and generator units-to inspect and repair motor starters and generators-to diagnose motor and generator troubles-to figure new windings for old cores-DC and AC windings-to test armeture windings-test induction motors, etc. etc. One book is full of trouble-shooting charts that show quickly symptoms, causes, specific remedies, atc

Take the first step toward improving YOUR future— Mail this coupon TODAY

No money down-special price-easy payments-PREE trial

McGraw-Hill Book Co., 330 W 42 St., New York 15, N. Y.

Send me for ten days free eministration the Electrical Main-leannes and Repair Library of estimations; the first send you \$1.40 is "O days and \$300 in daily was take processed \$13.60 a part of first wanted to it return books postpaid. To be sure primited shipment write passing and fid in all lines."

Home Addresse f dy and State

Pastijan.

Name of Cumpany

PSM 1 44

180 action photos and move-by-move directions make it possible to master Judo s overpowering "bag of tricks." This new, enlarged edition includes instruction in the best defensive and offensive holds for handto-hand combat in action





So cartain are we that you can martet Jude at home - without outside instruction — that we'll let you prove it to yourcell without your risking a panny. Just meil the coupon for your topy of JUDO: 41 LESSONS IN THE MODERN SCIENCE OF JIU JITSU Practice a few of the mavements. See how noth of the helds becames your servet stock-et-trade against emergency. Then return the book for refund within 7 days if for any reason you decide not to keep it.

#### \_\_\_ PRENTICE-HALL, INC., Dept. JT-20 70 Fifth Ave., New York 11, N. Y.

Please rush a cupy of July) 41 LESSONS IN THE MODITAL SCIENCE OF JIL JITSU to the undersigned I will pay personal \$4,50 olds personal back within 7 600s, for pefund. If I decide not to keep it.

ADDRESS

Check here if you prefer enclosing \$5 89 in full payment, Directly saving pentage: (fame refund quarantee.)

## SHORT of GASOLINE

Do you have to curtail your driving? Is your truck laid up? Your tractor idle? In short, is gasoline abortage burting you" Well, it needn't. You can generate your own gas from waste wood or cost and water' Such a generator can be made from scrap materials easily obtainable and attached to your car truck or tractor. Save money and help beat the Axis! Cash in on this vital knowledge Complete instructions \$1.50. Limited éillt₄na.

THE MATTHEWS MANUFACTURING CO., DEPT. 110 CALGARY, CANADA

Inventions can now be > a dia . Anten expense If you have a tactor eten for sale either unpatented or patented, write today!

bartered Institute of American Inventors Dept. 3, 631 Pa. Ave. N. W., Washington, D. C.

My Parsonal service assured structual courf. dence em all your patent problems. Bend me a model or drawing, or

sketch and description of your invention, and \$5.46. I will make a search and report presspily as to its patentalistly and send you a copy of my 72 page honeset. Or, if you profer to read my booklet first, write teday for FREB copy. Registered Patent Attorney.

L. F. Randelph, 340-D Columbian Bldg., Washington, D.C.

Mrite for free Book and "Cortification of Invention" form

427 SHOW BUILDING, WASHINGTON 1, D. C.

Learn

Splendid opportunities. Prepare in spare time. Easy plan. No previous experience peried, common school education sufficient Send for free booklet. Opportunities in Pho-tography. particulars and requirements


American School of Chotography 1313 Michigan Ave. Dept. 1361 Chicago, 141

water Comme Plat a Bridgework, etc. thath way to carn mechanism for the best to the first time First Eq. 11 MENT of Treels And MATER ALS INCLUDED WITH A Right Low to the bast terms Wells for FREE SHOR about the manney bearing profession that is not affected

MCCARRIE SCHOOL OF MECHANICAL DENTISTRY 207 N. Broad St. Dept 622 Prinadelphia. Pa.

NEW 2 to 1 cending course! New you can leave the वैद्यारी सामस्य disclinated the state accomplished master to pile at the state Learn rase way to multiply 4 figures by 4 figures by 4 figures and the state without using a dischanged multiply called, add tong cultures of figures this labels me about cut method. Learn horsepower stude cule, talescentists have them would measure peaks in set etc. Large 1 has a sed volume complete with magnetic. Only \$1 fit posteries. Satisfaction or reformed Armais freedom with your footent. Learness and Armais freedom with your footent.

Complete details, mail coopen TODAY! MILEM CO., 2015 Walson Pleane send frey deta lankest Short ht Mathemas re-und Practical Methanics Simplified. 'No obligation.



## Add a Language To Your Assets BY LINGUAPHONE

★ In War, in Peace, ability to speak another language is an asset which will tip the scales in your favor . . . open new opportunities, earn promotion.

ITALIAN SPANISH **PORTUGUESE** RUSSIAN JAPANESÉ

POLISH **NORWEGIAN** FRENCH GERMAN

or any of 20 other languages

#### Quickly, easily, correctly by LINGUAPHONE Ear-Eye METHOD

This omazingly simple and delightful way to learn to speak any of 29 languages in your own home is the work of 150 of the foremost language teachers of famous universities.

You merely LISTEN to the voice of native teachers. Your EYES follow the text and illustrations . . . and before you are aware you are repeating the questions and answers as notyrally as speaking with a notive.

Endorsed by educational authorities, Linguisphone is used by Army, Navy, Flying, Signal, Medical Corps and other services: by 14,000 schools, colleges and by more than one million home-study students. Do not confuse Linguephone Ear-Eye Method with any other.

Send for FREE book, Call for FREE Demonstration,

LINGUAPHONE INSTITUTE 58 RCA 8fdg. • New York (20), N. Y. • Ct 7-0830

#### ENGINEERI MONTHS

INDIANA

t surger in Aermantical, Chemical, Civil, Flectelral, Mechanical, and Badlo Engineering One year current in Badin and D'afting Covernment ap-TECHNICAL DE LA Croude School courses, Prep courses at most popules ous Law to the Lange Industrial center sporton, by to each part I he expenses knive at June September Iberman Cata or 814 E Washington Blvd. Ft. Wayne 2, Ind. Deportunity of the

#### MONEY-CARTOONING ? LEARN

Rease stript had method that has hatped truly eccution of Terry of A Pirates "Wash Tubles" Dut Ogressy "Wash Winds" Of Register Fe tern "Strange As It Seems. Secret Agent X.9. and many others Earn while fearing Rush for for It ture Chart die test cone shifts I and full details "State age." TCHROL, 4427 Mailwani U



No previous training or talent necessary. Unique Stuart System teaches you, by mail in 10 simple, easy-to-follow jessons to make excellent charcoal and oil likenesses Detailed guidance for your every step. Send for free book todes.

121 Monument Circle, Room 281, Indianapolis 9, Ind. Please send me free book and out ine of sessons.

Name			
Street			
City		State	

## DRAFTING





Get ready for a peacetime career. Look into the opportunities in Drafting. Read the want-ads for proof of the urgent demand for draftsmen in the aircraft, machinery, electrical and building fields. The draftsman always comes first on any new project in industry,—in peace or wartime.

#### The Draftsman—"The Key Man"

No new machines can be built, no airplanes constructed, no bridges or buildings erected, no ships or submarines launched until the draftsman has completed his work. Real immediate opportunities exist in Drafting—the profession upon which all construction is vitally dependent. Drafting is clean, interesting, well paid work. Investigate today what Drafting offers you

#### Learn in Spare Time.—at Home!

(or at the College In Chicago)

With our easy step-by-step method (and the tools we furnish! you can learn in your spare time at home. Convenient terms. Now is the time to prepare in Drafting for peacetime opportunities. Send the coupon or a post card for the Trial. Lesson and complete information,—all FREE.

	STREET, THE PARTY OF THE PARTY	
CHILDRES	TECHNICAL	COLLECE
		LULLUL
the state of the s		

CHICAGO	-		
A-215 Tech. @idg., 2 Yes.—please send n			
Aircroft Draftin	ie ing	☐ Machine ☐ Structo	P Drafting (a) Orafting
Architectural O	rafting		Construction
Address		न्यः दैः	* ***
City		State	Assessment the same
Occupation			Age





## NOW READY!

A practical, Illustrated Encyclopedla covering all phases of Sheet Metal Work Including Pattern Cutting, Pattern Develop-ment, and Shop Procedure -Developed by experts for Sheet Metal Workers, Layout Man, Machanics, and Students,

1001 KEY FACTS AT YOUR FINGER ENDS

10 Big Suctions, 354 Layeuts, 1800 West. FULLY INDEXED FOR READY REFERENCE in answering your layout problems. Easy to read and understand Well printed in clear type, Flexible covers,

1.430

COMPLETE - PAY ONLY \$1 A MO. To got this assistance for yourself simply (iii in and mail order today.

4	6. P. P. C.		Charlest L.		40.0	ALC: N	45.00		Marian	Warner .
L				shers,	-	77 C S T	4314	3 t	17 T T	I OTH
	Mall A	LOCK	SHEET	METAL	PATTER	NLAYO	DUT'S BO	OK. Pyl	CO 54 OF	7 Days
ı			( D. H. 1	will remit	B. L. Lee ?	daren a	md 21 se	onaltiv i	MARIO BA	a moid.
ł	Other	erfean d	will not	MATERIAL PROPERTY.						

NAME		 	**	 		 	
<b>PDOOK</b>	#E	 		 -	*		-
DECUP	ATION.					 	

Buy War Savings Bonds and Stamps requierly.

#### Got a HOT idea? OR A SWELL GADGET? Let's get ingether-our Engineering and Production Staff and our Unionted Financing will develop and POST WAR promote your brain-thild for P. W. P., and arrange PLANNING for patent. You are fully protected-Specializing in Plastics, Electronics, Metal or Wood, Write Today ADBRESS DEPT. @ BOX 2745, KANSAS CITY, MO

\* How to get the \* VOCABULARY yee wast WITHOUT using a DICTIONARY

HIGHER PRICED RESIDENT SCHOOL COURSE ONLY




A comp etc grac ta and higher priced STA DETAIL No a Villa sought our aft . Fag. years in our restent about Guarantes to increase and bros on the service of the free to increase on the service of the service

TX BURNS w 1. Learn you MOW to CREATE OR.G)NAL RTOONS of Rome that you may SELLI Course cours as least one, and lever \$60 Ministrations, All for Only.

Bood name and address for free details, BURNS SCHOOL, Dapt. S. Box 1268, DLEVELAN

Hunters also for relief at home until you are Temporary 11 ling Statels) Touthache remede Excellent for tampers and dedative coment filing material simple instructions,

Sullivan Products Co., Sox 435, So. Fallshurg, N. Y.



and Make up to \$12 in a Day!

Let me ernd you a union inflored to measure suit FREE
All A BOMLS, Just to 170 my rany plan and take a few
olders Make up to 812 m a day eastly. No experience
—no house-to-house canvassing necessary. Big opportently—full or spare time.

Send for imples—FREE OF COST. White this for
FRIE ATTI AL CIOTH SAMM EX

For our skeeting to a first age
no money M J Collie, PROCRETS TAILORtwo CO , 500 to Throop St., Dept. A 221 Chicago, fill



We build, elevanthem the vocal present not with singling leasement but by much actent firstly content aftent and rotal as evelope and absolutely guerantee complete satisfaction with counting Waste for Voice Bank FREE, front to an one under 17 hours and quicks a smed by parent.

PERFECT VOICE INSTITUTE, Studio 1361, 64 E. Lake 8t., Chicago, 10,

## Asthma Agony **Curbed First Day**

#### For Thousands of Sufferers

Choking, gasping, wheezing Bronchial Asthma attacks polson your system, rain your health and put a load on your heart Thomsands quickly and easily palaste recurring choking gasping Bronchia) Asthma symptoms with a doctor a prescription called Mendace to help nature remove thick strangling excess macus and promote freer breathing and restful aleep. Mendacu is not a smoke, dope or injection. Just pleasant tasteless tablets. Iron clad guarantee money back unless satisfactory. Mendaco is only 40c at druppiets.



DESIGN ENGINEERING

As once applications have proved the peacetime post of the of PLASTICS, for mady now for his tig post as companied frequency of form high wipsof position to Plastics had be in the entire in a part in the training consecutive available to obtain an in the age onto the training of Termonomy, Box 5-135 Greenwitte. Only

#### MEN, Feel Vitally Fit!


Amaro's contuctes-old Handu Becret stimulates entire system, restoring yourhful pep, strength and vigor in many cases Bene-fits assured on Money Back Guarantee, PREE information sent in plain, sessed envelops, Bend name, address today to BASIC SCIENCE, 475 ELIOT, DENVER 4, COLO.

ATUDY AT HOME for PERSON AL SUCLESS and LARGER PURINCES 32 years expert the or then the 100 000 mindens on a set 17 B. Degree awarded All tests furnished Easy payments Send for PRICE ROOK - "Law and Executive Guidance

AMERICAN EXTENSION SCHOOL OF LAW Dept. 37 S. B East Huron St. Chicago 11, 111.

## TYPEWRITERS

A 5 mp their Practical and Larent Barrier Barr It po WEBER TYPEWRITER MECHANICS SCHOOL



2-



#### Learn at Home in Spare Time

Begin now to turn spare hours into money. Be a draftemen. the connecting link between a mechanic and an engineer.
En by the wonderful opportunities for promot on that exist now No experience or artistic talent is needed. You don't have to leave your present job while tearning. Use spare time

American School, Bept. 80146. Drenel Ave., at 58th Street, Chicago 37, III.

Centremen | Send me FBEE information covering special training in subjects checked below. No obligation on my part

- Drafting and Design for men and wumen
- Cost Accounting for Mig Architecture and Building Automotive Engineering
- Rusiness Management
- | Electrical Engineering
- Diesel Enginerring
  High School Course
  Pinsiles
  Mechanical Engineering
  Ariation
  Radio Shiphuliding

MARIE

Address. . .

## for a great future in



## NG and ELEGIR



#### "Learn-by-Doing" on Real Radio Apparatus!

Asroorts, radio statione, film studios, ponce divit wave, televinon, indus-TRAINED RADIO SPECIAL. IST's Learn the or k practical way, on actual or apprent in the great once but be monet truining based on 45 years of "know-how".

## I'LL FINANCE

Don't let lack of money hold you buck. My pear lets you start now, has to on in easy non-cly payments who a your tracked and on the solt I be placed get not time work to belt pay living expenses at le training give son Lifet me Job Service as a Coyne graduate.

#### Prepares for Govt. License

Many of the better Radio jobs requere government acenne. Coy no has ceraded from the to proget in tent seconds, you learn to send Code you you do trouble-shooting. have le real transmitting equipment.

#### **Dozens of Branches to** Choose From

Why be entieted with a narrow nofocuse one when Ly rolling to a chart time on my Shope you an quality for unbinded again uncertaint RADIO AND FOR IT TROVICS. ted a few growing fields! These parages shew only a few of the big

#### SEND FOR FREE BOOK

Fully illustrated with hig pictures of my Shape-facts about your water No salesman will can. Act today)

#### R. C. LEWIS, Pres., RADIO DIV. COYNE ELECTRICAL SCHOOL 500 Sa. Panilea, Book. 14-48, Chicago 12

We have facilities for oven with hands and or plu sical disabilitieswrite for particulars.

H C. LEWIS, Pret.,	
RADIO DIV. COYNE ELECTRICAL SCHO	OL,
Send FREE RICH, Nobr Future in Madio	. and details
of easy "Pay After-Graduation plan.	,

RAD

-		_	_	-
1	4	Α	1	E

ADDRESS.

CITY

## POPULAR Opportunities (Abbited and Gully \$5 per word of not see the second section of the section of the second section of the section of the section of t

#### ADVERTISING

ADVERTISING p.s ed any publics ion lowest fales complete agency aervice. fikuled advertising merchand ing couneel. Rate, at and bookiet en stied. Ad et-tising Resilia Por Saie free Baker Agency 3302 West Dodge, Omaha, Ne-

MAIL-Order or agent ad reaching 1,000,000 fam. ice throughout United States \$15.40 tneb Newspaper magazine, making-hat ratebook, free Chicago Advertor & Agen-cy 20 SP West Jackson, Chicago

CARTOONS for your Advertising, Up to 1 square inches \$1.00. Send dollar with copy to Henry Littlejohn, Box Zi, Green-ville, South Carolina.

ADVERTISE 24 Words, 148 newspapers 46 50. Lists Free. Advertising Burray 4815 P Cottage Grove, Chicago 15

24 WORDS 10 newspapers 12 to Goodale 37 Oardner, Valeto Califo na.

EVERYONE With Anyone in the Service wants a Personalized Honor Seroll and Service Record. Timely, fast sellers, pro-fitable. Complete data on request or \$2 gets Sales Kir with samples and his amount ref nded upon rathern of Kit or of er \$20 anies. Harry P Late Service, \$42 West \$5th Street N Y 18, N Y

AMBITIOUS School Seniors Sell Class mates its "tope" in Oraquation Name Cards Sest Commissions, Free Cards Agencies 4 ing ika wildhre, Hurry! Craft-tards. Box 238-M, Fittsburgh 10, Pa

BCKOOL Sentors—Sell America 8 most beautiful, distinctive Graduation Name Carde, Positively highest commission. Low-est prices. Free sample kir. P. picratt 1423 East Elm Street Screeton Pa

QOOD Paying Buildess St. Fring mirrors. pin . g surops a reflectors b: scient bathroom fix of some of by are merhod. No tanks of about my steel on fix fix abed Free Bouker Conmetal Co. A. e. G. De ent r. Labour

TAKE orders for new sense sone. Plastic Lifet the Reptodur tone of all pho o of negative Amating vibence it Bureau a opportunity Park or full time. Oct details quick v. Quaker Service Co. 914 Walnut Bt. Ph. adelp via Pa

EXCELIENT Between for Printing Sales men Decalcoma is Name I's expression tale on Automobiles Free Samples Raico 1483 Washington Boxon tale

CALL on founds with G esting Ca d As notiments Easter Brithday giver occu Mona Personal Bia tonery G is Wraph and Big profit a Experience of hetereasty Sain les on approval We lace Br with 125 Fifth

WRITE for his package actual sample lab rice and styles Absolute. Free dresses lingerie hasers at ris et Take order Commusia s big Send no motes. We effor your Free line idea Me a Company Dept 1757 Cr. nat. Obio Wre

ACIENTS It's new it's her Everyone wants rad ant plastic Lunch Kit Sample en trial Comm wong advanced. We de liver Collect Kondon, Box 157, Upper Darby Pa

BUY Direct-Cave 50', or more un Tonica, Linimenta, Herbs, Herb Teas, Ointments, Vitamina, etc. Write for Free details of day Cellonia Medicine Co. 10 6 Len rail Ave. Cincinnati, Ohio. Dept. P.S.M.

BEND stamp for bargate sheet on 30 use tal Xmas g to 1 ems from 25c 0 8 7 50 Goldsh e.d Products, Dept. 8, 150 Green-wich Street, N Y

OOLD Laco eved window sprn le ters. New styles, Absolutely beautiful. Pree sam-ples—catalogue Atlas 7941 Halated, Chi-Chico

Profitable scher to thousands of homes LUMINOUS Pant stores, offices, and factories, Details, Ward, 97B, Baybruck, Connecticut.

HANDY Hair Trimmer, Bells like wild. Trims as you comb. Saves barber bills, Samples sent on trial. Kristee, 131, Akron,

PLAYING card game, 250°, profit Sample game 25c. Box 142, Denver 1, Colorado.

FREE Water and our concentrates makes flavors, lottons aframpoos 72 prod a 5 labels, bo-tles furnished. Qualco, F 20040.

AGENTS-300 . Profit seiling Gold Leaf Window Letters; stores and offices. Free samples Metallic Letter Co., 437 N. Clark.

LICK After war invoffs' Blatt own bustness home office Booklet describ it Collection of 171 Tested Plans free Elder

Co 2 4A Grand B. New York LIFETIME Business' Man factore a mple products' Profits 500 to 5 000 Informs tion free Thermopiab Peorta 4 I know SELL Parnous He Zil Arch Write Everett Foot Cushion Company Everett

MIDGET B ble Charma L terat re Free if Tooker 630 K Chestian, Raminon.

#### AIR CONDITIONING

PURE Air assistes greater comfoct better health increased production impfat gue lenare Unit maily instance anywhere Low Write for details Eimer Goodson Careton Wyoming

#### AMERICAN POLICE JIC JITSU

SUPER Ju-Jitsu-Lightning defense and a tack system. Sensational new home study course now ready! Learn to lick brutes twice details, Nelson Co., Dept. 509. Chicago

#### ANTIQUES, RELICS INDIAN GOODS

276 ANTIQUE Pirearms, Swords, Car-tridges, Rifes, Indian Relits. Catalog. 10c (Photographs of Most ) Helke, Wenozut. III.

6WORDS rapters daggers pixtu a smot most and catalog 25c Robert Abels 36c , Lex gion Ave N Y

PREHISTORIC 5: one Tomahawk \$1 00, 100 good Prebistoric Arrowheads \$3 00. List free. Lear a. Glenwood. Arkansas,

25 GENUINE Indian Arrow beeds, \$1 00. Catalog, Geo, Holder, Glenwood, Ark.

#### AUTHORS SERVICE.

NEW Writers Wanted to re-write total in papers, magazines, books. Splended op-portunity to "break into problette wit-ng field. Rush postcard for Free Details Comfort. Writer's Service. 210 R. South Seventh, (2), St. Louis, Mo

TECHNICAL and professional mes- exect, es a perstant Wr, e arte es for te l' nical magazines We se , o editora Free d'am à ar un Bux 89. He pharmon N.Y.

#### AUTOMOBILES.

BAVE Osseline and your Motor Improved Octone Hyperlube the Synchronistic Hyperlubric Motor Portifying Super Fiel Energizer, Bend One Do ar for 900 Miles of Ot at a Hiperlube Motor Main enable Agents Wanted, Money Back Charantee H per abe to Box 46 Long Island City

WHIRI GAS Tarbinatur \$3 b ings remark ab a efficient economic motor perform three by cyclor it raportial to be that as to Wrench that also be intimuted to be a see that a see that as to make, year John Hanley 5719 Loraine Detrott B. Machigan

AUTOMOBILE Racing Book Pitth Edition -Revised. Tells how to build dart track bod es frames era nes Records superchargers rules form to pians, stock con-versions, roadster racing, fast Fords \$1.00 postpaid \$1.15 COD. Ray Kuns. Depart-ment 274 Mad south le Cochnosti. Ohio.

SAVE One With Morp-Pure" new scientific laboratory to ed tablet Users report any regard up to 40. Res in gran as eed 3, 00 parkage treats 140 gal into I beral support 25c. Free literature Moro P et Distributors Ames Station Omaha Nebraska

RENEW car batteries inexpensively inrine. Wasconstn.

1941 IONITION Supercharger \$3 50 Fast star ing M leage Pep EO Bases Mig. Co 50 John Street N Y

#### AUTO SUPPLIES & EQUIPMENT

USED parts (Guaranteed) All cars. Describe needs fully; immediate reply, Victory, 243914 Gunglson, Chicago.

CLYMER Chromed Spotlight for Automobues Motorcyces, Bonta Hunters Trigger switch purol grip, very powerful off any 5-5 battery Reduced to \$5.00 postpaid. Chimer to firm A uniform Pistons V for Model: A \$1.00 each California combination set Dua, Mumers V I and Mercury saves gasoline, beautiful deep lone, \$20 00 comple e C'viner, 2,25 W. Picu Los Angeles 8 Cauli rolla

DIESEL conversions for auto, tractor and Mar ne engines Cheap installation, Wonderful performance Proven farity method. Different and better Costs nothing to investigate Write for free cirruget No 3 Harring on Company 201-204 Manthester Bidg Portland Oregon

LATEST Scient Sc Discovery New miracle star saver Su e a most 30 Ouaranteed read of Profit very harmies to motors 5, supply from a 140 ga long (Liberal supply 25c) Oua c labri Taba 636 Howard Avenue, Brooklyn, New York

1,000 MOTORISTS peeded to make gas saving test Up to 10 savings Por free test offer write Vacu-matic Carburetor Co., 7617-883 W State S Washa-TORE. WIR

AUTOMOBILE Pitel without gaso' ne Guaranteed formula send \$1 loday, United Research Box [3] Orange N J

ANTI Preeze noncorronice trespensive, manufacture you sed Send ic stamp Bette Bux 499 Borger Texas

OASLESS Oas! Quickly, Easily Com-pounded Formula, 25c, Duffy, J47 Coung on Kenneky

#### AVIATION

AIRPLANES SIES up. Motors, crackups. parts. Send 25c for latest War-Bargam Catalogue Used Aircraft Directory Ath-Mr. Ohid

PROPELIERS of Quarter at types in-cud g J budge for steds bears. Line free Fird movie conserse in diagrams 25c Fandard Actor all F. World Tilk

BULLD a difference own me provide now-eted monoplane from Test cheap Tested paint guaranteed \$1.00 Aero ech Dea hour M. h.

#### BATTERIES, GENERATORS, LTC.

KLABON Batteries Power Ligh Five year guarantees. Fit sen vear le Complete lighting equipment Free Aterature Bee-Jay Company, 321 Youkers Avenue. You-kers. New York.

#### BOATS, OUTBOARD MOTORS, ETC.

FULL are cut to shape boat patterns, b sepring 7, 36 feet 1 lastra ed Band a Boat cate og 10c (cott) How o Build Boats book 8 00 Cievelard Boat B seprint Co., Station A-77, Clevehard Oh w

MARINE Power Eas y con ert any Ford thator 'dothestic a d Jure gay w h Os o par a gad k a Compere ca a sque 25c (roin) Osco Motors Corp., 2027-29 N. Law-

OUTBOARD Motors. Used and Rebuilts. Save money Used parts. Bargein list free. Crandall-Hicks, 155 Commonwealth, Boston, Mass.

#### BODY BUILDING COURSES

SUPER system of Natural Physical Training. Free booklet. Harry Good, 3361-PE, Watson Road, St. Louis 9, Mo.

DEADLY Judo, Wrestling, Boxing, Stamp brings (free offer) details. Variety House, Box 56 C, Station N, New York Olly,

#### BOOKS, PERIODICALS

MAGAZINES Bust ess Vocations, Diveraton Current single copies Choose from 360 different publications covering ad er thong art motomorale a taion, building dairving hobbies absorber interacre interacre. metal working. music, postery, radio, refrigeration, aports, transports-tion and more than 150 other fields. List with prices free Commercial Engraving Publishing Co., 140 North Retter, Indian-apoles I Indiana

WANT to Convert grams to ounces-min-utes to tadiants B I U to EWHrs? Let the Engineer's Pocket Diary and Address Book con a ning Tables of Conversion Facfore for Engineers save you time. Handy porket size-only \$1.00 pos pa d Room 901, General Electric Building New York 22, ADULT Books -Catalog, Sample 25c. Le-lavor, Box 571, San Bernardino, Calif. FIRST Aid—Be prepared to render Pirst
Ad, Most complete pocket size Pirst
Ad instruction booklet ever printed, illustrations, charts, etc. Send 50c today.
Gus J Schaffner Co Arasm Pa

ANY Book New Used On of sprint, Rarel promp it supp. ed. Lower prices. Set d. for free bargain ce alogue. Old Prof. : Book. Bhop. 8.6 Arcadia Court. Poutiac. Mich.

CHINESE Privar and Serie's 145 pages rare illustrations, unpublished trub secret healing arts, peculiar custom. \$1 Write Oarding Lui. Box 6227, Metropoli tan Station, Los Angeles, California.

EDUCATIONAL Books sold cheapty or rented for small fee. Books bought, Money back guarantee a 700 Havga of Calaing Free ICourses Bought) Lee Mountain, Pagah A labartia

Se HUYS back-dated magazines, Foreign domestic, arts. Catalogs 10c. Civersore a Magazzana, BAJ Pirsa Ave., New York 17, N Y

EXCELLENT Sparetime profits handling tal Catalogue, Starting Supplies Free Pines Bubscriptions, Plushing, N. Y.

BOOKH rout-of-print, new used) quickly supplied many 35c bargains. Catalogue. T Jamacushi, 18870 Mark Ave. Detroit 3

t 'Oll Inl' O'er T'e Treasury he d ing" exposes the "Money Trust"; cloth 01 00. Ur detatand Money! Meador Publishing Co., 324 Newbury, Boston 15, Mass. PHOTOGRAPHS! Pictures! Books! Lat-Oakland 6. Castfornia

"PROVIKEBBIVE Malltrade," leading ma 1 order magazines, 52 page sample copy, 10c. R. Burgess, Talladega, Alabama.

BOOKS Periodicals any st. lect, as do en What do you need? Doharty \$122 Eud-Jam, Chicago 30, Illinois.

EDI CATIONAL Books, not found in Book Stores, Write today, Erthainen Sales, 3'86 16 A. her Ch ago

FOR Mon. Thrilling Pres Book Offer. Blamp brings details. Variety House, Box 56-B, Station N. New York City

"A RATIONAL View of Life"-40c. Ben-Jamin Beibert, Urbana, Ohio.

ADULT books, Sample and estalog, 10c. Austone, 200 Lunanburg, Mass

#### AUILD IT YOURSELF

PRINTS and Instructions for building parden trac or \$1, William Tanger, Beliafor a neighbor of

#### BUSINESS OPPORTUNITIES

PLANTEX Industries offer industribus man an opportunity to start a business of their own, manufacturing art goods, no-cities and utility products in Plantex ard marble investion by material makes res what 100 store seller. Rubber mulds In h abed for speed profit in Bole in their
ment brings but to selle Bole in their
paring big claim a one orders with manutant was Amber our men base claims or
real prospet of Paster India ries Dept
B 1986 Weahlington Ave., New York, N. T.

EXPERIENCED Brokkeepers Accomplants to \$5000 Peec as Cost Consultants mata. ling new modern practical cost systems. Learn direct from Philadelphia firm of successful Professional Cont Consultants and Industria A a s a Practice Pr 21 able less Comprehensive Parts or les sous \$5 50 per les a Write or Regi er though W O More 111 Oak Termon Merchanty Be New Jersey

BOMEWORKERS 650 00, 675.00, \$100 00 Weekly Castwood plastic gifts, placques, novelties. Material molds instructions furnished. Sample large scottle, woodcut, mold morada no h epted his frig circulat mode with a cated his trig circulation the grown and categorie burndled new Set bir mode \$ 00 Prespaid, Pinaus Products, 1416 Beamont, Clicago,

COLOR Concrete with chamicals. Stuccorock, Coment Artistry, Wishing wells bold concrete pottery, Benches, Garden Ornaments, Cold glass, concrete pan a marbling Sample 10c Holya and Comen Craft, \$330 Wonderband, Hallywood 44. Calif

START Home Business making statuary plaques, art goods, noveltes, souvenirs concrete pottery garden first a art-ficial marble flooring inquid marble Make your own fieldle moids. Amazing profits Valuable folder free. Creative Publishers, PS1, Giencos, Illinois.

EARN Money at home. Opportun ties, 10c. Dot, Highland, Wheening W Vo.

MECHANICALI Y Inclined Men- Own and operate genera Appliance Repair shop omplete a latra ed coulte shows you we Weld it Refrigeration Motor re-Compare. how Welding Reingerston Motor re-part How to get but teas, etc. an phases covered. Free itera its Christy Bupper Dept 735 Zhi5 N Central Ave Chicago.

LIQUID Marble andwwhite mult rot-wrd Gazed Unguard, Conposition Planting I to ame wear Any color No-prin. Tee Flexible much Planter carring the mice the big moder now Fill h or-written given free Write-Occupa Tex Box 186-F. St. Louis Mo

BUCCESSPUL mark Jer e ers cite campaigns, planted he en the directived experience proporting boosts. Beer to dive over the production In vestigate! Finkle Advertising 12011; South Ogden, Los Angeles 25, California

GOOD Paying Plathesa Silvering bureo a plat in air paris. reflectors by cles-buttermen flavores ere to la e me tod N. tanas or shop required, outfit furnished. Per Booker Ounmetal Co., Ava. E., Deca ur Lat. 15

LEARN Hell gets inn Bes tre. Open to f this become demail capital logisted and the Fire expost such for useer Kasy then hoset Mechania fiction Dept 2 21 470, West P o Los Angre 6 CAN'T Leave Home? Help Waraldes by

mail-To qualify quickly for national drive read "False and True Mail Order Sales" 10c coin, Waraides, X 26. Gunder, Oukpark, 111

MAL. Order Business Course shows you how o make morey spore or fulltime. Teacher profession .. mall order technique not pen-

POR' IPY 1 to 1 to Own Bushess No. Make a Plant. Name of the Post PAINT Signs for Profit with a d of letterarm patterns. Free literal re Sample Be ' p'e For Hamilton Sta. Bracks p. B. New York 127 WAYS to make money in home or office, business of your own Full per office, business of your own Full per St., New York.

FFART Profitable collection business your community. Fine income assured. Convincing Bigrature free. Matrison Business Betwee. Pontotoc Miss.

BE independent, operate a pleasant profitable b. new of 7 or own. Rush toe to G Jepson, 271 Almond St., Sait Lake, Utah, for complete plan.

200 EXPOSED secrets-Tricks-Maylo-Rare formulas-Literatura Prec. Write Franco France 316 Kiefaber Day of 000

HOW In Make Surple Made and Placer Book et 15e P as er raft 1406 E. 43rd St., Cleveland 3. Ohio

BELL Books, plans and folios by mail ing plan for one dime. E. Minnick Co.

Sperating Simplified Tax-bookkeeping Statem locally Permanent, Write, Thrifty, The of Trinks

INCORPORATE In Delaware, Many Many ad Paul Company, Inc., Belawate

OFFHATE New paper C troing B earlies as a region of the Paper of which Post Madison are fine the 2"

YOU Too can leave how to make make and east Real Plastics, Send stemped er re ne Box 436 Garan e

BITH TIME B a ness Mail of the a Stamp beings details Da. on Box 1363, Seattle, Washington

TURN Accounts into cash, Good income quick results. Newark. Ohio. Collectors Association,

PATING Mail Business—stamp by car proof Orneral Pub. cut one. Ossuring !

ture, Big Mail, 10c. Lloyde a 250 R & ers Investment Bidg San Francis of Cabi 250 FRESENT Day Opportunities. 75 pages, 25c. Home Industries, 1325 S. 30 A. Omaha, Nebraska

SELL Books By Mail. Easy Profits, Lytis Supply Co., Avenue 14, Fredericks. hurg, Ohio,

AMAZING profits making carmelcorn. Country and formula 50c, Relph Brooks,

Arkansan Was MAKE M res at home in spare time by mail Wille Oordon Publishers, Box 21, Pas acket R I

MOLD MAKING Plaster tasting Money-

making Bis. ess. Lie nture Free. Ken o Park Hinge Limites SWISS Music Box Works—\$1 05 to \$2.25.

Suitable for many novel w. Mermor Manufacturers, 147 West 48th fitreet. H Y Mermod Types mer Muchine en Bebook, Simplified homestudy Repairing Increating. Conton 5. Ohio.

READ Robert Collier a Home Mail Order Methods, Get M day trial offer, Dow-pos, 1217 Park Row Bldg N Y

MONEY Making Ideas, Latest Books, 'Cara'ng Come 'Russell, \$12-B Anniston, 27 de a cha Austration

#### CAMERAS, PHOTO SUPPLIES

WE Par Top Prices for used comerce and plotograph conjugated. To o Bete:up and equipment ate a cash as a sale of what you have it Just send Bia'r make mode age for d. of We h it write you at thice to age is, what we I pay P o pure our is oday he d to Cup A Cabie a Co of her as apric Headq a sets a. to 1650 210 8 Wabash Ave Dept L 182, Chicago II bis

AMAIKI H. Photographers attention! Imbe a few to trake more white With day for our ed page book ca mon sed a sample trops of American Procugraphs, end end of the world a full most of the ston Management of 153 Newton H. Reston Management of the ston and stone stone

WE pay peak prices for cameras, lenses movie razneras, movie projectors, movie movie cameras, movie projectors, movie lenses, binoculars, Bell now! Write giving full particulars, condition or send in via railway express collect for free astimate of COD, with Inspection pri tege If no particular of the first transfer with the particular of the first of the first transfer of the first of the fir

BARR Box. War tille pr ves Buse landerone as le a Cotas Koresie Beffes, A g v new and tired a f new table Wrt.e your money refunded. Base buys 'em, se le em, trades 'em, Base Camera Company, Con St. 118 W Mad etc. 5. Ch ago, 1

CANH Root cash for cameras le see focusate, Ess is of acta, sound projectors. Send July description by mail, or wire for prompt cash offer. Over 30 rears of dependability insures honorabe des rigalisms Camera Company 178 West Madison. Sirect Chicago, Illinois

Oil on dipercepts a faccinating hotely or profession because Learn at those Passons on piece are ned Passons formation and requirements. No one, Art School, 1315 Michigan, Dept. 1741 Chi cate

Al Las Ar = d 1 gat be's ag patented develops : W rev apo, when not to me, LT-30 soft-working LT r med am contrast, Quart 60c. Graphic Economy Developer Co., 1624 S. Trumbull, Chicago

MAKE winne or 6. was apr. Learning gokly at home. Easy plan. Previous experience unnecessary Common school education suf-Scient, Booklet and requirements free, American School of Photography, 1215 Michigan Dept. 1761 Chicago

PRESS Ident festions" for accrede ed news gatherers, Press Supplies, 1834-8 Ekventh, Washington 1, D. C.

### CARTOONING, SIGN PAINTING, DRAWING AIDS

New Fals Method Oly are Comic Charters In a a Prepared by Ru-ET AS Delau Free Na or as Ar mia, P. O. BOX 4748 C Da as Teras

CARTOONING East me had course 36 estors 1000 para a e remplete 01 % Sample assor sheet free Home In-CARTOON course, Manual of plans, markets Car out been Detain. Resteman, 2638 W. Lincoln, Nebraska

#### CHAIR TALK STUNTS

CHATR Talks Laugh Producing Program \$1.10 Blue rated Catalog 20c Carroonist Basele. Oatskach, Wasconson

CHEMICALS & APPARATUS

CHEMISTRY Laboratory opposition and them rais for industral, a.m. ical, and experimental labora ories. Complete supp y service for a uder to taking correspond postage for free 66 page catalog Dept M26, Biological Supply Co., 1176 Mt. Hope Ave., Rochester I, N T

WINN 5 new idea Home Laboratory Chemscal K to and appere us on "to for home experiment of Se id a for it era is e and terms supply on a name of H White Confidence of 11 120 W 23 d St. N Y

100 DIFFERENT Chem to One of a sach Exce test coporto v for dir a feed labora ory stock to 90 M over fied labora ory State \$6.00 Mowelf Chemical Co., 1716 Second Ave. No.10 Chemical Co., P14 Se Minhespolis, Manpesols.

HANDBOOK for Chemical Experimenters. Hand odn of exper outs give rated to Experiment Hank et 15c ( emerg) Latable 5c. Reading Scientific Co., Read-

COLCHICINE-Evolution chemical creates new mutant plants. Illustrated booklet plus Experiments magazine 25c, Questop. Websley 6) Mass

26 Pikt E cheir ein) auf experimer bindelet, only I of Colorias Chemicas.

GI ASSWARD 40 pieces \$2.00 IS Chemicals \$ 50 Calaing Razikin, Olover Midg., Earnes C. Mo.

Lt M NOt S Pa min will g! w .n dark & t co.ors Pa rm ri Chemica. Co , 126 Lib-griy St. New York City 6

PREE Catalog Chemistry Marshing B. ology, Optica, Tracey Labora eries, Ev-

LABORATORY Spectroscope for themical analysis 22 50. McCutting Some, Camp-bell California.

268 PAOE Apparatus Catalog sent for 75c, 172 Page Chamical Catalog 25c, Laboratory Materials 73 7 Vicences Champs

PREE them to catalogue, Enclose 3c Post-age, Greenwood, 398 Broadway, N. Y.

#### C. I. N. IDS

OLASS Curtos, Minerais, Indian Relics, Crimes, New Mexico,

#### DETRUTEVES

DETECTIVE ira ing Secret mare on the --International Detective System, 1791 Moqtov NE. Washington III. D C

BETTITLE Training Phillips Secret Service, 1917-Q North Memoth, Chicago.

PINOS RPRINT punder new and a perfor pender. Waltam Crod. Box 602, Northtown Pa

DR PC71VES With home Travel Ex-P-126 West 96th, N. Y., N. Y.

#### DOGS, MINDS, PETS

STOP Munning Pits, Money back guaran-teed remedy \$1 bo. Circulars sent free, Edisto, Aile. Denmark, South Carolina ben e Frank e You'r RJ, Roverhead, Long Island, New York

#### DRAFTING INSTRUMENTS

ENGINERICS Timers Studen a New design of ruling pen permits longer use between reflik, Present pens reconditioned, New pens on market la er Cr. int in request Waller S. Kulen. Draumburg Pa. PREE ratalog of drafting an inches a a disapplies. Gordon s. 182-D Madison,

#### DRAWING A ART SUPPLIES

ART'S (S. Ou. Paultug. Set., 12 Tubes Chil. Coor '514 arrhes turper me braced on brus es pur e and annias bon d \$3 bs. Edward s # # 44 b Ave Pr = Pa

#### EDUCATIONAL & INSTRUCTION

HOW Secure is Your Job' How sound is your Harmen' Whether you are a cark, laborer, mechanic, inspector, etc., your chances for rea, lob secur y and success will be greater as his with Analysis knowledge. This is not core so had technologied to an east one who can read. Easily applicable to any Job or any business, and written by one of America's lead of war plant than the own descript your future. The price \$3.50 Mao Feder Training Systems, West Treaton, New Jersey. ton, New Jersey.

PSYCHOLOGY teaches about mrd Bio-Prychology taches about powers of mind over body Use powers substances as in ind Grow Breaden education Descriptorionality Con rollemations Burkerd Correspondence Dept P Taylor Behavior Big-Paythology, Chattanoga t Tens. PREPARE pourself now for a well paying factor post on after the war. Obtain your PCC commercial fadoutelephone a d lesegraph liceraes through our bode a uter a es Written for the man win "ag let en higher mathematics. An eas a fend ess ly understood course Made a s 7 on fee W s for part rulats. And ten Ra did Institute, 44 Kans 23rd Street, New York, N. Y

WELDING-E.sciric Arc, Learn quickly by sas Plat ce at Hobert West & Set as I to idital absolution a bate control of a single by a stal absence to a stalling by a stal absence to a session beginning Behood, But P 142

PREPARE. N w for the a car, e of America's Post-War Billions in business enterprises. Get set to secure your share. figuretal understanding. money, Particulars Pres, Educational Page 217 N H 'an Winter Kn sas

CLINICAL Laboratory Technicians in great me it your ewn home. You can place of while studying. Write for free caras Imper of Technical Institute, Box 973-B. A of D S. Leige

RADIO Engineering B ondessting Se ir Kiecizonina As a on Marie & Pro . o Radic a gh Listragi y Al supe ses sew to endes intel Catalog free Bodge Intel see Dept 500 Vaspara o Ind PROPHECY Club reveals prophers foresaw was a r d Det 62 met sets district to see Ristraging Reveators dimer Cry is here done Nation But 53 Wa fam Many

OCOO I seek educations bunkase also busels to ashit seed rented exchanged. He intacts in gian in feed. Complete details and 84 pages it is a reflector in a source of Williams with Company Dept. States. and BF A Dos or Learn clitteries in Past growing profession Residence course unly, Write for catalog Texas Chiroprac-to College San Pedro Park, Ban Autonio,

BE 'OMF a Deer r of Printeriogy 17% Dil Teach or et of circles men. Pape ce u of Universal Truth, \$451-A North Ashland,

EXCEPTIONAL Opportunity Operate & Levi Advice Code II read Quek ly learned. Many make \$5,000 yearly up. Write Cole Associates Syvacus. N Y

LEARN Me a lesepa ha Paptre a r friends leach sers Ear state of tions, 25c hast Box 1504 C. Cor eland

MAKE p to 825 \$35 week as a Trained Francial Muner Legen quickly at home Proker for Clicago School of Mursing top M 12 Ching

CHall Co respondence Crucies and Tech r as Bosa Hought S. id Her ed Cala log Free Educational Exchange Hanagar

REFRIGERATION Service Course, 24 ft-Pres to det, Marhanas School Dep B 22 470 West Piro, Lin Arabics 4 to Free Health Book W to K ST 2254CS No. h 72 d St M wanter W s

HOME Study course, drugless therapy Free Serature Institute of Druggess Dietapy Institute of Druggess

MASTERPIECE Charts — Anatomical Astronomical Color Science Scotts, Re-cearch De. (3) C ages Fan Francisco

ACCOL VIINO Quarty of this inexpen-leb fit its' free bountet. Adams School, 713 Ambassador Bidg., St. Louis

OCKSMITH Course, Lock picking key fitting, etc. \$1.00 prepaid, Miller's Ker Shop, Canadian, Texas

DRAFTING-Learn easily at home. Mon. roe Institute, PS-1, Alton. Illinois

#### ELECTRICAL SUPPLIES & EQUIP

ELECTRIC Pencil Weires-Engraves at Mein a \$1.00 postpaid Be er Mig 4515-O Cottage Grove, Chicago 15.

FOR Mor to Welders Ograns em On Ter call ems Write LeJay Mig. 371 TeJu Banding Minneapous, Mira

WIND Electric Motors Yourself. Write. Simplex, Box 260A, Pontise, Mich.

#### EMPLOYMENT RERVICE

BLL IABLE Is format on how to secure apie. did permanent maxied position. New Angles Explained Free hookie: Empire-ment Cr. relors Sedulla Missour

#### PAGINES, MOTORS, ETC

WINDING Data 225 motors, aingle and here phase 41.00 Motor Data, Box 7631 Kanses City 3, Mo

#### FARMA, OTHER REAL ESTATE

BER the Highlands of Louisians where water bridgs no idea arres. Choice and water and at low prices with terms Bend for descript is book without obligation. Long Ben Farm Land Corporation, No. R. A. Long B.dg., Manage City, Mo.

GOOD Form bargains Washington, Min-beiota, Monana Idaha, Oregon North Debo a. Dependable crops, favorable co-ma e. Wina for hierature fina des ribe g "pocal farma fine fr which aters. J. W. Man, 136 Northern Pambe Ry, St. Paul.

dree bang I andreds of proper as in all alter from Man e to Florina and west to the Mississipp, many partures, rock but-on prices W. a today for this make making time-saving book. Free, Strout Rearly, 255 ZB 4th Ave. New York 10 N Y

to ACRES, near White E.ver, unim, reaco poultry land, \$180; \$5 down, \$5 count.

Free list and literature, Hubbs of, 269 Grossman Bidg., Kansas City, Ka is 10 ACRES good land, \$250,00-\$10 to non n \$10 to mon hly. B. W Stewart, luver-

ness if reida MINNESOTA W some it Lake from our IT acrel 2602-C Rutherford, Hollywood 28,

#### FIFTD GLASSES, TELESCOPES, ETC.

MICROSCY, I.M. Telescopes. Bose is a and microscy, chemical ashers ony apparation bought, exclusioned En any ecologic bosons for Pf sea years. Not get ricking a hoper anters. Trust of labour the medical property of the pro h on sepata as, highest prices paid. Harry Russ, 66 W. Broadway, N. Y.

POWERPUL Telescope Lens Kil-Consists
I' diameter 75° focus objective-50X and
100X as focus of superces. While they
all \$1 to postured W b 50X terrestrail estree 62 15 Ph-1, Pfleeger Optical Lo.,

Mac ROSC OPER Resear h. Indus rial -Aria en. At Successes We sell-buy-re-pair en harge 1 queten invi ed. National M rescope hartmore. 118 Chambers St., New York M Y

ASTRONOMICAL Triescopes been large po red Send live ( of at all at a re-

Mic ROSc OFER Select he Tamerato y his one brug's and reps ed, and changed Ca also or George Kirm, 225 Fifth Avenue, New Y va

P.P.D Gravers brokulers, Tele sees By Set, Paul Schweer, Donnellson,

# PYIMEN Bermants Send for literature. V que, 7759 S. Helated, Chicago

#### FOR THE HOME

PREVENT Breakage Glass Coffee Makers. Details 25 cents, Donato, 23-23 Ellington Road, Fairlawn, New Jersey,

#### FOR INVESTORS

INVENTORS I dunity Need 1 r Idens New To Research | Manufacturates a certain dr. tig fracty him for post war same a. and 2 Runt now man a c seeding product the r experted in ... es fun products to take up the since of er war of detection to be a var change tomas in hips ent priver on time de sy blay er de leer y rechange thet out New Fine Lo er it a Stock fort a lid to able intell to Hesory. To se This respect does not obligate you. At now Write for day McMorrow & Berit an Patent At at leys, 143-Z Albes Bldg . Washing on E.D. C.

PATENT Your Idea. Write immediate y 

INVENTORS Lain now with tion grato he to proced a dear point of the form for establishing date of your invention—and Free Book "Patent Guide for the lien about patent procedure and to one en any it a along over 150 basic mer tancel movement a Deay may be costly.

For primpt in whiter the letter to feel or one A O Brief & Hartey Jacobson, Regio ered Palent Altothesis, 424 A Adams Building, Washington, D. C

POT VIAIN Per have you developed a new type? We have congresses with mai ufact irer prepared to buy outright or priduce on funal's beats predict of this

pe mee ing approva. Pa ent your idea a d comer is Pos War Panning Depar - Par Sc Nat Onal Adve 1 ng Agency, 645 Union St., Seattle I, Washington

INVENTORS: New military and commercial inventions uterally needed by manufacturers. Write for puriousity. Chartered Institute Dept. J.A. Wasting on D. C. MAVE, you a Patent? Will manufacture on shares. Campbell, 272 Mt. Vernon, Detroit Mich gap.

PATENTS, Inventions, Ideas promoted or financed, Allied Patents, Box 5781, Los Angeles \$5. California

NEW gland stimulating vitamin. Details accompany "Colchicing" offer, See

CASH for practical ideas and inventions.

#### FORMULAS, PLANS, ETC.

AUTHENTIC Formulary 924 pages (illustrated) 12 700 M mes making form as peripes, instructions, substitutes, \$2.00 postpace of COD, (Poreign, \$2.35) Catalog. Adams-Brown, Chestnut Hill, Mass.

#AVE those point brushes? Straight, pliatic as new after year of use a occationa, use How come? Bend 12 M for FROME Charles Truesdes, all Union Bire Rend, y Mass.

FORMULAS - Latest, best, Analysis, Latera are free K Seifort, Engineering Building, Chicago 6

PORMULAS-All kinds, Latest moneymakers, literature Free, Kemikal, Park Ridge, Ill.

126 ONE and two ingredient formulas, Descriptive circular free, June, 191-8 Besch, Holyoke Mass.

MEW gand star a stram n Detain accompany "Colchieine" after tee

PREE formula catalog. Latest money makers, Western Chemical Salem. Oregon.

#### FER FARMING

CHIN CHIN C ant Chinchilias, K or of Mabbers Most beaut ful fur, Sine in very set, Large Profit, Free illustrated book at Willow Brook Parm, R.D. 16. Sellerance Pa

#### GAMES & ENTERTAINMENT

Plays, Entertainment Came Books, Operettas, Minstrel Shows-Bongs, Skits, Betite tions—everything for your home talent show. A necessary Entertainment Source Book for families, individuals, schools, dramatic clubs, lodges, churches—any orsanization—for all occasions—all ages brac's in med of non-ber dior your Prelingest new? T B Decision & Company (Lerab and 1876, 223 North Walsah, Dept. At & C. rage 1

#### GARDI NING

PRINTS and Instructions for building garden tractor \$1. William Tanger, Scalefontaing, Ohio.

#### MEANING AIDS & REPAIRS

HEARING Aide Hepairs and Batteries Quick Service, Whotesale, retail gives teed Marshall Brown, 18 East Congress Street, Chicago, Illinois

#### HIGHGRADE SALESMEN

ADVERTIBING Book Matches, America's largest manufacturer of Union Label Book Matches, Past selling line, Large sales producing his flampie maties Compared on the Past Compared on makes white cast Commission in at the Past Open Match Compared Task Give world A e. Dept. P. I. Chicago.

CALESMEN—Saleswomen—6c (cost to you article sells on sight to workers everywhere for 25c, \$6 to \$10 day easy Send 25c coin for sample and full details Brumley Products, Dept 8, 1016 Champs Denver Colo.

#### HOBBIES, COLLECTIONS

OFN' INE A se a Ruby and Desert Supper Sent Quarter for both. Mineral Speciment Commany Box 2651 Phoenia.

UNUSED Match Book Covers 100 all different \$100. 25 Royal Flash Covers \$1.00 Free list, Charies Edelman, 1311F East \$4, Cleveland 3, Obio

MAKE Money With Hobbies! New book reveals many money-making plans for hobbyists! Only \$1. 3. Rahn, \$45 Bergen, Jersey City 4, N. J

ABALONE Shells—are—Beautiful Britdant—Natural Ash Trays. Two for \$1 00. cir for \$2 00. Parcel post collect, Abalone Shelm, Box \$13 Fort Braze Captorn a

FEW gland stimulating vitamin. Details arcompany Co-checter' offer Ser "Chemistry".

BEAUTIFUL Stones removed from rings. | etc. 100 second \$3.00 Lows. Box W 311 St Louis, Mo

PREE's Sensational fun feet magazine Sc firm age Hooky Elimon Q Liber's

#### HOME CRAFTSMEY

CRAPTISMEN make your hobby pay? Reproduce original works or anything, using Rom R by Firt ble Mouds 31 50 pauch Carra large Carvabloc, with directions and parterns, for Make tork and lown orname to up h 3-molor patterns 25c At Sept 1 pus paid and guaran ced, Rom Bottom 1, Whitestone N h C

28 LAWN Occament patients for Other patients as as as high patients, Durch girl, Dutch but on a w builterier, Mexican girl, Mexican buy dwarf, penauin, flower girl, 10c each 1 for 25c 25 runely patients 30c Au 67 full are patient to 8 90 pas paul product Box bull FB Bet a on W. St.

CATALOG: Tools, Decal Transfers, Patterns Novelty Furniture, Lawn Ornements, Schoosten, Letters & Numerala, Over I see 500 articles finely for railed Write We Met Shop, Ashburn, Georgia, LUCATE at d Pick glas y a statistic Make Corn may give Paris or rections

free (. to aire or \$1 o bargain assort nen' Transplantics, 21 Poilen, Boston 16

PLASTIC Lar to and Piergass Beautifully clear rous and above One provide assertime good street packet 6 90 Craft Beautifully plywood or edgedfibre kitchen cabinets, Plans 25c. Roger Underwood 44 7 Johnson Avenue, Western Springs 11 Junea

#### HOTEL TRAINING

GOOD Jobs for you in hotel and institutional field, wartime housing took and
recreation projects. Thousands of mep
and fromen—all news reeded for we
paid pour and that offer color excitement
ever new and lawars ng du tes Aurady
by to runder count act in are over I b,
not do are mer n of gusernment stread
and recreation at be ading, office n cute.
etc increases because their in hotels,
et he trained as in means even greater op
por univers. Lewis school receive a cute.
etc increases houteless, executive house
keepers of rebuilting ments, atewards
house a supernanta cafetoris directors,
etc. Pressour experience proved unnecessars? No need to leave your job to qually
I am a quasifier you at home in source
time. Our National Planettent Bu may
be pade place you, and under our around in
Cer feed Job Plan or as a guarant ere
you way, "make good" when placed. Write
total for free book! Lewis Hotel Training
is book. Room CA XSS, Washington I
D C (Plant and only school of its kindNow by its 28th year)

#### MUNTING

sport Cash for your Guns of Ammunition! Or Trade for merchandise in our
winter "Guaranteed Bargain Carains
featuring thousands of Guns and its &
to-get" items, send 25c for Catalog re
funded with Real order). We pay More
sell for Less because we handle (nones is
of guns in all models, gauges, militres,
both new and used, front 25 to \$1000 We
also buy or trade Reels, Rods Outhourds.
Typoc slave, Cameras, Radios, Watches,
Darma de Manie riv use price the
serthe your thurchandise fully Money
Back Guarantee, backed by two generations
of honorable dealing, Kimn's Sporting
Goods, 504J South Haisted, Chicago

#### INFORMATION

INFORMATION—How to locate most any article made in the United States (Dime Coin) Rakes Specialty Service, P-2051 West 35th St., Chicago 9, Illinois.

#### INVENTIONS WANTED

SUBMIT your ideas—patented or unpatented Many manufacturers are seeking new lieus suitable national distribution 15% commission. Albert G Burns—"The National Gudget Chief." Alameda, Can

invention for sale, patented or upper ented? If so, write Chartered Ins. 'e of American Inventors, Dept. 3-C. Washington D C

ATTENTION: Have you a waste product byproduct or sensible mechanical idea or device with wide commercial possibilities? Address Matt, 1613 Great Northern Bidg Chicago

patented so as to be manufactured with Power Presses. If Solomon Inc. 75 Epring Street New York Cl y

INVENTORS! Have you good patentable ideas! Write Mr. Metaler 11 West 42nd

INVENTORS—Fatented or unputented, we promote your invention. M. Butuphries.

212 Otto Bide., Phia., Pa.

CASH for Inventions Patented, unpat-

#### JEWS INT

OENTINE diamonds, out-of-pawn low prices. Wonderful values. Unredeemed home and hig buying power enable to the offer heartful gents at prices for inspection, Appraisal Bend for hig Free Lat showing fine diamonds at startling low prices. Loyd J. Butler, President, Prudential Loan Association, 112-OA North Clark St., Chicago 3.

#### AEGAL BURNE CORY

MEXICAN Logal Matters reliably handled.

A M r 2 200 J 4 e2 Mexico

MACHINARIA TONIS & ST PPITES

brow-Lewis Castings, Materials, Blus-priots are available on MRO, ratings for build a Mills, Shapers, Vises, Dr. 1 Presents and transporter parts, marking these and transporter parts, marking the deserting of the prior of the form was worse with Lewis Tens. Whe for a strated carsing demand of the form of the marking for Lewis Machine Tool to Box 16 Station A, Dept. 836, Los Angeles 31. California.

BUILD your tractor from second-hand automobiles! Convert your horse drawn farm equipment into tractor drawn eq. pment. Nolan's Garaga, East Wareham, Mass.

BUILD your own lathe grinder, castings, building his ear' us \$2.50 Pattentury soo. Star Machine Shop, Kingfisher, Onlate ma

STEEL beam trammels for draftsmen, engineers, mechanics, Circular Free, Clair Company Box 97 Bartisrbourne Station, Box 20 M Y

NEW enliper direct road up speeds up defense with cheep From municated cirrula: Pactory 5.1-H East Just. Hames City, Mo.

TW N C) u der A.c Compressors \$12 to Var mis M sin Hoffmann, 2740 Coy, Cincinnati, Ohio

RECLAIM dult and broken drills with Ru-Way for 1 Or der C trains free Tractor to-Mig. Co., Spirit Lake, Iowa. ON ND Drills L to Factory Attachment for Benen Or der Cheep Factory 011 A Ent 11 Ka sas t Ir Mo

SHARPEN Drills like factory free particu-

### MAGIC TRICKS, FLZ7IES, JOKER NOVELTIES

1943 EDITION Douglas famous Ontains of 500 Tricks you can do! All the latest with cards, coins, thimbles, he is ropes apparatus, books, illusions, 120 pages only let, in since Man and the se letter

QUALITY Magic since 1907. Three new catalogs ready, twenty-five cents each Book catalog and lists free. Theyers, Box 1765, Withhire-La Brea Station, Los Anseles 16. Calif

AMAZING Mystifying Tricks, Make Money Entertain Irlends Big mario package 25c. Ploneer Mario Studios, 4418-PS Clarence, St. Louis 5 M.

ROLLY WOOD Special. Magicians button catalog ghost litusion and free trick for 20. Marie Rouse of Charles, Box 5556, H. I. wood Calif

YOUR name accounting headlines, Hollywood newspaper 25c. Lefavor Arrow-head Springs, San Bernardine, Calif. LEARN Professional Magic in ten dear less.

worm. Success guaranteed. \$1.00. Dishle.

\$568 Poster Are., Worthington Ohio

WORLD S largest professional magic shop
keeps you in touch with latest tricks

To receive mailines send 25c for 1943 cats
ing Madens P-220 W 42s d 8s. New York

ing Hardens P-220 W 421 d Rt. New York
MA'-I IANA Charter are set et moned
to de luce P and Chill Martine
Co and for Book Co Box 672 84 Lenia

MAGE CTA'S H. Heads par ers. 21d page to 1 stea ed catalog 25. Kupter a. B-1316 War it. Physics hip. 7. Ph.

62 a Magician. Large professional magic catalog of intest tricks. 25c Ireland. F-109 North Dearborn, Chicago

#### MANUFACTURING

MODE'S small of manufact the metals, plastics, etc. Muhurn Burlington, Kentucky

#### MITER GOLDS

DA RY Goat Journal Dept 488 Columbia Mo Monthly magazine crammed with he pful information & year y introductory 5 march a theorie ton 25c

#### MISCELLANROUS

SEMBATIONAL The long Medican Cuhan art pictures, books, miscenshous, Same ex hats Sec, Jordan, 136-L Brighton St Buston

10 WATT Amplifier 2 12 speakers, Crystal Microphone, Willard Schuller, Columbus Orose, Ohio.

OREAT Fun Make bulget you are in New York Chicago, Mami, Canada. J carde sent, you write, return, I mail, 25c. 7-toc Letters 15c. Revers up forwarding souvenirs, Snappy fun cards, Girls pictures, Details, samples 10c. Agents wanted. Haller, 436 N. Y. Ave., Brooklyn 25, N. Y.

MED'CAL Laboratory Technicians in great demand. We train you in your apore time in your now home. Y a rain practice with a runding. We, a few free cata name imperial Technical Institute Bux 971-8. Austin 5, Texas.

MOONS Paning By The two Pating My The Man 1944 Man a dileminan 15c such Planetarium Box 1986 La Jone. City Contract

ENLARGERS Build your own, Kit of parts, \$6.00. Free particulars. Crescent Engineering, Box 251-C, South Pasadens,

NEEDED Civilian goods, supplies scarce Everyone Buy Sell Busp anythms. Ranky No mm to the god Water Highes Service, Shillington, Pa

OZARK Guide, Lonsdale, Arkansas, For

Опру. 35с WILL buy watchmaker tools in useable conthe traine paid. Armos Bosier Mulord, Pa.

GOT D Partie w & Premote & P. L. Tr. Deciser 4 Colorado

VICTORY Handkerchiefs, 250 part. Free catagon Hales s. 29 East 39th New

Oman 642 Broadway, St. Paul, Minnea trop

NECTIVE on a magadater soloped Your name in patter a But of to Ith Round 336 B course, New York

PHPR | term re how to norm a to ted treasure and more ale Figher Latera-tory, Palo Asto. Calif

PSYCHOLOGIST discovers amazing, new eary way to auccoss Details Free, Victor 475 El.ot. Denver 4. Colorado

PREE Drug Last-Dr 42 1 Z Robins, 26 South Hamilin, Chi ag 1 5 23

#### MODELS & MODEL SIPPLIES

Bill? model kits and Situas C noise line Fisher model packt equipment At Bourber haper Mar le Midel and Idea. K a fitting a d b sept that a sandrid prices. Mail complete study in New Eraland, James Bass & Cu., Inc., 220 State 61 Boston, Mass

COMPLETER wan p Moden Coach Moden Concred Wagon As parts but to the no shaping required stack histories only loss needed Everything its used mans wiresid ringing Bend Scistamp for estator Minis-ture Ship Modein. Dept. N. Perkusie, Pa-

MOST complete Illustrated Catalog—"O-HO OO Model Restrond Parts ever gub when Send Sc for man he Sent 117" Ontes Ave., Dept. 301, Brooklen N Y RAILWAY models, complete line informe tive catalogs. O Gauge 104 pages, 35c HO 10 pages 13c We there 200 krie, 36c. washee Wiscons a

TIM Pia e Richarders Natura re vitar road bed with ties Very Diespens e Postcard Brings debita Betach Cu 1345A Shaampeare A e Brick N. Y.

ILLUSTRATED Price List. Models, Pro-peders Supplies 50 Model Builders Supply, Hutchinson, Kansas

BHIP Mode, and va of supplies complete large 60 page Ca alog to 20th With With sarge 64 page Ca and to 20th W

PLANKS Boats, Hundreds of Hobby Items Calmon lo. America's Hobby Center, Dept 8-14, 40 E. Flat St., New York 10, M. Y MONEY MAKING OFFORTINITIES

Money making plans, formulas, other features galore, including Etiquette Golde Portune Telling Chart-Vitamin Chart Wonders of The Body M. racia Calendar — Grade to Perfect Sex Lure H w To In-treese Your Vocabusary or form at E. D. McAdarra, 12 Futh Avenue New York 3 N Y

MECHANICALLY Inch of Men. Own and operate general Appliance Repair shop Complete Lastrated course shows you how Welding, Refrigeration, Motor repair Row to get bus ness etc. An phesis covered. Pres Il statute. Christy Supply Dept. 1628, 2826 N. Cen. rel. Ave. Christy.

LEARN Me ascience Bemarkable drugiem hea og No man pula ion No apparat m Dobe syable a mp day and result. Instper et e curresp. ndence con ne. Write Meta ac ence. De Land, Pior da

CARM in on your sparetime, 100 tested movermakers 60 page book 25 cer's Bat staction or money but a guarance Pfetfler & Jamison, Box 4006, Washington,

'MAIL Order Neur' hrings proven, tested, money makers to start your own busi-ness, Sample copy No. Meets Pub., Box Weed, Caulornia

BALESMEN, Agenta Humo Workers agt them offers, we would be now elementere. Be the person to the Haman Berring, it I Breadwas New

pe d for Snappers (1, de 1's ) ; oppose a since 200 cap; Snappers (1, de 1's ) ; oppose a since 200 cap; Snappers (1, de 1 ) ; of the since 200 cap; Snappers (1, de 1) ; of the since 200 cap; snapp

Part 6 Tenarrow , Box 2360 P, etc. swood (a for 4

OPPORTUNITIES Galors, grant mails 10c sample matting free. Harvey Teepis, (PS) Decatur, Ind.

INTERESTING magazine Sc. Co-Publish-ers wanted, New Writer Benick, Holland,

BE your own boss. Operate a ingrazine :

\*\* har piton business at home. American

\*Readers' Service. Hatfield. Pa.

DETECTIVES fars Big Money, Experience unnecessary Particulars faw Wagner P. 175 West Mto M Y N Y

EARN money evenings, cupying and di-Comic-Ada, Argyle, Wiscons n

7 LEADING mad order magnitices-25c. N e h terprises Reno I Ne ada

MAKE Extra mice et al home details free TRADERS' Club atembers carn big money because? Anderson, Vineburg, Cant.

#### MONUMENTS.

MONUMENTS Direct Low Prices, Preight pa d. Onerapired Pres Calaba a descripies. We a Grande-Marks Pacture A49, Oneco. Florida.

#### VOTTON FICTURE & AUEND EQUIPMENT

White and Color, Sound or Blieft and White and Color, Sound or Blieft Largest selection ever compiled; The to \$100. We e for new Delays 1944 Catalog—proand Hillustrated! 35c (coin) refunded first proand Hollywood Movie Supply, Holand d Ca tort a

Ot analysis of Proch Make Bur' Theorem pools do his Sman 13 45' St. species Cities 42 40 Dailing load at the all rains to pe to Will ship O'O'D, estadog France and 1946 Central, Mahang City J. Mar-

JON 1 2 on Home Minus Pain C1 t 6 le s or So nd 8 ISSMI Same excha ged at usest rains Patte oats Lee Na . . L Excharge, Sta. E-Broadway, Toledo

16 vim 82 50 26 11 rot. Double 8 8, 25 MOVIE C Free Developing the Principles H bects having the er Frime, 742 New Lots H ork n 7 H Y

THE World's Orestest Panter Pant. Smm. 15 and 35 min, Specify Sound oc. 18 Ren of Path ast Hemenway Pin C. 33 & Me rose St Hoston 1) Ma a MOVIES for Men-Travel, comedy, glamgrammer san ple dine Reeley, 42 Pf Mar her, Comise, New York

YOUR Pres 1944 Home Movie Pilm and Accessories entalog now Ready. Set deard Easte Pists Products, 3827 Archer Arenue, Chicago 32, Illinois

paid. Write for list of complete audience. Blacksawk Flims, Dept. Frs. De ... enport, lows.

TORTIYE test ring so en He was a green from 50 to \$2.00 16000 on 14000 and 1

WANTED, Movie Projectors and Came at buy, trade. Goodwal Company, Jackson

M JAVE Plant 146 Ments \$1,90-45 C. inte-Berga 11 25 developing it sided A ha SALE—rent—enchange & 16mm 24 vs Send stamp for estalogue 1 ha ter F ms 853 Cosmo, Hollywood 28 Calif n a

NEW Film Lists and Exchange Pino Paramount Mig Company, Dept. M-30, Box 224 Backbes Boston 17 Mass.

I BUY drap-Rest dell fie i fein movie films. Herrey Iris, Bex 3.19 Brockton, Mass

51 AMOUR Newtreel Examples Dans 50 feet 8 mm only 8, 95 I ste a saided Wineholt, Woodbine 4, Pa

HOME Morres you dilke a temm. Ber rie Marshall, 413-P, Elmira, N Y

NEW Morle Plims-Wholesale! Pres C. stor Rarprise Sample: for Sipe in FOR Sale 35mm sound film projected

Box 2, Secaucus, New Jersey,

MIMM SOUND features! Shorts! Techni-color samples 10c, Democy, 1513 Stewart, Youngs wen, Ohio.

LEARN Movie Projection, Management, Pres catalog, Give ago, Theatre School, Cimira, N Y 81] ENT 8-16 mm Sound projectors H go-tel prices paid, Moguil's, 66 West 68th. Rd New York 19.

SEND stamp for 16mm, 2mm estalogue, S'erling's, 679 Northampton, Easton, Pa.

#### MOTORCYCLES AUCYCLES A

MOTORCY CIF May in 172 Page Arer - can "Questions-Answers" complete servicing information Harleys, Indiana, Hento us a Nerracycles U des to daing war to den \$1.10 Mar. ( ) Week-Two N age Me t en Si op S. 50 Two N age Me t en Si op S. 50 Two N age Me t en Si op THE Ideas Chr a man to ft for M av M errords Meria ica 435 juges 200 i lustrations, the most up-to-days and re-plete book on motorcycles ever issued. \$2.50 postpaid. Nichobson Brothers, Sesky toon. Canada.

M or personal M -100 Milles flates M ir Services M fore ies Whiter Bu ce hag et Mileet Auf miblies Cia Gile Eng en Notrept a Necessary P I jalumen e p es
y a ca to abig e dice t her 25
W Pico, Lie Angeles 6 Calif

Plans, Drawings, specification in ton-tions for building attractive Motor-proper complete \$3.00. Plans, instrucd see 8, 50 Scooter Causions attended in the Page W Plots, Los Angeles 6 Ca I ARRIVED carload motorcycle parts for history and Indians, Write us your needs. McCanb's, 2146 Texas Street, El needs.

Paso, Texas BEAUTIFUL Recap Motor-Scooler Tires Information catalog loc. Clymer, 2125 W Pico, Los Angeles & Calif.

MOTORCYCLE Parts, New and used, List 10c, Ballak, 811 N. Dib. St. Louis, Mo. MURICA MURICAL INSTRUMENTS

LEARN Popular Plano! Play but songs in boog e-awing style, Planats, send diffe for sample arrangement. Home-study fold er free. Christensen Budios, 765 Kleibeil Hal Chicago 4, In-

SON, WH. IRMS' Send your soums for o report and Free "Rhyming Di ' ner"
Phot wraph Records stade. Varide b '
Music Studios, Box 112, Dept. 4A, Copey Island, N Y

SONGWRITTES Write for Pres live fur-tive Booklet Outlining Opportunities. United Music Corporation, Dept. 31, Salem, Indiana,

WANTED! Lyrics, melodies for songs. We share p b. sh sels. Super or Song

PHONOGRAPH Records Slightly used 20 orn coch Roodwin Company, 4429 Broadway, Chicago, I cost.
Oth Goth, WATCHES, PRECIOUS STONES

COLD 137 00 Onnce Maled gon teeth carnelds fewerly watches free of cash h) return the l Saturda Lon glora steed. Free in Canadan Dr. Weshells (ind Refring Company, 1900 B Bernry h, Minimans a Male

MAIL old gold as a wiver watches, gold each lines jowners, dish and serviced one Cash return had short to round worth most beings had to conqueranteed. Information from Jews 14-

PATENT ATTORNEYS

INVENTORS Les e nos ion how to protect and sell your is from for as ablance of a section in onthe Towerfor one nutiting complete in fire rick into abreat the exp for each rich of her successful inventions, over 150 basic mechanical movements. Delay may be costly Put prompt contients, ser to we be-Chrence A. O'Brien & Harvey Jacobson Rug stered Patent A forneys 47B-A Acans Burd a Wasting on D C

INVENTORS Before ductor of the results of the control of the second of the form the conception, Schedule of Government and Attorney's Fees" and instructional feet free, Lancaster, Allware & Semmel, 413 Bowen Building, Washington D C

INVENTORS Bend for free copy my 72-page book on patents Reasonable terror Prompt action Confidential, per or al retu-te L. F. Randolph, Dept. 340-A, Warh-rigton D. C.

PATENTS Secured. Two valuable booklets. and When and Patent Protection Hew to Sell an invention together # 'h valuable Evidence of Invention form sent free. Write immediately to experiented patent course ore Victor J. Evans & Co. MI A Met in Bidg Wash turion & D

PROTECT your invention through medium of my expert personal service. Preliminary information without obligation, Horace L. Beall, \$62 P Street, M.W. 4, Washington D C

PATENTS-Trade marks. Prehminary acv.ce book and disclosure form free. Persona, service, Irvins L. McCathran 316 McLai den Brig Waanig on 1 D C Regatered Patent Allins

"INVENTOR 8 GUIDE" free, containing sbout petenting, selling inventions. Frank.

\*\*\* Ledermann, 154 Nassau St., New York. ' PATENT-Particulary" and Blanks, freeairmailed. Storling Buck, P-Hotel Plate.

Washington, D. C.

#### PATENTS

INVENTORS Foresighted manufactures t already planning pos war sale of new non in tary p. ed rts. If you have a useful intent on po en ad or unpoten ed ter to Chartered Institute of American Inventors, Dep. 1 8 Washington D C

#### PERSONAL

ATTRACT Success Feeith, happiness, through Ontology Solve your problems melaphysics of Discover your rest seef. Ontology illuminates the Scriptures, tea, has how to pray, reveals secret mind power. 24 page booklet Pres. Alexander Krene Seda a Massaut

DO Your Feet Burt? Irch? Burn? Sweat! Sme.!? Simple guaranteed home treatmenta elicitatie these inconveniences Read "Why Your Peet Hurt " \$1.00 peer pa d Educational Books, 237 E. Ruian,

PROR'ANTH B. Reck v. Pista in his brought ret of w en everyth in the latest the dries only as directed. Apply the same is dries quickly convenient. Try reg are 61 by the without investing a cont. We as Prince. Lab Box 1744 (leveland 3 Onle

LIVE a Lite of about dirg Happ on Hale Real West to Prosper to Low on the Unit Real Happ does a d Soccess of Out da Y prat 7 the Passar H J pant + On + 8 vo tra G Merrer HEAL H P mystr ) and Happine through Problem Advice and Truth Treatment Information free. Joseph Louis Scherts. 4413 Lindell Bird. St Let 4 M to per

biffens matters-Simply mix with wine or liquor to get pint of excellent Arigin turn type bitters. Order today, 25c-1 02 puckage. Desia Co., 2866 Avondose, Chi-CARO

TO enjoy good health use herbal home remedies for cold weather aliments. Free Information, Delfa Co., 1968 Avendate

MEN, why feel tired, old! Amuzing Hindu Secrets restors youthful pep and justy vigor Information Free, Rindu, 675 Eliot, Denver 4 Colorade

20 THRILLING "Pin-up Beaut as from miginal Hollywood photos fexclusive redistant to 1 00 Library Co. Dept. FR. Box This Del Valle Sta. Los A seles

Boft Waxen Ear Noise Stoppers Sample Pres Downes, 1215 Park Row Bldg., New

COROZOUS Christmas Foldets, 25 for the ar or 50 for Dollar, your name get of free Lafavor, Box 571, San Ber-PA d to Cull!

would you like your executit improved and do and garner Send 1 70 hr reinstructions. L. F. Neer Lake Worth, Fix 14 25QUIRE Deck Calendars-Twelve Var-

ga O'rls-80c-Require Agent, 1919 Gir-

BYPNOTASM Complete 29 Method Co. 25: Mertern Institute Hyprotism D. 4.9 Palat se I'l

LESRY Vent of m Jonam has part are Smith Dept 246 fol large low Per a 1

BUY Vitamins direct. Sava Postcard Matoaka Products, White Bear Lake

the VED Let ein to ter prem per man ship ew house Wile Orders 6 8 Louis Mineral)

PIN CPS 180 Glore & Gr. 8 hrs. Samples 780 Bate Baren & Pack 5 60 Closer Screber Ji C. H. in 7 h. j.

MIMEOGRAPHING Cheap! One day serv ice. Send stamp for samples, prices. Sawyers, 732-F. Oninerville, Florida

RUPTURED?? Improved Appliance Reduces. Often Gutes. No Truss. Free Trial. Earles Company, Flint, Michigan

FIMPLES - Prorison - Ernema, My swin remedy-Amazing Pull size 50c. ' Dezm', 512 H. Clemens, Lansing Michigan.

SOCIAL Romantic Magazine Photon addrauses 25c Western Agency \$15-5g Hill, Lou Angeles 14.

TALENTED? Your handwriting tells. Complete analysis \$1 00. One Hunter Analysi. ACCIONA M CO.

12 VI : AL Happiness Secrets. J. E. Ourolf., 135 Chestnut, Scranton, Pa

#### PHOTO FINISHING

IMMEDIATE Service Pictures returned Pre War haven' bis een gnaranteed Duck-led Edge Vilox print from rol 25e Or or els ored or two pia per largements Pree p n's fritt negt i es lot Candid Bolls dereaged Maga Ere Timed Vapors ed and en arged to 3 x 4 on Deckted Edge Vrice Paper M sep 15mm \$1 of 18 exp. for a Ferp No 127 50t Berp Ban am 25c Mep n's 1 x 8 locar's We have ewperfect 3 tom Dim' Low prices Free Mailers de's is on leques American Studies, Dept 507, LaCrosse, Was with a treckled-Edge prints 25c 16 re-Dept 607, LaCrouse, Wiler

BEAUTIFUL 6 m 6 pic area 3 pt warm from 116 and 130 pegatives, 3% m 42 g from all other sizes All work guaranteed. Over-hight service. Roll developed and 0 size-tures the Roll, 12 parts on the Roll 16 pt was 60c Entergements on device weath portant paper 5 t 7 30c 0 u 10 life ( pair made from new per 15c Pa-cific Phero Bertice Box 606, Sen Fran-

BEGEFEST \$1.00 value in 35MM fruit no tectary 36 expansion the grain 3 and pen-integration a declared emboared matter and date. Each teem expansion The achieve ex-posure sp. a 55c. Free the lette 8 exposure ro is in beautiful derkied contact fi ship in him beautiful de maigin. No Ma bad Prim Bern ce. Bus \$446A. Chicago 80

ROLL Developed photo a brim 2 ch arev ments 6 pr nts 25c Geppert Studios. Pert J 2 Des Montes Lana

OIL coloring photographs a fascinating ( hobby or problable business Learn at home. Easy simplified method Pres as experience unnecessary, Send for free to formation and requirements. National At Behoot. 1313 Michigan, Dept. 173C, Chi-

BEAUTIPUL Enlargements made from n r fa o tu nega e Prompt Bervice! Photo Bupple Co. 1044 Locust St. Cole rado Ci y Texas

ROLL de einged and 8 benut filler arte me s 3 to 8 5 mes larger, deckled edag high gloss. And I expense it in a 2st cotur 64 4 Avior 8 a no Boston, Mass.

FILMS Scientifically developed beautiful 4 x 6 enlargements, 19c com-plets, Photo Berrico, 107 Dewey 5t , New-

MEPRINTS 2c such (filty or more) less than filty 2 pc each. Pinest workmanship; fast service, h Dearborn, Chicago 2 Mercury, B-109 North

Fit Me 8 expensure negative size 25c, Enis a 700 West Chester Pennsylvania

INTRODUCTORY Offer-east enlargements from your favorite negative, 25c. Sky-land Studios, Moz 4t1, Dept. ' 25', Asheville, N C

#### POLLINY & SUPPLIES

YOUR greatest poultry problem w. on ample when you read American for I Journal regularly 500 000 poultrymen do why not you? Only 200 year, 5 years \$1 00 American Foultry Journal, 500 8. Clark

MOCER'S Post v Magnetine specifing enper me be of Yest 25c 5 years ing we be up Year No. 5 years \$1.00 B herr or 's day' Pressry Tribung Dept. 352, M., 91 M., 7a, 2

## PRINTING, MULTIGRAPHING, MINEOGRAPHING, LABELS

PRINTOMATIC" Self-feeding Rotary Stencil Post Card Printer, 19 50 Com-per Ali Makes Duplicator Supplies Legality Free Pittsburgh Typewriter Supply 136-MA Fourth Avenue, Pittsburgh 22. Pa

Letterheads and 200 63 En expes 500 of each 54 75 postpaid, Mero Products Sox 344, Punisstantes, Pa.

MIMEOGRAPHING—posteards to legal size -rea-onable, send sample for quotation Genduso, 154 Seventh Ave , New York 11 statements. Benneville, 907 West Roosereit, Philadelphia

PRINTING of all hands write for price list and samples. Edgewood Frem, Box C 167 Edgewood Mars and

CLASSY printing economically produced Quick desiverses Sampies, Storong, \$348. Windham Mt Lutits 20

Dist Notive Suppose at Reasonable Prices Samples free Stump Printers.

Prices Samples flew Stump Printers, South Wn let Jodiana 200 BOND Letterheads, Envelopes Sec. 2000- 55 98 Samples, Joseph Johnson, 1342-8 Fifth Ave. New York 20

WONDERFUL Bergain! 500 Letterheads 190c. Established 1863, Wanpress, Wauregan Conn.

PRINTING and labels all kinds, samples.

Printrate, 20 Spruce. Asheville. N. C. PRINTER S Supply Baygain Catalog. Send

78142 Franklin, Cleveland, Ohio

PRINTING Presses, Type, Supplies, Lists ic, Turnbaugh Service, Loysville, Pa.

#### PRINTING OUTFITS & SUPPLIES

PRINTING Outfits and Supplies. stamp for details or dime for complete illustrated supply book Kelsey Inc. W-L. Mer den Caure

you can make your own printing ruta les atropue eurs. Plustupus e pine-Sa mein chemitate Dergervice, A gale Ween a p

PROPERIONAL ater to pos taid printer, complete \$2.45 per paid Challenge As-socia on D II C in h a l

INEXPENSIVE home-made printing press. Details free, Sovelty Shop, Downsville,

PRESSES. Type, Supplies, Specimens, 3c. La Garta, Box 364, Cambridge, Mass.

#### PROFITABLE OF CUPATIONS

MECHANICALLY Inclined Men Own and operate general Apparance Repair shop Complex fastisted cause aligns you how Welding Renge after Muler re-par New o get bus less of an phases contrad. Free c'étable Christy Suppli Dept. 1035-2835 N. Centra Art. Ch. agu OPERAIR your own Retrigent on Meyeur Step is Good John new and after the war Est a few and at home Common selection was new Pres booker Mechanics School, Dept. 8-20, 4701 West Plos. London Angeloo d

LOCKBRITHING COLOR PRACTICAL INCH persons bracks for handy ment. Just out ? Free Deta a Nesson Co Dept 100 Chicago \$60.00 Whikily Made growing much-tu-me, Fresh Dried Don non-Paincy 331583 free spawn North American, 168Y Young Tutter o Canada Made greeng mush-ried Don non Parest

\$3000 PROM Half Acral Growing Oinsens Seed, contract supp. ed Particulars too Associated Growers, Dept. 13, St. Norbert

Manitoba.

RAISE busts profinble as a sample and mathematical way \$8.50 and difference to Cambridge and the White a Rabbitth Cambridge and a sample of the cambridge and a sample of the cambridge and th

William peg Mar.

RAISE Ear I worm f . Pr St " Information free Bureau of Zoolog cal Research 106-A Broadway, Peoria, It.

RABBIT Profits Booklet 10 cents, salver Boonte r Bunnyland. Mustic. N Y

#### NADION, SUPPLIES & INSTRUCTION

RADIO Service men and experimenters send for our giant radio cars que Bave dollars. United Radio Co. (1000 t) New ark N J

ord 5306 miles), with "Radiobutider" ~ 21c Laboratories, 363-T Hampton, May ward. Ca liformia

LOWEST Prices. Radio Tubes. Parts, Free bargain lists, Potter, 3314-A MoGes, Mansas, City Mo.

CRYSTAL Radio Experimenters, Write Hulet, 29 E. 39th, New York

#### RAKE COLYS

FREE Foreign on buskou's and Com-Collectors' Himstrated Catalog to ap-proval se use and use to fond it postage Up to 520 cash pa 3 'or Ind at head ret's Al. do to wan ed has no star loc. Tarham, Cotnoo. Springfield-D50, Mass.

COIN Concertors Rend Tab Kamasha-tar P b shed non-thir News (it is try ed fea a t Arians on coins and median Bample copy 25c. American Nu-minmatic Association, 90 Livingston St., Brooklyn Z N Y

CENTS 100 years old 25c Indians 10 different 25c New Silver Dollar \$1.50, 1943-5 cent and nickel 15c, Big Illustrated Coin Book 50c Coins, Box 17, Alameda, Calif 19 INDIAN Head cents, different dates, also possible, 35c Schultz, 1953 and Richmond Cincinnati. Ohio,

WR buy Indian Cents Lincoln Cents. Old.

Rate rotin war ed Highest prices paid.

Seed 16c oday for new 1943 price Cars.

Leve of a. 'I & Coma American Rate.

Com Co., Dept. 4, Transportstom, Side. (Parago

Willie, Pay 8,0 00 each for certain & needs Perment India heads \$50 or Dimer 3 000 NO Caralogie Or Federal Com Exchange 12 Of Columb as 15 Of 10

COMPLETE Catalogue of all U. 5, coms fac to \$1.00, 75 illustrations, 3500 Quo-fations, Price 10c James Randall, 341 South Dearborn, Chicago

WE purchase a Indianhead penniss. Com-ple e calabigue 10c, Waltman, 350 Broadway New York

FIVE foreign bills, 25c. Twenty-five dil ferent \$1.00, Beffel, Box 27-A, Ottawa, Minote

FREE coin list. Horry Flob in Box 3014 P sb gh at Pe . auch

#### RAZOR BLADDA SHAVERS

TRIM RITE comments out on the bar Cimpiete fiet jum pie din juriger eed. Wat von Heiser 226AF Richen, New Kensungton. - 4 4

#### RIBBYR STANES

2 LINE stamp Mr. cust oved, indexed the Biguntures \$1.50. Prin rise, Wauwatoos,

ONE 5 e 13c 2 5 es 25° 3 Jines 35c Es ceon Buk 50e 8 exeptet Louis e is CUSHIONED I area 450 surgis to \$2 Property Mig. East P. Isburgh Pa

TWO-Line Sed-Inking Stomp, 5, 00 free hat, Free, Warm Springs Ga

#### MONGWEITERS

SONOWRITERA Send to a poems for our offer and Pres "Rhyming Dictionary", Phonograph Records made, Vanderbitt Music Studies, Sex 112, Dept. 5-A, Coney Island, N.

MONGWHITTH'S WE'R P DIA 1g for good timbre al wigt We pat i gbest fer-ter We e fer our pie mien and die-bitieb proportion forman Formana to be their proper to the and F bit C 143 B Comment Mi Cheman 5 MONGWEST IN Res Melades a pro-ed w ho cut tage t ne it ny fintroid Comprisers Ma us pr jest process of tere do forma es. C nam a Bong Company Box 6 985 a Refer t State flat 2 a POEMS Wanted for Mar at Serie g Send pole of ter more a serie dera in 2 ap State Muste Musters, 666 Beacon Buraling House,

SONO & RITERS Send Form For Immediate Examination and Free Rhyming Dictionary Richard Brothers, 46 Woods Building, Chicago.

MONTH Part W. 1ed Wr a 'ng Pree In-No semi II is also

LOOD Music composed to good words, Music printing Regionald Belcher, Chat-New or or To all a Bed

NGSCI poems we ted. Whole for ree book West 46 to Nam Viels.

2 ORIGINAL Songpoems and 5 Songpoem ' more St. Corning, New York

Profit Sharing Plan. Altied Music Com-pany, 204 East Pourth. Cincinnati, Ohio MONOWRITERS! Quistanding songwrit-ing service, Roscoe Barnhart, 1320 4818, Des Moines, Iowa

BONG Poems set to music free publish re-royalties. Song Writers Guild, Box 2230.

BONOWRITERS Of stand g ameng g 1010

#### SPORTING GOODS, GUNS, FISHING TACKLE, ARCHERY

BOWS Arrows for Recreation Him one 7 sh. a Beautiful Archery has actue book, 90 pages 50 illustrations only 50c Liustrated catalogue Free. Archery, \$17 Bouth State, Chicago.

OUNSMITHING Readily learned at home. Easts ex a motor repairing he'g? nor bond a filening Free cale on 25 fivearm and gunsmithing textbooks. Beinworth. Plantersville. South Carolina.

USED Onna, Binoculars, bought, traded, a and Ammun, on bought Mighest Ca h Prices Paid, Storger Arms Corp. 501 fr h A e New York, N. Y.

ARI HENY Equipment: Catangle Pres M d West Archery 2000-D East 75th Chinney A.

Chicago 48

BEND 10c for list 100 used gams. Pray-

USED gurs, bought sold exchanged, List stamp, Howe, Coopers Milk, Maine.

#### STAMP COLLECTING

WOW signs Worth of Fun for only like and Powers Bran pe unsurted and us pritted miss to on by a of papers just no rere ed from the church missions and other so rices. Africa, Bo America. Aus rega. to cour er ale represented. Includes a tala og a. g up in 2se of mery early! The bearty Package of his, in S'airpdoin and ou might find something really valuable Price only 10c to acrious approval applicanta' Money back if not delighted. Jamestown Stamp Co., Dept. No. 5, Jamestown.

PIND Stamps Worth Fortunes! Six Big Tiems Gover Count en Packe Dis-but Qual e ere Packe nearen Rusa a Ca alog prie 370 Pais packe of 25 del le e Brecch Column Lacks de Catera I as do hi derabad. Jaha a gir t ed Sars \$4.00 a d \$3.00 h gh values. Hig Fa. Las pa aut c. 20 cifferer i s'attipa from D ch I des Biam Phinpi nes etc. I sa rated 37 page to sky -te a where to look for, and sell, atampe worth up to \$10,000 apiece! Everything for only Sc to approval service applicants! Mystic Stamp pa v Densi me 33 R Caurden N V

POSITIVELY Greatest Proc Offer—Latent Stor all erra and al 14 60 Blamp A burn on error er a World con a by 20 300 is to red descript a sports Bot a sat No. 44 d. 53 00 Catal gues 1th sately a Encycloped all—absolutely Proc to applicants for Foreign Approvals becoming customers. Bargain Stamp Service, Palm Spirings California

135 All different C 8 91 m Old new Anies Courins Pintage II es Persona Anies and A manages Died roud to Light corresed Overanteed to please Try pur forest parkers are each 3 for 25c 16 po he's 81 to All different Bar Bamp Co 6' Abers M Y

INVEST a to postal in writing for "Treasthe Island to it offer as ing, on a cly free—to purchasing customers of our fine totalgn approvals; latest hig 1200 page to it international than for \$7 mm Louse len() Pusings Stamp Album; Scotta 1944 \$5.00 Catalogue, "Treasure Island" Service, Vista Ca fore a

600 UNITED States for 10c! 600 US A absolutely unpicked and unsorted—just as received from church Master & Many ar it text fate richtig cummitte ital itemale high ha real spirit all and decreasing the Price douglife to a spirit all applicants. Movey balk if son de selled Sunt Stamp

FREE! Leeward Is., Cayman Is., Turks and Chicos plus 60 different mint Geo VI Correlation poster a sugar to appear ser ne an trapic sending 3c postage. Tel-

WORLD'S Largest Dismond And Triangle Binmps, Proc Stamp Magazine, Sampa from Fighting Free Firstin 28 stamps from 25 different to ted Nation Court ex Posters Artis in Fig. Binguin 5c with approvant Capsta, Watupe, Dept. 18, Livile R- L AFE

6) 09 (Cat Price) for let Two mint U & A bout Marb is er i senter sell in bout Marb is er i senter sell in appropriate of Concessor Biggins to Concessor Bi

VICTORY Purher Pres Lichates stamos From Tanga - Resells of Carmen Lalands - Anima - Parce Babilized Corea in - Early Vroman - Arma,
Map Stampe to b Big Catalogue all
free send for for protace Church amp
Company Dept PR Toronto Camada

SMOKY Mountain commemorative sheet arkest U B, stamp issued and 12 U B. including commemoratives, airmail revenues, etc. Catalogs 75c—To approval appli-cants for 5c Cuthan Stamp Company Dept C, Gloucester, Mase

PINE Approve a fresh a encurred Past personal service Tell the what countries you prefer and PR send their slamps. Millon Skinner, 345 Bust Ocean, Long Beach Cahf

121 DIFFERENT Stamps including Free Fight of Freeth, Haiti, Johote, Ferak, or in 10c 6 approva approvant Ret h Samp Co., 4647 Ernmart, Chicago, Dept. 87

BRITISH Empire Collection! Burms, Cyprus, Owalior, Berawak, Tasmania, Ales and Commemorative Approvata, Lyman, 17 New York Civ

EPECTACTIAR approval service for o og Inferna toma, or Modern upbums, Philatelist, Arcadia, California,

SEABOARD Stamp Exchange, Box 121 Claremont, Calif. Postcard brings good

1979 Century U.S. Commenn., Civil War Revenues, Battleships, 35 & 316 Stamps Free to U.S. Approval Applicants, Metropol tan Stamps, 186 G Broadway, New York

UNITED STATES approvals complete roserage D e qualit at rar ive prices, for I am Statege. Box 436, Cocomut Grove, Flor.de.

tue DIFFERENT int id ng matie airmail f ang r ik to appriva service applica s Avalon Stang Co., Dept. 8, Spring-Arred B. Mass

PREE-Your choice of any 10 stamps from our first U. S. Approval selection. Hiss-trated list included. Cosmopolitan Stamp Company, 1457 Broadway, Dept 4P N Y C. SPECIAL-Airmails-21 different, includ-

etc., 5c with approvals, Continental Stamp Co. Pro. and New Respense New York PHIF Complete Listed Bares Send Se ca a on B th a 200 country hard Bend Se for pentage. Harris & Oc., 98 Transit

Bu lding, Bocton, Mass SOLOMON Islands, Seychelles, New Cavhe with approvate Viking, 136 (P) Canton

PREE Outfit? Album, stamps, hinges go go, detector be Oeners, foreign approvals seed Manches er Stamp Com-

Maucheste Cor. pan PREE Canadian Sela, Royal Visit, Ocorga VI Ocorga V Cont. atta. Julyan Obsect, to approval applicants. Englgs, Box 118-P. So. Orange, N. J.

SPECIAL 46 d.Corent U. S., 26 Canade,

If Airmatis, and surprise packet—only for with approvals, Harmit, Box 4314, Kapsas City Mo BR. I ALN and Colonies "h dell cortud e cotons tons pa er ale labures or loc atte paperorale. Cresceus Bramps, London,

25 DIPPERENT Russis, Large Pictorials, Corembin and are and Airma is a trac as-imited 50c postpaid, Benjamin Bren, Station A. Box 141, Munchester, Conn.

PRFF Word wide pa ket Approvate Kratzer 143 0 Sedgwick, Wichits. Katitat

BARCIA'NH of the approvalet Write toville, Texes

PORKION New Issues on approval Bar-esin Priced. Raymond Koch, Muscoda,

RUNDIAN War set depicting New crief ten only the with that other barga hat Phoenic 717 Escationy Circums a Into BETTION Qual ; U est Sta ev appro ale Reass ab e Speedy service - Box Means ab e.

11QUIDATING-Approval remnants, sets packets-500 mixed \$1.00. Beacon Sales, Maynard, Mass,

10 DIFFERENT U.S., many commemora-tives, Sc. Oerhardt 2804 Rao Grande, Austin, Tex

FREE Canada War Stamps with approv-

PREST Prove Puppers of the extent Pringests. Mich.

PRESI 10 Attractive Ecuador-(postage 3c). Box 6618, Northeast, Kansan City,

cants, Pair Slamp Company, Bristow

se DIFFERFNT Un ted States Incl. Com-memora ves. An Pricelast free, Seid-enberg, Baroda, Michigan

PREE! | British Empire Packet, Postage 3c. Williams, 601 Archarbidg, Bayel s

U. S. 56 [Hfferent Sc to Appraisal Ass. 1-canta. Neumann & Co. 1314 W. Okas-home Ave., Milwaukee T. Wisconsin

APPROVALS, Lists serviced, new insues any country Melbos, 148-38 Heech Plashing, New York.

PREE! Wes ern Hemisphere Packet Posts age 3c. Gospo, 461 Weichbidg , Bayerty, Math.

MEXICO Census Commemorative Bet Free with approvale Pladon Stamps.

A \$2,000 stamp plus 50 different, 3c with approvals. O. Knopp, Box 1381, Bristel,

75 M'XELLS thomas "c app mals refer-er ces, Valentine, 10.08 66, Curuin, New

55 DIFFERENT United States 5c with Approvals. Bookman, Box 145-P. Maple-

PENNY Approvals that satisfy, Nell Gronberg, Bot 54418, Philadelphia 43, Penn. 50 PREE, pictorial etc., stamp dictionary, list. Builard, Newcastle, Maine,

PREE Mint Bet Manchukue, approvals. Eagle, 6043 Columbia, Ph., adelphia 31, Pa. 3,000 GRABBAGS 15c each & different \$1. Sandy, 630 Bingaman, Reading, Pa.

CURACAO Set new issue 10c with approvale, Vargo Stamps, Racine, Wisconsin, CANADIAN Stamps Complete from Jubites Approvals, Ellis Bros., Wadena, Sask, Alexandra, Sask, Alexandr

Zampino, 2022 West Ninth, Brucklyn 1000 MIXED U S. Old and New 25c, 2 lbs.

1,000 WELL mixed U. S. 25c Monjar 1750 Fairmount Cincinnati Ohio.

TRY my to Approvals. Chick, 712 High St., Bath, Maine

#### TATTOOING SUPPLIES

TATTOOING pays big! Anyone can latton with our outfles. Instructions included. Prec Illustrated literature Write Tatooco, 651 S. State, Chicago 2.

#### TORACCO-PIPES

FREE To P.pe Smokers—For a new pipe smoking thrill, write us your brand of tobacco and get Free package Mild, Tasty, Nature-Flavored "Green River", Pete Moberly, Box 964, Owensboro, Ky

#### DAFFERD

TRAP For and Coyote: on bare ground or deep show. Learn modern tricks to outwit the sky forbearers. Pres illustrated circular. Q. Bunch, Weich, Minnesota

POXES, Nine in one day, Trap all furbearers, Particulars Free, Guaranteed, Write-Ratabrook, Sherburne, Vermont

NINETEEN Deadfails Complete blueprints, 30c Wee Sho You, Box 51, Detroit, Michigan

ELEVEN But Traps, Complete blueprints, 30c. Wee-Sho-You, P.O. But 51 Detroit

Mich.
NINE Good Mink Seis 30c Wee-Sho-

NINE Good Mink Sets 30c Wee-Shotot, Box 51, Detroit Mich gan TWEIVE Good Muskrat Sets 30c Wee-Sho-You Box 51 Detroit Michigan.

#### TREASURE FINDLES

MT SCOPE Metal Locator fully guaranteed and unsurpassed in efficiency Time payment plan, trade-in and accessories. Prehterature. Pusher Research Laboratory Palo Alto. Cauf

#### WANTED-MISCELLANEOUS

MERCURY—Highest war prices paid. Any quantity or quality. Pree information and containers. Or, ship mercury today. Mercury Terminal, Notwood, Massachusetts

CASH For Bicycle Engines, Scooters, Motorcycles, Outboards, Gasoline Engines, Exercycles, Describe, quote price, Clymer, Los Angeles 6, Calif.

MERCURY (Quickstiver) we pay \$1.50 per pound. Western Meial Co., Blooming-

#### WELDING, SOLDERING

NEW model electric welder 110 volt AC-DC:
will weld all metals, easy to use, full
directions. Complete with power unit, flame
and metalic are attachments, carbons,
fluxes, rods, mask; all for \$19.85—Used by
the Navy Marvel Electro Welder Mfg. Co.,
195 SP Center Bt., New York City

BLHD d.c. arcweider without rewinding armoture Plans \$1.00 each. 25 to 600 amperes from Vehicle motors Light plant giverators. Au omobile star er generators. Weiders Club. WB-1432 M Mart. Chicago 54.

ARC Welder Bund it yourself Costs less than \$1.00—Use available scrap Ouaranteed No toy—Complete plan \$1.00—International Corporation—4347 Parnell, Chicago Illanois.

WELD. Cut Braze with gasoline! New discovery Make your own torch Instructions one American dollar, Matthews Mig Co Catgary, Canada

SLIGHTLY used Arc Wolders, Recommended by R. E. A. Guaranteed, Forney Mig. Company, Pt. Collins, Colorado

## If You Get Up Nights You Can't Feel Right

If you have to get up 3 or more times a night your rest is broken and it's no wonder if you feel old and run down before your time. Functional rather than organic or systemic Kidney and Bladder trouble often may be the cause of many pains and symptoms simply because the Kidneys may be tired and not working fast enough in filtering and removing irritating excess acids, poisons and wastes from your blood. So if you get up nights or suffer from burning, scanty of frequent passages, leg pains, backache, or swollen ankles, due to non-organic or non-systemic Kidney and Bladder troubles, why not try the prescription called Cystex? Because it has given such joyous, happy relief in so high a percentage of such cases. Cystex is sold under a guarantee of money back on return of empty package unless completely satisfactory. Cystex costs only 35c at druggists.




## 730 SHAVES FROM I BLADE

New sharpener for all makes of double-edge casor blades a pring naracies! Not necessary to change blades writer one pact.

writes one user Another says.

Have used I blacewers is topen. MAZDROLL rests sharpens blacewers is toppe in each of alrests sharpens blace been so toppe in each of alrests says and process pressure—astematics by Just topperation of adjusted by the pentity of adjusted by the few sences. Will had your Makes ideal gill.

## MASTER DRAFTING MACHINE



Biggest time saver for dimensioned a ketches, lettering and layouts ever sold at—This Low Price—While they last. Limited Supply..only

53.95 ORDER TODAY

RANDOLPH RADIO SIL West Randelph St.



#### **Army Haversacks**

heavy canvas, 715 by 11 lockes, with pockets second hand, with seather aling. Postpaid for 15 cents. 1940 75th Anniversary catalog 105 pages, 2000 illustrations mailed for 50 cents, 1943 circular for 3c stamp.

Francis Bannerman Sons 501 Broadway, N. V. 12

### MASCOT SLIDE RULE

Pits the pocket. Quickly solves any problem in multiplication, division, proportion. Gives the square, the square root, logarithm end reciprocals of all numbers. Trig scales give sines and tangents of numbers. Fine black graduations on white celluloid. Price in fabricoid case \$1.00 in leather case \$1.25. Money back if not satisfied. Special offer to agents and dealers



TAVELLA SALES CO., 21 West Broodway, New York, N. Y.

## INDUSTRIAL WELDER AND SAVES AND SAVES AND SAVES

AMAZINGLY SIMPLE & EASY TO OPERATE
This portable Dynamic Walder—easily car-

ried right to the jub—plugs into any convenient, properly wired 110 volt
light careau.—works on Iron, Steel,
Brass, Brosse and other metals has
eight metals and safet, more expensive methins.

\$ 23<sup>50</sup>

COMPLETE

DESIGNED TO DO HIGH GRADE WELDING INEXPENSIVELY
Maintenance Men. Farmers Mechai es: Machine Shops. Foundries Auto, General
Repair and Job Welm of Shops using the Dynamic find it so indispensable and
Useful that they cannot affect to be without it
inexperienced, you can use by learn to do a variety of high grade welding jobs by
lowing the practical, summified operating and welding instructions furnished

DYNAMIC WELDER CO., 13-5 Fost 23rd St., Chicogo 16, III.

Once you see a Dynamic in operation you won I be without it his aimplicity will amake you. In a year the Dynamic only costs you about 6c a day.

Comes complete with betmet, rous, rables, electrode holder and operating finanticions, etc.

Write loday for free priority analytance and particulars on how to qualify for one of these amazingty low-priesd welders. Act now while they are still available. Get details on our lo-day trial offer,

## Movie Hero? No-no\_its his





To test a Navy rubber life raft and its accessories, six "costoways" are tet adrift in the Atlantic under conditions simulating those of wartime shipwreak. Right, a "survivor" drinks from the new Permutit desalting bag being tested for Army and Navy flyers



# Allrink from the Ocean

Flyers no longer need suffer the tortures of thirst when forced down at sea.... A compact kit employing a chemical precipitant offers a new solution to an age-old problem.

Ву


JEAN ACKERMANN

THE recent development of a chemical precipitant that makes sea water as safe and palatable as the water from your kitchen tap marks an all-time high in man's endless struggle with the problem of midocean thirst. Never before was sea water purged of its toxic salts by a practical method employing chemical reaction.

Directly inspired by the needs of flyers for additional water rations without additional bulk, the desaiting compound is being packed in a kit which will occupy the same space as the current G.I. water can in a 'chute pack.

The statistics are eloquent, An Army flyer now carries a 11.5-ounce can of water; a Navy flyer, two cans. Reckoning a pint per day as a base ration for a man, the

## HOW NEW "DESALTER" PRODUCES A PINT OF



Simplest device yet developed for making sea water drinkable is the Permutit-Navy Desalting Kit. It consists of a plattic bag and five briquettes, each of which will desalt a pint of water—enough to keep a man going for at least a day



2 The pouch and desalting bag are both fitted with lanyards, which the user puts around his neck to keep them from getting last overboard in rough weather

single can will last barely two days, while two may be stretched to last for three days. The kit, containing five briquettes, each capable of desaiting a little over a pint, would give the Army fiyer a potential of six pints; with one kit and one can, the Navy fiyer would have a potential of seven pints of potable water.

Developed by the Permutit Company, a leading water-conditioning firm, with the advice of the Naval Medical Research Institute, at Bethesda, Md., the desalting process is as simple as making a cup of tea. Packed in the kit is a plastic drinking bag with a cloth filter at its base and a drinking tube set below this. There is also a supply of chemical, not identified at this time, which comes in compressed bricks, each the size of a candy bar. These are guarded from moisture by two heat-sealed wrappings.


When he wants a drink, the castaway fiver scoops the bag full of sea water, drops in a briquette, straps the top opening closed, and shakes the bag from side to side to hasten the reaction. In 20 minutes the liquid is black with tiny granules. Of the 3.5-percent salt volume that sea water holds (2.7 percent sodium chloride; .8 percent salts of calcium, magnesium, and potassium), a total of 3 percent has been precipitated out.

To take a drink, the survivor simply uncorks the sim tube beneath the filter and sucks. The first mouthful will be saity, from filter leakage, but after that only a faintly stale taste distinguishes the desalted liquid from naturally fresh water.

Why wasn't such a simple solution thought of long ago? Probably because it was never so urgently needed before. The only hint of chemical desalting heretofore is a legend of some plant used by the Phoenicians to make sait water potable. Beyond this, mariners seem to have been content to use distillation methods, or to carry an ample supply of fresh water if the vessel was too small for a still. Distillation, the physical process of drawing off and condensing vapor from sea water, leaving the salts and other impurities behind, is still an excellent method for supplying large groups. But the weight and bulk of a still preclude its use on life rafts and small lifeboats, although there is an experimental miniature still that may become standard equipment in larger lifeboats.

As with Permutit, the great bulk of desalting research has been inspired by the war-born needs of airmen. One of the more

#### Alexander Graham Bell's Idea




The inventor of the telephone tried to solve the problem of drinking water for castoways. He worked, however, from the angle of condensing maisture from the atmosphere. His simplest plan was to floot a tumbler on the ocean's surface. If sea-water temperature was below the daw point, moisture would condense in the tumbler. "But how fast?" Bell wondered. "Even a dew would be sector to a thirsty man. But if it is no more, then a dew (adieu) to the man"

POPULAR SCIENCE

#### FRESH WATER FROM THE SEA IN 20 MINUTES



3 With bag filled to its blue line with sea water, briquette is dropped in through opening at top



4 The top of the bag is then folded down four times toward plastic buckle and fastened



5 Bag is now kneaded and shaken to speed the distribution of the chemical. After 20 minutes of this, the user can remove the plug in the sucking tube and drink water that is still a bit salty but completely harmless

#### OTHER METHODS OF DESALTING SEA WATER



TWO-BAG DESALTER developed by the Novy is similar to Permutit device in that it uses secret desalting chemicals. Within 10 minutes it provides a man with drinking water for two days



DISTILLED WATER CONTAINER


LACK TURKISH TOWELING

VINVLITE COVER

BAG FOR DIPPING LET SEA WATER

SOLAR STILL. Sea water poured into chamber at top drips down to saturate black toweling, which absorbs heat from sun. The salt remains in the toweling while water vapor condenses and drips into container at bottom

BELLY STILL. Strapped to a man's stomach, this ane-pint "bailer" uses body heat to turn sea water into a vapor that is carried to and condensed in a vessel trailing in the cool water of the ocean. Although simple to operate and requiring no fuel, it is cumbersome and takes eight hours to produce one pint of water



FUEL STILLS. At left, above, is a seven-pound still that produces about six quarts of drinking water for every pound of solid safety fuel that it burns. It is fitted with a flexible tube that is dropped over the side to serve as a water-cooled condensing cail. At right, above, is a still designed by the British for lifeboats. It can burn any type of fuel, and produces fresh water at the rate of five pints an hour

publicized methods was also a precipitation scheme, the work of physicist Alexander Goetz, of California. It involved four steps conversion of salts to alkalies, filtration, precipitation of the alkalies, and a second filtration. Intrigued by its possibilities, Navy researchers studied and improved upon the Goetz process to some extent, reducing the number of bags used from four to two. At its simplest, the Goetz method is still more complex than the Permutit-Navy process. It has never been officially adopted by any branch of the service


Though dissimilar in action, the Goetz and the Permutit-Navy devices share the advantage of compactness, so that they give a high ratio of water for their size and weight. The water cans used by our flyers weigh a pound each and hold only 11.5 ounces of liquid. The Permutit kit weighing less than a pound and a half, can produce five pints of water. But, like any other chemical method, its efficiency is always limited by the amount of chemical on hand. Other processes are just the reverse; the equipment is heavy and bulky, but it is self-

sufficient. Given sait water, it can keep on producing fresh water indefinitely. One out-fit, a compressor refrigerator, is based on the principle that when brine freezes, its saits center in "core water" in the middle of the ice, the ice itself remaining fresh and saitless. This is in the experimental stage.

Besides the miniature fuel-burning still mentioned above, two other small stills have been developed, both ingenious devices that save the weight of fuel by harnessing a natural source of heat. One, the "belly still" draws its heat from the human body. A hand-cranked vacuum pump keeps pressure in the "boiler" low enough that water evaporates at body heat. The resulting vapor is passed to a vessel trailing in the sea, which is never warmer than 78 degrees, the 20-degree drop is sufficient for immediate condensation.

The solar still absorbs heat from the sun through a square of moist, black toweling. Evaporation from the wet cloth produces water vapor, which condenses on the inner side of a Vinylite covering and drips down to a tube from which it can be sucked.


four-way protection for fighters is provided by the Navy's latest battle costume. Though it weighs less than four pounds, the garment contains enough kapok stuffing to stop bomb and shell fragments, keep the wearer from drowning, and prevent "blast" shock from underwater explosions. It also guards against burns.



BLAST-FURNACE temperatures of new U. S. incendiary bullets turn enemy aircraft into sheets of flame. Self-sealing gas tanks, immune to tracer bullets, ignite as the new ones pass through. Rounds alternate with armorpiercing and tracer ammunition.



Here are two styles of the Navy's battle costume. Officer holds a one-man rubber boot which can be worn callapsed on the back. A pull on a cord inflates it—with the man inside




FIVE AUTOMOBILE ENGINES equal one tank engine. How Chrysler Corporation engineers, following this remarkable formula, helped to develop a power plant used on thousands of medium American tanks has just been revealed. In the photo above, four six-in-line auto engines have been assembled around a single crankshaft. A fifth completes the job.

BOMB REFUGE? Oddly patterned after less permanent air-raid shelters, the massive structure below was found intact at Naples, Italy, after the Allied occupation. Ruins of surrounding buildings suggest that its design spared it a similar fate, although whether it was actually used as a bomb refuge remains a mystery.



operates a power-driven "chin turret," shown below and at right, on the eighth and latest model of our Flying Fortress Replacing flexible-type guns, the two .50 caliber turret guns repel frontal attack on the B-17G believed the world a hardest bomber to down






TWENTY-FIVE CASTAWAYS, with enough stapplies to last them 30 days find ample remain the world's largest rubber raft produced by the Firestone Tire and Rubber Company and tradeout by the Coast Guard Deflate I and packet, as at lower left, the

boat measures only seven by five by 112 feet. Only four minutes are needed to unpack and launch it. Three transverse pneumatic benches, 10 feet long serve as sents a weather curtain (lower right) protects occupants from wind water an sun






THE LARGEST nonrigid airship ever built is being test-flown by the Goodyear Aircraft Corp. Akron, Ohio. Designated the M-1, this super blimp will serve the Navy, cruising up and down the coasts in search of enemy submarines. Compared with the naval K-ships which have been on coastal patrol, the M-1 is larger by 50 percent and holds 50 percent more helium. Greater size and volume of the giant ship permit larger cruising radius and bomb-carrying capacity. In the photo at the right can be seen the airdock of the plant in Akron where the partially filled gasbag awaits placement of a nose cone





Air freight is quickly stowed or discharged by the new Hi-Lift Sky Freight Loader, seen at left, designed for the Army Air Corps by the Hell Co., Milwaukee, Wisc. Twin cylinders on the unit lift cargo, weighing up to 8,000 pounds, to any planedoor level between 4½ and 10 feet high—the distance from the door still to the ground varying with every type of plane

MOTOR FRAMES that will house rotors of 6,000 to 10,000 horsepower are lined up at left for inspection at the General Electric plant, Schenectady, N. Y., before being installed in U. S. tankers and factories. When assembled with motors, the four frames in front will be part of a unit weighing 112,000 pounds; behind these are three which in complete assembly will weigh 145,000 pounds. Two great rotors in the background were designed for a 10,000-horsepower, 850,000-pound twin engine in a steel plant that will be the largest west of the Mississippi.







Simplified Controls are an outstanding feature of a new helicopter design developed by the P-V Engineering Forum, of Philadelphia, Pa. A midget model, using a three-blade rotor of 25-foot diameter, is shown being demonstrated at the National Airport in Washington, D. C., by Frank N. Piasecki

HIGGINS, builder of landing boats for Uncle Sam, will bid for the postwar helicopter market with the craft shown in the drawing at the left. It was designed by Eneas Bossi, who built Italy's first airplane in 1909, and will be built in Louislana.

TWIN ROTORS lift and propel a teardrop plywood craft designed and built in his spare time by Fred Landgraf, engineer at a Los Angeles, Calif. aircraft factory. By eliminating the problem of torque, the twin-rotor feature makes it possible to replace the usual rear rotor with a vertical fin. The twin rotors have 16-foot diameters. Landgraf will test-fly the plane within a few weeks.





# How Strong 7s Germany's "Fortress Europe"?

The road to Berlin is guarded by the greatest defensive system in history . . . but our forces will hack through to victory.

By HAL BORLAND

Drawings by DOUGLAS ROLFE

VERY day's fighting in Europe carries
our armies closer to Hitler's Inner Fortress, where the decisive battles will be
fought and the war will be won. Many
secrets of that Inner Fortress are now
known and have been studied exhaustively

by the Army Engineers, whose job it is to open the way for the conquering armies. How these secrets were learned cannot be told until after the war, but the outline and much detail of the Fortress itself may now be revealed.

First of all, it must be understood that the name "Fortress" is deceptively simple. All occupied Europe is a part of the mammoth system of defense the Nazis have devised. The Inner Fortress itself is more than twice the size (Continued on page 52)

#### THIS IS THE "INNER FORTRESS"

German ingenuity has turned all of occupied Europe into a fortress, but the real citadel of Nazidom is the steel-ringed area outlined roughly in the map on the two following pages

JANUARY, 1944





of Texas. Its boundaries are, roughly, the Baltic on the north, the Yistula and the Dniester on the east, the Danube and the Po on the south, the Rhine and the Siegfried Line on the west. It includes not only Germany, Austria, Hungary, Czechoslovakia, Poland, and Rumania, but slices of the Baltic States, Russia, Yugoslavia, Italy, France, and Belgium.

These defenses are no single line of fortification. Their extent varies greatly with their situation, but in general they are an elaborate system of defense in depth—with the accent on depth. Thus, the occupied area outside the boundaries cited is actually a part of the defensive system. It is a huge maneuver area, a cushion to absorb the shock and soften the sledge-hammer blows of the Allied armies driving in toward the Inner Fortress.

And, finally, the Fortress is more than a system of fixed fortifications. It is mobile defense as well, the area inside being criss-crossed with lines of communication, high-ways, railroads, navigable rivers, and canals, and dotted with major air bases. Look at the map and you will see how well the outer lines take advantage of natural barriers, chiefly rivers and mountains. You may be sure that every range of hills and every watercourse in the maneuver area is a part of the intricate defense.

With this broad picture in mind, lay out a line of approach to Berlin from any point on the periphery—from the Channel, from the North Sea, from the Mediterranean, from Russia, from the Balkans—and you can begin to understand the possible prob-

lems for an invading army. The Nazis have not overlooked any of the possibilities.


Suppose the approach is from the sea. The first problem is that of landing. Coastal defenses are particularly heavy, especially at favorable invasion points. The water is alive with mines. The land rises sharply above a relatively narrow beach, and on the heights are gun emplacements—every type of weapon from machine guns to 16-inchers with a 30-mile range. Just back of these emplacements are rail lines, and all along the coast are big guns on railroad mounts, which can be moved into position overnight.

In the water just offshore are steel and concrete barriers, shark-tooth affairs designed to rip the bottoms out of landing barges. The beach itself is sown with land mines—the deadly Tellers to blast tanks and the terrible S mines which leap from the sand at the alightest touch and spray shrapnel at belly height. Literally millions of mines have been planted along hundreds of miles of beaches. Back of the mine fields are tank barriers, which include everything from concrete walls and steel rails bedded in concrete to roll barriers which look like gigantic sewer pipes six feet in diameter. Around these barriers and behind them is the wire—thick, tough, heavily barbed, and set up in an endless tangle.

This is where the invaders must set foot on land.

Back of the beach are villages and the open country. The few roads leading to them bar every kind of vehicle with walled mazes, steel rails, and concrete blocks.

DEFENSE IN DEPTH. Surrounding the bastions of the Inner Fortress itself is a vast maneuver area, designed to cushion the blows and sop the strength of an invading force before it reaches the main defenses



Guarding these roads are guns hidden in the walls of old stone buildings, guns set into the hillsides, guns commanding street and road intersections. And overhead, of course, is the Luftwaffe—as much of it as can get through our own air umbrella—operating from a dozen fields back beyond the hills.

This is the first line beyond the beach, actually a part of the beachhead defenses. Once it is breached, the attackers can move on into open country.

But the open country is not so peaceful as it looks. Roads are barricaded, and the barricades are guarded by gun emplacements which have been there so long that the wind and weather have blended their concrete and atone with the billsides, and the grass and bushes have provided perfect camouflage. As the tanks and trucks leave the roads and cut across country they find themselves again in the midst of mine fields over which the grass has grown a perfect cover. Every watercourse is a hazard. Not only do its banks hide gun emplacements, but it must be bridged under enemy fire. Mobile artillery has moved in behind the next range of hills.

This is the open country, the maneuver area. Here and there are "strong points," pillboxes, and special cover for rifle companies; and always there is mobile defense moving up, hammering and delaying the invading force. Tank companies make driving flank attacks. Tank killers wait on the hilltops and beyond the streams. Every wooded area is a nest of artillery, hastily drawn up from less-menaced areas.

As the invading armies move on, the


defense deepens. By now, reinforcements of every kind have been gathered, and the tank battles roar to the heavens, more often than not masked in a rolling screen of smoke. Villages become minor fortresses, with guns hidden in barns, houses, pigsties, and haystacks. Antiaircraft guns are lowered to pour concentrated hell into the advancing armies.

At last the invasion reaches the outer lines of the Fortress itself.


At the risk of oversimplification, let us say there are three roughly parallel lines of fortification, the second line from six to 10 miles behind the first, the third as much as 25 miles back of the second. The' first line will have, in a typical area, a frontal defense of tank traps. These consist of everything from broad, deep ditches to concrete barriers. Their purpose is to halt the tanks long enough for the antitank guns to get in their heaviest blows. Tanks can cross ditches, but, as they emerge, their lightly armored underbellies are open to brutal fire. They can sometimes crawl over the concrete barriers, but there again their bellies are exposed.


Behind the tank barriers are endless snarts of wire which tangle in tank treads and slow up engineers and infantry. Under and behind the wire are land mines in countless numbers. Beyond the mines are bunkers and blockhouses, set into the hillsides like molars into a jaw and pouring steel and death into the oncoming armies. No two bunkers are built the same, and each one's guns cover at least two of its neighbors. Nor are (Continued on page 204)

This cross section, greatly compressed, shows how gun emplacements, strong points, and open ground are mingled to give the greatest possible apportunity for mobile defense by artillery and fast mechanized forces




A PERPETUAL-MOTION INAchine built by Capt. Eddie Rickenbacker at the age of 14 has taxed the ingenuity of Twentieth-Century Fox Studios. In their new film "Rickenbacker—an American," the apparatus is shown as it originally appeared, centering around a hand-operated air pump and incorporating a keg, wagon wheel, bicycle rim, and several croquet balls. Rickenbacker found at its first trial that the machine fell apart, but Hollywood prop men made it work by putting a motor under the table top on which it rested and concealing wires in the table legs. A D.C. motor drives the wagon wheel; and to heighten illusion, a second one gives the apparatus a bouncing motion. Smoke and sparks accompany the scene of its breakdown.






A SHORTAGE of lamp sockets somewhere in the South Pacific has been eased by two Navy "Scabees, G. A Brien and E. S. Ryan. Working with worn-out hose, steel and insulated wire, bits of tin, and sections of bamboo, they fashioned the socket shown.



SPARE-PARTS BOXES of aluminum made by Westinghouse now require less metal than formerly, yet they remain the same size. An ingenious pattern for cutting the boxes reduced the sheet of aluminum needed for a single box from approximately 10½ square feet to 7½ square feet. The new box, designed by Emil Stolte of Westinghouse, is stronger, requires less welding, and annually saves two tons of aluminum. See if you can revemp the old pattern, below, to save three square feet of scrap. (Solution on page 106.)





Mastery of a bulldazer is one of the things this Seabee recruit learns. Overseas, and under fire, he may take it apart, put it back tagether, and make it do tricks

# The Seabees Can Do It

Whatever the job, the Navy s
Construction Battalions will
tackle it . . . with their own
brand of rough-and-ready
engineering.

#### By ALBIN E. JOHNSON

FFICIALLY they're known as the U.S. Navy Construction Battalions. Popularly they're called the Seabees, a play on alphabetics, Among themselves, and by the regular Navy and the Marines who have seen them in action on the beachheads and bases of the seven seas and in Alaska and Greenland, they are the Can Do's—the boys

who can do, and do do anything. They are to the Navy what combat engineers are to the Army. Their motto is Construinus Batumus two Build and We Fight), and they are one of the secret weapons of this war

Ben Moreell (Rear Admiral Moreell, to be formal), chief of the Navys Bureau of Yards and Docks, goes all out for his Seabees. Taken from the ranks of civilian con-

Intensive training in landing operations conditions Seabees for going oshere as engineers with our first waves of invading troops. These bomb bursts simulate actual conditions in exercises on the East Coast



struction workers and technicians, they now have reached the formidable total of about 200,000 and are still being recruited. Moreell recalls what they did at one spot in the South Seas, where they were sent after

Pearl Harbor.

"A supply road was needed there," he recounts. "Ten Seabees with two Diesel bulldozers were available for the job. The problem was to construct a 10-mile road over a 1,500-foot mountain ridge, through virgin jungle so tangled that a man could not penetrate it. The Scabees split into two gangs, worked 12-hour shifts, and for three days and three nights they kept the two buildozers going constantly except for fiveminute stops between shifts to refuel. Having no spare parts, they improvised repairs. In 72 hours the first jeep went over the road to the new base."

Improvisation is the watchword of the Seabee, and ingenuity is inherent in his character. There isn't a piece of machinery he can't fix. Moreell tells of the radio condenser that went havwire at a remote base. The nearest new parts were 1,000 miles away. Seabee Phillips, chief petty officer and former carpenter, collected tin foil from cigarette packs around the camp, some waxed paper from a fruitcake which a sailor had received from home, and a flatiron. He rolled out alternating layers of tin foil and waxed paper, stuffed them into a discarded beer tin, and made a condenser that worked.

"If a Seabee doesn't know the answer,"

says Moreell, "he makes up one."

The war had not been under way long when a crew of 40 Seabees were transported to Liberia by Clipper to do a rush job. In six weeks they built 13 lighters, and improvised barges which they made out of pontons equipped with cranes. They were on the job seven days a week, from the crack of dawn until dusk, in steaming tropics where the thermometer climbed to 140 degrees in the sun. And they finished the job on time.

The British had been trying for three months to assemble a crane; the Seabees took over and had the operation ready in a month. They dug one crane out of the weeds where it had lain for nine months. British sailors had discarded an old boat because it wouldn't run; with a screwdriver and pair of pliers, Seabees took the engine apart, cleaned it, installed a hand-

•

made condenser, got two cylinders working, and made the boat serve until their equipment arrived. Defective spark plugs, lowgrade gasoline, and various other kinds of grief didn't prevent the Seabees from having the landing barges ready when freighters and cargoes began to arrive.

Seabee construction odysseys are also being written on the barren tundras of Alaska and in the rocky Aleutians. There Seabees shared foxholes and dugouts with the soldiers and sailors at Attu; they built barracks at Dutch Harbor when Japanese bombs were falling and the williwaws—the terrific windstorms of that region-ripped apart the Quonset buts as fast as they were bolted together. A williwaw carried one Seabee 30 feet through the air. Another Seabee broke that record with a 40-foot flight. and got a fractured leg. Divers worked in water 108 feet deep and so cold that the oxygen hoses froze. One Seabee diver carried black and blue marks for three weeks as a result of too close acquaintance with an octopus.

It was in the Solomons that the Seabees made history. Four hundred and fifty of them with 250 cases of beer landed on Guadalcanal and went in with the combat troops. Their ages ranged from 17 to 50 years; in the outfit were veterans of the first World War, college students, athletes, and artisans Side by side with the Marines they fought off the Japanese snipers between working shifts, and sometimes spent the entire day hunting the enemy in the jungle. One sharpshooting Seabee got five Japs in a single day.

When equipment failed to arrive, they made the best of what they had. On Island X they erected a sawmill at the jungle's edge in order to build a mahogany bridge that will probably stand for years to come as a permanent memorial of Seabes ingenuity. Another bridge, connecting Henderson and Carney fields, is built on mahogany logs, some of them two feet in diameter, driven 17 feet into the ground. The decking is bloodred planking, 60 feet wide, and can carry two-way traffic. The natural color of the mahogany is blended with the blood spilled by tough Seabees who wouldn't take cover when there was a job to do.

The Navy needed a scaplane ramp built. It was partly a sea-bottom job and there

was no diving equipment on hand, That didn't stop the Seabees, Out of gas masks and old inner tubes they manufactured a diving apparatus good enough to enable men to work for hours under water placing concrete slabs on the ocean floor. On the same job, jagged coral chewed up the tires on the earth-moving machinery, so the Seabees mixed palm-tree

sawdust with cement, filled the tires with it, and kept the scrapers moving until the

ramp was finished.

For five weeks one Scabee crew went without bread until baking ovens arrived, then they taught the natives a few things about cooking and the Marines about trad-






Mud and jungle fail to halt the Navy's Construction Battalians. Here Seabees dump rock from a beach to harden the soft New Guinea sail for road building as others in the outlit erect shelters

ing. A bottle of Seabee beer brought \$5. or a good samurai sword. In British Samoa the natives now do a Seabee version of the Harlem jitterbug dance. One inquisitive Seabee, an ex-Marine with an eye to culture, cultivated the natives and unearthed an original Robert Louis Stevenson manuscript in a house in which the famous author once lived. He added to Stevensoniana the tale of a fireplace where Stevenson, on chill days, swept out the dying embers and sat upon the hot rocks to cook up some of his stories.

Romance also biossomed for some Seabees in Pago Pago, but they soon learned that you can't beat the game even in the South Pacific. The native damsels liked the Seabees even better than they liked the sailors and marines. Marriage was just a financial transaction, however, until the parting of the ways. Then it cost more—a down payment and a monthly allowance. And, to add insult to injury, local custom permitted the girl to marry again and again, drawing "compensation" and "allowances" from several husbands, although the ex-husbands were forced to remain "out of circulation" for the duration of their stay.

When the Guadalcanal gang found that they couldn't build an airfield on a certain spot, they transferred their equipment 18 miles overnight and built Carney Field. At one advance base where Marines were string-



Improvisation and ingenuity go hand in hand wherever the Seabees take hold, as this tin roof in the South Pacific shows. It is made of partially flattened gasoline drums


ing barbed wire along the beaches to fore-stall Jap landing attempts, an enthusiastic Scabee, intent upon making the job easier for the Marines, shoved coconut tree stumps into the sea. He ventured out too far with his buildozer and sank into the quicksand. The Marines suggested that the buildozer be written off as a complete loss. "Hell, no!" said a Scabee officer, "that cat cost Uncle Sam \$15,000." From 11 p.m. until daylight, while the tide was out, sweating and swearing Scabees labored until they finally salvaged the machine.


No usable equipment is ever acrapped by the Seabees. On our far-flung battle lines, spare parts are too scarce for anything to be wasted. Japanese dive bombers hammered hell out of a steam shovel on Island X; the cab was (Continued on page 198)



#### AIR-FILLED BAGS

raise the wing of a Boeing Flying Fortress, somewhere in England, for testing of landing gear. Canvas bags apread the lift over a wide wing area, are easy to handle, and save precious metal. They are especially handy when the ground is uneven.






HANDY HOT AIR. This portable engine heater weighs but 38 pounds, burns gasoline, and produces 90,000 B.T.U. of heat an hour. Using 92 percent of heat units from burning gasoline, it is effective under all weather conditions. A small motor blower, using the standard plane power output,

drives not air through a flexible conduit to the engine hood. Developed by the York Oil Burner Co., it has proved particularly useful in starting scaplane engines, owing to its ease of handling by crewmen in rough seas. It can also be used to heat tractors, snow scrapers, and other heavy-duty equipment.

SPECIAL PARTS TRAILERS have been designed for easy moving of units of Consolidated B-24 Liberator bombers from one part of the factory to another. The trailer below is loaded with a B-24 nose section and

fin and rudder units. The man is seated upon part of a wing's trailing edge. To prevent the possibility of friction and damage during transit, the heavier parts of the big bombers are carefully protected by means of specially designed cradles,










BUILT TO BE BURIED in airport runways, these heavy-duty lights can stand the pressure of 50 tons' dead weight standing on them. A Flying Fortress passing over exerts a 36-ton pressure, but Westinghouse builds 'em tough.

MODEL OF PERFECTION is this OCD control room made to a scale of one inch to a foot. Designed and built by two General Electric employees, it is used to help OCD units better to plan and lay out their offices. Walls fold up and the entire model can be packed for easy carrying from place to place.



A TRAINING GUN SIGHT designed by the American Optical Co. for the U.S. Navy duplicates the famous Spitfire combat sight at one-tenth the cost. A light at the bottom of the sight tube projects sight rings on a glass plate through which student sees his target. The sight rings are projected from film mounted between the light and lenses that carry it to glass plate at the top. The Navy is using the sight on laboratory trainers that simulate actual flying.



A RIFLE GRENADE, carrying a wallop that makes it a baby brother of the bazooka's rocket, is the Army's latest antitank weapon Springfield rifles, shelved in favor of the modern Garand, lob the grenades in much the manner of a mortar shell. Resting on one knee, which he places behind the gun butt, a soldler holds the barrel in his left hand, puts his foot in the sling and thrusts the grenade over a special muzzle fitting from which it is discharged,



WHO STABBED THE GOLF BALL? The scene was the 13th hole at the Baltusrol Golf Club, Springfield, N. J. The players were Charles A. Saitta and A. C. Fetzer. It was the former's turn to tee off. He took a lusty swing with a No. I wooden driver, and the ball rose with the burring sound of a startled cock pheasant. It landed 110 yards away. Examination disclosed that the tee had neatly stabbed through the cover. The mystified golfers pointed out that the ball was a pre-war Kro-flite—and so tough that you couldn't drive a tee into it with a hammer.

# AN HONORABLE-DISCHARGE BUTTON, signifying his or her service to the nation, will be awarded by the War Department to every eligible person who has served in the Army during the present war. Although in the process of manufacture, the gold-plated plastic button is not yet available for distribution. Details will be made public as to



how it may be obtained.



## Electropiating Mill

## HUGE MACHINE, A MIRACLE OF ELECTRONIC CONTROLS, COATS STEEL BY A CONTINUOUS, HIGH-SPEED PROCESS

#### By Alden P. Armagnac

Drawings by B. G. SEISLSTAD

LECTROPLATING steel with tin, instead of dipping it into a moiten bath, now makes the war-scarce metal go three times as far. Since tests have shown the product highly satisfactory for tin cans and other coated articles, plants throughout the country are adopting the process, pioneered by the U. S. Steel Corporation. Its Carnegie-Illinois subsidiary operates three strip production lines like the one pictured here.


In traveling through the line, the uncoated material is subjected to 45,000 amperes of low-voltage direct current in the electroplating bath, which coats it with metal from tin anodes, Subsequently, alternating current momentarily heats the tin to its fusion point to brighten the surface.

An electric eye with timing attachment unerringly detects a portion of metal containing so much as a pinhole. The cut sheet containing the perforation is kicked into a rejection pile after it has traveled a circultous course of 450 feet. A second pinhole detector checks on the first; a third electric eye counts the finished sheets; and a "feeler" gauge detects variations in thickness.


CRANES HANDLE

TIN ELECTRODES

#### ELECTROLYTIC TINNING UNIT



## Stretches Our Precious Tin



JANUARY, 1944 63

# Their Inventions Set Shipyard

Green workers do the impossible as former salesmen, farmers, and housewives devise tools to help build our cargo fleet.

#### By REINHART KNUDSEN

HERE were grave misgivings among the sober heads of Portland, Ore,, when Henry Kaiser began hiring farmers, automobile salesmen, clerks, cowhands, butchers, and bakers to build ships in his three big yards. The yards, located only a few miles from each other in the Portland-Vancouver area, turn out Liberty ships, tankers, and escort carriers.

"You just don't make a skilled workman overnight," the old hands said. "There's

going to be lots of trouble."

Nevertheless, the greenhorns were hired. They had to be hired because there weren't any trained workers left. Kaiser managers divided up every operation into its smallest component and tried to teach each worker just one small task that he could learn quickly and do well. They, too, had misgivings, but ships had to be built and this seemed the only way.

That was more than a year ago. Kaiser, as a shipbuilder, is now world famous. His greenhorn laborers not only learned the little tasks assigned to them, but came forth with suggestions of their own—suggestions that whacked great slices of time

off ship construction.

Managers freely assign a great deal of the credit to a labor-management suggestion program launched in the yard in September 1942. The whole idea of the program was to invite workers to make suggestions of ways in which they could speed up their work, make their work easier, or contribute to the safety or improvement of working conditions in the yard. War bonds were offered as rewards. Primarily a move to improve morale, it was not expected to produce anything very tangible.

As the labor-management committee reviewed the achievements of its program for its first 10 months on July 1 of this year, it was amazed to find that in the three yards, employing approximately 85,000 workers, 8,695 suggestions had been turned in. Of these, 792 were acceptable and went into immediate use. During the 10-month period, 113 bond awards totaling \$6,150 had been made,

One worker developed a clamp to fair hatch-end beams that saves over 200 manhours per hull. A former automobile-agency




MOLDS are now being used to speed the repairing of welding-electrode hold ers. Three shapes of molds are employed, one for each major part of a holder—lower jaw, upper jaw, and teeth, Placed in the proper mold, the part is held firm while it is being worked on. The inventor, Mrs. Ello Barkie, above, is a former Partland model, the mother of four children

Records

WELDING shell plates to the shell frames can now be done 50 percent faster with this pneumatic pusher, quickly brings the plate and frame into proper alignment. Copable of 8,000 pounds' pressure, the pusher, consisting of a preumatic cylinder and a ram, rides transversely on a beam, which can be moved the entire length of the assembly bay. With this two-way movement, a comtrolled pressure can be quick ly exerted at any desired point over the area of the jig section. The device was des good by Wil iam Davis, right








BEVELING DECK PLATES was speeded up 40 percent when Ray Parcher, above, a former salesman from Rainier. Ore., devised this hand-cutting torch. With its head held in a collar supported by two small legs, the torch can be set at any angle with the aid of a calibrated dial. By running one of the supporting legs along the edge of the overlapping plate as a guide, the torch can be pulled along smoothly to make an accurate cut

DRILLING AND REAMING holes in universai joints can be done on this one machine, designed by Byron Mark Johnson, shown above, intended primarily to increase the efficiency of these cutting operations, the two-spindled device by making it unnecessary to move the work from one machine to another to complete the operation is soving to man-hours per hull. Johnson is the shippard's leading idea contributor

PLIERS designed by an electrician's helper now make it possible, in repairing welding-electrode holders, to extract and Insert the springs and spring cups in a matter of seconds instead of minutes. This simple but timesaving device was made merely by brazing to the jaws of an ordinary pair of pliers clips to fit over the springs. The inventor is a typical "greenhorn"-Mrs. E. L. Norwood, who has three children, and who never held a regular job before entering the shippords





man devised a bending machine to make special straps for electrical cable hangers. It saves about 500 man-hours per hull, Still another devised a bracket for holding welding degaussing channels that saves 140 manhours per hull. A couple of South Dakota farmers teamed up to develop a simple jacktype deck puller that saves 4,250 man-hours per ship. A mother of three children, who had never held a job before in her life designed a pair of pliers for extracting and inserting springs and spring cups in Jackson "stingers," or welding-electrode holders, cutting what used to be a 10-minute opera-

A MOVABLE SUPPORT to which a portable drill press can be securely fastened so as to be kept square with a ship's deck, is the laborand time-soving invention of W. P. Watts, who appears above. The support permits much more accurate work, eliminates much of the chance for drill breakage, and is said to be adaptable to many shipbullding operations

SHRINKING THE PLATES of Kaiser's escort aircraft carriers is done in one third the ordinary time with this device, which puts four shrinking tarches to work simultaneously. The terches are sarried by a small cart made of pipe and scrap iron, and mounted on wheels for complete moneuverability. The idea came from an ex-restaurant operator, a former road-cray foremen, and a graduate of Dortmouth





BEVELING Is done automatically with the machine shown at left, which sever 20,000 feetof pipe a month and reduces by 50 percent the man-hours required by former methods, Designed by George Allen and Ivan Chapman, left, the machine consists of a set of collers synchrenixed by a motor with a cutting torch. As the pipe retates, the torch burns in the bavel. The torch can be moved to make a cut at any point

tion to a matter of just a few seconds. There is no counting the total number of man-hours saved by the multitude of little ideas, gadgets, and suggestions that this program has encouraged. Managers point out as significant, however, that even though the bottom of the labor barrel is being scraped, the average number of manhours per Liberty ship at the Portland shippards of the Oregon Shipbuilding Corporation has dropped from 523,469 to 349,-494 since September 1942.

During the first few months of the program only about six percent of the suggestions were acceptable. This proportion changed steadily until by June of this year 15 percent of all the ideas turned in were of the type that could be put into immediate effect, and some were outstanding.

Here's how the program works: A worker who gets an idea must put it in writing along with drawings, if these help in clarifying it, and then drop it in one of the many conveniently located suggestion boxes in the yard. The letter is picked up by the suggestion supervisor, who records it and notifies the worker that it has been received. Then he and the labor co-ordinator of the yard review the suggestion. If it merits technical consideration, it is referred to an operating department. From there it goes to the eightman labor-management committee for final decision. This committee is composed of four men representing labor and four representing management. The ownership of each suggestion remains in the name of the contributing employee. He is free to sell, commercialize, or otherwise dispose of his contribution in any manner he desires. The Kaiser company merely uses his idea. Bond prize awards are given at each of the yards each month for the four best suggestions. Prizes are \$100, \$75, \$50, and \$25 in war bonds and are put up by the Maritime Commission. Where several men collaborate on an idea, the award is split among them.



PORTABLE DRILL PRESS. This drill turn and rooms belos in handralls three times as fast as could formerly be done by two men. Fastened to a jig, the drill is held firmly in position by two claws and a supporting arm. By eliminating vibration, the jig has considerably reduced breakage. The inventor, Sylvester Smith, phown above, is an ex-former who was working as a salesman in an Oregon furniture store prior to going to work in the Portland shippards.

JANUARY, 1944 67

### How Army Air Forces chart 8,000 square miles a day

# Superspeed Mapping Puts our flyers ahead

Simple new method plots world's most remote air routes . . . does 30 years' work in one . . . and gives United States a head start in the Air Age to come.

Photographs by WILLIAM W. MORRIS


HE science of charting, for generations keyed to the man on foot or on horse-back, has finally caught up with the man in a P-38. Using a wholly new and simplified technique, the Army Air Forces in the past year have charted 3,000,000 square miles of rugged, remote country—an area that would have taken more than 30 years to map by old methods. This amazing achievement, an average of nearly 8,000 square miles a day, was made possible by the tri-metrogon process, perfected since Pearl Harbor.

The process, named for the lenses in the compact three-camera unit with which the master photographs are made, was developed by Col. Minton W. Kaye, commanding officer of the First Photo Charting Group, Army Air Forces, and Lt. Col. Gerald Fitzgerald, chief of the Aeronautical Chart Service, formerly of the Alaskan Branch of the U.S. Geological Survey. It is so simplified that one airman can now photograph 20,000 square miles in less than half a day, and the transfer technique is so swift that not long ago a finished map of 89,000 square miles in Africa was produced just seven days after the photographs arrived at the compiling unit.


Aerial mapping is not new. It was used during World War I. But old methods were either fast and inaccurate, or accurate and slow. In more recent methods, highly complicated and expensive cameras, some of them taking as many as nine pictures simultaneously, were used. It took a year, however, to train a man to operate them; and after the pictures were made, a staff of experts was needed to transfer photographic

#### FIELD PARTIES LOCATE CONTROL POINTS . . . THEN PLANES

Although tri-metrogon charting is done almost entirely from cerial photos, geodetic control points must be located with the atmost accuracy by field parties consisting of from two to four Air Corps men. They are flawn as close to these points as possible, then proceed as best they can. Control points are preferably spaced about 50 miles apart Before camera planes are sent out, flight lines are indicated on the best available maps of the district to be charted, although these are often no more than guesswork sketches. The planes fly parallel courses about 25 miles apart. The camera unit in each consists of a vertical comera and two oblique cameras at 30 degrees below horizontal







Tri-metrogon charting at a glance At regular intervals the plane takes three photos, one straight down, two obliquely. The threads indicate various angles used in projecting points to form the chart

#### AT 20,000 FEET DO THE CHARTING WITH SPECIAL CAMERAS



Inside one of the trimetrogen charting airplanes a cameroman
clad for high altitude
flying, is adjusting the
film magazines. The
cameros (at top) have
wide-angle lenses of
six-inch focal length.
They take a set of
pictures every three
miles, which provides
sufficient overlap for
on accurate assembly

detail to planimetric maps by slow, tedious processes. Tri-metrogon, by contrast, does an accurate job quickly and with a minimum number of specialists.

The easiest way to see how this is done is to follow a tri-metrogon project through

from start to finish.

It begins with field work, as does any mapping job. The area to be charted is first laid out on the best available maps of the district, which often are no more than guesswork sketches. Flight lines are indicated and well-distributed geodetic control points are chosen—river junctions, promontories, lakes, islands. These points must be located with absolute accuracy, for they become the figurative corner posts on which the whole map will be squared.


Field parties, each consisting of from two to four Air Corps men, are sent out to establish astronomic control and make accurate descriptions of each point, so it can be identified on subsequent aerial photographs. Ideally, control points should be about 50 miles apart. To reach them is often back-breaking work, for although the field parties are flown as close as possible to the control points, they often have to go in by boat, by dog sled, or on foot. But on their work depends the ultimate geodetic accu-

racy of the map. Field work, under the best conditions, is relatively slow. However, while it is going on, the aerial photographers begin their assignments. In the photographic planes, they fly parallel courses about 25 miles apart, considerably farther than in the old mapping methods. The tri-metrogon camera unit takes three pictures at a time, one vertical and two matching obliques, that cover a six-mile strip from horizon to horizon. The cameras have wide-angle lenses of six-inch focal length, and automatically take a strip of pictures every three miles, which provides sufficient overlap for final assembly. Photographic flights are made

When a flight area has been photographed, film is processed, and prints are made whenever possible in the field at the temporary headquarters of the Photographic Squadron. In some cases, the film is forwarded to this country for final printing. Field printing is desirable because it offers an opportunity to check photographic coverage. The negatives are titled with project number, date, location, roll, strip, and exposure number, and the prints are indexed.

at approximately 20,000 feet.

Two sets of contact prints are forwarded to the Army Air Forces Aeronautical Chart Service in Washington, which files one set for permanent record in the Central Film Library and forwards the working set to one of the three Army Air Forces Compila-



CONTACT PRINTS, made in sets of three, are nine by nine inches. Key points are taken from oblique photos with a special rectablique plotter



1 CHARTING STARTS, when the contact prints reach one of the three Compilation Units in the United States, by marking the position of each photo and its number on a master index map

4 When a set of paper templates is assembled, the intersections of similarly numbered lines represent detail points. A pantograph changes the scale as necessary. Then metal templates are made








Horizon-to-horizon coverage is given by three overlapping pictures. The use of the six-inch metrogon lens at 20 000 feet gives a scale of 1:40 000 on the ful size vertical print (here shown much reduced). The air-line distance between the small arrows at the extreme left and right is approximately 110 miles




2 Now 't is necessary to indicate on the prints [with a circle inside a triangle] the geodetic control points established by field parties. Field notes and descriptions help to identify them



3 True horizontal angles are obtained from an oblique photo (left) by a pointer pivoted over the plumb point. This controls the straightedge for laying act a paper template (at right)

After the lines on the paper templates have been transferred to metal templates, the latter are laid down on a huge cellulose-acetate sheet which is to form the master-map base. The template centers [below] represent lines of flight of the charting planes. Paper triangles show special geodetic control points. Purs are driven through the intersections of the rays, the templates are taken up, and the base is marked





6 Meanwhile the contact prints go to sketchers who study them through magnifying stereoscopes. They select and outline in ink the principal geographic features which are to be transferred to the map



7 The acetate map base, with all its location points marked from the templates, is cut into three-foot strips; and detail sketchers, using a sort of camera lucida, draw in the details indicated on the photos



8 When reassembled the base map is compared with photos and other available data by checkers. Place names are then lettered in, contours and other data added

9 Contours are determined with a photoalidade, as on the facing page. Separate contour sheets are made (right) and printed in light colors on the finished map

tion Units—one in Washington, D. C., one in St. Louis, Mo., and one in Colorado Springs, Colo. Now comes "translation."

From here on, every operator on the job—there are 250 in the Washington unit, half of them women—has what amounts to a grandstand seat 20,000 feet above the area being mapped. With specially developed instruments they can see, in three dimensions, mountains and valleys that may never have felt man's footstep . . . can calculate the height (Continued on page 188)






Kodachromo by William W. Marris

To provide a chart with contour details, which eventually will appear in color, this operator carefully studies an aerica photograph through the photoalidade. This instrument is small, occurate telescope which, while placing the operator figuratively at a height of 20,000 feet above the earth enables her to triangulate vertically any point on the chart

FACTORY STYLE

CEEDLING tree "factories," with an annual production of millions of tiny Douglas firs, Sitka spruces, and western hemlocks, have been established by the West Coast Lumbermen's Association to restock Northwest areas that have been ravaged by forest fires. Prior to the planting of the seeds, special labor - saving machines plough a weed - killing gas six inches into earth, and then mix the earth with shredded peat to form soft seed beds. During their growth, the seedlings are "toughened up" for forest life by being alternately sprinkled and then allowed to dry in the hot sun. After they have reached a height of five inches, they are mechanically transplanted to the es of hand sowing, which allows the plants to grow in forests, where, if they survive fires pirder they please, the seeds are laid in straight lines and storms, they can be expected



to grow to a height of 250 feet.


3 Close-up of the mechanical feeder which lays the seeds in straight rows. Wooden sleds at bottom cover the seeds


4 A small two-wheel tractor is used to pull a pair of miniature offset cultivators between the narrow rows of seedlings





formit a mechanical weader to do its work between the rows







DEAD SNIPER. A Yank patrol, fired on by a Jap sniper hidden in a tree, sprayed the tree with bullets and saw a body drop. Continuing its advance, the patrol was again fired on, Again, it replied and again a body dropped. The third time it' happened, the patrol investigated and found a sniper alternately firing and dropping dummies from trees by means of pulleys.



## From the Enemy's Bag of Tricks



DEAD BIRD, A favorite ruse of Jap pilots is to put a plane into a spin and release plumes of smoke to make it appear that it has been hit. In this way a pursuing Allied plane is sometimes lured into the range of other Jap planes.

so solly. A supposedly surrendering Jap may be
found with a special
automatic revolver
which, hidden under
his tunic and pointing forward, can be
made to fire 25
rounds by means of
a wire running up
his sleeve to his upraised hand.



A FAKED DOGFIGHT is often staged by two Jap planes to trap a lone American flyer. Thinking to help out a comrade, the American plane dashes into the fray—only to find bullets suddenly spitting at him from both planes.

transports are sometimes covered with jungle foliage to make them appear as tiny islands. When set off by an incendiary, however, the highly inscharas disas. Totaly by turning the boat into a pyre



### The Facts About

## Fighter-Plane Firepower

Our flyers meet their enemies in the air with faster-shooting, harder-hitting weapons.

By ARTHUR GRAHAME

Color Mustrations by JO KOTULA Drawings by FRANK TINSLEY

THREE seconds isn't long—only as long as it has taken you to read this far. But in the split-instant business of air fighting, three seconds is a long time—abou the longest continuous stretch of time that a pilot of a single-seat fighter plans ever can hope to have an enemy plane within range of his fixed guns and in the ring of his sight screen. Usually he has considerably less than three seconds in which to make his kill. If he can get in a one-second burst, he calls it a good break, and even a fifth-second chance for a snap shot is something worth trying for

So, to be an effective weapon for a single-seat fighter, an aircraft gun must be able to hit fast. It also must be able to hit hard; the vital parts of Nazi fighters and bombers are sturdily armored these days. High velocity is an essential characteristic. Everything else being equal, a high-velocity gun has more penetrating power, longer range, and greater accuracy than a weapon of the same caliber which propels its projectiles at lower speed.

The best fighter-plane gun for air-to-air combat—fighter vs. fighter or vs. bomber—is the one which punches out the greatest number of the largest projectiles at the highest muzzle velocity in the shortest time. But because rapidity of fire decreases as projectile weight increases, the finest ail-round fighter-plane gun must be a compromise between these desirable but conflicting characteristics.

The aircraft guns which best combine the qualities vital in air-to-air fighting are the 20-millimeter automatic cannon and the aircraft machine gun of halfinch or larger caliber. Although the British still are arming some of their Spitfires with 12—and some of their Hurricanes with eight—of their 1,200-shots-a-minute ,303 caliber Browning machine guns and all the embattled air forces continue to use some similar rifle-caliber machine guns in combination with heavier weapons, the trend in fighter armament is atrongly toward larger calibers and more power

Some Nazi and nearly all Japanese fighter planes still use as their principal weapon the 20-mm, automatic cannon with which the Luftwaffe started the war. This weapon is a short-barreled version of the Oerlikon antiaircraft gun. Its muzzle velocity—which, because of the


design, can't be increased—is under 2.000 feet a second; its effective range is only about 500 yards; and its rate of fire is 10 shots a second. These old Oerlikons are definitely inferior weapons which are hopelessly outranged, outshot, and generally outclassed by our .50 caliber Browning aircraft machine gun and by both the American and British Hispano-type 20-mm. cannon

Late this summer, it was reported that some Nazi fighter planes were armed with new and extraordinarily efficient 20-mm, guns. When a specimen of this weapon, the Mauser M.G. 151/20, was captured, it impressed Peter G. Masefield, one of the soundest British unofficial experts, so strongly that, writing in the magazine The Aeropiane, he ranked it as the world's best aircraft gun. He gave its rate of fire as 800 shots a minute, and rumors had its muzzle velocity as high as 3,500 feet a second

There are several methods of rating the comparative merits of aircraft guns, but none of them is altogether satisfactory. The most-used comparison is weight of fire delivered in pounds of projectiles per minute—a misleading criterion because it takes into account only one of the gun's several characteristics. Massfield ranks the weapons by their muzzle horse-power, which he calculates from the rate of fire, the weight of the projectile, and the muzzle veloc- (Continued on page 82)


When the Mustang P-SI was found to perform as well at 50 feet as it did at 15.000, military designers decided to replace its machine guns with cannon so that it could deliver heavy blows in low-level attacks. The drawing at the right shows the plane, armed with cannon, blasting a truck convoy






#### THESE ARE THE "BIG FIVE" OF AERIAL

Nation	Gun	Caliber		Muzzle Velecity	Walght of Pro-	Max. Rate of Fire		
		ln.	Mm.	Pt./Sec.	(actile	Free	Syn.	
Germany	Mauser M.G. 151/20 auto. connon	.7874	20	+3500	.25 16.	800	600	
U. S. A.	Hispano-type aircraft gun-M-2	.7874	20	2850	.29 lb.	450		
Britain	British Hispano	,7874	20	2850	,25 lb,	<b>#50</b>		
U. S. A.	Browning M-2 aircraft M.G.	.50	12.7	2900	800 gr.	850	A00	
Germany	Mauser M.G. 151/15	.5906"	15	2800-2900	.19 fb.	950		









ity. With the data he had, he was fully justified in putting the Mauser 151/20 at the top of the list. On paper it seemed definitely, if slightly, superior to any United Nations aircraft weapon.

Like the much-touted German 88-mm. antitank gun, the Nazis' new aircraft gun is a good weapon which has failed to live up to its too-good advance notices. Firing tests of a captured Mauser showed that its muzzle velocity is a mere 2,300 feet a second. Its rate of fire is about the same as that of American and British 20-mm. aircraft cannon, but it definitely is inferior in range and hitting power. It is more prone to jam than are our guns, and—like many German weapons—it isn't well designed for large-scale production.

Both the American and British 20-mm, aircraft cannon are descendants of the original Hispano-Suiza. Each fires explosive shells which weigh a little over a quarter pound, at the rate of about 700 shots a minute. They are of the same weight, 135 pounds with their mounts—15 pounds heavier than the German 151/20.

The normal effective range of the .50 caliber Browning and of the American and British Hispanos is the same, about 800 yards, but the Browning has the great advantage of being able to "reach out" farther when necessary, and if the pilot is a good anough shot it will score deadly hits at well over 1,000 yards. The Hispano's .29-pound supersensitive-fused shells are explosive. The Browning is just as deadly. Its armor-piercing builets have higher striking velocity, and its incendiary ammunition-considered the most efficient ever produced anywheredoes its job so well that our pilots know that one or at most two hits on an enemy

To be effective, bullets from aerial guns must hit hard. A projectile traveling at, say, 2,700 feet a second might not penetrate armor, while the same projectile with no increase of weight might bore through at 3,500-foot-second velocity





plane's gas tank means a goner Jerry or Jap. The Browning fires 14 shots a second to the Hispano's 11½; and its higher velocity speeds its bullet 1,000 yards in a quarter second less than it takes the Hispano's shell to travel that distance—a saving of time that may mean the life-ordeath difference between a hit and a miss

when the target is an enemy plane flying between 500 and 600 feet a second. One of the salient characteristics of the Browning is its remarkable dependability. In the Tunisian campaign about 85 of our P-40-type fighters fired a total of 25,000 .50 caliber armor-piercing and incendiary bullets (Continued on page 186)

# Miniature Battlefields SAVE LIVES IN INVASION

Dioramas and scale models teach our soldiers how to win when they meet the real thing

#### By JACK O'BRINE

EXPERT use of natural concealment and camouflage safeguards the lives of our troops in this global war. Beforehand knowledge of difficult terrain along invasion beaches and other prospective battlegrounds makes it possible for our military leaders to hit the enemy hard with minimum loss. Our fighters knew what they were up against in the Solomons, North Africa, and Bicily. Victories resulted.

Some facts behind this achievement must remain a military secret. But one part that now can be told in the development of dioramas and training models as instruments of war. That project is a special task of the U.S. Army's Corps of Engineers. At engineer headquarters, you'll find miniature reproductions of coasts, deserts, and mountain ranges where our troops have already

This Signal Corps photograph shows the amoring detail and realism of the diaramas which the Army uses to familiarize traops with terrain they are about to encounter. Can you tell where backdrop meets diarama's horizontal surfaces?

struck and where they're going to strike. You'll find a beach scene in the Solomons so realistic that you almost expect to see Jap snipers dart from behind palm fronds. Next to it is a strip of cold, blue coast line in the Aleutians, with camouflaged antiaircraft units shown going into action. Across the way is a hot, windy section of Africa, which vividly illustrates the scant camouflage possibilities and other challenging aspects of the desert. You get intimate glimpses of a dozen war fronts in five minutes without leaving that engineer workshop. These are the dioramas whose peacetime development reached its peak during the New York World's Fair three years ago.

Equally important in teaching camouflage and familiarizing officers and men with foreign terrain are the Army's training models. They differ from dioramas in that they depict terrain on a set scale, instead of tapering to give the illusion of distance. Models give you aerial views of beaches, hills, woods, bridges, lakes, and villages. They vary in size from one 20 by 40 inches, which can be packed in a carrying case, to a huge layout of an invasion coast that depicts miles of ocean frontage as it would

Made to show American troops the limited comouflaging prospects of the African desert, this diorama illustrates the use of burlap to cover trucks and wire netting to hide tanks and artitlery. Kodachrome is by William W. Morris





DIORKMAS

look to approaching troop convoys or fleets of troop-carrying planes.

The striking realism of these discamas and training models results from the thoroughness with which the engineers and their civilian artists and craftsmen detheir research. For into each miniature goes a vast amount of data from the wartheater it will depict. Aerial photographs, scenie films, drawings, maps, writings, and reconnaissance reports are carefully studied. Findings are sorted, catalogued, and turned over to artists who produce a notored sketch. From that sketch-if it successfully passes the exacting standards set by the Army Engineers-eventually emerges the highly detailed miniature as a strategical military gem.



Folioge for the ministure trees is made from lichen mass, which, after being socked in a wateralcohol-glycorine solution, is dried and pointed



Here a skilled technician carefully stains sawdust which will form part of a new diacome. Wire, wax, gloss, putty, and papier-maché are also used

On a portable training model, on officer points out computaging possibilities. View appears as it would to a plane flying at several thousand fact




To produce a loofy effect on the larger treet, an artist sprays shellos on tiny bits of green paper scottered on a not placed around the lichen clumps.

Field hits enable soldiers in combat areas to make to an-the-spot dicremus. Fifty square miles of ter- to rais can be duplicated on a six-by-six-feet model (





His Models Died 40,000,000 Years Ago






"Natural Blatory"



I Dones are often found incased in hard rock. To unearth them safely, the fosell-digger must use special tools. Erosion aften helps him to make a valuable find



2 Once the bone has been uncovered, it is prepared for shipment by being splinted, wrapped with cloth dipped is wet plaster, and they crated





S Not until he has made a number of sketches of the animal's skeleton, musculature, and covering, is the artist ready to point the beast realistically in a sarefully planned setting



In the laboratory, a proparator removes the wrappings and proceeds to the delicate job of shipping away rock that still incases the bose



A specialist now studies the fossil to determine which of the bones it is, and just how it will fit in the complete skeleton




The Zebra
and the
Red Fox

STATIC TEST. Here a fighter model designed by the Bell Arcroft Corporation, the makers of the famous Arracobra, is being put through a punishing weight test at Wright Field, Dayton. Ohio, Lines painted around the fuselage give a check on the strains and stresses produced in the various sections. Engineers are taking readings off wing


Kodochromes by Horold Kulick

CADET AT WAR. This tiny plane is an Army version of the Culver Codet, being used in test work at Wright Field. The Cadet, a popular light-piane for sportsmen in peacetime, is here equipped with tricycle landing gear in place of the two-wheeled gear it employs when an pleasure bent




ANY an injured person has bled to death because those around him took time to improvise tourniquets or waited for a doctor to arrive. Such tragedies often can be averted by a knowledge of first-aid "pressure points," where application of the fingers will check the flow of blood through the arteries. The drawings on this page, based on material in "Air Force" magazine, show the locations of six arteries and the pressure points that control various areas,


# Javing Lives with Your Fingers




Pressing the temporal artery in front of the middle of the war will reduce ecolo bleeding




If the wound is in the cheek, press the artery in the notch on the under edge of the jew




Pulling caratid artery in nack against spine stope bleeding above that point on that side



The temporal artery (1) can be lacated with the fingers by its pulsation. Only light pressure should be applied to this artery, as well as to the artery (2) under the law. In pressing the carotid artery (3), at least a moderate pressure should be exerted. To reduce arm bleeding materially, it is necessary to hold the subclavian artery (4) firmly to the collarbone. Strong pressure is also needed as the brachial (5) and femoral (6) arteries. In the farmer, wrist pulse should sleappear



Sehind collarbons is subclavian entery. Pressing it against sollarbons stops arm bleeding



A hemorrhage in forearm can be controlled by pressing brechiel arrery egalast the bone



Holding famoral entery firmly against polvic bone with heal of hand decreases log bleeding

SECUND SELLEVEL	620 MILE		LONG-RANGE CAMERA "SHOOTS" 620 MILE believed to be the lengest-range shot ever made with an acrie camere is this picture taken by J. H. Washburn, Leckheed photographer, from a plane 26,000 feet ever Oceanside, Colif On the herizen is Mt. Shasta, 620 miles away. Infrared film was use	AILE estric hotes On th
	"IW (	IW 9E	·IW 3	
	SSAG 19	PEAK 3	ILMER 33	
TEHACHAPI MTS.	TEHACHA	PYRAM PYRAM	SIERRA NEVADA EL	
INTERNATIONAL PROPERTY.	Solver Programme	MOJAVE MOJAVE	MT. SAN ANTONIO - MOJAVE DESERT	W JZ
PASADENA	MONROVIA	AZUSA	PAS	o l
			TAKEMANTHEWS	3 ME
というというというというというというというというというというというというというと	THE WAY AND	DOBLINGS		7



BY PEERING into this transparent celestial sphere, student aviators see navigational stars and conatellations on the opposite side just as they would actually look in the heavens. This is better than the usual sphere, which shows the stars as if seen from outside the universe. The sphere was designed by Lt. Col J. E. Davis of the Instrument and Navigation Branch, Wright Field, Dayton, Ohio,

A NEW WIND TUNNEL for testing plane models under conditions simulating the temperatures and pressures of altitudes up to 50,000 feet is being built by the Air Forces, Wright Field. Two giant fans will develop wind velocities of over 600 miles an hour, while a refrigerating unit will chill the winds to as low as 67 degrees below zero. A special device will enable the air pressure in the tunnel to be reduced to as little as one-eighth that of sea-level pressure.



## FLYING OFF THE ESCORT CARRIERS WITH DEPTH CHARGES, VERSATILE TBF'S CLEAR THE SEAS OF SUBS

### By William S. Friedman Kedochromes by Harold Kulick

Somewhere in the middle of the Atlantic, a submarine's periscope breaks water. Scarcely have the first men scrambied out of the conning tower before a pursuit-speed, single-engined giant drops out of the clouds. The plane opens its capacious belly bomb bay; out tumble depth charges, and the erstwhile wolf of the sea becomes just another oil slick.

For the success of the Navy escortcarrier system that has vastly reduced the percentage of merchant-vessel sinkings, much credit is due to the Navy's carrierborne maid-of-all-work, the TBF Grumman Avenger

Designed as a torpedo plane, the Avenger was the first single-engined U. S. carrier type to carry internally a full 21-inch tin fish. It also serves as a light bomber, carrying the standard bombsight and bombs, and as an antisubmarine plane.

The Avenger was born when the cruising speed of the Douglas Dauntless fell short of modern combat standards. The new ship had to have enough cruising range to attack enemy capital craft inside the widest possible protective not, with weight to spare for defensive armament so that it would not require a fighter escort.

Grumman's answer was a midwing monoplane which many early Jap spotters mistook for the F4F Grumman Wildcat fighter. The new ship had a wing span of

The Avenger Scores Again

54 feet 2 inches and was 40 feet long Powered by a 1,700-hp., 14-cylinder Wright Cyclone engine, it developed a top speed of 253 m.p.h., at sea level. Cruising varied between 120 and 200 m.p.h., depending on the mission. Carrying a normal load, it had a cruising range of over 900 miles.

The Avenger is a three-place airplane, carrying a pilot, observer-gunner, and radio operator. Probably the greatest single advantage of the plane is its amazingly low landing speed. The biggest ship on the carrier, it actually requires the same take-off run as the fighters, and even less deck space on which to land


AS A BOMBER, the Average carries about a ton of "eggs" and uses the standard bambsight. For entisebmerine work, the bambs are replaced by depth charges. Wings are folded, as shown below, by hydraulic mechanism controlled by the pilot—a great advantage in operation from a crowded carrier deck

AS A TORPEDO PLANE the TBF houls a full 21-inch tin fish. At the right, the 2.000-pound projectile is being hoisted off its dolly through the bomb-bay doors with a winch












GLIDER. An all-wing, tailless, singleseater glider has been announced in the British magazine "Flight" as a recent achievement of the Horten brothers, German aircraft designers. Known as the Horten IV, the ship is reported to have stayed aloft for 914 hours. Like all other tailless aircraft, the ship can be turned to the right or left only by banking. This is done by means of three individually operated flaps set in the trailing edge of each wing, which can be made to serve as elevators as well as ailerons. To add to the ship's maneuverability, two additional pairs of flaps, one in the leading edge of each wing, have been installed to serve mainly as "negative" elevators.







SHARP BULLETS are made possible by a shaft which the explosion forces forward so that its needle-sharp point extends beyond the bullet's nose. G. N. Albree, of Winchester, Mass., is the designer.

MIRROR-AIMED MACHINE GUNS, mounted at the rear of a single-seater fighter plane and pointing backward, have been suggested by John F. Haberline, of Beattle, Wash., as a means of enabling the pilot to blast any enemy plane that "gets on his tail" A mechanical arrangement permits the pilot to adjust the vertical angle of the guns while tracking the enemy plane in an overhead mirror.







FAKED AMERICAN TIRE TRACKS came close, but not close enough, to luring American trucks into desert mine fields planted by German sappers. A Yank scouting car was prowling around one night with its headights on when it came upon a German patrol laying mines. Seeing the headlights, the Naxis thought it was a friendly vehicle. They were promptly showered with hand grenades. Investigation then revealed that the Germans had run American tires over the sandy mined areas to give the impression that vehicles had safely passed that way.




SHALLOW-SEA DIVING, without the costly and cumbersome equipment usually needed for underwater work, can be done with this diving "faceplate" designed by Richard B. Comstock, Consisting of an oval frame fitted with a glass window and a sponge-rubber cushion around the edge to make a watertight contact, the plate is held on the wearer's head by means of straps. Fresh air enters through a hose connection at the top of the plate; exhaled air passes out through one-way

valves at the bottom.







Our Navy can raise ships as well as sink them!

Mammoth salvage operations add priceless tonnage to the war and cargo fleets of the United Nations.

Drawings by STEWART ROUSE


proximate cost of five Liberty ships, a single day's launchings. It also happens to be about all that Navy salvage in U.S coastal waters has cost since the beginning of the war, not counting the Normanda.

But this second five million has paid a return, in the salvaged values of bulls, cargoes, and supplies rescued from the sea, estimated at over \$400,000,000. We say estimated because the sum grows every day and because the Navy isn't saying too much about some of the phases of Navy salvage's world.




A student diver at the Navy's Salvage School in New York City gets ready to tackle an underwater training assignment. (Kadachrome by Robert F. Smith)









#### THREE METHODS OF KAISING A SUNKEN SHIP ...






DIVERS put patches on holes in shell plating and seal up all companionways, ventilator trunks, and other openings in selected parts of the ship. Water is blown or pumped out of these compartments and the ship rises.




#### 2. COFFERDAM METHOD (IN SHALLOW, SHELTERED WATERS)




CUPERSTRUCTURE is cut away and smaller holes are sealed. Wenk decks and partitions are shored. Then a watertight cofferdam is constructed in sections and floated into position, where it is fastened tightly to the vessel with cables and turnbuckles. Since the top of the cofferdam extends above the surface of the water, it and the hull can be pumped dry as a unit. Thus lightened and made buoyant, the hull then rises and floats.

#### 3. PONTONS (ESPECIALLY EFFECTIVE WITH SUBMARINES)

N DEEP waters. where the methods shown above are not practical, salvage engineers use pontons. Tunnels are cut under the hull by hydraulic pressure and chains are passed under. Pontons attached to the chains lift the vessel to the surface when the water is blown out of them. This method is impractical with large ships.





wide activities, the greatest and most farflung salvage work of all time.

Since 1941, when Congress passed a law permitting the Navy to salvage both publicity and privately owned ships, we have heard a lot about some phases of this work; the raising of the Normandie and the refloating of the battleships in Pearl Harbor. But most of the work has been done quietly, either to prevent enemy interference and bombing of work in the war zones, or because there was no need to inform Hitler and Hirohito that ships they thought safely sunk are again

carrying cargoes for the United Nations.

The Navy salvage chiefs, whether they work in Eritrea or in the Solomons, in the fog-bound Aleutians or en route to Murmansk, must always work pretty much on their own. Every salvage job calls for quick, flexible planning and ingenuity in devising salvage methods.

All salvage jobs, however, fall into a few general classes. The trick is to adapt the standard salvage methods to fit each new task.

One of the largest classes, in terms of

tonnage saved, is that of ships which are disabled but not sunk. Here salvage in the Navy begins the moment a ship is hit, when repair parties explore the damage and try to limit it. They shore up weak bulkheads, patch small holes, pump out compartments, and restore or improvise hose and communications lines, so that the ship can, if possible, get under way again

When the injuries are so great as to prevent the ship making way under its own power, towing is resorted to a tricky and dangerous job in heavy and icy sens with enemy

To train divers for the exacting work of ship salvage, the Navy set up a unique school at Pier 88 on the Hudson River, in New York City, where the Normandie lay, Navy men who apply for this work are given classroom instruction, and then go down from the float shown below for practice in using cutting torches, applying potches, and other tasks encountered in salvage operations

#### NAVY TRAINS DIVERS ON THE SPOT #5






aubs always presenting an added element of danger for both the injured ship and the rescue vessel. Once towed into harbor, a disabled ship can usually be repaired and a very high percentage of its value recovered.

Stranded ships fall into an in-between class. In wartime, these are often ships that have been deliberately run aground to prevent their sinking. Hence they may have great holes in their huils, which must be repaired or temporarily patched in an angry surf before the ships can be refloated. In such cases, the most obvious things are usually the worst things to do. The amateur would think that discharging ballast and cargo would lighten a ship and permit her to float off. But usually, when this has been done, rough seas have heaved the ship farther ashore and either completed the wreck or made salvage far more difficult

The skilled salvage man, therefore, first tries to make his ship stay put. He adds ballast. Then he runs out beach gear, setting anchors a few hundred feet from the ship. Usually he plays safe and sets these to all four quarters, until he can get a chance to study the lay of the bars or reefs and decide which is the best direction in which to haul off.

Another bright thought of the amateur is towing. If a ship is very, very lightly aground, towing might help in a rising tide and a calm sea. But whenever conditions are bad—and they usually are—towing may make things worse instead of better. A 10,000-ton vessel may be resting 1,000 tons of its weight on the ground. Three hundred to 500 tons' pull will be required to overcome friction in pulling 1,000 tons along the bottom. And the biggest tugs seldom have a pulling power of over 15 tons, because they must gain all their power through the pull of their propellers in the water. What usually happens is that the tug stays put on the end of its cable and its propellers churn up the sandy bottom and send it against the hull of the ship, making the task harder. With beach gear and anchors.



a much greater pull can be exerted.

Tugs can be useful, though, in refloating a stranded ship. One way they are used is to scour the silt and sand away from the ship's hull, by the ac-

tion of their propellers. Sometimes they tie themselves by the bow to the stranded ship and thus dredge a channel through which the ship can be hauled into deep water. High-pressure hose lines are often used to remove silt or to form working channels alongside of stranded or sunken hulls, when patches are to be applied to the sides or bottoms.


By far the most spectacular sort of salvage work, however, is that in which sunken ships are raised. One method utilizes the ship's own structure to attain buoyancy. Divers go down and explore the hull, locating all holes and measuring them. Then the engineers decide which holes must be plugged up or seated to make pumping or blowing possible. Since modern ships are divided into compartments, it is not necessary to seat all openings under water. Many can be left to later work after flotation and docking.

The choice of pumping or blowing depends on circumstances. Pumping is accomplished with ordinary large-capacity gas-driven pumps or with electric underwater pumps. Blowing involves the use of great air compressors on the salvage vessel, which force air down through hose lines and thus blow the water out of chosen compartments. When a sufficient number of compartments have been blown free of water to restore buoyancy to the vessel, it rises to the surface

For ships in relatively shallow water and in protected bays and harbors, the cofferdam method offers some advantages. This method involves building up a ship until it stands clear of the water at high tide. If this can be accomplished, the water can be pumped out of the combined structure—hull and cofferdam—very much as if a giant bailing operation were being carried on.

The cofferdam itself may be built around the whole hull or around selected deck openings, such as cargo hatches. The structure is usually built in sections ashore and floated or carried on barges to the wreck. Floating derricks aid in setting it in place, while divers secure each section to its corresponding portion of the ship, using cables and stays and turnbuckles until they achieve a watertight joint.

While both the cofferdam and seal-andpump methods involve the restoration of buoyancy to the ship itself, this cannot always be accomplished economically. Ships



methods. This involves the use of large cylindrical pontons—great tanks that can be submerged alongside of the wreck. Once attached, they are pumped or blown clear and thus float the wreck to the surface in a single stage. The method is ideal for the raising and relocation of relatively small wrecks lying at substantial depths.

Curiously enough, some of the jobs that look the hardest are actually easier than some others. A floating dry dock, for instance, seems to present the most difficult of all salvage jobs, especially if it has been effectively scuttled. However, a dry dock is a vessel originally constructed for great buoyancy. It must float both itself and another vessel. Thus, to raise the dry dock alone requires the sealing off of only a few of its many compartments.

The decks and bulkheads of a floating dry dock also are built to much higher standards of atrength than are those of most ships, for the decks must support the weight of great ships, and the bulkheads must withstand water pressures in the process of submersion and flotation, which is the dry dock's way of working. Hence, salvage of such a vessel may actually prove easier than the lifting of a much smaller hull.

By no means all sunken or derelict ships can be salvaged, even in peacetime. Four hundred feet is almost the maximum depth at which any work at all can be carried on; most salvage work is done at much shallower depths. Many ships that sink even in shallow waters are simply blasted away as dangers to navigation, since their value "as they lie" does not sufficiently exceed the cost and risk of the salvage operation they would require.

Despite these limitations, Navy Salvage does not lack for work. Before the war is over, it will have restored well over a billion dollars' worth of ships and cargo to the United Nations, and that figure is based upon value after salvage. The true worth of Navy Salvage cannot, of course, be estimated, for it must include the immeasurable value of having cargo vessels and combat ships now, which could not be built new it our capacity-taxed shipyards. In that sense, the hulls that rose out of the mud at Pearl Harbor, and countless others, are "finds," ghost ships rebuilt to better-than-before fighting power, now hitting back at the enemy that treacherously sent them to the bettom.-ALBERT Q. MAISEL.



American bambers, swarming in from the sea, are depicted drapping black-busters into the croters of Japan's volcanous to set them into fiery eruption

# Can We Blast Japan from Below?

An eminent geologist suggests that bombing volcanoes might let loose a wave of destruction and terror among the enemy.

By HAROLD O. WHITNALL, D.Sc.

Professor of Geology and Geography, Colgote University

Drawings by B. G. SEIELSTAD

APAN sits astride the most unstable piece of crust on the earth's surface. It has 30 active volcanoes, to say nothing of hundreds that jut skyward in uneasy slumber. Earthquakes are as numerous as shooting stars in August. Hardly a day passes without some of Hirohito's dupes feeling the earth wobble beneath their feet. Fear of volcanoes is so thoroughly ingrained in the minds of the Japanese that they have made gods of them, placing shrines at the bases to appease threatened anger with gifts and supplications. So great is their awe of


these smoking mountain deities that it is reasonable to believe that bombing attacks on them would loose the same cataclysmic terror that undoubtedly would ensue if our bombers blasted the palace of the Emperor—the so-called descendant of the Sun-god.

But block-busters might do even more than that. Since shortly after Pearl Harbor, I have recommended that our all-out attack on the Japanese homeland be accompanied by bombing raids on Japan's volcances. I believe that explosives dropped down their throats may cause such a vomiting of lava and ash as to hasten the day of unconditional surrender. Bombs are growing bigger and bigger, and I am increasingly convinced that such an attack is worth trying.

Rising abruptly from a deep part of the Pacific, Nippon's island empire is largely volcanic. Adding to this precarious condition is a series of long and deep fractures or faults in the earth's crust that run along its eastern coast. Similar lines cross the islands from east to west. These lines of weakness are like an inverted sword of Damocles which threatens from below instead of from above. They permit great blocks of the earth's crust to slip against one another. Each time such a displacement occurs, an earth tremor results. The possibility of widespread volcanic activity as well as severe displacements puts the crust of Japan in double jeopardy. Sometimes havoc comes on a large scale. So it was in 1928, when a portion of the crust auddenly snapped and slipped 100 feet along an extensive line. It brought violent death to 150,000 Japanese and caused terrible destruction in Tokyo and Yokohama.

The relationship of volcanoes and earthquakes is obscure. One seldom results from the other, yet there is evidence that in some mysterious way both are connected with the deep, hidden plumbing system beneath the thicker portions of the outer shell of the earth. There's no blueprint of this intricate arrangement of reservoirs, pipes, or connections that exist in that bewildering labyrinth. Only the surface manifestations are definitely known. In a volcano, the main outlet can be studied. From that, it is generally conceded that after eruption has ceased, the molten matter remaining in the vent or chimney often becomes hardened and acts as a cork sealing the upper portion. The thickness of such plugs varies and cannot be ascertained. Moreover, their lasting qualities are unknown.


In a dormant volcano, gases and molten matter beneath the plug may be gathering again and exerting new pressure for a blowout. Should it be that the time for an eruption is near, it is quite within the



realm of possibility that a raid on the crater with block-busting bombs might be the force to set it off. Applying the same argument to earthquakes, it is by no means unreasonable to suggest that a terrific jar produced at a time when an earthslip is in the making might accelerate the dislocation.

Because of their quaking land and treacherous volcanoes, the Japanese have produced some of the leading students of earthquakes and volcanoes. They know well the physical danger that constantly threatens their country. The Japanese Navy during target practice and battle maneuvers significantly moves far offshore. Some years after the earthquake of 1923, the U.S. fleet steamed into the waters of the bay between Tokyo and Yokohama. Japanese officials on abore radioed a request to this effect: "The Japanese Government requests that only the smaller guns be used in exchanging salutes. So sorry, please." These evidences of caution may add up to something

If the story broadcast from Berlin telling of the cruption of the big Japanese volcano Aso San after the Doolittle raid is true, it is safe to wager that the cruption caused



more jitters among the little people of the empire than did the bombing of Tokyo itself. Curiously enough, Nipponese official-dom was silent on the subject.

The idea of bombing volcanoes into activity and jarring the earth into earthquakes probably will be met with mingled derision and approval. Ultraconservative scientists, whose vision is often swathed in mathematical formulas, will anort, "Impossible!" while those with the imagination of Ben Franklin with his kite may murmur, "Could be, could be."

If all voicenoes were sealed tight to a great depth, no explosive now known to man would be able to crack the cork. Neither could any amount of surface pounding bring about a new dislocation in the earth's surface. But if the plug, like a slightly loosened cork in a champagne bottle, was about to blow because of pressure within—or if the earth's crust was in danger of becoming dislocated again owing to the force of internal strains—high explosives might well set off either delicate trigger months or even years before its natural time.

It is estimated that a bomb shelter capable of withstanding a hit by a 4,000-pound block-buster must have a cover of at least 100 feet of soil or 50 feet of solid rock. That, of course, doesn't mean the bomb could penetrate that far. But it does represent the approximate depth at which severe cracking would cause the collapse of the shelter. While there are no figures available as to the depth at which even bigger bombs would cause cracks, their effect would surely be felt farther down. Added to the depth of the sone fracture would be the extension of the shake-up.

This we know. Two-ton bombs are being supplanted by much heavier ones, and it is likely that still newer bombs will make the original block-busters resemble exploding firecrackers. There is no reason why these superbombs shouldn't be tried on Japanese volcanoes. The targets are many, and the openings are wide. To those conservatives who may ridicule the suggestion, we toss a quotation from the eminent psychologist Dr. Albert E. Wiggam: "A conservative is one who believes that nothing should ever be done for the first time."


JANUARY, 1944 195



A DRAFTSMAN'S TOOL of Lumarith plastic has the important working feature of dimensional stability. Besides not registering effects of temperature and weather, the triangle is lightweight and transparent. Designed and patented by Earl J. Early, of Drexel Hill, Pa., the "Line-O-Graph" incorporates a ten-inch rule, straightedge, various angles, French curve, gradation markings, and holes for drawing parallel lines.




### HERE IS THE SOLUTION OF THE BOX PROBLEM



Four small triangles of scrap mark the box pattern diagrammed above. The old pattern used at Westinghouse for making spore-parts boxes (see page 54) wasted four rectangles, requiring a sheet of aluminum 10% feet square. Now a sheet 7% feet square makes the same size box by this new, stronger, less costly design

FOOT-PEDAL CONTROL of this rotary welding fixture, developed at General Motors, enables the operator to regulate the mechanism without interrupting his work. With the push-button control formerly used, he had to lift his shield each time he wished to stop the device. Now both his hands are free for work, while his foot controls the fixture.

A NEW VOLTAGE TESTER that reads like a thermometer is a versatile tool for all electrical maintenance in industry. When the needle-pointed prods are connected across any line, the tester indicates, among other things, the voltage, frequency, and type of current.




### Evaporation Cools Big Bomber Plant

NABLE to obtain standard air-conditioning units, engineers successfully lowered the temperature in Consolidated Vultee's sweltering Tucson, Ariz., hangars by reviving an old desert trick of cooling through evaporation. Workers now turn out Liberators in comfortable temperatures of 85 and 90 degrees while the mercury registers 105 outside.

Sheds on top of each hangar are set with huge pads of excelsior. which are overhung with perforated water pipes to keep them molat. Behind these lie fanlike blowers that suck in the dry air through the damp pads. Cooled 15 to 20 degrees through evaporation of the water, the air is then forced into all parts of the hangar through air ducts. The output of the entire system is 2.564,000 cubic feet a minute. Besides cooling, the pads also filter the airvery important in keeping instruments and engines dust-free.

Miniature pads and blowers are used to cool the interiors of Liberators stationed on the outdoor assembly line. Though not as effective as refrigerating units, the system of evaporative cooling, which has long been used in private homes of the Southwest, but never before on such a large scale, is highly satisfactory except on rainy days, when the air refuses to absorb extra moisture.

To cool drinking water in the arid Southwest, Indians use porous jars that let a little seep out and evaporate. This chills the jar and cools the water. The reason: The molecules that escape into the air are extra lively—for above average. So the ones that are left have




erage. The less their velocity, the cooler the surface becomes. This is exactly what happens when you step out of a swimming pool and let the moisture from your the idea to cool a desert bomber factory



Fans range in capacity from 22,500 to 65,000 cubic feet a minute. They change the air every four minutes in hangars

Above, for room foced with excelsion pads, kept constantly moist. Below, outlet and baffle in office ceiling. Paper strips indicate air flow





## Coal to Our Rescue

We can forget our worries about dwindling oil supplies. Wartime research has found miraculous ways to get power and chemicals for a thousand years of better, richer life.

### By ALBERT Q. MAISEL

DOES "coal age" sound dismal to you?

Does it make you think of smoke, dust,

soot, and shaking the clinkers out of the
old furnace?

If it does, calm down and think again. For you are on the doorstep of a new coal age right now; in fact, you're more than halfway through the door.

It's going to be a richer, cleaner, healthier, easier-to-live-in age, too-thanks to what research chemists have discovered while applying coal to new war uses. We aiready get a large proportion-often a major proportion-of our power, our heat, our plastics, our industrial chemicals, our solvents, insecticides, tars, varnishes, paints, and even perfumes from coal or its derivatives. But that long list of present coal products is going to look short within the next couple of years. We'll get brand-new products that, today, are just a gleam in some laboratory chemist's eye-and many of our present coal-based commonplaces will become far more common and far cheaper than they have ever been before.

When you check up on some of the new coal processes, you find that a lot of them

first began to be developed 20 or 30 years ago. But then along came our gushers of oil and our developments in oil cracking, making it possible to obtain competitive chemicals from oil far cheaper than the just-born coal processes could produce them. Now the war has taught us that our oil resources are not inexhaustible. In fact, at the present rate of consumption our proved reserves won't last much more than another 15 years or so. And new discoveries are lagging far behind consumption. Last year they replaced only 57 percent of the oil we used up. This means that we may be forced to turn to coal.

But don't get the idea that such a turn will be a total calamity. Right now, gasoline from coal costs somewhat more than does petroleum gasoline. But petroleum costs will go up while coal-processing costs are going down. So in the end, after a few years at most, you may be getting your gasoline as cheap or even cheaper than when you took it from the oil well. More important, you'll be sure of getting it, come what may. For we have 670 times as much coal in the ground as we have oil. At the present rate of use, our coal should last nearly 4,000 (Continued on page 112)


Like puffed rice, lumps of cool are exploded and pulverized by high-pressure steam. In this finely divided form, the cool can be piped to a furnace as readily and economically as liquid fuel or gos




Steam from a high-pressure bailer feeds into the coal filled polyerizing tube so that each pare of the coal is saturated to the very limit



When the tube's steam load is at peak a hydroulically aperated valve releases it, and the pressure within the coal explades it into dust










This modern by-product coke plant of the Carnegia Steel Co., at Clairton Pa converts coal into coke for blast furnaces, and pipes off coal gas from which countless valuable chemicals are obtained

Pulverized coal may prove a book to hydroelectric power-generaling and irrigating works by bringing into general use the Humphrey pump, which can raise water back over a dam to replies shithe reservoir.





A mixture of pulverized cost and air is ignited in the cylinder of the Humphrey pump. The resulting explosion rains a column of water down the cylinder and into the U shaped tube, which takes the water back over the dam into the supply pool. Water remaining in the discharge tube runs back, clears out combustion goses, and compresses a new fuel mixture, as inlet valves admit the following charge of water






### Making Coke for Steel and By-Products





ABOUT ONE MINUTE IS REQUIRED TO PUSH A CHARGE OF COKE OUT OF OVEN Filled from a coal bunker by an electrically propelled larry car, this battery of coke ovens supplies fuel for the blast furnaces of a steel plant. Each individual oven is 144 feet long, 12 feet high, and less than two feet wide. A traveling pusher ejects its 2-ton charge after about 17 hours of coking. Coal gas, driven off in the heating, yields valuable materials in a by-products plant (diagram in insert at top)



The "pushing machine" at left lifts off the end door of an oven, rams out the cake, and replaces the door. An electrically operated "luting buggy" (right) then seals the door with clay

years. Even if we quadruple that use, we still won't have to worry about running short for at least a thousand years.

One nice thing about getting gasoline—and other things now derived from petroleum—from coal is that we won't run into regional shortages again. Coal, despite temporary shortages in production, is available in more than 30 of the 48 states, so we won't have to think about safe routes for tankers or about building new oil lines.

But gasoline from coal, important as this may be to a ration-conscious America, isn't the only new thing that is coming our way from the coal mines. We're already beginning to use some new coal fuels, and we're going to use them a lot more in the For instance, there is so-called "fluid coal." This is a special form of pulverized coal that is mixed with air and then made to flow through standard pipe systems, sometimes a quarter of a mile or more in length. The Columbus Bolt Works has used one of these furnaces, developed by the Battelle Memorial Institute, Columbus, Ohio, one of our major coal-research laboratories. And it did its forge-heating work at only one mixth of the cost of the oilheated furnaces in the same plant,

Even so, the use of "fluid," or pulverized, coal might not be too desirable if another group of researchers, at the Armour Re-

a way to pulverize coal by steam explosion, a method similar to that by which puffed rice is "shot from guns," as the ads used to say. The lumps of coal, direct from the mine, are fed into a pulverizing pressure tube fed from a high-pressure steam boiler and equipped with a hydraulically operated, quick-opening valve. Steam, admitted under pressure into the gun, soaks into the pores of the coal. Then the hydraulic valve releases the pressure automatically and—presto—the pressure within the pores of the coal causes it to explode into millions of tiny particles.

Curiously enough, the process serves to clean the coal at the same time. This occurs because the impurities, such as bone and pyrites, are much less porous than the coal substance. Hence these impurities break into larger pieces and can be separated from the pulverized coal by a simple screening process.

Like the "fluid" coal development, colloidal coal was experimented with back in 1917 and 1918, but was dropped because of oil competition during the last war. Today colloidal coal—a mixture of oil and powdered coal—is again proposed. It can save more than 30 percent of oil consumption. And it is particularly handy because it doesn't require the rebuilding of large furnaces, such

as those in power plants, which were originally designed for oil and have no ash pits and grates.

Pulverized coal may be called upon to bring about a rebirth of the Humphrey pump, a unique type of engine designed over 30 years ago but still used only in its original installation. The power to operate it is generated in the same cylinder serving to pump the water; it is thus an internal-combustion engine and a pump combined. But instead of actuating a metal piston, as in ordinary engines, the explosion pushes up a column of water, which is discharged at a higher level.

The pump is shaped like a U tube with one leg much longer than the other, in fact extending 40 to 60 feet above to the discharge end. The short side is a closed end and is the head of the engine. Inlet valves admit a charge of water into the lower part at the proper time, which is just before the water remaining in the discharge tube starts to back down at the end of the power stroke. The returning water scavenges the combustion gases and compresses the new fuel-air mixture introduced meanwhile through the head. Ignition of the charge causes the cycle to be repeated automatically

The original Humphrey pumps, still in use on the River Lee in England, operate on producer gas, a rather expensive fuel. It is now proposed that pulverized coal be substituted for gas in order to lower operating costs and, quite probably, improve the over-

all efficiency of the pumping operation.


In connection with hydroelectric generating plants, the use of Humphrey pumps, placed alongside of the dam, would accomplish two useful and economic services. First, judicious use of the pumps over the various seasons would compensate for the vagaries of rainfall and fluctuations of river flow by making it possible to pump water from the tailrace of the turbogenerators back to the reservoir for use over and over again. Thus the average power output of the plant could be put on a continuous basis, unaffected by flood or drought. Second, the combination of a storage reservoir for the water together with the pumps makes it possible to meet daily peak loads by drawing on the reserve water without the necessity of providing corresponding pump capacity. For use in waterworks and irrigation, the simplicity of the Humphrey pump holds great promise as a further application of pulverized coal,


By no means is all our coal consumption today accounted for by its use as a fuel. And in the future, despite the new ways of "burning" or exploding coal, we shall probably use a still larger percentage than we now do for making products out of coal

Most of our coal chemicals are obtained today by an indirect process in which we first carbonics the coal into coke and take off tars which yield dyes, drugs, and a host of other chemicals. Then we process the coke further to (Continued on page 184)

### HOW COAL IS CONVERTED INTO GASOLINE

Courtesy of "Cual Age"





An INGENIOUS "slide trombone" device that projects sound waves visually on a screen has been developed by Dr. Claude S. McGinnia, head of the department of physics at Temple University, Philadelphia, so that his students may study sound by seeing it as well as hearing it. Ordinarily, an electronic oscillograph, employing a cathoderay tube, is required for this purpose. This latter instrument, however, is suitable only for definite wave lengths, while Dr. McGinnis's device can be used to project sounds of any wave length without adjustment.

Considering the function it performs, the device, which is diagrammed above, is amazingly simple. When a tuning fork A is sounded at the "mouthpiece" and the valve at B is closed, the musical tone travels through the short tube at the left of the mouthpiece to a thin steel diaphragm D. So sensitive is this diaphragm that it will respond to all sound waves entering the mouthpiece, irrespective of their frequencies. From the center of the diaphragm runs a cocoon fiber E, through which the

sound vibrations pass to oscillate a bearingmounted mirror F on its horizontal "axle." A powerful pin-point beam of light emitted from G is then picked up by the small vibrating mirror and reflected to H, composed of four rectangular mirrors set edge to edge and made to revolve at a controlled speed. From H the light beam is projected on a screen (1) in a series of light dots, which follow each other so rapidly that the observer sees what appears to be a continuous curved line, such as is shown at 1, above.

Now suppose that the valve at B is opened. The musical tone will then travel through both legs of the trombone before reaching the diaphragm D. If the slide C is properly adjusted, the crest of one sound wave will coincide with the trough of the other, as illustrated in S, and the two will cancel each other. What will then appear on the screen will be a straight line (5), showing that the two sounds have merged into silence! So intense is the beam of light that in a room lit in ordinary fashion the wave pattern can be seen on the screen. For a photographic record, sensitized paper is used as a screen.

### Adhesive Is Stronger Than Materials Joined

NEW bonding process that unites metals with extreme firmness, and joins rubber, plastics, leather, or wood to metal, or to each other, with a bond stronger than the materials themselves, has just been made commercially available by the United States Stoneware Company, of New York, Known as the Reanite process, it is already finding vital war uses in the fabrication of airplane subassemblies, shock-resisting motor mounts, sound and vibration-dampener units, instrument mounts, and in bonding rubber or plastic insulation to wire or cable. It is expected to find hundreds of peacetime applications when available for general use.


One of the major features of Reanite is its ability to unite dissimilar materials, enabling full use of the individual physical properties of each. For instance, thin sheets of stainless steel or aluminum can be bonded to chemically impregnated plywood to form lightweight, fire-resistant, waterproof structural assemblies, which can, in turn, be formed into prefabricated housing units, boats, airplane or motorcar assemblies, kitchen

cabinets, and furniture.

Application of the process is simple. The surfaces to be joined are brushed, sprayed, or dipped with Reanite. After drying, mild heat and pressure are applied. With standard testing machinery it was found that a Reanite bond between metals would stand a direct pull of from 1,000 to 3,000

pounds per square inch before breaking. The bond
between rubber and metal
runs from 900 to 1,500
pounds per square inch, the
rubber itself breaking before the bond. A knife is
required for separating the
rubber from the metal

In a test of the adhering strength of Reanite, four 150-pound men were suspended from the lower of two pieces of aluminum banded with Reanite. The results are seen at farright





In using Reanite, surfaces to be joined should first be washed thoroughly with soap and water, or other cleansing agent



The liquid Reonite can then be sprayed or brushed on the surfaces. Parts should be allowed to set until they are well dried



3 After the dried surfaces are joined, the Reanite is set chemically by applying a firm pressure and a heat of 290 degrees F.



Above are the two pieces of bonded aluminum used in test at left. Note how metal has broken while bond has remained intact

# Modern Living



ALUMINUM YARN will be used in a variety of postwor fabrics if further experiments bear out the promise of laboratory tests made on the new material. The girl shown above is wearing an evening sweater of shimmering, golden-hued mesh waven entirely of aluminum yarn. One pound of aluminum can be spun into 33,000' of yarn and still retain great tensile strongth. The yarn is washable, and it will come in various colors

ICE-CUBE TRAYS made of light, transparent plastic, like the one below, prevent the cubes from obsorbing an unpleasant, metallic taste, no matter how long they may remain in the freezing compartment. Another advantage of this new type of tray is the ease with which it can be removed from the freezing unit. The shape of the ice cubes formed in this tray is such that they can be extracted as needed with little trouble





GRAVY WON'T LUMP if thickening is blanded by being swirled about inside a patented glass mixer such as the one above, declare the makers. Contours in the base and the plastic top of the mixer impart an action producing a smooth paste when ingredients are shaken against them for a few seconds. Markings on one side of the mixer make it also useful as a measuring cup. A bead around the top of the glass effectively prevents leakage

STORING FABRICS in a dark, moderately cool place is recommended by textile experts of the U.S. Department of Agriculture, who conducted a four-year test on cottons, linens, and wapiens stored at differing temperatures that ranged up to 102 deg., which was regarded as the summertime heat of the average attic. Although changes in the fabrics in hat storage were not great enough to render them unserviceable, they did show more deterioration than those stored in cooler places. In hot storage, cottons and linens yellowed, and some fabrics weakened. Light seemed to affect the textiles more than heat, for lesser chemical changes were noted when all light was excluded

THIS WASHING SOLU-TION is so concentrated that it takes but a small amount in a pail of water to make the dirt fly, according to the manufacturers. Autos washed with it will gloom without polishing, say its sponsors, and like results can be obtained on windows and other hard surfaces of high sheen. The solution is also hailed as a sover of labor, since articles cleaned in it are easy to tinse, and need no drying





FRUIT-JAR SEALS of a pliable plastic have recently been placed upon the market in a design intended for use on a special glass for and top. The new seal fits around and slightly above the top of the jar. The rim of the cover, beveled on the inside, compresses the seal and molds it over the top edges of the jar when pressed down firmly. Glass does not touch glass at any spot, and no clamps are required for a perfectly airtight seal

ENAMEL THAT DRIES HARD IN ONE HOUR is now made, it will cover some jobs when one coot is applied either with a brush or spray gun. Resistant to bailing water, alkali, alcahol, and acid, the enamel wears well as an interior finish on floors, tables, breakfast-bar tops, chairs, and other woodwark. As an exterior finish it can be used also in clear form an doors, such, and boots





INSECT SPRAY GUNS now being manufactured of wood, paper, glass, and plastics have proved to be as durable and efficient instruments as those formerly made of metal. The tough constituents will withstand long submersion in various kinds of insecticides, while acetone joining of their plastic parts provides as much strength as the soldered joints of the old-type metal sprayers. Lightness is an added advantage of the new guns

A CREAM HAND SOAP devoid of harsh chemicals is being used by the girl warker below to remove factory grime. Possessing an antiseptic quality that guards against infection, the soap combines landlin and other ails with granules of calcium that rout out Imbedded dirt, yet leave the hands soft and unscratched. It gives a good lather in cold water as well as bot, and will cleanse as effectively as many of the absasive-type soaps





preferably a noninflammable one, on flat and pile fabrics. Soap and water may sometimes be used in general cleaning of pile, but be sure that the soap is nonalkaline and always have m re suds than water, Badly pressed-down pile can be retreshed by steaming with a hot flattron touched lightly to a damp cloth laid over the surface of the fabric, or by the repeated applications of steaming bot cloths. While the upholstery is still damp, brush it lightly with a whisk broom, and brush it again when it has dried.

Leathers may be washed with thin auds of lukewarm water.

### Helping Auto Upholstery

#### WHAT TO DO ABOUT UNSIGHTLY STAINS THAT CAN'T BE AVOIDED

#### By RALPH ROGERS

ANY a car owner is like the proverbial housewife who swept dirt under the carpet. In the case of the car owner, scrupulous care is often given to the motor and the body is kept spotlessly washed and polished, but once the door is opened the auto has somewhat the appearance of an unmade bed.

Granted that keeping the mechanical parts of a car in good condition is more important and that all the attention in the world to the upholstery won't make the engine run better, yet you may be surprised at the uplift in spirits a clean car interior can bring—as well as the sizable reduction it can make in your personal cleaning bill at the tailor's.

Use of a whisk broom is all that is necessary most of the time, but occasionally a more thorough job should be done with a vacuum cleaner or an old-fashioned carpet beater. Seats should, of course, be removed

when a carpet beater is used to knock out the dust. This isn't always necessary with a vacuum cleaner, but even then removal of the seats will permit better cleaning of the corners under them

Flat-woven cloth, pile fabrics, and leathers are generally the basic types of fabrics used for automobile upholstery. If dirt is imbedded too deeply for removal by a vacuum cleaner, apply a volatile cleaner, Use a nonalkaline soap. The surface should then be wiped with a damp cloth containing no soap and finally wiped dry with a soft, dry cloth.

On occasion the upholstery may be soiled in spots by some matter other than ordinary dirt and dust. These various accidental stains require special treatment and should be removed as quickly as possible after they have been noted. A number of specific cleaning instructions are contained in booklets published by General Motors and Chrysler. In some instances, especially when water is required, there may be discoloration of the upholstery involved in the cleaning, but often this will be preferable to allowing the stain to remain. Always use clean cloths, change frequently to clean parts of the cloth, and use as many cloths as necessary.

Battery Acids. Soak the spot with household ammonia for about a minute so that the acid will be neutralized, and then wash off the place with a clean cloth and cold water. If the acid is allowed to remain on the fab-

ric, it will eat away the fibers.

Blood. Rubbing with a clean cloth and cold water is often sufficient. If some of the stain remains, apply a little household ammonia and water and, after a minute or so, rub again with a wet cloth. If this is not sufficient, apply a paste of corn starch and cold water. Pick and brush off the starch when it has dried. Several applica-



GREASE

tions may be necessary. Never use hot water or soap on blood spots, for they will set the stain and make removal virtually impossible.

Candy. Stains from candy other than chocolate should be rubbed with a cloth dipped in very hot water. If any of the stain remains after the fabric has dried, sponge with carbon tetrachloride. Chocolate spots are rubbed with lukewarm water, and then sponged with carbon tetrachloride after the upholstery has dried.

Chewing Gum and Tar. Moisten the gum or tar with carbon tetrachloride and acrape

with a dull knife before it dries.

Fruit, Liquor, and Wine. Try rubbing first with lukewarm water, scraping, if necessary, with a dull knife. If this does not remove the stain, use hot water, but remember

Rub the iron-rust soap in the spot with the fingers and, after a minute, wipe it off with a dry cloth, repeating until the wiping cloth no longer shows a stain; then rub with cold water. In applying ink eradicator, always use the No. 1 solution, since the No. 2

will change the color of the fabric. Put ink eradicator, oxalic acid, or sodium bifluoride on the upholstery with an eye dropper and blot with blotting paper, repeating until a clean portion of the blotting paper shows no stain; then rinse by rubbing with cold water.

Lipstick, Apply carbon tetrachloride to the spot



### Keep That New-Car Look

that hot water itself may cause some discoloration. After the fabric has dried, sponge with carbon tetrachloride if any stain still remains. Do not use soap, as it may set the stain.

Grease and Oil. Scrape first with a dull knife, and then sponge and rub with carbon tetrachloride. Dirt contained in the grease may remain on the fabric and can be removed with

lukewarm scapy water, which should then be rinsed off with a clean damp cloth.

Ice Creum. Treat first as a fruit stain, which may be sufficient. In persistent cases, follow by rubbing with warm scapsuds, and then ringe out the scap. When this has

dried, sponging with carbon tetrachloride will remove any fatty matter that remains.

Ink and Iron Rust. Iron rust requires initial rubbing with warm soapsuds and rinsing with cold water. When the fabric has dried, it is treated the same as ink. For this use iron-rust soap, ink eradicator, a saturated solution

of oxalic acid, or a two-percent solution of sodium hifluoride. These are usually efficient in the order listed. The composition of writing inks varies, however, and it is impossible to find an agent equally effective for all. Ink rarely can be completely removed from velvets and flat fabrics without injuring the material.



FRUIT

and blot with blotting paper, repeating until the stain is removed.

Mildew. Rub vigorously with warm scapsuds and then rinse. Old mildew may leave a stain that cannot be completely removed. Try scaking with a 10-percent solution of exalic acid, removing the acid after a minute by alternate biotting and pouring on of hot and cold water.

Nausea. Sponge with cold water before the stain has had a chance to dry; then wash with lukewarm suds and rinse. Use carbon tetrachloride on any remaining stain.

Paint. Rub with turpentine or a half-andhalf mixture of denatured alcohol and benzene before the paint has dried. Saturate dry stains with the alcohol-benzene mixture and work out as much paint as possible with a dull knife. Repeat this several times; then rub with lukewarm suds and rinse.

Show Polish. Use carbon tetrachloride on black or tan polish. White polish can often be brushed off; if not, use cold water, let it dry, and brush again.

Urine. Sponge with lukewarm soapsuds and rinse with cold water; then rub the surface with a solution composed of one part house-

hold ammonia and five parts water. Let this remain for a minute, and then rinse with a clean wet cloth.

Water spots. Sponge the entire panel of upholstery with cold water; then rub with carbon tetrachloride.



ICE CREAM

# " fill her up with half a cord of oak ...


Can We Use Wood to

ARDWOOD chips are now driving the first solid-fuel trucks to appear on American highways. The standard gasoline motors of these trucks have been converted to the use of producer gas, a mixture composed of hydrogen, methane, carbon monoxide, carbon dioxide, and various tar gases. Pictured on this page is an experimental conversion made by the Rheingold Brewery of New York City, and believed to be among the first efforts in this country to adapt producer gas for use in commercial vehicles. Under ordinary driving conditions, wood is added to the gas producer


Chunks of charcoal-like ash are removed from the generator daily through a cleanout door

Before it enters the motor, the gas is mixed with air by the perforated valve on the pipe






Browery superintendent Herman Reese adds wood to the happer of the first truck he converted. Below, a diagram of the producer



Beat the Gasoline Shortage?



Gas generated by wood chips is the fuel which powers this truck of the U.S. Forest Products Laboratory

every 50 to 60 miles. Hardwood, cut into chips less than 4" in length to prevent arching or pocketing in the generator, is used in preference to softwood such as pine because it leaves fewer tars and gummy residues. Even so, the cooling tanks and filters on the vehicle must be cleaned every 900 miles, and motor overhauls are in order every 5,000 to 8,000 miles.

Technical studies indicate that about 1.76 lb, of wood are required per horsepower hour. Gas producers fueled by coal or coke are more efficient, but they are much larger and more complicated. With wood, if no major changes are made in converting the engine, the maximum horsepower is about 70 percent of that on gasoline, provided that the spark is advanced and the fire is properly managed. But if the compression ratio of the motor is increased (producer gas knocks less readily than gasoline), horsepower can be pushed up to 85 or 90 percent of the gasoline rating. In general, tests show that substantially more gear-shifting is needed with producer gas.

When a cold start is to be made, wood is added from the top of the hopper and an electric fan is attached to the gas offtake pipe so as to suck a current of air through the producer. Ten minutes after the wood is lighted, the generator manufactures enough gas to run the truck. Starting the engine on gasoline will create sufficient suction to build up the fire, but this takes much longer.

As shown in the schematic drawing, the gas producer is a downdraft type. Air is supplied to the fire—within the conical walls of the refractory, or gas-generating area—by five air nozzles which run through the

firebrick from the outer air jacket. The gas, produced by partial combustion of the fuel, flows out the offtake pipe to four cleaning and cooling tanks, fitted with baffles and connected in series. As it is cooled the gas becomes denser (under Boyle's Law) and hence more B.T.U.'s are supplied to the motor at each intake stroke.

A condensate trap is provided at the end of the fourth cooling tank to catch any moisture deposited by the gas, which next passes through a steel-wool filter and oil bath in a tank on the running board. Just before the gas pipe reaches the intake manifold, a valve admits air to the gas, at about a one-to-one ratio, and the mixture is then fed past the throttle to the motor.

During stand-by periods with the motor off, the stack valve at the top of the producer is opened, giving enough air to keep the fire going. This valve is also used to release excess gases at the end of the day. A dashboard control affords a means of varying the amount of air mixed with the gas as it enters the motor; the correct setting changes frequently with the behavior of the fire and the speed of the engine. In practice, the driver controls speed with the throttle and intermittently readjusts the air-gas mixture for best performance. Direct linkage of the two controls is not practicable.

Whether such vehicles, long familiar in Europe, will succeed in replacing conventional trucks in this country depends in large part on whether gasoline shortages become more acute. Certainly the indications are that reduced power and more frequent servicing lay heavy handicaps on producer gas in free competition with gasoline.



# Gus Clears Up a

#### By MARTIN BUNN

O'S WILSON was bringing back the Model Garage wrecker a little before seven o'clock of a cool fall evening. Lighted dining rooms along the quiet suburban street reminded him that if he didn't hurry there wouldn't be anything left at the Park House for his dinner.

Just as he was pressing a little harder on the accelerator, a banshee shrick assailed his eardrums. "Whoo-o-whee-e-who-o-o!" moaned the siren in the courthouse tower down on Railroad Square. "Whoo-o-whee-e-who-o-o!"

"Three," Gus counted. "That's a fire."

He drove on. Down the street, lights flashed on in a garage that stood beside a white Colonial house; seconds later other lights went on in the garage of the cottage next door. Gus grinned. "Jim Allen and Fred Spratt," he thought. "Fighting each

other for the Buffs' Medal because the one who wins it will be the next chief of the Volunteer Fire Department." Headlights flared beside the white house; a car shot down the driveway and into the street. "There goes Jim," Gus told himself. "Always backs into his garage for a fast getaway if the siren blows . . . Fred'll be right on his tail."

He pulled in to the curb and stopped so as to give Fred Spratt a clear road. But no car came dashing out of the open garage. "That's funny," Gus thought. "I wonder—"

Suddenly a dark figure darted across the lawn and ran down the street. "That's Fred," Gus thought as he let in his clutch. He honked his born as he pulled past the runner, a stout man in his shirt sleeves, already puffing hard. He swung aboard as Gus brought the wrecker to a stop. "Step on it, Gus! I gotta get to the firehouse before the engine pulls out!"

Gus stepped on it. Overhead wailed the siren. The sky at the end of the street had reddened to a sullen glow. "There's the fire," Gus said.

"Damn the fire!" Spratt snapped. "You've got to get me to the firehouse before the engine goes out. If you don't, Jim Allen'll win the Buffs' Medal. The dirty rat! Step on it, Gus'"

Once in Railroad Square, they could see the firehouse and a half dozen men running toward it, "What's the matter with your car?" Gus demanded.

"It wouldn't start," Spratt growled. "I dunno why, but I've got my suspicions." Gus kicked on his brakes by the firehouse just as the engine emerged with its siren yowling. Fred Spratt jumped off, landed running, and swung himself onto the engine. "I wanta see you after the fire!" he yelled back at Gus.

Gus told the Park House waitress he'd

"Now, Gus, you can't do that!" Spratt pleaded. "This is important—a real emergency call. Stop at my place on your way home, will you? My car's been tampered with, and I've reason to believe a certain party is responsible—the double-crossing rat!... Have I got proof? I've got enough to bring charges against him at tomorrow's meeting of the V. F. D. But I want to be fair, so before I do, I want an expert to go over my car and find out exactly what's been done to it."

Ough spots without taking a cent for his services because he realizes its value to the community. Its efficiency was bound to suffer if strife broke out between Spratt and Jim Allen. So he decided he'd try to straighten things out.

"O.K., Fred," he said. "I'll be over in fifteen minutes."

When he stopped his roadster in front of Spratt's garage the doors had been closed, but lights were burning inside. Spratt opened the side door to his knock.

The hood of the green sedan inside was raised. Spratt banged it down. "My car's just the same as it was when I tried to go to the fire," he said. "Now you try to start it."

"All right," Gus agreed. He got into the sedan and switched on the ignition. The starter ground over sluggishly, but the engine didn't take hold. Gus waited a half minute, then tried again. Finally he switched off the ignition

"Your starter isn't getting enough juice to crank the engine fast enough."

"Why not?" Spratt demanded,

"Offhand, I'd say your battery probably is run down. That may be your trouble."

# Case of Sabotage

have a rare steak. He got a pitying look and a green pepper stuffed with assorted vegetable matter. Later, he drove back to the Model Garage to finish a job. He was washing up when the office telephone jangled.

"I'm glad I was able to catch you," Fred said over the wire. "The fire's just out—it was a tough one . . . You doing anything special, Gus?"

"Yes," Gus told him. "Something very special. I'm going home, and I'm going to

Spratt grinned crookedly. "Yeah?" he scoffed. "Well, it isn't. I had it recharged only last week, and it didn't really need it. But don't take my word for it. Check it yourself."

Gus nodded and did so. The gravity reading for each cell was well over 1.250.

"Well?" Spratt demanded again

"Your battery seems all right," Gus said. "But hydrometer readings don't tell the whole story. The only way to be absolutely sure of a battery is to check it under operating conditions."

"All right," Spratt said. "Go shead and

check it your way."

"I've got a low-reading voltmeter here," Gus told him. "Switch on the ignition and keep your foot on the starter, will you?" As the starter ground feebly, Gus placed the voltmeter prods on the posts of each cell. The readings, with the battery discharging some 200 amperes, showed good voltage at each cell and very little difference between cells. "Turn her off!" Gus called,

"Was I right?" asked Spratt,

"You were," Gus admitted. "Your battery has plenty of juice, but a lot is being lost somewhere between it and the starter." He examined the terminals, cable, and ground strap. "Everything seems tight," he said, "but suppose you try turning her over again."

With the starter churning feebly, Gus put one voltmeter prod on the frame and one on the grounded battery terminal, meter indicated a voltage drop of less than a tenth of a volt. "O.K. there, at least," ha said. Quickly he put one prod on the startermotor housing, leaving the other on the frame, and again the meter showed an insignificant drop. "There's a good ground connection between the starter and the mount," he remarked. Finally, he placed one prod on the starter-motor terminal and the other on the ungrounded battery terminal, then whistled as the meter hand swung over to two volts. "That's where the trouble is," he said. "In the starting-motor cable."

Fred Spratt let out a bellow. "Now let me tell you something!" he shouted. "You've found something wrong with that cable. Well, that cable isn't the same one that was in my car this morning. It was put in my car right in this garage this afternoon."

He went to his workbench and took a battery cable out of a drawer. "Here's the proof—this is the cable that was in my car. I found it in the trash box over there. And here's the worst of it, My wife saw Jim Allen sneaking out of the garage this afternoon. She was looking for our daughter Marge when she saw Allen close our garage door and walk away. I'm going to bring charges and I'll run him out of—"

"Wait a minute," Gus said. "Let's see where we stand before you start a war." He disconnected the starting-motor cable and compared it with the cable Spratt handed him. His face clouded. "It's hard for me to believe that it was Jim Allen," he said, "but it looks as if someone had done you dirt. This new cable is the same outside diameter as the old one, but instead of being No. 1 gauge it looks as though this were No. 4 gauge, which has only half as much copper, and so only half the current-carry-

ing capacity of No. 1. Less copper means more resistance, so your starter couldn't get enough juice to spin the engine."

THERE was a rap on the door, and Jim Allen came in with a pair of tree-pruning clippers in his hand. "Hello, Gus," he greeted. "Trying to fix up Fred's old wreck? Fred, I saw your lights on and thought I'd bring back these clippers I borrowed this afternoon without asking — knew you wouldn't mind." He noticed the silence of the others then. "What's the matter? You look as if you'd caught me in your chicken coop in the dark of the moon!"

"Chicken stealing is honest," sputtered

Fred Spratt, "compared to-ouch!"

Gus's heel had landed on his shin bone, "Here comes someone else," he said. A car had stopped in the driveway. The door opened and a girl came in, slim and smart in a WAC uniform. It took Gus a couple of seconds to recognize her as Fred's daughter Marge.

"Hello, pops," she said cheefully. "Hello, Mr. Allen. Hello, Mr. Wilson—don't you

know me?"

"I didn't, for a moment," Gue said. "So you're in the Army now. That's fine."

Marge giggled. "I hope you keep on feeling that way," she said. "Because after the war I may ask you for a job, I'm a grease monkey, you know—just finished my automotive mechanics course."

"That's fine," Gus said, "How do you like getting all dirtied up around cars?"

"I love it!" Marge said. "Why, I can't keep away from it, even when I'm home. Pops didn't take his car out this afternoon, and I went all over it for him." She turned to her father. "You ought to be more careful about your wiring." she told him. "That starting-motor cable you had would never get by a motors sergeant. It was all frayed and its insulation was half worn away. I got a new cable downtown and put it on for you. Well, I'm going to turn in. Good night, everyone."

She went out. So did the conversation. Spratt looked at Allen, and his face turned from red to purple. Gus cleared his throat noisily. "Fine girl, Fred," he said. "You can't help admiring these modern kids."


"She\_she\_she\_" Spratt sputtered.


From outside came a banshee wail. "Whoo-o-whee-e-who-o-o! Whoo-o-whee-e-who-o-o!"

"Another fire!" Jim Allen yelled. "Come on, Fred—we'll go in my car." He started for the door, Spratt at his heels. "Want to come along, Gus?" Allen called back.

"Nope," Gus said, "I'm going home and go to bed. I've had too many emergency calls today, by gum!"


### USEFUL AUTO HINTS





Drawings by William Patrick.


- NEXPENSIVE WINTER FRONTS that will look well and give excellent service can be made from scrap pieces of linoleum. Cut the linoleum carefully to fit the radiator grill and attach it with regular spring fasteners after punching a hole in each of the corners. Finish with a coat of good-quality aluminum paint.—C. R. G.
- 2 A DEFROSTER TUBE can be used to keep a driver's feet warm when the heater is remote from him, as heaters are in some cars. The device is sure to prove a great comfort in very cold weather, and only a few minutes are needed to install it. Secure one end of the tube to the heater and run it under the cowl to the steering post. Clamp the tube to the post, pointing it downward as shown at the left. This will provide a flow of warm air where it is needed.—C. B.
- 3 PACKAGE HOLDER. This will carry a lot of bundles and fold flat against the front seat when not in use. It requires a 36" long board, a similar length of %" by 1" stock, a piece of canvas, and some strap iron. Hung on two books screwed into the seat back, it is readily detachable. A small catch will hold it firmly in the folded position when it is empty.—M. G.
- WASHING CARS is often made easier by a hose nozzle that will project a thin, flat stream of water. Such a nozzle can be fashioned out of a rubber tip like those used on the ends of crutches. Simply cut a slit with a knife across the closed end of the tip, and twist the open end onto the threaded coupling of the hose.—A. H. W.





125

# HOME AND WORKSHOP





Book the attack on tuberculosis by buying more Christmas seals

Lustrous metal by mellow condlelight . . . In the mood of the season, this candlestick makes an appropriate gift

ryZugine is an in it Zugginghagage

# Machined Candlestick

## IS TURNED FROM OLD PISTON ON THE ENGINE LATHE


LD-FASHIONED in concept, yet strikingly modern in design and execution, this candle-stick proves that interesting craftwork projects can be made on the metal-turning lathe. A single aluminum-alloy piston provided most of the material.

Clamp the piston in the three-jaw chuck and cut off the skirt with a parting tool as shown in Fig. 1. Turn out the head to a diameter of 3", leaving a fillet inside (Fig. 2). Polish with fine, well-worn emery cloth to a high luster.


Reverse the work on the expanding chuck jaws with a paper lining inside to avoid marring the turned portion. The ring grooves can then be turned bright as in Fig. 3 and cut back slightly for the step effect shown in the drawing. Take a finishing cut across the bottom with a facing tool.


Saw the two piston-pin bearings out of the discarded skirt, chuck a short mandrel, and drive on one of the bearings (Fig. 4). Cut off the waste metal and turn the shoulder for the step joint. Turn the second bearing with a corresponding step to a force fit, press the two pieces together in a vise, and mount them again on the mandrel to turn the socket to the dimensions indicated.


A scrap of 3/16" thick aluminum can be mounted in the four-jaw chuck for boring the handle hole. Jigsaw the outside contour to shape, using kerosene as a cutting fluid; then drill and tap the mounting holes and polish the piece. File a matching notch in the socket flange. Assemble the socket, handle, and base with 2-56 screws.—C. W. W.




Base and socket are turned from an old piston, Insert a bushing if a condle fits the socket too loosely










# Don Uuixote and the Windmill A COMIC WEATHER VANE FOR JIGSAW ENTHUSIASTS By HI SIBLEY

DON QUIXOTE astride his charger, Rosinante, is in luck this time, for he never quite catches up with this windmill, but he will make an interesting figure for your weather vane, especially when painted in bright colors. Both the mill tower and the horseman are jigsawed from %" stock and assembled between sidebars of the same material.

The beveled vanes are constructed by mortising the two members at the hub, through which a bole is bored for the installation of a short length of tubing to act as a bearing. Oil-soaked cotton should be packed in this bearing as well as in the vertical axis of the vane, which should be corked against rain. After the windows and doors are cut, the roof and sides of the mill are painted to represent shingles, while stonework is simulated at the base. The horse may be white, and the rider varicolored.



### Place-Card Favor Features Tiny Skier

A NUMBER of these engaging little place-card figures can be made from a pair of shoelaces and a package of pipe cleaners. Clothe the figure in ski pants by slipping pipe cleaners through short lengths of shoelace and bending the ends to resemble feet. A wooden bead makes the head; colored yarn the bodice. The base is a bit of cardboard.—B. N.





### Novel Jardiniere and Hurricane Lamps


### MADE FROM SCRAPS OF COMPOSITION BOARD

#### Designed by Ernest R. Dewalt

HESE two composition-board projects will yield pleasure in the making as well as decorative objects of real utility in the home. The flowerpot holder is composed principally of eight tapered segments, or slats, which are laced together to form slanting sides. Thus the sides are fitted securely around an octagonal base, forming a jardiniere that nicely accommodates and conceals a clay pot and dish. A pair of hurricane lamps set on bases of crossed composition board will keep their candles alight in a brisk breeze, when used to shed pleasant, mellow light out of doors.

For the jardiniere, cut all the slats at the same time from ¼" stock, suiting their dimensions to the size of the pot and dish. To determine the taper of the slats, draw a circle the diameter of the rim of the pot, and another the diameter of the clay dish. and circumscribe an octagon about both circles. Measure a side of each octagon to obtain the top and bottom width of the slats. Drill holes for the lacing as indicated in the drawing, and also rout slots ¼" up from the base of each slat to receive the tenon tabs of the base. Make the sides of the base equal to the width of the slats at the line of the slots, and fit the tenons into the slots snugly. Finish the jardiniere with three coats of varnish.

The stands for the hurricane lamps are designed to hold 5%" chimneys with 2%" bases. Cut the four standards at the same time. Lay out the chimney notches, the tapered shoulders to hold the candles, and the deep half-lap slots. Center all cuts and use a 1%" radius to round the ends. The wood handles should be slotted and joined to the standards with dowels. Notches are made in the center rings where they fit over the chimney notches. No glue is needed when the stands and rings are assembled.









#### By ELMA WALTNER

ANDLES are so traditionally a part of the holiday season that even in their plainest form they rival holly and mistletoe as symbols of Christmastide. Gay candles like those above, however, will lend an added air of festivity to any surroundings, and they can easily be made at home in many different and fanciful shapes.

You will need some inexpensive glass or china figures such as are stocked on the knickknack shelves of variety stores. By using these figures as patterns, you can cast various different candle molds. Any type of figure will do so long as it is nonporous and has neither undercut surfaces nor frail parts extending too far out from the main mass. The molds are made by pouring ordinary plaster of Paris around the patterns.

With a figure at hand, obtain a light cardboard box that will accommodate it with at least \%" to spare all around. Work a small lump of modeling clay into the shape of a cork and stick it against the bottom of the figure as shown in the drawings. Oil the figure evenly with hight machine or olive oil. Mix a supply of plaster to a creamy consistency. With one hand, hold the figure about \( \frac{1}{2}\)" above the bottom of the box; then add plaster until the model is half immersed in it. Keep holding the figure for a few moments until the plaster is stiff enough to keep it from sinking. In 15 minutes, use a knife, drill, or countersink to form the two keys which will later aid in locating the other half mold properly.

Now thoroughly oil the top surface of the half mold to permit separating of the two parts easily after the top half has hardened; then completely cover the figure with more plaster. Allow another 15 minutes for this new "pour" to set. Peel away the paper box and use the blade of a knife to pry the mold apart. It will separate easily


Melt the wax of some inexpensive colored candles and remove the wicks. Heat the wax over hot water rather than directly over a flame, for overly hot wax will create bubbles in the finished candle. At the top of one of the halves of the mold, cut a little groove through which the wick may extend. Then lay in the wick from the top of the mold to the bottom, where it should be long enough to extend through the pouring hole formed in the plaster as it hardened around the lump of clay. Join the two halves of the mold and bind them securely together with

# Holiday Candles

stout cord. Turn the mold upside down and pour in the melted wax, which should first be allowed to cool to a point where it will harden immediately upon contact.

The wax will shrink a little as it cools in the moid, and you may need to add a little after the first complete filling. Allow the wax to set, but not to become completely cold. Then untie the mold and remove the candle. If the first candle has a tendency to stick, grease the inside of the mold before pouring the next one.

Figures modeled in clay, as well as glass and china figures, can be used as patterns for candle molds. Amateur modelers can produce many appealing original pieces.



### Star-Shaped Santa and Pine-Cone Bird Help Decorate Tree

SANTA CLAUS, in the genial guise of a Christmas-tree ornament, appears in the photograph below in a really stellar role. A number of these fat little star figures, dangling from the boughs of a yuletide evergreen, will be more distinctive than most machine-made tree baubles; and they can be turned out in jigtime with little more than a pair of acissors and a few household materials. Cut the star from a piece of red construction paper and paste a small strip of white paper on part of one point to serve as the face. Ink in the eyes and nose; then add the fur trim, buttons, belt, and the old gentleman's whiskers, using wisps of cotton attached with glue. Slip a wire or loop of colored string through the tip of the uppermost point of the star.

The cocky little bird of paradise at the right will also grace a festooned spruce or hemlock. Shape the head from a small pine block and attach it to the pine-cone body with a dowel glued into holes drilled in each part. For plumage,

use either real feathers or swirls of bright-colored paper glued to the cone. Suspend the bird from a ring of wire covered with crepe paper. A painted wooden ring, if you have one handy, will serve as well for a perch.








old powder box, a wooden candy bucket can be easily converted into a permanent Christmas-tree stand. Almost any music box will do, for the tinking little tone is appropriate for Christmas. Your candy store will usually have some empty buckets made of white cedar, which has good resonance.


In use the bucket is inverted, its base serving as holder for the stem of a small tree. Strengthen the base by attaching inside a 4" block of two by four. This reinforcing piece is held in pace by 2½" flathead wood screws which are countersunk in the top of the stand. Bore a hole through the top and the block together, using an expansive bit set to about 1". To secure a wedging effect on the tree stem, taper the hole with a rasp. If the tree proves too small for a snug fit, it can be held firmly with several pine wedges.

Attach the motor to the inside of the bucket after boring a hole for the winding key. Then replace the bucket top for extra strength. A hinged door makes the stand useful for storing tree ornaments between seasons. If labeled "Secrets," the door gains added fascination for children.

Outline designs on the unfinished wood with a burning tool, and paint with gay colors, or use stencils or decalcomanias. Finish by applying two coats of varnish to the entire bucket. RICHARD F. TRUMP.



Music coming from his tree will charm any child



Take the "musical mater" from an old powder box

install it in the base and cover it for protection



# GUARDING YOUR HOLIDAY TREE AGAINST FIRE


ATERING your Christmas tree, just as you watered your Victory garden last summer and water your potted plants and cut flowers now, will keep it fresh and alive through the Yule season and will prevent discoloration and falling of needles. More important still, watering helps to reduce the ever-present fire hazard.

The U.S. Department of Agriculture's Forest Products Laboratory at Madison, Wis., in co-operation with the University of Wisconsin, has investigated various treatments and recommends standing your tree in water as simple and satisfactory. It advises cutting off the end of the trunk diagonally at least 1" above the original cut and keeping the water level above this newly cut surface while the tree is in use

Four types of stands containing water


receptacles are shown in the drawings below. All can be made in the home workshop. The size of the container is optional but add water as the supply is absorbed


Although a tree treated with water will resist an ordinary candle or match flame, it cannot withstand intense heat, and additional precautions are necessary. Don't use defective electrical connections; don't overload a circuit and risk a short, don't neglect to replace a broken bulb, since the socket may touch metal foil and short; don't put large amounts of combustable decorations on or near the tree; don't stand the tree near an open fireplace or portable heater, don't place the tree where its accidental burning might ignite curtains, and above all, don't place it in a doorway where it might trap occupants of a room



A stand made of a wooden box and a pail


Cross-braced feet hald the tree upright





A galvanized tub with strap-iron braces.

This container is built from a washtub.





some reeded doors, embodies many qualities that will appeal to the amateur craftsman and is so easy to make that only simple tools and elementary ability are needed for its construction. Its adaptability to a variety of purposes will make it as useful as it is ornamental. When hung low on a wall, it will serve both as a very handy recess for odds and ends and also as a

### OCCASIONAL

By
Charles and Bertram Brownold

console table; raised higher, it becomes an excellent china cabinet; and it will take the place of a capacious night table when fastened to a wall near the head of a bed.


When closed, the cabinet is one half of a hollow cylinder bisected vertically. The shelves are semicircular, and the doors are constructed by acrewing pieces of halfround molding to curved cleats.


Lumber yards carry 1%" half-round molding as a stock size, and it can usually be had in oak and pine, and often in other woods. When attaching the molding to the curved cleats, test the straightness of each piece before screwing it into position. Hold it against a straightedge and, if light shows through, trim the edges with a plane or with sandpaper. This is a necessary precaution, because some of the pieces of molding will be found to be slightly bent, and a good job requires that they be fitted next to each other tightly with no cracks showing between.


When marking the wood for cutting the curved cleats, as indicated in one of the drawings, it is useful to know that an 11%" chord on a circle having a diameter of 18" will subtend an arc that accommodates nine pieces of 1%" half-round molding. Each door of the cabinet includes nine such pieces.

The curved cleats can be made from any kind of scrap wood, those in this cabinet having been cut from scraps of %" five-ply fir panel. Any kind of hardwood will do as well. However, if a softwood such as pine is selected for the purpose, each cleat should be made of two pieces glued together end to end with a splined or a scarf joint,

The hinges used to attach the doors to







### CABINET WITH REEDED DOORS

the back of the cabinet should be sufficiently long for each hinge to be screwed to at least two pieces of the molding, as indicated in a photo on the facing page. The screws should also be located so that they piece the thickest part of the molding, and this may necessitate the drilling of special holes in the hinges.

As the door hinges cannot be seen from the outside when the cabinet is closed, the lines of the completed piece are not broken by them, nor by any knobs, door pulls, handles, catches, or other hardware. The doors are held tightly closed by two spring catches, one of which is fitted to the inside of each door in such a position that it engages a small, curved block of wood screwed to the underside of one of the shelves. Each catch is made of a scrap piece of flat spring metal, about %" wide, and is bent so that a longitudinal cross section of it describes a

figure 6. The doors are pulled open by means of a depression or finger grip 4." deep cut into the lower ends of the two pieces of molding that meet when the doors are closed.

Sometimes a larger cabinet will fill a particular need better than this medium-sized one. If so, a builder will find it easy to alter the accompanying measurements to suit his purpose. It is also possible to construct a circular table out of two such cabinets fitted with legs and bolted back to back.




### Hand-Tooled Design Decorates Compact Cardboard Sewing Kit

COMPACT, neat, and highly useful to men who are serving in the armed forces, this sewing kit contains a pair of scissors, four reels of thread, and a compartment for needles. The body is built up of five layers of 14-ply show-card stock cut out to provide recesses for the scissors, thread, and needles, as shown in the drawing, and then glued together.

Covers are made of one layer each of the same type of cardboard glued to the back edges of the body and bound there with tape. The four reels for the thread are made of three layers of cardboard, with the center layers cut to form a slot for wire axles that can be removed from the body to free the reels for rewinding.

All the surfaces of the kit are finished with two coats of colored varnish and a coat of liquid wax. The caricature of a man darning a sock is drawn on paper and then traced on the cover with a tooling instrument. A hand-tooled mottled design further embellishes the covers.—FRANK SHORE.



JANUARY, 1944

#### PROSAIC CHEESE BOXES FORM

### Custom-Built

### THAT MAKE WELCOME

#### By HERBERT BAST

ASSOCKS and footstools are much in demand in a home where a fireplace is the center of attraction on winter evenings, and they are also useful in other rooms. Attractive ones like those shown in the photographs can be made from a round cheesebox with the addition of padding and a yard or so of uphoistery material. Though you won't have the ration points to order a whole cheese, your grocer probably will be glad to give you an empty box for the asking or at a small charge. These boxes are standard, measuring 14" in height and 15" in diameter

Clean the box thoroughly inside and out, using a solution of trisodium phosphate or very hot soapy water; then, after it has dried, set it in the sun to remove any remaining trace of smell. Examine the box next to determine what reinforcing will be needed to make it a safe seat. Three equally spaced 1" by 2" or similar uprights should add sufficient strength. If the bottom is not substantial enough for taking tacks, replace it with a %" thick disk, as in Fig. 1.

Two types of welts are shown on the finished hassocks on this page. For the socalled side welt at the bottom left, extra padding is required on the top. Cut a piece of burlap or muslin 24" in diameter and center it on the box top as in Fig. 2; then tack it to the top all the way around a circle 214" inside the rim. Place a few layers of cotton felt or stuffing around the rim under the burlap and draw the cloth tightly

Both top and side coverings for this hassock are sewed together before being drown over the frame





This pleated summer slip cover may be fitted over the padded top of the hassack just below



The top piece of this hassock is tacked in place before the welted side fabric is likewise applied



#### THE FRAMEWORK FOR

### Hassocks

### CHRISTMAS GIFTS


over it, tacking the edge to the sides of the box about 1" down from the top, as in Fig. 3. Distribute stuffing evenly on the top and secure it with a layer of cotton felt. Cut a piece 22" in diameter from the upholstery material for the top cover and stretch it down over the stuffing, tacking it to the side underneath the padded edge.

For the side uphoistery, use a piece the width of the material—50" or 54"—and 14" in length, and to it sew a 1'4" welt made from the same or contrasting material folded and sewed around a cord. Then tack or sew the side piece at the top (Fig. 4), putting it high enough to cover the tacks used in upholstering the top, and tack one or two layers of cotton felt to the sides of the box. One layer is sufficient if the upholstery material is 50" wide, and two are better if the width is 54".

Work the side cover down carefully, as in Fig. 5, to keep it from wrinkling, and tack the edge evenly to the bottom. Start tacking from the center of the material and work alternately a short distance each way toward the open ends, which are sewed together with an upholstery needle (Fig. 6) when the tacking has been completed. To finish, turn the edges of a circular piece of black cloth and tack it to the bottom.

The hassock with the pleated skirt has the same built-up top and side welt and should be attractive in an early American room or a bedroom. Extra material is needed for the pleats, but side padding is unnecessary. Cut the skirt 16" by 108", hem the bottom the full length, and fold the top into box pleats, pinning each pleat 24" wide with a 14" space between pleats. Sew the welt over the pleats and tack or sew the skirt all around the top edge. If desired, this piece may be made as a slip cover for use over the side-welt upholstered stool.

To uphoister with a top welt, as shown in the photo at the bottom of the facing page, make a 1½" wide welt and sew it to a 22" diameter top cover, leaving the ends open. Cut fabric for the sides 14" by 50" or 54", and fit and sew this to the welt and the circular top. Pad the box with three layers of cotton felt on the top and one or two layers on the sides; then fit the cover over it, pulling it down carefully, and sew up the open edges.





LAY is started in this exciting new top game by winding a string around one of the tops and inserting the top in one of the starting blocks, with the other end of the string in the slot in drawing position. When the string is pulled, the top spins out of the hole and onto the board, finally coming to rest in one of the acoring holes. Scores are tallied according to the value of the holes. If the top lands in the center jack-pot hole, the game automatically is over. Players can spin in turn, or two tops can be spun simultaneously from either end of the board, providing livelier action and the possibility of unpredictable collisions.


The playing area is made of hard, smooth plywood or composition board. First lay out and bore the holes, sanding off any feather edges on the upper rims. Mark hole values


as shown in the drawing. Note that both the high-value and minus holes are near the center of the board. The numbers can be printed on the board with a lettering pen and black India ink, but first test to see if the wood fibers make the ink spread. If so, apply a coat of very thin shellac before lettering, and rub lightly with steel wool after it is thoroughly dry. The rules of the game are glued on the playing area, as shown, and then the whole surface is given a coat of white shellac, finished with a coat of varnish, and allowed to dry 24 hours.

Cut a groove in the hardwood frame, 1/4" from the bottom, for the play board. Bore the string hole in the endpiece and saw out the slot. The lower starting chucks are %" shorter than the upper ones, so that the upper and lower notches will be brought

into good alignment.

Next, assemble the frame around the playing area and mount the starting chucks. The lower blocks are fastened with screws from below, while the upper blocks are mortised in %" on the frame and held with two 👫" round-head screws. Apply a coat of varnish on the frame and blocks. Turn the tops from hardwood, with a flattened edge on each. The shaft is made of 14" dowel glued firmly in place. For smooth spinning, insert a brad in the end. Decorate the tops with bright enamels set off with a few contrasting stripes.-O. E. OLSON,





EEPERS! This road is bumpy," you can almost hear the toy soldiers say as, heads bobbing, one swings over the steering wheel while the other falls backward, clutching the side. Their

CEATTLE TOTAL TO JIM IN

jeep, bucking and rolling, can take it—and so can these bucking buck privates.

The amusing toy is constructed entirely from scrap wood, a few nails and screws, a few inches of a spring-type curtain rod, and glue. The bouncing action is caused by having the rear wheels off center, while the soldiers are made to bob by eccentrics on the


### TOY JEEP

Jounces As It Is Pulled Along

By C. W. BERTSCH

front axle. If wood screws are used instead of pails for pivots and setscrews, the toy can be taken apart for repairs.


Paint the jeep olive green, the tires dark gray or black, and the uniforms tan, with brown outlining collars, ties, and pockets. Finally, use a small, pointed brush to paint in the soldiers' features.




### THE REAL PARTY.




Toping the handle of a hinged magnifying glass to a flash ight barrel will be of help to habbyists and others who have accasion to read fine print, vernier scales, and the like. The glass can be easily adjusted or folded back against the barrel




If the lid of a canister fits too snugly to be readily removed, try fostering a pot-tid knob at the center. This will provide a firm grip for removing even the most stubborn lid. To attach a knob, punch a hole in the lid to take the screw




Any spiral wire binder from a notebook or a similar firm, light spring, will serve as a pencil holder if fastened to the wall near the kitchen memo pad. Loop the ends of the wire and attach with thumbtacks or upholsterer's tacks




Linaleum cut from a scrap end out of the salvage bos will serve as an unusually attractive filler for a desk pad. It will autwear a considerable number of blatters and it supplies a firm, smooth surface on which to write. You can keep it clean simply by an occasional wiping with a damp cloth




ladine stains on linoleum can be removed with a small partion of row patato. If left on a stain, the potato will absorb all of it




A coarse needle for sewing burlap can be made by straightening the handle of a key-type can opener. Sharpen the needle with a file




Tongs for canning jars may be made by twisting the ends of a proper-sized loop of heavy wire over the jaws of common pliers







Should the perforated spout of a sprinkler be lost, you can use the top of a 1-qt. can like that shown at the left, if you happen to have one, to make a good replacement. Cut off the top and bottom of the can, and solder the round bottom piece across the flaring mouth of the funnel formed by the severed top. Punch the holes and solder the piece to the old pouring orm



Hairpins will hold a lamp cord securely on top of a baseboard if the pins are slipped over the cord and wedged behind the board



Hose clamps can be made quickly by forming loops in the ends of wire wropped twice around a hose and tightened with a stove bolt



Before pointing woodwork, tub a coating of petroleum jelly upon doorknobs and the like. It will let you clean off any splashes


# ONE EVENING CHPISTMAS PROJECTS... PEASANT STYLE


LOWERPOTS and holders decorated with bright peasant colors and designs will strike a gay note when arrayed on a window sill. Those at the right are embellished with lively primary hues. Each is designed for a 3" pot, but the dimensions can be changed to suit most requirements.

Construction throughout is of 14" stock. The shallow holder looks best with a pot that's also gaily colored. The sides of this holder are high enough to hide the saucer under the pot, but not high enough to conceal the simple designs on the pot itself. A plain pot can be used in the taller holder, which is high enough to screen it entirely.

Also jigsawed from ¼" wood is the flat back of the five-candle aconce, while the candle holders are cut from %" stock. Fasten the holders with screws driven through the back. Drill suitably sized holes for the candles. These candle sockets should be at least %" deep, and the tops of the holders can be slightly hollowed out to help catch candle drip.

Details for building the sconce and napkin barrow at right are given in these drawings





These gay holders will arrament any winter window sixt



Brighten up a dark corner with this five-candle sconce




Roll out this borrow when your luncheon guests appear

As for the pushcart, which holds a portion of a package of paper napkins folded just as they are packed, make it, too, of 4," wood. The wheels are put on for appearance only, since they are glued to the dowels and do not turn. The handle is a short length of dowel glued in place.

Apply two coats of quick-drying enamel in ivory or white as a background to show off the designs to good advantage. The designs themselves, in bright reds, blues, and greens, can be done with ground oil colors thinned with a little turpentine and varnish, or prepared enamel may be used if the surfaces are held horizontal to avoid running.

If you wish to simplify the decorating, it is possible to achieve attractive effects by using suitable decalcomania designs on the white or ivory background.



Plans for the two put holders on the facing page

### WHITTLED GIRAFFE ORNAMENTS ASH TRAY

THE dubious expression of Geraldine—for that's this giraffe's first name—is caused by what she beholds in the feed bucket. Smokers will covet this accessory, and whitters will enjoy making it, but a creature like Geraldine could hardly be expected to fancy a hearty meal of cigarette ashes.

Lay out Geraidine's profile on a block of white pine 1½" by 3½" by 5½". Bore a series of holes between the legs to make removal of wood easy, and shape the figure with a sharp knife, turning the work often and completing one detail before beginning the next; then curry the body with fine sandpaper. Use toothpicks for horns and white map tacks for the eyes, painting on


black pupils. Mane and tail are tufts of yarn glued in small holes, and the spots are stained. The feed bucket is turned, with carved staves.—E. W.






A CROSS-SLIDE SHIELD on a lathe may help to prevent damage to the cross-feed screw. On certain lathes, advancing the cross slide eventually uncovers this screw and thereby exposes it to chips which may work into the threads. Protection against this may be secured by a celluloid shield which is held by a bolt to the cross slide. Being transparent, the shield does not obscure the micrometer collar when the cross slide is moved toward the operator. Drill a No. 7 hole in the end of the cross slide and tap it ¼ "-20 for the screw. The shield should be as short as possible to prevent interference with cross-feed handle. Sheet celluloid can be bent around a moderately hot knife blade to the requisite right-angle form .- W. E. B.

SCRAPERS for putting the finishing touches on metallic surfaces can be made from worn triangular files. The three surfaces of an old file are hollow ground on a grinding wheel and brought to a point for use in narrow openings. The tool will have long-lasting edges, ideal for removing scratches, high spots, and burra.—EDWIN DREWITZ.






SMALL CIRCLES can be drawn with precision by using a sewing needle bent as shown at the left in a bow pen. The needle should be heated to a cherry red and allowed to cool gradually before bending. With this, a circle can be drawn which is scarcely larger than the point. By reversing, the needle, as dotted lines show, you can draw extra large circles.—SAMUEL T. TILTON.



BROKEN TWIST DRILLS or pieces of drills at least an inch long can be salvaged by means of the simple holder shown below. Although not capable of making deep holes, the drills so saved will be found useful for sheet-metal work, for centerdrilling, and for other jobs not requiring great penetration. The new shank is made of a steel rod, shouldered as shown below, and drilled to be a close fit for the stub. It is then drilled and tapped for a setscrew.—C. W. W.





SHOP IDEAS

FINE DRILLS that are too small to fit properly in the jaws of a drill-press chuck may be gripped instead in a pin vise which in turn is held in the drill press. By this method extremely small drills, No. 60 and finer, may be accurately mounted in a standard chuck. High speeds, fine feed, and a well-balanced chuck are essential in using such small drills. Rigidity of the work being drilled is important, as is the absence of end play in the drill-press spindle. The correct coolant or lubricant should be used with fine drills.—C. W. W.




BUSHINGS can be pulled from blind holes with a device designed by Robert Eckhart, of Peoris, Ill., and shown at the left. The semicircular key is pivoted in a slot at the end of the stud. A wire which passes through a longitudinal slot turns the key at right angles after it has been inserted in a bushing. A pipe spacer is slipped over the stud and the nut tightened against it to pull the bushing





DOUBLE-END BORING CUTTERS can be adjusted for wear if made up of two pieces separated by shims as shown at the right. Worn or broken cutters may thus be utilized. On heavy boring cuts, a bar fitted with an adjustable single-end cutter will often spring excessively, while a double-end cutter may have to be discarded when it wears undersize. But if it is divided into two parts and shims are placed between them, the doubleend type of cutter is readily adjustable. It can best be sharpened between centers on a tool grinder, after the needed shims have been placed inside and the setscrews tightened. The same idea can be adapted for a tool to be used in a drill press for counterboring or spot-facing.-D. C. HARRIS.

PORTABLE SHELVES for use in tool cribs were built by one supervisor who found himself cramped for sufficient shelf space. Made in various sizes, the shelves can be nooked to the enclosure screening wherever needed. Small cabinets and compartments may be constructed for use in the same manner. The shelves are built of wood and are attached by screws to two or more hookshaped pieces of strap iron which are spaced to fit the screening.—Kenneth Murray



The magnifer above is valuable for descate work



A magnet holds this lens to stee or iron surfaces



Above, a slotted base all ps a lens to a steel ect

The lens below helps increase accuracy on a lathe



# LENSES LEND


### Four Optical Aids Toward

By WALTER E. BURTON

NEXPENSIVE magnifying lenses are used in these simple optical aids that will save time and eyestrain as well as increase accuracy in almost any workshop or laboratory. Scrap materials may be utilized for the most part in their construction, while the lenses themselves may be taken from discarded optical devices or purchased for a few cents apiece from dealers in chipped-edge lenses.

A general-purpose magnifier, mounted on an adjustable stand, is pictured at the upper left and on the facing page. The advantage of the built-in light shown with it is, of course, that the intensity of illumination needed for fine work is supplied wherever the magnifier is used, without need for readjustment of room lights. Any positive (magnifying) lens which is 2" or more in diameter and has a focal length of 5" to 8" is suitable.

The base of the magnifier is a horseshoe-shaped piece of %" hardwood. On this an upright metal rod is mounted, its length governed by the normal working distance of the lens. A metal or plastic cell is provided for the lens. A simple and satisfactory way to make one is to machine a recess in a brass, steel, or plastic



### A HAND IN THE SHOP

### Greater Precision in Inspections and Measurements

ring, and then cut a shallow groove in the recess to receive a spring-wire retainer.

From %" bar stock, machine a ball arm 1" long which screws into a hole tapped in the lens cell. The ball fits into a socket formed by the countersunk holes near the and of a pair of steel plates, of the type mually gold at hardware counters as "rebair strips," These strips, separated by a spacer 5/16" long, are held together by two bolts located near the end holes. The other ends engage a ball driven onto the upright.

The lighting system consists of a lens-type flashlight bulb, a cylindrical shade, a pushbutton, and two pen-sized (AA) cells which slip into 5/16" holes drilled in the "toes" of the base, Depending on the uses to which the magnifier will be put, it may prove preferable to use a switch rather than a button, or a 110-volt bulb instead of the battery arrangement.

A magnifier with a magnetic base which holds it on any iron or steel surface also makes a handy shop instrument. As shown in the drawing, it consists of a lens cemented in a plastic or fiber holder which is screwed to a cylindrical magnetic base. Alnico alloy, used for the base illustrated, cannot be machined; but since a hole ran through this magnet, it was possible to insert a wooden plug and to attach the lens holder with a wood screw. You may, of course, magnetize a piece of bar stock yourself, or perhaps a suitable magnet can be salvaged from an old permanent-magnet radio speaker.

A convenient variation on the magnetic base magnifier is another type which can be clipped to your favorite steel rule. A plugshaped base of brass, aluminum, or steel is provided with grooves which receive the edges of the scale; those in the model shown were formed with a milling cutter mounted in a drill press. The base was also split part way along its axis, and partly threaded for a thumbscrew to hold it in position,

One of the handlest locations for a magnifying lens is over the graduated collars on the micrometer screws of lathes and other shop machines. The lens shown, mounted on the cross slide of a bench lathe, has been found to save both time and eyestrain. The lens ring was machined from a piece of brass tubing, while the holder to which it is attached was bent from sheet metal.


The dimensions will depend on the diameter and focal length of the leng used. However, it should be borne in mind that the lens is best mounted at a distance from the surface to be magnified which is slightly less than the focal length of the lens.

Details in the construction of the general-purpose magnifier are shown below. Note that the lens is held in its cell by a spring-wire ring which fits into a recess. The lens might also be comented in



JANUARY, 1944









A High-Speed Steam Engine
That Requires No Castings







ODEL engines, favorite projects with many workshop enthusiasts, involve so much interesting hand and machine work that the making of one is almost a shop course in itself. This little high-speed steam engine can be built from scrap without the use of a single casting. Powered by a model boiler of medium size, it will do yeoman's service in driving a model generator or small boat. For testing or display purposes, it can be operated on compressed air from a paint-spray compressor, tire pump, or shop air line.


The dimensions given can be altered as necessary to permit the use of different stock thicknesses than those specified. This should not affect the design or efficiency of the engine, but it may be necessary to relocate the ports or alter the length of the piston rod in order to secure proper timing and correct piston travel.

Two pieces of flat stock are needed for the cylinder plate and the base. Square these with a file or on the shaper. Lay out the center lines for the column and bearing holes and file the cylinder plate to the shape shown in the drawing. Clamp both pieces together in the drill-press vise (Fig. 1). Run a No. 21 drill through both parts at the same time for the column holes. Tap those in the base 10-32 and open out those in the cylinder plate with a No. 9 drill to clear a thread of that size.

The columns can be turned from 5/16" atock held in a collet chuck (Fig. 2). A sheet-metal gauge, such as is shown in the drawings, is helpful in turning all six to exactly the same length across the shoulders. Polish each with fine emery cloth and thread both ends 10-32.

If regular stock hexagon nuts to fit the columns are not available, they can be made up in the lathe from 5/16" hexagon stock. Chuck this as in Fig. 3, drill a No. 21 hole through, tap it, and chamfer the corners slightly before cutting off each nut.

Both main bearings must be accurately squared across the bottom. If the lathe is the only machine tool available, this can be done by machining them in a four-jaw chuck or by the use of a milling attachment. Drill the bearing holes 1/64" undersize through both parts at once while they are clamped together. After screwing the



bearings fast to the base, as shown in Fig. 4, run a 5/16" reamer through both shaft holes at once.

The cylinder plate can be chucked in the lathe as in Fig. 5 for boring out the cylinder hole. After drilling the hole for the valve chamber, lay the plate aside until the cylinder is ready.

This can be turned from a solid bar or a heavy bushing (Fig. 6). The inside must be lapped, reamed, or bored to a fine finish. Use a boring tool sharpened to a V-point and then rounded off slightly with an oilstone. Take very light finishing cuts, using a high spindle speed and a very fine feed. Brass or cast iron can be bored dry, but a good cutting oil should be used for steel.


Slip the cylinder into the plate and drill through the latter into the cylinder with a No. 50 drill as in Fig. 7. Tap the eight holes in the cylinder 2-56, but open out those in the plate with a No. 42 drill. The plate can then be mounted on the columns, as shown in Fig. 8.

To complete the cylinder, form a %" flat with a file or on the shaper (Fig 9) so as to face the hole drilled for the valve chamber in the cylinder plate. Then drill the exhaust ports as shown in Fig. 10. The cylinder head is easily turned from a small disk (Fig. 11). Snap the finished head on the cylinder and use a No. 50 drill to make the holes for the retaining screws, running it through into the cylinder as shown in Fig. 12. Here also, tap the holes in the cylinder 2-56 and open out those in the head to clearance size.

Make the exhaust manifold of a piece of brass or copper tubing by cutting away part of one wail. Bend it around the cylinder as shown in Fig. 13; then put it aside to be brazed in place at the same time as the valve chamber.

Turn the latter from solid rod, drill it to a depth of about 1 7/32", and finally ream it to a smooth finish. Form a small flat on one side to match that on the cylinder; then braze or silver-solder these parts and the exhaust pipe together. Drill the steam port through both walls of the valve chamber into the cylinder.

The valve rod, although a simple lathe turning, must be a smooth-running, steamtight fit in the chamber and should be cut a



little longer than shown so that the length may be adjusted after a trial assembly of the engine. The button that rides on the cam can be hardened if desired, and the spring can be made from piano wire if a suitable one is not available.

Turn the cam from a piece of steel and file the flats to shape by hand. A 4-36 setacrew will serve to lock it on the crankshaft. If the builder wishes to experiment with 
various lead and cutoff combinations for the 
utmost steam economy or power, several 
cams might well be turned up at this time.

The piston can be turned from solid stock by boring out the inside. Make the outside a snug fit in the cylinder, which may be used as a ring gauge. Turn the oil grooves with a pointed lathe tool; then cut off the piston, as shown in Fig. 14. Reverse it in the chuck to face off the head. Drill the hole for the piston pin with the part clamped in the drill-press vise (Fig. 15) or in the crotch center on the lathe. Cut the piston pin from drill rod large enough to be a push fit in the holes and slightly shorter than the diameter of the piston so that it will not project and score the cylinder.

As shown in the drawings, the connecting rod can be built from \%" flat stock, additional pieces being soldered to both ends to increase the bearing surfaces.

The crankshaft is 5/16" rod. Chuck this in a collet, if possible, to centerdrill the end, which should then be turned down to ¼". Rivet the crank disk to this end, rechuck the shaft, supporting it with the tailstock center, and machine the crank disk concentric with the shaft (Fig. 16). The crankpin should be threaded and acrewed tightly into the disk. It is tapped for a small retaining screw. A washer under this keeps it from unscrewing.

A heavy flywheel is required to carry the piston up on the return stroke. It can be chucked as shown in Fig. 17, turned to shape on one side, and drilled and reamed to a perfect fit for the crankshaft. Reverse it in the chuck to turn the other end to shape. Then mount it on a mandrel held between centers in the lathe and take a light cut across the face to insure its being perfectly concentric with the shaft. Drill the hub for a setscrew as shown in Fig. 18.


If stock of the thicknesses called for in the drawings is not available, and substitutions are made, it is best to make a trial assembly before the exhaust ports are drilled. The exact position of the top of the piston at bottom dead center can then be ascertained with a depth gauge, as shown in Fig. 19, and transferred to the outside of the cylinder. The ports should be drilled slightly above this point so that the piston uncovers them completely at its lowest point of travel.

CASE A NA


As steam is worked through only one half


of each revolution, all parts must work freely without binding at any point and without undue play. Fig. 20 shows the finished parts before assembly. The completed engine appears in Fig. 21.


Adjust the cam on the crankshaft so that the valve opens just as the piston reaches top dead center and remains open almost the full length of the down stroke. It should snap shut shortly before the exhaust ports are uncovered.



### Tailstock Tap Holder Produces True Threads in Lathe Work







Starting taps square in work chucked in the Stathe is greatly simplified by the use of the sliding tap holder shown in Figs. 1 and 2 above. Slipped over the tallstock barrel, it is both advanced and held against turning by one hand. Its advantages over an ordinary tailstock chuck for this purpose are that it permits the tap to enter the hole as the threads draw it forward, and that it can be instantly released and allowed to revolve if the tap binds, thus preventing tap breakage. Tapping can therefore be done under power, although it is advisable to use a low, back-geared speed.

The chuck is of 3/16" capacity and has a straight shank that is held in the sleeve by a setscrew. Turn the sleeve from a bar of cold-rolled steel. Chuck this and support the free end with the tail-stock center for the knurling; then bore it out, as in Fig. 3, to a close sliding fit over the tailstock barrel. Drill through with a ¾" drill and open the hole out to ¾". Reverse the piece in the chuck, with cardboard under the jaws to protect the knurling, and face the end. Finally, drill a No. 29 hole and tap it 8-32 for the setscrew.—C. W. W.

### TAP DRILL SIZES

10.24.

12 24...

43

#### [SHOP METHODS]

8-36.

18-32

12-28

Busil machine-screw taps are commonly designated by numbers instead of fractions of inches. The number before the hyphen represents the diameter of the tap or of a corresponding screw measured over the threads. No. 0 is the smallest being 060° in diameter. The sizes increase by increments of 013° No. 1 being 073", No. 2, 086° and so forth Between No. 8 and No. 10, and between No. 10 and No. 12, the increment is 026°. Although this series runs up to No. 30, the number designation is little used above No. 12, being supplanted by actual sizes in fractions of an inch.

A second number designates the number of threads per inch. For example, a 2-56 acrew is 086 in diameter and has 56 threads per inch. The size of the tap drall is very important in obtaining a good thread. The following sizes of drills will produce approximately 75 percent of a full thread.

Amercan National Amercan Hatienal Course Throad Series Fine Thread Series MUMBER **Historiber** Top Ortif Managher 6-32.... 1 HL 4 3 64" 0-20. 5-44 37 W- 32 29 1-72 **€-40**....

25

Longer tap life better threads, and easier cutting result if a cutting fluid is used. Animal lard oil or sulphurized cutting oil is generally used for tapping steel. Kerosene is satisfactory for aluminum. Brass and cast Iron can usually be tapped dry.


2-64.

3-56.

4-44-

POPULAR SCIENCE MONTHLY SHOP DATA

... 21



SALVAGED WIRE SERVES IN BUILDING THIS COMPACT

### Soldering Transformer

By HAROLD P. STRAND

APABLE of many heavy soldering jobs, this small but efficient transformer delivers up to 110 amp, at about 5 volts for short periods. The heavy current raises a carbon electrode to white heat when it is held against the grounded work. No electric are is formed as in welding, but the heat transferred is ample for soldering

The materials used in making the transformer require priorities if purchased new, but most home workshop mechanics can probably salvage what is needed from junked parts. The No. 16 wire for the primary can often be found in old motor fields, magnets, or solenoids. If one continuous length cannot be found to make up the 270 turns required, wind to the end of a layer and bring out a tap or splice which can be soldered and taped. The heavy flat wire for the secondary can be obtained from old automobile starting motors. If the wire is not as large in cross section as that specified, .321" by .1", lay two lengths together and wind them on in parallel, joining the ends in soldered lugs.

If no heavy flat wire can be obtained, an electrical shop or building salvage yard may be able to supply some old No. 8 rubber-covered wire such as is used for service conductors, submains, or motor wiring. Two pieces about 8' long will be required. Burn off all insulation, wind the clean wires with

a layer of friction tape, and apply a coat of varnish. When this conductor is wound on over the primary much the same as the specified flat wire, it will serve about as well.

To get high efficiency from the small core cross section, the core material should be silicon transformer steel. Strips cut from the laminations of burned-out lighting transformers can be used. Other necessary items can generally be found here and there with little effort.

The first step is to cut the sheet metal into strips 1\%" wide. Altogether, about 7\% ib. of steel will be required. Cut half the strips into 2\%" lengths, and half into 4\%" lengths, as in Fig. 1, and make two piles of strips of each length. Cut enough strips so that when they are piled and tightly compressed, each of the four piles will be 1\%" high. Make all cuts perfectly square.

A wooden form is now needed to stack the core, as shown in Fig. 2. Wooden blocks nailed to the baseboard provide a slot in which a C-clamp is later fitted to hold the laminations. Start by placing two of the long strips and two of the short strips in the form as shown, butting the edges tightly together. In the next set, strips are laid in alternate positions so that they will cover the joints of the first. This procedure is followed throughout the stacking. When all



The white-hot curban heats work enough to melt solder freely

the strips are in place, compress them tightly with a C-clamp so that the unit can be lifted out of the form.

After applying a layer of friction tape to the two sides of the core to pull them together as much as possible, the next step is to make four side from, as in Fig. 3. Clamp two of them with 3/16" stove bolts to the end of the core opposite the C-clamp. Release the clamp and then carefully remove the laminations from this end. Lay aside the core, which should now look as it does in Fig. 3, and start work on the coil

Another wooden form, shown in Fig. 4, will facilitate hand winding of the coil. Wrap three layers of varnished cambric, or a layer of thin fiber, around the form and secure it with cellulose tape. Insert the No. 16 wire through the hole in the side of the form and wind a layer with turns close together. A layer of brown paper is next wrapped around, a second layer of wire wound on, and the process continued until five layers have been applied. As No. 16 wire will wind about 45 turns to the 3" winding space, the winding so far will include 225 turns. At this point bring out a loop or tap, and wind on a sixth layer, making 270 turns in all.

Good insulation is required over the last layer. Several turns of varnished cambric will serve the purpose, or a layer of rubber tape followed by cellulose tape will do. Over this insulation, the heavy secondary winding is applied. Put on 12 turns, which may be in the form of six turns in each of two layers, depending on the width of the wire available. Bring the two ends to within 1/2" of each other, pulling them almost together


with heavy cord, but being sure that they do not touch. Now take the form apart and remove the coil, which should look as it does in Fig. 5. Dip it in insulating varnish and allow it to dry very thoroughly in a hot place.

Place the coil on the open leg of the core and weave in the remaining laminations. Strips of fiber wedged between the coil and the core will keep the former tightly in place, and prevent a ground or short circuit. This fiber is best inserted just before the attachment of the last two side irons.

Next, measure the length required for the ends of the secondary winding to reach the wingnut terminals. If the wire strip is wide enough, holes can be drilled in the ends for the terminal screws, but otherwise soldered copper lugs should be used. Before the final tightening of the side

irons, drive all joints of the laminations solidly together and true up the core.

In Fig. 6 is shown the plan of the top panel, for which %" plywood or a piece of



radio panel can be used. The two wing nuts are the low-voltage output, and the three insulated terminals are the 115-volt input. Four 3/16" machine acrews hold the panel to the top ends of the side irons.

The plan of the wiring is shown in Fig. 8. To prevent overloading, a fuse should be connected in one side of the line. The holder for the fuse can be made by removing two of the clips from a 30-amp., 250-volt cartridge-type cutout. These are mounted on a %" strip of plastic with a thin piece of fiber under it to prevent grounding to the core, and the fuse block is secured with a single machine acrew. The carbon holder and ground-clamp details are given in Fig. 7.


Using the input terminals plus-minus and No. 1, the output will be close to 5 volts; by changing the second wire to the No. 2 terminal, about 5.6 volts will result with an increase in amperage adequate for the heaviest work. Never connect the line to the No. 1 and No. 2 terminals. This might damage the winding and would probably blow the line fuses. The amount of heat can be regulated to some extent by the length of the carbon in the holder. Long carbons increase resistance and reduce heat.

In soldering, the carbon should be held

behind or at the side of the work. This will help protect the eyes from the intense light, and will also keep the carbon from blackening the cleaned area. It takes only a few seconds for the work to heat up to a point where solder will flow. Small parts can be placed on a piece of sheet metal to which the ground clamp is attached, thus avoiding the grounding of each individual part. For such work, use the plus-minus and No. 1 posts, since this gives a smaller output than if the leads are attached to the plus-minus and No. 2 posts.

Keep the carbon in contact with the work during the soldering operation. The end of the carbon turns first to a red and then to an intensely white heat. As its heat increases, the electrical resistance of carbon becomes less, which is a characteristic opposite to that of most metallic conductors. A short carbon is best for heavy work, since it will pass the maximum current when fully heated.

Parts to be soldered should be thoroughly cleaned of all corrosion and dirt. Brass and copper are about the easiest of the common metals to solder. Whatever the metal, bulky and awkward jobs can be done more efficiently this way than with an iron.





STANDARD FREQUENCIES and time signals are all that are broadcast by a powerful new station of the National Bureau of Standards. Casual dial-twisters who tune in on the transmitter, which broadcasts continuously on 5,000, 10,000, and 15,000 kilocycles, may be puzzled to hear only hums, whistles, and ticks. To radio engineers, military and naval technicians, scientists, and manufacturers of musical instruments,



CATHODE-RAY TUBES are used by one manufacturer to test carbon-element volume controls as they come off the production line. This method, said to be superior to the earphone and neon-bulb tests customarily made, uses in addition to the cathode tube a volume control of known characteristics. The unit to be checked is placed in a fixture where it is rotated to the same extent that the permanent control is also rotated. A varying pattern reproduced on the screen of the cathode-ray tube reveals such characteristics of the instrument as the resistance curve, effective rotation, and hop-off. It also detects any grounds or irregularities in the carbon element.

however, the station provides fixed standards of great value.

For example, one of the audio frequencies transmitted, 440 cycles per second, is the musical pitch corresponding to the A above middle C, and the broadcasts may help in settling some past disagreements as to the identity of tone A. The frequencies broadcast are reported to have an error of less than one part in 10,000,000.



A MOCK-UP of the radio rack used in United Air Lines passenger planes has been built for test purposes at the maintenance base of the company. The mock-up contains all radio equipment carried on the planes and is wired for actual operation. It is used by maintenance engineers in making studies of proposed changes in equipment, which are thus possible without holding a plane out of service.

CONDENSERS of the metal-enclosed tubular paper type are being used in many applications previously requiring molded mica units. The hermetically acaled condensers are also valuable where temperature-insulation resistance, voltage capacitance, and temperature capacitance are important. Their capacities range from .0001 to 1 mfd.



### REPLACING HARD-TO-GET TUBES


"Servicing Your Radio"

F YOU can't obtain the correct replacement for a defective radio tube, your set needn't be laid up for the duration. Simple circuit changes may permit you to use other types of tubes. For example, the 3525 is a popular rectifier now difficult to procure. Fig. 1 shows how it can be replaced with a 50Z7 or a 50Y6. The difference in heater voltage between the original and its replacement will not materially alter set performance, it will in fact add to tube life. When neither of these replacements is available, an older tube such as the 25Z5 may serve, while if a 35L6 or 50L6 power tube burns out, it can be replaced with a 43, a common pentode. But since the heater voltages of these substitutes differ from those of newer tubes, some changes in heater wiring are necessary.


Let's suppose you have an A.C.-D.C. superheterodyne with a 12SA7 converter, a 128K7 I.F. amplifier, a 12SQ7 diode detector, a 35L6 or a 50L6 pentode, and a 35Z5 rectifier. If the set is to be adapted for a 43 pentode and a 25Z5 rectifier, make the changes indicated in Fig. 2. A new line cord with a 125-ohm resistor is installed, and the heaters of the 12SA7 and the 12SK7 are rewired in parallel instead of in series. An 85-ohm, 4-watt resistor is placed across the heater of the Two 6-prong sockets are 128Q7, substituted for the 8-prong sockets.

Battery-operated tubes may also be pressed into service. Suppose that a receiver has a 6AS converter, a 6K7 I.F. amplifier, a 6Q7 or a 6J7 detector, a 25L6 pentode, and a 25Z6 rectifier—and that all but the 25L6 and the 6Q7 become defective. A 25Z5 is used for the rectifier, while such battery tubes as a 1A7 or 1A6 and a 1N5 or 1D5 replace the 6AS and 6K7, respectively. The hookup is shown in Fig 3.

If the 25Z6 did not burn out, the other substitutions can still be made, provided the 25Z6 socket is rewired as shown. By using the proper line-cord resistor, any combination of A.C.-D.C. tubes with 6.3-voit, .3-amp. heaters can be used in circuit A. Any combination of battery tubes can be used in circuit B by changing the value of the 3,000-ohm resistor.



The circuits above show two ways of replacing a scarce 3575 rectifi



A superheterodyne as wired for the more obtainable 2575 and 43 tubi

Below, how battery tubes can be utilized in a madified A.C.-D.C. a BATTERY TUBES INS CACUIT B 3000 OHMS -2525 SO MED 50 YOUTS 2576 20 MFD 50 VO. TS 607 CIRCUIT A RESISTOR 2000 0H43 1000 0HMS | W B LEAD (2 MATTS , 2 WATTS) **^**^~~~ CHASSIS SW TCH 20MFD 10MFD 8MFD 200 V 200 V 185 -OHM UNE CORO ALL VIEWS SHOW RES. STOR **BOTTOM CONNECTIONS** 7LQ. 3 TO SOCKET CHASSIS

USING BATTERY TUBES IN AN AC-DC SET

JANUARY, 1944

### Amplifier Circuits and

### FIRST STEPS IN ELECTRONICS

A SINGLE pentode can readily amplify a feeble input signal 350 times, but what if we require an output strength 350,000 or 3,500,000 times that of the original impulse? An example of this is the home radio. A distant station may generate in the antenna a signal to be measured only in millionths of a volt, whereas the loud-speaker may require several volts. Here an amplification of several million is needed. It is obtained by using tubes in cascade.

If the output of one tube is fed into the grid of the next, the amplification of the two tubes is not the sum of their single amplification factors (a value called the mu of the tube) but the product. Thus if a high-mu triode amplifies 50 times, two in cascade will amplify 50 times 50, or 2,500 times.

But when we begin to feed the plate current of one tube into the grid circuit of another, we run into trouble. Figure 1, for example, shows a simple hookup of two triodes. This won't work at all. The second grid, being connected directly to the first plate, is at about the same potential as its own plate, which is connected to the same plate supply. The result is that the second tube won't react to small changes in grid voltage and will not amplify at all. In fact, the high grid voltage will attract so many electrons toward the plate that the tube will probably burn out.

As shown in Fig. 2a, this fault can be overcome by inserting a grid bias battery of about the same voltage as the plate supply. The grid is at approximately the same potential as the cathode, and the tube will

react to small voltage variations produced on this grid by the output of the first tube.


A similar result is achieved in Fig. 2b by using a separate plate supply for each tube, and in Fig. 2c by dividing the potential of a single large plate-voltage supply across a resistor

These two circuits are frequently used as so-called D.C. (direct-current) amplifiers. They will amplify a variation in D.C. or the voltage of D.C., and will faithfully reproduce the wave form of a signal. Medical research makes use of such amplifiers. Figure 3 shows some of the odd wave forms they will follow and reproduce.

But for other purposes, including radio, these hookups are unsatisfactory. One reason is that each tube requires its own plate aupply (or two tubes require a single one twice as large, if a voltage divider is used as in Fig. 2c.) If screen grids and suppressors are to be connected, still more power supplies may be needed.

Even more serious is the fact that these circuits amplify the total input current as well as any variation in it. Suppose the average input is 1 milliampere and varies 001 milliampere. To read that variation on a meter, we may wish to amplify it to one of 10 milliamperes, or 10,000 times. But a D.C. amplifier, in stepping up the variation to this extent, must also amplify the 1-milliampere input current, which will become 10,000 milliamperes, or 10 amperes—a current only heavy-duty transmission tubes could handle. Figure 4 illustrates this.

The answer is, of course, to amplify only the variations and not the D.C. component. Figure 5 shows how this can be done with transformer coupling. A transformer can-



### How They Work

By John W. Campbell, Jr.

not pass direct current; its secondary responds only to changes in the primary current. The D.C. component flows through the primary from the plate to the B supply. Only variations in the plate current (caused by the input signal on the first grid) are impressed on the secondary and so carried on to the second grid.

A second way of passing only current variations on to the second grid is shown in Fig. 6. Several previously neglected features have been included. A variable resistor or potentiometer R1 is included as a volume control; the whole input voltage is impressed across this and the desired frac-


tion applied to the first grid by adjusting the sliding contact. The plate current flows through the plate resistor R5, and coupling is through the blocking condenser C3. This blocks the D.C. plate supply from the grid of the second tube, but passes the varying component freely, because a condenser in effect "conducts" A.C. In an audiofrequency amplifier, this condenser would be one of .004 to .01-mfd. capacity.


Since it is desirable to have the grid negative to the cathode, we can either add a grid bias battery or make the cathode slightly positive to the ground. The latter effect is achieved by adding the bias resistors R2 and R3. The plate current flowing through them causes a voltage drop across each of these resistors, so that the cathode has a few less electrons on it—
is slightly more positive—that if it were
connected directly to ground. The grid,
grounded through R1 in the first tube and
through R4 in the second, is therefore negative with respect to the cathode.

However, to get the full voltage of the signal on the cathode, we don't want it to fight its way through R2 and R3. We provide an alternative way for it through the by-pass condensers C1 and C2. Being A.C., the signal passes these freely. For audio frequencies, these condensers are from 1 to 10 mfd, and 25-volt electrolytic condensers are often used. [CONTINUED]

Microphone impulses are amplified by this unit before entering the transmitting tubes of international short-wave station WGEO Photo courtesy of General Electric







INPUT STAGE SECOND STAGE OUTPUT

OR

VARYING CURRENT

AMPLIFIED VARIATIONS

AMPLIFIED VARIATIONS

IN AN A.C.AMPLIPIER, TRANSPORMER OR RESISTANCE COUPLING PASSES ON ONLY THE VARYING COMPONENT

We need the resistor R4 because, as the condenser C3 cannot pass D.C., the grid would be insulated from ground without it. Stray electrons from the cathode would soon charge the grid so strongly negative as to block the tube completely.

Still another way of connecting tubes in cascade is by impedance coupling. A choke coil (an inductance) is substituted for the load resistor R5 in Fig. 6. This passes a constant plate current unhindered, but variations generated in it by the signal impressed on the grid will be resisted by the inductance and will result in an A.C. voltage across it, which in turn will be impressed upon the coupling condenser C3. This coupling method finds little application in A.F. amplifiers, because a small resistor can do the same work as a larger, more expensive choke coil. At radio frequencies, choke coils are very small and offer advantages over resistors.

The decoupling resistors and condensers (Rd and Cd) in the amplifier circuit on the facing page keep plate-current fluctuations of the output tube from feeding back into the plate circuit of the first tube

through the common plate-supply connection. Were they to reach this tube, they would cause fluctuations in the first blocking condenser and so affect the grid of the second tube. This tube, after amplifying them, would pass them to the third tube, from which they would return further amplified to the first one—and how the amplifier would squeal!

Instead, they go to ground through the condensers Cd, which to them represent a closed circuit, while the D.C. plate current is impressed on the plates through the resistors. For audio frequencies, Cd is usually an electrolytic condenser rated at 250 to 400 volts and having a capacity of 4 to 8 mfd.

In building an amplifier, remember that audio-frequency currents can pass, by induction, from one wire to another. That includes 60-cycle current. Keep heater leads away from grid leads, preferably twisted together in a corner channel of a metal chassis. Don't let plate-circuit leads pass near the grid leads of a preceding tube. It's wise to mount plate resistors right on the tube sockets, and to attach the decoupling

condensers to them there, cutting the leads off to & " or less.

The result of jamming parts together may look anything but neat, but the real problem is one of electrical neatness. Keep every lead as short as you can—short leads mean smaller "aeriats" from which currents can jump by induction. Keep input and output leads as far apart as the chassis will permit. A straight-line layout is good. So is building the power pack in a separate unit.

If despite all these precautions your amplifier still hums or whistles, bitch insulated test leads to a .5-mfd or larger paper condenser and touch it across the various bypass condensers. Keep your fingers out—use long, stiff, well-insulated wire probes. If no improvement is apparent, try hooking an 8-mfd, high-voltage electrolytic condenser across the decoupling and cathode by-pass circuits. In testing, be sure that you always connect such an electrolytic condenser with due respect for polarity.

Since these tests must be made with power on, extreme caution is indicated. Remember that the high-voltage current present is capable of delivering a serious shock. Take care to avoid contact with live wires.

### High-Gain Amplifier Can Be Used As Two-Way Communicator

THIS resistance-coupled audio amplifier will readily step up the output of a radio detector stage or phonograph pickup to loudspeaker volume. With two identical permanent-magnet speakers, it can be used as a room-to-room communicator, the speakers acting alternately as microphones. Water or steam pipes will serve as one lead to the remote speaker. The switch is of the ganged double-pole, double-throw type and

is located at the amplifier. It switches the input to either speaker. A miniature D.P.D.T. switch cannot be used, however, as the input and output leads cannot be brought so close together. The outfit will how! if both speakers are in the same room, as when testing, because of acoustic coupling between them.

A 6SJ7 pentode, 6F5 triode, and 6V6 beam power tube were used in the original. Tri-


odes alone, or other tubes of the same types, may be used, but other values of condensers and resistors may be needed. The following are right for the tubes specified:

Rvc, 500,000-ohm potentiometer; R1, 1,060 ohms; R2, 1,000,000 ohms; R3, 250,000 ohms; R4, 500,000 ohms; R6, 250,000 ohms; R7, 500,000 ohms; R8, 825 ohms; C1, C4, C6, 8 to 10-mfd, 25-volt electrolytics; C2, .1 mfd., 400 volts; C3, .005 mfd.; C5, .006 mfd.; Cd, 8-mfd., 250-volt electrolytic; Rd, 30,000 ohms.






"Support in five minutes," can be announced by the lady of the house to her husband downstairs without a skip of the beater. At left, the amplifier unit



"Coming right up!" is his answer. A switch reverses the connections






BEFORE YOU SHOOT

Canning

Hour Photos



### GIVES BETTER PICTURES FROM LESS FILM

### By KONRAD CRAMER

Director, Woodstack School of Photography

A PLANNED approach to photography simply means correcting your mistakes before you make them. We have learned through war shortages that we can ill afford to make wasteful errors. Such mistakes and oversights often ruin what might be an excellent picture. Who among us has not at times made a shot that would have been a "honey" if that big telephone pole were not growing out of cousin Harry's head? Errors like these are costly at any time; they are a keen disappointment when you have no opportunity for a retake—and yet they can be easily avoided.

Remember, few corrections can be made after the shutter has been released, so let us adopt the slogan "stop, look, and think" before we push the button. The major cause of the errors committed by the average snapshooter is unnecessary haste.

Confronted with what he thinks is good picture material, the average amateur will unlimber his camera and bang away in the best Western frontier style (only be rarely scores a hit). Such speedy trigger action is only justified when the movement of his subject matter demands it. Using a tripod

Sketching in the subjects before you anap your shutter, as illustrated at the top of this page, gives you better composition and a good picture

# Photography

whenever possible is a great aid to

picture planning

The successful artist and photographer actually sees the picture or the photograph he is going to make before he touches paint to canvas or clicks the shutter of his camera. A great help in this visualizing is the habit the professional has of making little plans or sketches for his future pictures. These sketches are really working plans and do not require any skill in drawing. Even the tools for such



#### LOW

There is a sense of loftiness and height in the picture above. It comes from the low horizon

#### MEDIUM

Where you place the harizon of your picture is most important. A medium harizon like that at the left is usually a humarum choice

#### HIGH

Distance is the illusion given by a high horizon. Below, it permits a vast stretch of foreground snow

drawings can be almost anything. A pointed stick scratching lines in the sand is enough to help you plan the layout of your budding master-piece.

I recommend to my students that they always carry with them a small piece of soft charcoal about 2" long. Such soft, broad drawing material is preferable to the fine point of a pen or pencil because it will not tempt you to make a regular drawing of what is before you. Remember, the idea is not to draw the birch trees in front of you, but to make a mark which shows





NO HORIZON. With the horizon outside the picture area, a variety of unusual arrangements is possible. Here the horizon is over the picture; in a photo of airplanes, it might be under

the place where the camera lens is to draw them for you in the picture space.

This is the way to begin. On any old piece of paper, or in the sand or snow, draw a rectangle of the same proportion as your film. (I carry a few pieces of wrapping paper cut to film dimensions in my camera case.) The first decision you will have to make is whether your picture material looks best in a horizontal or vertical arrangement—and it is an important decision. A peaceful landscape with low, rolling hills usually fits better in a horizontal frame, while the tall buildings of New York seem to cry out for an upright picture space.

There is another most important aspect of picture planning: deciding where best to place the horizon in your picture. In the picture at the top of the preceding page the horizon is placed very low, conveying an illusion of height and loftiness. The medium horizon in the picture below it seems to be the least exciting choice, and yet 90 percent of all amateur snapshots generally display this tiresome choice. In the picture at the bottom of the page a very high horizon gives an illusion of distance, while in that at the top of this page the horizon is placed

outside the picture space—a practice that permits all kinds of unusual arrangements.

Pick up a magazine and look over the pictures, studying the various effects achieved by the judicious placing of the horizon. Not only landscapes and seascapes have horizons, but even still lifes and portraits often exist in some relation to a horizon. After you have determined what we might call the apace relation, it only remains to distribute the rest of the major picture elements within this space. To do this, take your charcoal, and inside of the four lines that will confine your picture make an appropriate mark at the spot you think it would be best to place, say, the barn in the top or bottom photo on page 171. Then see how the rest of the picture elements fit into your picture space. Keep in mind that, while it might be troublesome to move the barn itself, it is no trouble at all for the serious photographer to move his camera.

Too many pictures are taken from the spot where the idea of a picture first occurred. This is one of the cardinal sins of picture making. Don't be satisfied. Poke around, watch the picture change in your finder as you move a few feet to the right

or left, or forward or backward. While the photographer has not quite the same freedom of changing things in front of him as the painter has, he can nevertheless achieve innumerable variations of arrangements by such means as camera position and angle and by lens selection. A wide-angle lens differs drastically from an ordinary lens in the way it records your chosen scene.

One more admonition. If, after having planned your future masterpiece, you find that it holds little promise of success, put your camera away and congratulate yourself for not having wasted time and material This method of picture planning has its greatest value in keeping you from shooting

blindly and haphazardly with the idle hope that, as long as you make enough photographs, one or two of them ought to be all right.

And most valuable of all, in carefully planning your picture approach, you teach yourself to see pictures before you take them. There is a tremendous difference between just looking at things and seeing them. Developing your visual memory is one of the best investments you can make. You may have looked at the Grand Canyon, but can you see it again in your mind's eye any time you want to? If you can, you have a faculty which should be a great help to you in taking pictures that satisfy.


### Toys and Statuettes Form Impressive Props for Trick Shots







This isn't a shot taken in an Asiatia temple; it's a double exposure using a tiny statuette





OFTEN, when you look at small toys and statuettes, you can imagine many interesting picture possibilities, if only these miniatures were of huge, majestic proportions. It is a simple matter, though, to magnify their size and use them as props, adding greatly reduced human figures to the composition for emphasis.

For this stunt, a black background is necessary to prevent registering of an exposure on the unused portions of the film. Set up the miniature prop in front of this background and shoot a giant close-up, framing it in such a manner that sufficient portions of the film are left unexposed by the black background.

Next, trace the image of the prop on the ground glass in order to mark the section of the picture on which it will appear; then, moving the camera back, focus on a human model or models so placed that the unused parts of the film will be filled to complete the composition. When this second exposure is made, the result will be human figures in a picture with a gigantic statue or toy. Be sure that the black background is large enough to cover the entire field when the camera is moved back.—Louis Hochman.

### Heating Element Used as Wire in Photographic Developer

IF You need a piece of wire inside a developing tank, tray, or other photographic equipment, take it from an old toaster, heater, or flatiron. Wire used as the heating element in these appliances is nichrome—a

nickel and chromium alloy, as resistant to photographic solutions as silver wire and far stronger. Typical darkroom uses include repairing broken plastic parts and linking together sections of cut film.—J. W. C.

### MILLIONTH - OF - A - SECOND



SPEED photography chalks up another fabulous record with exposures now being made at a millionth of a second. This is possible with a new mercury flash lamp that has a useful life of but one second, yet in that brief span is good for 1,000,000 exposures, far more than the amateur photographer will make in a lifetime.

Using the mercury lamp, engineers at the

### Made with Pencil-Size


General Electric Company, who developed the flash-lamp device, made the photographs on this page. That at the left shows what happens as a stream of heated air is drawn through an electric fan revolving at a speed of 1,800 r.p.m. Below are three views of an arrow leaving a bow at 400' per second, and one of the first jet of water from a faucet turned on full force.


The mercury lamp, no thicker than a pencil, is the source of high-intensity light. It is housed in a reflector lamp resembling a small auto headlight and can be operated manually by push button or automatically by electrical contacts or a phototube and preamplifier. Illumination is sufficiently intense over 20 sq. ft. for photographing the fastest moving objects.

Using household current, the device rectifies it to D.C. in an electron tube and
charges a capacitor that in three seconds
accumulates enough power to operate the
tamp at full flash intensity. The current, at
approximately 2,000 volts and 2,000 amp.,
reaches a maximum of some 4,000,000
watta, lighting the lamp for a millionth of
a second. All equipment fits in a readily
portable box and weighs less than 20 lb.

Though the archer is unaware of it, there is an appreciable gap between bow and arrow at the start of a flight, as these millionth-of-a-second photos show. This throws light on the ancient archer's paradox, that phenomenon by which an arrow flies straight despite its initial slant







Water rushing from a faucet turned on full force — taken at the instant the jet breaks



### PICTURES

### Mercury Flash Lamp





The high-speed mercury lamp, above, is scarcely longer than a kitchen match, but it consumes some 4 000 000 watts during its brief flash. Left, S. Lowrence Bellinger, one of the engineers who helped develop it, inspects the compact electronic control

### Professional Pictures Teach Amateurs Good Photo Technique

THE techniques used by professionals when they are "covering" a photographic assignment for a newspaper or a magazine can provide valuable lessons for the amateur. The subject matter, camera angle, and composition of the two photos at right, showing a mounted U.S. Coast Guard beach patrol and its Army-loaned horses somewhere on the coast of Washington, have been used to attain the best results both photographically and from a journalistic viewpoint.

A wise choice of camera angle is demonstrated in the first photo. It shows to full advantage the trailer, the horses, and the men in action. An amateur would probably have photographed the trailer from a lower viewpoint, in which case only the horses heads would have been visible along with the one man in the foreground and part of the Coast Guardsman in the cart. The beach scene continues the story the first picture began to tell, but in addition to this, it is pictorially excellent.

What this news photographer has done can be applied to any picture-taking problem. Often it may mean the difference between just another anapshot and a really valuable photograph, or series of photographs, telling vividly and artistically an interesting story. A careful study of the subject at various angles, together with particular attention to composition, will go far toward achieving these results.






### MIDGET ICE YACHT

### **Gives Youngsters Speedy Rides**

This tiny iceboat, designed to carry a 10-year-old, is capable of enough speed to satisfy any youngster. Material to build it can be found in the average home scrap pile. Two %" by 6" boards serve for the chassis; the mast is trimmed and tapered from a 5' length of straight-grained 2" by 2" stock; the 30" boom is formed from a shorter piece of the same material; and %" stock

will serve for the runners. Brace the mast with wire looped over a pin at the top and drawn taut through eyebolts at the bottom.

To gain speed for the boat, cut grooves in the runners and lay in heavy wire, bringing it up around the curving ends and anchoring it with acrews. Bevel the edges of the wood away from the wire along the whole length of each runner. The forward runner, or foot rudder, should be pivoted on a 3" lag acrew, as shown in the drawing. Use washers as a bearing between the chassis and the rudder, and install a bushing in the hole in the chassis through which the lag screw passes. Unbleached muslin, hemmed as shown, forms the sail,—H. S




### Yardstick Scaled from Middle Locates Centers Accurately

CENTER-LOCATING rules that can be made from a straight strip of wood will often save an otherwise perfect job from an unsightly off-center error. The wood stock should be

about the same proportions as a yardstick, and a yardstick may be used as a guide in scaling it with drawing ink into divisions reading from the center toward each end as shown below, If preferred, paper may be glued over a yardstick and rescaled as indicated from a central reference point.

When held to the work so that the same readings are obtained at both ends, such a rule will indicate the exact center of a job



at zero. Such household tasks as locating the center of a chair to be upholstered, fitting an eyelet in the center of a window shade, and locating a keybole in the center of a drawer can thus be done with a great degree of accuracy.—H. B.

### TOY BLOCKS AND WAGON

Keep Pre-Schoolers Busy



TOY consisting of gaily colored blocks stacked on dowels atop a pull-about wagon is just the thing for the young construction engineer, boy or girl. It's fun for the child to haul the blocks to the job, either on the carpet or across the sand lot, and an absorbing game as well to stack them on their pegs when building operations are over.

The 12 pegs must be carefully located so that the blocks will slip into place easily. There are 32 blocks in all, but four of them are double blocks with two holes so placed as to allow the blocks to slip down over any pair of dowels.

Four wagon wheels are turned on a lathe, or they can be cut from a rolling pin and the edges sanded smooth. The 12 circular blocks could also be made from a rolling pin if a lathe isn't available. The wheels run on dowel axles glued into the edges of the wagon. Turn circular hubcaps and drill holes part way through them; then glue them to the ends of the axles to keep the wheels in place. A string for pulling the wagon can be looped through a hole in one end of the bottom board, or a small acrew eye in the end of the board will serve the purpose even better, being less likely to fray the string quickly.—E. W.

196 White Cit. 13\* 4 DOMELS WHEEL PLAN OF WASON BUTTON 4 (a) F2 3N FSU (# FR TOWE DOME. 54 3 A L.F LONG BLOCKS DETAIL OF WHEEL AND ATLE 4 REQUIRED 5 4 DIA -OLES ROUND BLOCKS SQUARE BLOCKS 2 REQUEED 34 = 2 - 2 6 REQUIRED

JANUARY, 1944

## Plowing Under

#### **OFF-SEASON ADJUSTMENTS**

By E. W. LEHMANN

Head of Department of Agricultural Engineering, University of Illinois



PLOWING—an essential operation on every farm before seed can be put into the ground—requires more power and more labor than any other single job connected with the production of crops. To reduce these to a minimum, a plow must be kept in first-class condition. If it is free from rust and is well adjusted, if its shares and coulters are sharp, its wheels properly set, and its hitch correct, and if all parts are tight, then a plow becomes a top-quality tool with which a man can do a real job.

All moldboard plows operate essentially on the same principle, whether they are walking plows, sulkies, or tractor plows. Their functioning parts are the share, the moldboard, and the land side, which are built around a frame or frog. Together, these parts are called the plow bottom, and they should be of a design suitable for operation in the soil for which the plow is intended.

If the moldboard is not kept free of rust, the plow will not scour, that is, soil will stick to its surface, and the result will be rough, uneven furrows. The application of abrasives, such as emery cloth, a polishing stone, a soft brick, or special grinding compounds, is a help if polished surfaces are corroded. A rusty plow may be made to scour by first using it in sandy or gravelly soil. At the end of the plowing season, coat all bright surfaces with a good hard oil or a rust-resistant compound, and check occasionally to be sure the surfaces remain protected.

The share must be sharp and properly shaped for penetrating the soil, cutting through the furrow, and turning the ground. Because a share is easily spoiled when not handled correctly, most farmers depend on experienced blacksmiths for sharpening. The process in-

# Your Plaw Troubles

# OF THIS VITAL IMPLEMENT INSURE EASIER WORK IN THE SPRING

volves heating and hammering the share along one small part of the cutting edge at a time. The task is not difficult if it is well understood, if the necessary tools are available, and if overheating is avoided.

A warped share must be restored to its original shape while being sharpened. If it is made of soft-center steel, it should be hardened after sharpening by being heated to a uniform cherry red, then dipped into a tub of cold water or oil with the cutting edge down. A solid-steel share is heated and cooled in air, while the edge of a chilled cast-iron share—the type most used in sandy and gravelly soils—is ground.

Set the share for "suction," that is, penetration of the ground, by turning the point down 1/16" to %" as the share is shaped. Somewhat more of a turned-down point is


better for tractor plows. The point should also be turned slightly toward the unplowed ground for what is known as "land suction."


Examine the beam of a walking plow, and the beam and frame of tractor or horse-drawn riding plow, for bent sections or other distortions. Comparison of the shape with specifications in the manufacturer's instruction book, or with a new plow, will be a heip.

It is always good practice to make a thorough check at the end of the season, noting all broken or badly worn parts, so that your order for replacements can be put in early if you do not have parts from an old implement available. Often a first-class repair can be made by welding, and frequently a welded part will outlast the rest of the plow.

All wheels on riding and tractor plows should be adjusted to aid in holding the plow steady and to reduce draft. Remove the wheels and wash the boxing, bub caps, and axles with kerosene, removing all old grease and dirt; then replace them and pack with clean grease. Adjust the front furrow wheel in or out to set the width of cut of the front plow bottom, keeping it running in the corner of the furrow. Make an adjustment of the rear furrow wheel for land-side clearance of '%" to %" with the plow set in normal position on a level surface, following the instructions of the dealer or manufacturer.

The bub of the coulter should be approximately above and slightly back of the point of the share, with the coulter adjusted to penetrate somewhat into the soil as it cuts through trash. Set the jointer attachment so that it will cut about 3" deep and help to make a clean furrow. The point should just touch the coulter, which should





nevertheless be free to turn easily. Concave disk jointers, sometimes used instead of both a jointer and coulter, should be set so the center of the disk is approximately over the share point.

All levers require checking for straightness, bolts for wear, and lift springs for proper tension. There should be slight tension from the lift spring when the plow is raised out of the ground and the depth control and leveling levers are set for medium plowing of 6" or 7". Vertical and horizontal hitch adjustments must be such as to cause the plow to move forward smoothly without bobbing and without tending to go to either side.

For best results, the center of load on the plow and the

center of draft of a team should coincide. It is a good practice to string out the horses in tandem whenever you find that it is necessary to use a large team. If more than three horses are harnessed abreast, plowing becomes difficult and undue side draft is likely to result.


# Welding New Abrasion-Resistant Edges to Worn Plowshares




HARD-SURFACING, usually called hard-facing, will often make a worn plowshare as good as new. It consists of applying weld metal to the worn surface in order to build it up. With severely blunted shares, a new carbon-steel point may be welded on, after which the edge of the share is surfaced with an extra-hard welded bead. The share is then hot-forged to the proper shape. The stages in this process are shown in the accompanying photos from the Lincoln Electric Company of Cleveland.

Cast-iron shares are repaired by welding with a mild-steel type of electrode.
Care must be used to keep the share from
overheating, since cracking might result.
Electrodes for use on ordinary steel
shares are made of a semisustenitic alloy
that is highly resistant to abrasion and
increases in hardness during use. With

plowshares of high-carbon steel, welding has sometimes proved difficult when attempted on an untreated share. In such cases, the share is first annealed and then hard-faced with abrasion-resistant electrodes.




At left, a worn plawshare before and ofter being reclaimed. Both sides are shown right after the point in the first photo had been welded on. This step calls for an ordinary electrode, after which one made of an extra-hard alloy is used in resurfacing the cutting edge. A final hot-forging finishes the job



# Mechanical Stirrer Speeds the Cooling of Milk in Cans





Dairymen will value this simple, mater-driven device for the time and labor it saves. It can be built on the form from inexpensive add parts

STIRRING greatly hastens the cooling of milk in cans, as every dairy farmer knows, and on many farms there will be found most of the materials needed to construct this electrically driven stirrer that will agitate the contents of three or more cans in a cooling tank. Simple in design, as the drawing shows, the stirrer exercises an effective double action, since it keeps both the milk and the cooling-tank water in motion.

Essential parts include a ¼-hp. motor, a speed-reduction gear, and a shaft for the

rocker arms. The reduction unit can be made from an old hand tool grinder with a gear ratio of 10 to 1. A 2" pulley is used on the motor and belted to an 8" pulley, which is substituted for the grinding wheel. With a pitman bar fitted to the end of the grinder handle and connected to the rocker-drive arm, an oscillating motion is imparted to the rockers. Sash cords suspend hand stirrers in the cans and cooling tank. The device can be attached to the ceiling or bung from supports.—E. W. L.

### JANUARY CHECK LIST

### [ SHIPSHAPE HOME]

- Remove snow from low-pitched roofs before it forms ice.
- Clean gutters to protect them from the overburden of solid ice, dislodge icicles.
- 3. Brace rafters if a snow load tends to make them sag
- 4. Face-nail loose or squeaking floor boards, and set nailheads.
- 5. Wedge and glue or nail members of a creaking stairway.
- Pry off uneven moldings at the bottom of baseboards and renail them close to the floor.
- 7. Patch worn or cracked linoleum floors.
- 8. Refinish unsightly wood floors, or lay new floors on top.
- 9. Clean out all plumbing traps and drains.
- 10. Renew or repair frayed extension electric cords.

POPULAR SCIENCE MONTHLY SHOP DATA

JANUARY, 1944 173





# home EXPERIMENTS

THE PRINCIPLE OF INDUCTION. which causes electric current to be transferred from one circuit to another with which it has no metallic connection, can be demonstrated with the simple equipment at the left. First, bring to a red heat an iron bolt about 5" long, and allow it to cool slowly. Then wind about 100 turns of bell wire around half the bolt nearest the head. Wind-a second coil of about 200 turns of finer, insulated wire around a thick pencil or dowel of such a size that when it is removed the coil will fit loosely over the bolt. Connect a flashlight bulb and socket to the ends of this second coil, and then connect the ends of the coil on the bolt in series with a resistance such as a heater unit and to a source of 110-volt alternating current

Now slide the second coil onto the balt and the balt will light, increasing in brightness as the coils are brought loser together. Transformers and spark oil operate on the same principle except that the efficiency of commercial equipment is increased by presses of core and windings.

IN A TRANSFORMER the voltage ratio between the two coils is almost exactly equal to the difference in the number of turns in the coils. With 100 turns on the primary, or input coil, and 10 turns on the secondary, or output coil, the voltage from the secondary will be one tenth of that impressed on the primary. A transformer in which the secondary voltage is less than the equipment voltage is called a step-down transformer.

Bells and toy trains are operated with transformers of this type. With such a transformer in a 110-volt A C line, a low-voltage bulb may be lit safely.

That the voltage ratio is reversible can be proved by impressing low-voltage interrupted current on the secondary and obtaining high voltage from the primary. Connect dry cells in series with the sec-

one of the primary, and interrupt the currul by drawing one of the wires lightly
wer a file connected in the circuit, as illustrated. The lamp will glow brilliantly, although only one pole will light up. This is
due to the fact that direct current is employed. If you reverse the leads, you will
find the opposite pole will light when the
intermittent current is supplied.



A HOMEMADE D.C. MOTOR that will really run can be constructed quickly by duplicating the apparatus at the right. Two bolts about 2" long should be annealed by heating, as in the first experiment, and then wound with a continuous length of bell wire. Wind 50 turns clockwise on one bolt, leave 4" straight, then wind 50 turns counterclockwise on the other. The direction of winding must in both cases be considered from the bolthead end. Mount the bolts about 2" apart with head facing head. Then, when connected with one or two dry cells, they will become the field magnets of your motor.


For an armature, or rotor, wind a slightly smaller bolt with about 50 turns of finer wire and mount the unit on a shaft contrived by thrusting a length of stiff wire through the coils of the winding. Crude bearings and a commutator are now all that are needed to complete the motor.


The bearings are strips of notched tin. A cork will make a good commutator when fitted with two strips of thin sheet metal Press the cork onto the rotor shaft, as indicated, and glue the two strips of sheet metal to its sides. The strips should be just wide enough to go around the cork except for slight separations between them. Solder the two ends of the rotor windings to these improvised commutator segments; then arrange a terminal wire from one of the field magnets so that it presses lightly against the underside of the cork, and connect the other wire from the field poles to one terminal of several dry cells in series.

Hold the other terminal wire from the dry cells lightly against the cork, as shown,

rent by rotating wire coils between the poles of powerful magnets so that they cut magnetic lines of force. This principle of an electric alternator may be demonstrated by means of the equipment used above, minus the commutator, but with a galvanometer added to the circuit as shown below.








and the motor will spin rapidly. The function of a commutator is to reverse the direction of current flow through the armature twice in every revolution so that each pole is first attracted and then repelled by the adjacent pole of the field magnet.

For the galvanometer, use a toy compass wound around the center with 50 turns of fine, insulated wire. Connect this current-detecting device with the two ends of the armature winding, and station it far enough from the magnets so that the needle will not be influenced by stray magnetism. If you now twist the rotor shaft while our ent

flows through the field coils, you will discover that the compass acedle ia deflected first in one directi n and then in the other as the rotor passes through each half of a full turn. In a regular alternator, brushes would collect alternating current from rings fitted around the rotor shaft and connected with the windings which are built into the rotor.



# Mysterious PHOSPHORUS

PHOSPHORUS, that curiously active, waxlike element glows weirdly in the dark and ignites spontaneously, accompanied by clouds of dense white smoke. It was discovered, appropriately enough, in an alchemist's musty laboratory nearly three centuries ago. Brand, of Hamburg, chanced upon it while experimenting in search of the mythical philosophers' stone.


Now phosphorus is found abundantly in compounds. Too chemically active to be found in the uncombined state, the element exists in all animal and vegetable life, in earth deposits as phosphate rock, in most river and spring water, and in the sea. Bones are made up of about 58 percent calcium phosphate. In Florida, South Carolina, and Tennessee there are great deposits of phosphate rock, probably the fossil remains of prehistoric animals.

Phosphorus is made by heating phosphate rock or animal-bone ash with sand and carbon in an electric furnace. In the reaction carbon monoxide is burned, calcium silicate is drawn off as slag, and phosphorus is distilled over and is condensed under water.

An ounce of white phosphorus in thin



Fumes from burning phosphorus collect in this test tube



Adding a speck of iodine as a catalyst helps change white phospharus into the relatively inactive red variety. At right, continued heating changes the red phospharus back to white, which condenses on the small tube inside the other

sticks is sufficient for many experiments. The chemical is extremely poisonous and combustible. Take care to store it under water; always handle it with forceps or tongs, never with the fingers (phosphorus burns are poisonous and difficult to heal); cut it only under water; return unused pieces to the water-filled bottle immediately; and burn waste bits.

To produce smoke like that used for smoke screens, cut under water a piece of phosphorus about half the size of a pea. Place this on a slice of cork, float it on a pan of water, light the phosphorus, and cover it with a large inverted test tube. Dense white clouds of phosphorus pentoxide will form and collect in the tube

This "emoke," which is really a light,

spontaneously. Below this temperature, slow exidation causes its surface to glow in the dark. This glow may be demonstrated with "magic" paint. In a test tube dissolve a pea-size piece of phosphorus in 10 ml, carbon disulphide (keep away from flame). Add 10 mL olive oil, and shake gently to mix. Paint with it on heavy cardboard, being sure to immerse the brush in water immediately after use to prevent spontaneous combustion, and clean it later in carbon disulphide and then in alcohol. In the dark, the letters or figures on the cardboard will glow with a weird, pale light. Blow on them, and they disappear—only to reappear again when you stop blowing

Phosphorus dissolves in carbon disulphide without oil causes a more spectacular re-

# .. the Alchemist's Element

finely divided powder, combines avidly with water, drawing some of the water from the pan violently into the tube, and will disappear in solution after several minutes. Testing this water with litmus paper will disclose that it has become strongly acid. The acid is phosphoric acid, from which phosphates are produced, and it is prepared in its purest form by dissolving phosphorus pentoxide in distilled water. Because of its great affinity for water, phosphorus pentoxide powder is often used for drying gases.

If exposed to air at temperatures above 94 deg. F., white phosphorus catches fire action. Spread a few drops of this solution on a piece of filter paper placed in a pie tin or held over a tin by a clamp. The phosphorus will catch fire spontaneously when the solvent evaporates and will set fire to the paper.

Though quick to start a fire, phosphorus has a relatively low heat of combustion and most of its heat is directed upward. It therefore usually causes little damage except when in contact with filmsy materials, and a phosphorus fire is best fought by protecting nearby combustible material with a water spray while allowing the phos-



"Magic" glowing paint is a solution of phosphorus and carbon disulphide to which alive oil is added

phorus to burn itself out in its own time. Strangely enough, poisonous and readily combustible white phosphorus (sometimes called yellow) has a brother, red phosphorus, that is not poisonous and does not catch fire until heated to 240 deg. C. Red phosphorus is now used in great quantities in matchmaking, replacing white phosphorus, which was a source of widespread bone disease among match workers.

Mount a large test tube vertically on a stand, drop in two pea-size pieces of white phosphorus, and apply a small flame. The phosphorus may start to burn, but its own inert fumes will soon cut off oxygen. Under continued heating, the white phosphorus will gradually turn reddish. Add a speck of iodine crystal, a catalyst, and the change from white to red phosphorus will be almost instantaneous.

To change the red phosphorus back to white, fill a smaller test tube with cold water, twist a piece of wire around its neck for a support, and lower it into the large

tube. Heat the large tube more strongly than before, and fumes will arise from the red phosphorus and condense as crystals of white phosphorus on the outside of the cool inner tube. When the whole apparatus has cooled, lift out the small tube by means of tongs. and the white phosphorus on its surface will ignite spontaneously a few seconds after contact with the air.

Phosphine, a gaseous compound made by uniting phosphorus with hydrogen, may be the subject of an interesting experiment, which must be performed in a well-


ventilated room and with care paid to details.

Half fill a side-necked test tube with a strong solution of lye or sodium hydroxide, allow it to cool, and add a pea-size piece of phosphorus. Fit the tube with a one-hole stopper through which passes a glass tube reaching nearly to the bottom of the test tube. Clamp the test tube to a ring stand, and connect its side arm to a long glass delivery tube having an upward bend at its lower end. This end of the delivery tube is placed in a pan of water with its opening submerged about 14".

Connect the tube from the test-tube stopper to a source of illuminating gas through a rubber tube having a screw pinch clamp. Make sure all connections are absolutely tight; then flush all air from the system by allowing illuminating gas to bubble through for a minute or two, after which turn off the gas and close the pinch clamp tight. This flushing prevents spontaneous combustion of the phosphine.

Now heat the test tube gently. Bubbles of gas will soon rise in the solution and pass through the delivery tube and up through the pan of water. After a few minutes of operation, each bubble escaping through the water will burst into a little puff of flame as it comes in contact with air, the flame often changing into a beautiful smoke ring.

Pure phosphine itself does not ignite spontaneously at room temperature; it is a trace of a related compound that sets it afire. Phosphine is poisonous; therefore do not continue the experiment too long. To stop the reaction, carefully fill the pail with water and remove the flame under the test tube. When the vapors cool, water will be drawn into the apparatus. Remove the stopper after all tubes cool.





Leaving out the oil causes the phosphorescent solution to ignite paper

# Simple Hydrogen Sulphide Generator Is an Aid to Amateur Chemists

INEXPENSIVE apparatus for the generation of hydrogen sulphide in the home laboratory can be constructed in short order by duplicating the arrangement shown in the diagram. On a small scale, this setup will serve the purposes of a Kipp generator, and should provide enough hydrogen sulphide to fill all the needs of the amateur delver in analytical chemistry.

The apparatus consists principally of a 125-ml, distilling flask and a 3" funnel with a long stem. As in the drawing, the stem of the funnel is fitted through two stoppers in the neck of the flask, the lower stopper having a central hole and also two auxiliary holes through which acid passes as it rises from the bulb of the flask. On top of this stopper, around the stem of the funnel, are placed small lumps of ferrous sulphide. The distilling arm of the flask is extended by a stopcock fitted between rubber tubing further extended by a glass tube.

Warm hydrochloric acid is then poured down the funnel until it rises in the flask sufficiently to pass through the three-holed stopper and reach the sulphide. Gas from the reaction will pass the open stopcock and bubble through the solution to be tested. When the stopcock is closed, gas pressure will keep the acid from rising, and stop the action until the cock is reopened.—RICHARD BECK.

# STOPPER DO STOPPER 3'6LASS FUNNEL OR THISTLE TUBE ONE-HOLE STOPPER GLASS STOPCOCK TO CONTROL FLOW OF H<sub>1</sub>S STOPPER DO SMALL LUMPS RUBBER TUBING


HOLES ALLOW ACID

TO REACH SULPHIDE

GLASS DELIVERY TUBE


HYPROCHLORIC ACID (COMMERCIAL)

# Two Clothespins Form a Lab Clamp



Gluing two spring clothespins together, as indicated in the drawing, will provide a clamp that will come in handy for many purposes in a laboratory, such as holding glass tubing, funnels, and thistle tubes. It will also do much to reduce the breakage of fragile parts. The pins should be joined with a good grade of waterproof glue. If a C-clamp is not available, a third pin can be used to hold the legs of the other two pins together under pressure as the glue dries. When properly joined, homemade clamps of this kind will last a long time and prove themselves to be highly useful.—Andrew Lee Pecken, JR.

Wood Strip Prevents Short Circuits
SHORT circuits sometimes do much
damage to costly apparatus when a test



damage to costly apparatus when a test cord attached to spring clips is used to connect electrical equipment. Such mishaps can be effectively guarded against by clipping the equipment leads upon a thin piece of wood, or other non-conductor, as in the photograph. This will keep the clips from accidentally swinging against each other and thus causing a short circuit which might do irreparable damage to the electrical equipment. Little time and effort are required for this simple precaution.—W. E. B.





STORM BAY WINDOWS of plastic glazing, like the one at the left, will add to the winter comfort of many home owners as soon as military demands cease to absorb the supply of the plastic material. Heat-retaining properties of the glazing, coupled with its high ultraviolet ray transmission, fit it especially for enclosing space for a window garden or a bay for a child's crib.




SHOWER HEADS made entirely of plastic are finding a wide use in lieu of heads made partly of plastic and partly of metal. Even the joint and the threaded connection of the new head are of plastic, an advance in design over units of dual composition.


A COLOR WHEEL will save users of this tung-oil paint from mistakes in selecting wall and trim colors that do not harmonize with the basic color of furniture and hangings. The wheel presents a wide variety of multicolor combinations. If turned until a desired basic color is in one window, it shows complementary and contrasting hues.



CERAMIC HEATERS constructed mostly of hollow tile, and now in the process of perfection by engineers of Ohio State University, may soon reach quantity production.


Made possible by the careful blending of raw clays—more than one type of mixture is needed to make a complete unit—the ceramic heaters embody a method of com-





bustion by which a charge of coal is reduced to coke within the stove before it is ignited. Heat is transferred from the center of the stove to narrow convector passages formed by openings in the hollow tile of which the wall is constructed. These vertical tubes surround the fuel magazine and impart enough heat to a charge of coal to coke the charge before it is fed by gravity to the combustion chamber. In addition to the model illustrated, other designs include an oven. a hot-water heater, and a ceramic range.

# Tilting Stand Makes Oil Drum Easy for One Man to Handle



DRUMS of oil can be handled easily by one man if he uses a tilt-type drum stand like the one shown at the left. After the drum has been placed in position with the oil cock at the top, it is tilted back slightly and the stand is shoved against it with the toe bar under the front edge of the drum. When the stand is rocked forward, it will pull the drum with it and lay it on its side. In this horizontal position, the drum can then be readily shoved about until it reaches the desired location.—JOHN LAPIN.

# Tools Hoisted Safely with Bowline and Hitch

SLINGING an ax or a hammer securely, when such tools are to be pulled aloft, will guard those below against injury and at the same time prevent the minor mishaps so often caused by an object dangling haphazardly at the end of a long rope. A bowline affords the best precaution against both types of accidents. After the loop has been slipped over the head of the ax or hammer, the rope should be carried nearly to the end of the handle and thrown around it in a half hitch, as in the illustration.—W. H. D.

# Packing-Case Lumber Cuts Cost of Small Jobs

MANY things around the house, especially shelving, can be built economically from lumber used in the wooden cases in which sheet glass is shipped. Such stock is likely to be of a low grade. but in 3 to 6' lengths it is adequate for many purposes, and it will save the cost and bother of frequent lumber-yard purchases.—N.E.



### THE BOWLINE

[KNOTS]









Called the "King of Knots" and regarded as the best fixed loop ever devised, the bowline, unlike the overhand loop, is easily untied. In addition to this virtue, it is one of the easiest loops to fashion when once its technique has been mastered In order to the a bowline knot, hold

around the end, as in Fig 2. Then pass the end under the length and back into the small loop, as in Fig. 3. Now, holding the doubled end in the left hand. as in Fig. 4, pull the knot tight with


the rope as in Fig. 1 and carry its

length in a counterclockwise direction

the right hand

POPULAR SCIENCE MONTHLY SHOP DATA

JANUARY, 1944



# **Bigger Dividends**

ERE is a banker who carried the idea of dividends from his bank to his back-yard poultry house and made it pay. It is an idea that anyone with a few feet of space may cash in on. When A. W. Pipes, of South Pasadena, Calif., went in for raising chickens after retiring from the banking business, he acted on a touble-barreled theory and got results—he made his hens comfortable so they would lay more eggs, and he made his poultry yard attractive so he wouldn't mind working in it himself.

A plan for his yard and his two-apartment chicken house is given at the top of this page white photographs on the facing page show the steps he took to give the unit eye appeal both for himself and for his neighbors. The vard is in a back corner of his lot with the property fence enclosing it on two sides and a picket fence on the other two. If desired, the fences can be backed by chicken wire, but if the property fence is tight and the pickets are close enough, this will not be necessary. White paint adds to the general appearance of cleanliness, while a touch of color on the roof is a welcome and attractive note

In the chicken yard shown, pullets occupy the rear portion of the run and the back, lower quarter of the house. The front part of the yard is given over to laying hens, and they also use the roosts at the upper rear of the house and nest boxes in front. The floor of the house should be wood or concrete. Litter on it for secretching must be changed periodically

A number of practical details that may well be incorporated in any plan similar to the arc listed by the U.S. Department of Agriculture in its Farmer's Bulletin No. 1554. These cover such arbjects as nests, ventilation, heating, and feeding for the improvement of both the quality and quantity of a small flock's sucput of meat and eggs.

Although poultry requires sunlight, warmth, and generally dry surcoundings for best results, there are all does ark sests for use at laying time. Three of these are sufficient for a dozen bens. The opening should be at an end or a side rather than on top. Simple trap nests, such as the one shown in a drawing, will help you to check production. With this device, a hen is imprisoned after laying until you release her, thus giving you an opportunity to identify your good producers. Hinged at the top, the door of the trap nest is normally held open by a pivoted catch. When a hen pushes past the door, the catch drops and the door closes, held shut by the catch.

The house should be well ventilated with windows or slits high in the walls at or near

# from Back-Yard Poultry Flocks

the front and back. When the weather is very hot, both front and rear vents should be kept open. In cold weather it is best to open them at only the front end of the house, and then possibly not more than a few inches.

Hot water or small stoves will provide sufficient heat for your flock, but it will be necessary to employ artificial heat only in the coldest weather. It is a better plan to insulate the house by constructing a double wall at the rear—the inner one either of wood or composition board. A double ceiling is advisable where the climate is extremely cold.

Electric lighting may be employed to provide a 12 full or 14-hour laying day, thereby increasing egg production during the fall and winter months when it is at its lowest Two 40-watt lamps with 16" reflectors will be adequate for a house having 20 sq. (t. of floor area. They should be installed near the ceiling

Priy-mash hoppers pay for themselves by cutting down wasts and keeping dirt out of feed. They consist essentially of two boards nailed together a Tright angles and attached to a frame, as shown in a drawing. Crossed pieces at each end serve as legs. A revolving strip set up over the center will prevent the burds from roosting on the hopper.

Sprouted oats or other root-bearing grain is a good item to include in the feed. This can be prepared by noaking the grain and

allowing it to sprout on trave that drain web Also needed will be some form of commercial scratch feed or cracked grain that can be thrown into the litter to force the chickens to exercise.

For reasons of bealth, drinking stands should be raised about 12 off the floor. One simple arrangement consists of a platform of slats built against a wall and containing drinking vessels or a fountain. The platform should be large enough to give the chickens standing room Wire over the vessels will keep them from getting their feet wet

A useful accessory is a catching hook. It is made by attaching a wire to a wooden handle, as shown in a drawing, and bending the end into a hook that will catch a chicken's leg. A second wire attached to the handle and twisted about the first will add strength.









form such simple molecules as carbon monoxide, hydrogen, and acetylene. Only after these preliminary processes do we turn around and rebuild our basic molecules into more complex forms to make everything from summonia to plastics. Recently a lot of research has gone into the study of ways of deriving products from coal by a still shorter route.

The U.S. Bureau of Mines, following German and British experience but going beyond this, has set up a test hydrogenation plant capable of producing not only oils and gasoline, but also phenol, cresol, benzene, toluene, solvent naphtha, and a host of other major chemicals. The tar-acid yield, according to no less an authority than Secretary of the Interior Harold L. Ickes, will be increased about 10 times above the yields now obtained from the by-product cokeoven process. And these acids, the phenols, cresois, and xylenois, are vital to the growing plastics industry. Our new syntheticrubber industry will also be able to get most of its basic materials from coal hydrogenation-or degeneration, as the chemists call

But we won't have to put all our hopes in the hydrogenation process. Two new processes of conversion are coming to the fore. One uses a method of heating coal at elevated temperatures in the presence of solvents such as phenol or aniline. A second new process is known as "controlled oxidation."

Workers at the Carnegie Institute of Technology have developed apparatus on a laboratory scale that needs only the coming of peace for realization on a commercial scale. In this process the coal is burned at low temperatures in a reaction very much like the energy-conversion processes of the human body. An acid solvent is used with air or oxygen under pressure to produce organic acids such as oxalic acid, acetic acid, and the other carboxylic acids. The relatively simple process converts as much as 60 percent of the weight of the coal into usable products, while carbon dioxide gas is the principal by-product.

Another new process will prove of value in the cheapening of phenolic resins, the most widely used of plastics. This method, developed by M. W. Kiebler, of the Coal Research Laboratory, involves the treatment of coal with hydrogen under high pressure. It differs from more expensive German procedures in that caustic soda is first used on the coal to remove oxygen, thus greatly re-

ducing the amount of hydrogen needed. This trick is accomplished in an ingenious reaction vessel in which a motor, used to agitate the products, is enclosed in a bomb under working pressures of 6,000 pounds per square inch. Water is used to cool the motor, for the reaction temperature is 840 degrees F. Only one sixth of the power required by conventional arrangements is needed for this installation, and thus a further cost reduction results.

Coal is the means of developing a new field in water purification. From bituminous coal, chemists now are learning how to prepare "cation exchangers," particularly useful in softening hard boiler-feed waters and acid waters. This economical process may permit the location of industrial plants requiring large quantities of water at sites which are not usable today because the only water available has an undesirable mineral content.


The agricultural industries have long used coal by-products to increase production. For from coal we get insecticides, fertilizers, disinfectants, herbicides, fungicides, fumigants, preservatives, and food dyes. Recently research chemists have found a way of producing synthetically from naphthalene, a coal derivative, hormones that will greatly increase the yield of scientific farming. Hormones are the regulators of plant growth. They enable fruits to grow without cross-fertilization and help cuttings to develop roots. They also help to prevent fruit from dropping off trees prematurely.

The list of new coal uses might be expanded indefinitely and, indeed, is being expanded daily in the laboratories of our government agencies and our great industrial plants. And with each expansion, be it in the form of a new mildew preventive or a mold inhibiter, or a wetting agent like one new kind that actually makes a duck sink in water, the over-all cost of coal products drops a bit as production increases, and thus still further developments come into the range of commercial practicability. Truly, then, we are entering a new coal age, and with a thousand-year supply of coal spread all over our broad land we needn't worry too much about our dwindling oil reserves.

Subscribers in the armed forces who notify us of change of address are requested to give us the key symbols appearing on the wrapper in which the magazine is received. The lamp that paints a bullseye on Axis planes!

Fiver wonder how our gunners can fire accurately at 400 m.p.h.? One reason is a new kind of gunsight. Instead of straining to hold the enemy in your sights as you would with a rifle, you see a "bullseye" of orange light ... apparently painted right on the enemy plane! Diagram below shows how it works.





2. The problem G-E had was to develop a new lamp for gready increased brightness. Combat experience showed that the image had to be bright enough to show up against Sahara sands or bright clouds. Gunsights now are being equipped with a lamp G-E developed especially to meet these conditions.



this new lamp in a horry was a tough problem...but no tougher than many which G-E research has had to solve since Edison's first lamp. Between the big 10,000-watt airport floodlight and the tiny "grain-of-wheat" lamp used for instrument illumination are hundreds of different G-E lamps working for victory.

MADE TO STAY BRIGHTER LONGER



4. The same research that produces G-E lamps used in war is your assurance that the G-E lamps you use will give you the most light for your money.

Hearthe General Electric radio programs: "The G-E All-Giel Orchestra," Sunday 10 p. m. EWT, NBC; "The World Today" news every weekslay, 6:45 p. m. EWT, CBS.



THE BEST INVESTMENT IN THE WORLD IS IN THIS COUNTRY'S FUTURE ... BUY WAR BONDS



# PROPER USE OF COLD CHISELS

You can make cleaner cuts, save yourself work, and get more service from your cold chisels if you use the right type for the job and know how to handle it. Here are a few tips:

Lubricate chisel point only when chipping wrought iron or steel.

Use a narrow chisel to cut hales, and save filing.

Use a cape chisel to cut off rivet heads.

There are plenty more helpful hints in the STANLEY TOOL GUIDE, a 32-page handbook of instructions on the care and use of tools for the home craftsman. Simple explanations, hundreds of illustrations. Write for a copy today.

Tools are vital to Victory . . . make them last i



# Fighter-Plane Firepower

(Continued from page 83)

to bring down 72 German transport planes without a single machine-gun stoppage. Its hitting power is just as remarkable—four Wildcats armed with Brownings have sunk two Jap destroyers.

Another important factor is the comparative weights of the guns. The 61-pound Browning weighs about haif as much as the Hispano. In a minute, while one Hispano fires 700 shots weighing 203 pounds, two Brownings can fire a total of 1,700 shots weighing 172 pounds. The Hispano has the advantage in weight of fire, but the two Brownings fire more projectiles—important against fast-moving targets. Since the Brownings' ammunition is lighter, a fighter can carry more rounds, and so has a longer duration of fire.

The German Mauser 15-mm. (.59 caliber) is an excellent gun, throwing heavier bullets than the Browning, but having a lower rate of fire and less muzzle velocity. The Mauser 13-mm. (.51 caliber) is also good, but like other Nazi weapons, its involved design is not suited to mass production.

Airmen predict that in future air-to-air fighting, precision shooting will be made less essential by the use of high-explosive shells, set with time fuses, and capable of destruction over a large area.

Typical armament of present leading fighters is shown in the tables and illustrations on pages 78 to 81, but it must be remembered that armament combinations constantly vary according to the objective.

The fighter with the beaviest weight of fire is our Army P-51 Mustang, armed with four 20-mm. Hispano-type automatic cannon. In the same class are the British Spitfire IX, Hurricane IIC, and Typhoon. Just as bad medicine is our Army P-47 Thunderbolt, armed with eight .50 caliber Brownings. The Army P-40F Warhawk and the new-type Mustang—said to be the fastest plane in the world—carry six Brownings. The most diversified armament of any fighter plane is carried by our Army P-39 Airacobra-two .50 caliber and four .30 caliber machine guns, and a 37-mm, cannon. The Army P-38 Lightning packs a heavier punch, with four .50 caliber Brownings and one 20-mm, cannon. The hardest-hitting Nazl fighter is the new 109G Messerschmitt, said to carry five guns. Various combinations arm the ME-109F and Focke-Wulf 90. Jap Zero fighters usually carry one 20-mm. Oerlikon and four 7.9-mm, machine guns. None of these planes, however, matches ours in firepower.



# There's Been a Big Change

Almost any old-timer will give battle if you question the advantages of living in the old days. But few will deny that change in the mechanical world was inevitable, and good.

Take tapered roller bearings. Tyson found the way to add more rollers around the raceway—developed a heavy-duty bearing which solved many an industrial and transportation problem. Actually, a Tyson "All-Rolls" Bearing has thirty percent more rollers, on the average, size for size. Obviously, this means greatly increased load capacity. Many users say bearing life is doubled.

You can depend on it—Tyson is the most advanced, strongest, longest-lived bearing ever built.

The big name in bearings today is . . . TYSON!



\* BUY MORE WAR BONDS \*



# BOMBS FOR BERLIN

 The uncanny accuracy with which a homber holds its course, finds its target, drope its bombs, is rooted for behind the fields of conflict. It springs from the minds, eyes and bands which create the precision instruments that guide pilot, navigator and hombardise,

• Re indispensable as these vital instruments themsolves are the precision files which aid in their assembly. It is equally essential for the mechanic to know how to select and use The right file for the job.

 At Boeing and other factories. Nicholson and Black Diamond Files of many types, sizes and cuts help to shape thousands of parts to speed the victorious flights of our valiant air forces. Looking for a highearning job in America's great aircraft industry?
 Xnow your files and get ahead!

FREE BOOK, "FILE FILOSOPHY"- Newst and meet authoritative back of its kind-4d interesting blustrated gages so kinds, use and cure of files. Lots of other information.

MICHOLSON FILE CO., 19 Acure St., Providence 1, R. L. U. S. A.

(Also Canadian Plant, Port Hope, Unt.)

# FILES FOR EVERY OUSA

# Superspeed Mapping

(Continued from page 72)

of every peak in a mountain range without getting out of their comfortable chairs... can even scan 150 miles of escarpment or follow a river to its headwaters and never leave their desks. They sit in the seats of the gods and make charts for men who consort with the stars.

The first step in converting photographs into charts goes right back to the first step in the field work. Geodetic control points must be found and identified. Field-party notes show, for instance, that point 6 is the junction of two rivers at a given latitude and longitude. The index map shows this point to be on vertical photograph 74, and also to appear on 73 and 75. Field notes give the direction of each river's course, angle of junction, and bearing of three near-by mountains.


The laboratory man puts pictures 73 and 74 under his stereoscope and in five minutes can explore hundreds of square miles of country through which the field parties labored painfully for days. He finds the river junction and identifying mountains, verifies the river courses, and checks what he can see against what the field party reported. Satisfied at last, he marks the geodetic point with a circle inscribed in a triangle and similarly marks the same point on every photograph where it appears.

Now the technician figuratively steps into the mapping plane. He must learn the exact position of the plane and its direction of flight when each picture was taken. Updrafts tilt the plane. Cross winds cause drift. He calculates these factors mathematically from the relative position of natural features in consecutive vertical pictures and comparative horizon lines in the oblique pictures. Azimuth lines, true direction of flight, and plumb points—precise verticals dropped from the camera's position—are indicated on the picture.

Information is now in hand to begin transferring detail from the photographs to the map base. The first step is the charting of key points by triangulation on the rectoblique plotter, an instrument for determining true horizontal angles from an oblique photograph.

An oblique photograph is squared on the plotter with a pivot pin at its plumb point. Alongside is fastened a transparent paper template to which are transferred the photograph's azimuth lines. A master pointer, which swings on the pivot pin, is moved to each detail point on the photograph, and a

(Continued on page 192)



★ Don't wear out your precious battery on a hard-to-start motor these cold winter mornings. Add Casite to the crankcase and get summer starting every day, all winter long.

Casite guarantees it-or double your money back!

Over a million car owners accepted this challenge last winter, and eliminated winter-starting trouble to their complete satisfaction.

Follow their example. Ask your car dealer, service station, or garage for Casite's guaranteed winter-starting tune-up today.

THE CASITE CORPORATION - HASTINGS, MICHIGAN

# CASITE

We Guarantee

We guarantee that any motor copable of being started in a warm room will start in the coldest weather when Casita is added to the crankcase. Add Casita according to instructions, if your car faits to start, you get deable your meany back by filling out guarantee certificate and making it to the Casita Corporation, Hostings, Michigan, Maximum refund is \$1.30 per pint, which is twice the nationally advertised price of Casita.

CLEANS OUT MOTORS . KEEPS MOTORS CLEAN



# EVINRUDES \* ON THE HOME FRONT help battle an enemy deadly as the Japs!



TREACHEROUS enemy of all mankind is the malaria-bearing Anopheles mosquito . . . dreaded alike in New Guinea's jungles and fox holes, and in many a sector of the home front.

Along the placid back waters of Tennessee Valley's vast man-made lakes, the battle against Anopheles goes on endlessly. The war-busy population of this new industrial "Ruhr of America" must be protected from the ravages of malaria . . . and the Tennessee Valley Authority has energetically fought the Anopheles wherever it breeds!

Fleets of spray boats propelled by outboard motors are a strategic and highly effective weapon in this vital work. Outboards drive these boats from bases to "battle grounds". Outboards speed the inspectors on their rounds, and are useful in many other phases of Malarial Control Operations.

Throughout America, in countless unspectacular but essential services, peacetime Evinrudes are handling their jobs quietly and efficiently. Today Evinrudes are being produced exclusively to meet the specialized requirements of our fighting forces. After Victory there will again be Evinrudes for all . . . brilliant new Evinrudes packed with performance to surpass the finest you've known before!

EVINRUDE MOTORS, Milwaukee, Wisconsin





# "and now...Good Luck and Good Hunting"

This is the day I've looked forward to since I was seventeen . . . this is the day I win my wings.

Mom and Dad are waiting there. Dad's standing tense and straight and tall, and his face looks proud and grim, as though the General were talking to him.

"...they tell me you're hot pilots and navigators and bombardiers. And it is well you are..."

As we marched in, Mom waved and I caught the white flutter of her handkerchief out of the corner of my eye. In a moment or two she's going to cry—just a little—like she did the night we talked it all out, she and Dad and I, when I told them I wanted to fly.

"... to your families, I say—ours is the safest military flying of any of the world's air forces."

And now here on the parade grounds, with the shadows falling and the bright flag whipping in the sky, I remember Dad said, "Son, your Mother and I won't stand in your way. If this is what you want to do—do it with all your heart and soul and God be with you. I wish I were your age—so I could fly and fight."

"And I say to you cadets, get the enemy in your eights and let him have it . . ."

Now, in just a minute, we'll right face and walk up to the platform under the flag. And the General will hand me the parchment, and then he'll pin silver wings on my blouse and return my proud salure.

"The world has never before seen a team like the Army Air Forces . . . "

Thinking of all the days and nights packed with hard work . . . our college training . . . the numberless flights with patient instructors . . . the painstaking way we were taught to fly safely on instruments, how,

flying wing tip to wing tip, we were brought together closer than brothers . . . I understand what our General means. The Army Air Forces are more than planes, more than men, more than machines—a great team with one aim, one object, one goal.

"... to sweep the skies clear, so free men may walk with their heads up and without fear ..."

And as the last man receives his wings and the gun booms out and we stand retreat and the flag comes slowly down. I'll thank God my father and mother gave me the chance to win my wings... belong to the greatest group who ever fought or flew... gave me a future and a career!

"And now, gentlemen, we have work to do-and I leave you . . . good luck-and good hunting."



Examining Board today . . . if you can qualify for the Air Corps Enlisted Reserve, you will receive Folisted Reserve insignia but will not be called for training until you are 18 or over.

When called, you'll be given 5 months' training (after a brief conditioning period) in one of America a finest colleges... then go on to eight months of full flight training. When you graduate as a Bombardier, Navigator or Pilot—you will receive an extra \$250 uniform allowance and your pay will be \$246 to \$327 per month.

Meanwhile. . . you should see your local Civil Air Patrol officers about taking C A P. Cadet Training—also your High School principal or adviser about the recommended courses of the Air Service Division of the H. S. Victory Corps. Both will afford you valuable pre-aviation training.

(Expential workers to War Industry or Agricultura—de net apply)

U. S. ARMY RECRUITING SERVICE

# "Nothing'll Stop the Army Air Corps"

"KEEP'EM FLYIDG!"

For information regarding Naval Aviation Codet Training, apply at any Naval Aviation Codet Selection Board or any Naval Reconsting Station; or, if you are in the Navy, Marine Corps or Coast Guard, apply through your commanding afficer... This advertisement has the approval of the Joint Atmy Navy Petsonnel Board.

# UNBEATABLE COMBINATION for easy hack sawing



TUF-FLEX Super-tough, super-flexible

EVEN IP you don't have a Millers Falls hack saw frame, you can make sawing easier with the right blade, for it's the

blade that does the work. For general tinkering in the home or at the workshop bench — or for off-and-on maintenance use on a wide variety of metals — you can't beat Tuf-Flex. Like no other blads, it tackles tough tool steel, BX, pipe, or hard angle irons — and walks through them all in the same easy way. Won't strip, won't break. For stendy cutting of one type of work, you'll prefer Millers Falls Blu-Mol blade . . . but for general use on different materials, Tuf-Flex is the choice; a single blade will probably serve you for months. 8, 10, or 12 inches long; 14 to 32 teeth per inch.



FOR REAL back-sawing case, you need both the Tuf-Flex blade and a good frame. Finest of all popular-priced frames is Millers Falls No. 48 — not expensive, a quality frame without frills. Unusually rigid, fine balance; comfortable plastic handle, guarded pistol-grip, checked for firm hold. Frame is polished, nickel-plated, and buffed — you'll be proud of it. Adjustable for 8, 10, or 12 inch blades.



# Superspeed Mapping

(Continued from page 188)

to a corresponding angle. By drawing lines along the straightedge, the operator constructs a series of radiating rays—triangulation lines—which are numbered according to the photograph's detail-point numbers. Assemble a sequence of paper templates, and these detail points will be located at the intersections of similarly numbered lines.

To transfer this information to the huge sheet of cellulose acetate which becomes the map base, still another short cut is used. A metal template is made for each paper template by assembling slotted apring-steel strips around a hub corresponding to the paper template's plumb point. When these metal templates are mounted in order on the acetate sheet, the intersecting rays are connected by study which allow adjustment of the whole layout. Now the triangulation has become mechanical, and when the whole layout is complete, a marking pin is driven through the stud at each detail-point intersection into the map base. These pin points are marked and numbered on the map base with celluloid ink, and the metal templates are taken up.

The skeleton of the finished map is now ready to receive the details that will give it life. Key points are in place. Directions are established. Relationship of flight pictures is determined.

Meanwhile, the photographs have been studied under magnifying stereoscopes, and features to be shown on the finished map have been outlined in ink. Now the map base is cut into three-foot strips and sent, with corresponding pictures, to detail sketchers. By placing the photographs in a camera-lucida type of instrument cailed a "sketchmaster," the operator can project the image of the photograph onto the acetate base. Adjustments bring the image into proper scale, match its key points with those on the map, and compensate for tilt and distortion. This done, the operator draws the photographic detail on the map base.

With this detail on it, the master map is edited, checked, and labeled with known place names. After inking, it is a master transparency of a planimetric chart, showing all important surface features. Negatives can be made from it, reduced to desired scale, and emergency maps can be printed. But it still lacks contour detail and radio and aeronautical data.

For contour detail the photographs are (Continued on page 194)



Between the initial selection of the finest leathers available for their manufacture to the final shining-and-polishing stage, every single pair of W. L. Douglas Shoes is five times inspected by experts. Worked on by 130 pairs of skilled hands. And handled throughout with the painstaking care of the true craftsmen, who take pride in perfect work.

That's why you'll find W. L. Douglas good looks to completely satisfactory. Just try a pair today. Test them yourself for workmanship, smartness, comfort. You'll know, then, why men all over America are spending their ration coupons for W. L. Douglas Shoes.

Douglas Shoes
W. L. DOUGLAS SHOE CO., BROCKTON 15, MASS.


Stores in Principal Cities-Good Dealers Everywhere

\*6.50 - \*8.50

Some styles '5.50

Douglas ' Dou u-to-the Wood''
construction assures you bester fit.

THE COMMANDER
A favorite of service menand civilians is thi tan plain soe exfort Rugged feather sole for all weather comfort No. 4565. In bias No. 4035.





## with a SANDING STICK and JACOBS CHUCK

Most of the interior cuts made with a scroll, jig, or fret taw require sanding or smoothing to remove irregularities. Round and half-round files and sanding sticks have been used by hand for this work, but the hand method is slow and tedious. Using a sanding stick, as illustrated, speeds up this work immeasurably and improves the quality.

Sanding sticks are easily made up in any shop. With the drill press supplying the power, both hands are free to guide the work.

# To Get The Most Out of Your Drill Press or Lathe – get this New Book

The operation outlined briefly here is one of nineteen covered in detail in our new booklet just off the press. Printed in color and containing 49 illustrations, it shows how the set-ups are made, illustrates the tools used, and in some instances tells you how to make the tools themselves. If you have a workshop you will want the valuable ideas this book contains. If you are planning a shop of your own for after-the-war, you will want the booklet now to help you plan.



# Superspeed Mapping

(Continued from page 192)

checked through another specialty instrument, the photostidade—a small, highprecision telescope mounted on trunnions and calibrated for vertical angles. With it an operator can, in effect, sit almost four miles above the earth and vertically triangulate any point shown on the oblique photograph in front of him. The data he provides is transferred to the chart, and final proofs are made. Separate sheets are inked for each contour tint, for drainage, for culture features, and for the latest radio and aeronautical data. From these sheets, full-color charts can be printed.


Tri-metrogon charts are primarily for aerial use, aithough they have been used by ground reconnaissance forces. Ground engineers are sometimes critical, saying they may deviate two or three hundred yards in their accuracy. Airmen say such criticism is captious because these charts replace maps on which mountains and rivers often are shown many miles out of position—if they are shown at all.

Wartime transport demanded and trimetrogon achieved, virtually overnight,
working charts of the Far North, of South
American jungles, of interior Africa, of remote Asis. Man had never even seen some
of these areas from the air before.

Like much of the war transport itself and the supporting ground work, tri-metrogon charting has developed with unbelievable speed. Its very existence was unknown to the public a year ago, and its details have only recently been revealed.

While the routes now covered by trimetrogon charts are a military secret, it can be stated that the Army Air Forces have photographed more than 5,000,000 square miles, and its Compilation Units have translated three fifths of these photographs into maps and aeronautical charts. This tremendous task unquestionably is the largest single mapping contribution ever made; and for many years of postwar adjustments, these photographs, maps, and charts will play an important part, not only in aviation, but in the intensive development of natural resources in little-known parts of the world.

The particular function of tri-metrogon instruments and techniques, however, is to do a quick, thorough job of charting for the airman. And before the war is over, our military files will include working charts of every major air route needed, not only for war, but for the tremendously expanded Air Age that will follow.—HAL BORLAND.




# Hard Steels Cut by Heat Generated by Super High Saw Speeds

Ordinary band-saws, when operated at unbelievable high speeds up to 12,000 feet per minute, cut through hard steels and alloys by heat generated from the friction of the saw against the metal to be cut. The cutting effect is more that of burning through the metal than actual cutting. The heat generated is sufficient to melt or burn out the metal in the saw cut but not enough to draw the temper on the sides.


The hardness of either saw or metal to be cut is of little importance. Thin metal sheets are cut like paper, and plates up to one inch in thickness can be cut at speeds of ten inches per minute.

We hope this has proved interesting and useful to you, just as Wrigley's Spearment Gum is proving useful to millions of people working everywhere for Victory.

> You can get complete information about this method from Bell Aircraft Corporation, Buffalo, New York.



Proof of ability of new method to cut hard materials is demanstrated by aperator cutting a file.



The temper of curve cut section shown above is unaffected.

X-63



# DAMN THE BOTTLE-NECKS

Full Speed Ahead!



Making only Chicago Mounted Wheels and small Grinding Wheels-maintaining the highest qualityshipping orders promptly—this is our job, our harriefield.

With full WPB approval, we stopped making all large sizes and fixed our sights on wheels 3" in diameter and under.

We worked around the clock. 24 hours a day, and in a short time were able to fill orders on time. And, our central location cuts time in transit. Today there is no waiting, With the Army-Navy

E' at our mosthead, we are going full speed ahead.

Handes Tool of 1001 Uses and His Power Grinders are still available to all who have priorities.

Send for Free Catalog.

CHICAGO WHEEL & MFG. CO.

118 S. Aberdeen St.

Chicago 7, Ill.



# Wartime's Ideal Christmas Gift



The Tool With 168 Uses

POCKET-SIZE PROTRACTOR

for Engineers-

### Tool Grinders-Machinists-Tool & Die Makers

Xuctor is a significant, valuable Chrisbias giff that will be treasured for a lifebone. Dus carefully ward med. the precision fool made of the best grade of materials, measures angles to an incuracy of t, of t. Vermer compact its analysistable shaing arm payors the full asm. assurbig recurite measurement of any angle instabily,

Xector graduations are deeply etched for easy reading, even in poorly lighted shops. Size 6" v 2% v a 16",

Xactor is indispensable for every hagineer. Tool Grinder. Machinad and Tool and Die Maker as it saves THE THIRD ellumentes errors to checking and laying out

A gift that will be glidly recoved a and one you'll be promit to give Certification with priority of AA2X or higher required from employer



Angles of: Doll Points. Tool Bits. Machine Wors, Ports, 电线:

Xuctor somes in nest legitor vest-pecket suss-packed in box ORDER NOW in time for Amos:

A PATENTED PRODUCT OF INDUSTRIAL ENGINEERING CO., INC. Dept. S, 141 W. Jockson Blvd., Chicago, Illinois

# Test-O-Lite TROUBLE SHOOTER

31.17/ THE NEON GLOW ...LOCATES TROUBLE

INSTANTLY in electric chicests, feses, cel-outs, malans, radios, appliances. Yests everything electrical from 100 to \$50 volts. Indicates hot or grounded wires. Tells

AC from DC. For 14perior to ordinary closery test both.

UTS "FINGER" ON THE TROUBLE SPOT - - QUICKLY

NAVEL precious time Indispensable in show or home. Has patented safety features, Vest pocket size with clip, Lifetime guaranter. List \$1 80 (Priority A7 required) Purchase through regular electrical dealers.

S. BRACH MFG, CORP, interson St. 🏬 Messeck, it d., 🛚

MOTORS

# 1953: A New World

The Commencement of Divine Order

A New World is correging from the propegt conflict. A New Society is being learn. He yet applie to how to simplests of ('Hippenhip, its a rives not ideals its being and achievements? 1962 marks the leg on ng of a different hand of war if. What will be the? How will it cultural contents in a title in the large of a page of anyways with unusual information. From No obligation, Write Dept. Q.

LEMURIAN FELLOWSHIP
118 North Larchmont Boulevard Las Angeles, California



Are you a collector? A game and rumpus room decorator? Your treasure bunt ends in our entained listing over 1000 suthenite tiems including old pistols, swords, kn.ves, armor, etc. To get your 100-page (illustrated catalog send 25c to ROBERT ABELS, BOX PB, 560 Loxington Ave., New York 11, N. Y.



### GERSTNER TOOL CHESTS

If fit t also adequate protection for the tools much next and to brake a Fire retaing.

Dayton T. Onlo

CERSTNER TOOL CHESTS 944 Columbia St.

### PROTECTION FROM TOOLS--GUNS--LOUKS, TACKLE, ETC:


For years mosters have used Plendoll to keep their guns of an all a free from a dilequalty effect ve on all metal as fews. At Your Sports or Hardware Store. In abe das, Botile

FIENDOIL

McCombridge & McCombridge Co. -

Baltimore





# . . a source of endless pleasure, pride and profit

Here is a gift to quicken the heart of any man or woman, boy or girl who loves to make things. It is America's greatest collection of homecraft "knowhow." Books in various combinations, to suit any enthusiast and any gift budget - pointing the way

GROUP "A"-Operating Manuals for Better Secults with Power Tools ... A complete library on tools and operations. Close to 50 pages, more than 200 illustrations in each book.

Breater safety. Cutting the most out of your. Lathe —
Data on Spindle, Faceplace, and Spiral Turnings; etc. Drill Press — Laying out work; Routing, Shaping, drill sizes, speeds, etc. Circular Saw and Jointer — Ripping; Saw Projection; Cross-cutting; etc. Shaper—Adjustments, Guides, Patterns; Jigs, Fixtures; etc. Band Saw and Scroll Saw — Band Saw Blades; Ripping Curves; Tilt Table; etc. Abrasive Tools—Grinder, Buller, Belt Sander, Disk Sander, attachments, etc.

Group "A" Set of six books ....

Proctical Projects — What to Make and ow to Make It ... Material for many hours of enjoyment - most popular projects from Delta-

Craft publications. Nine books, as many as 41 projects in each. About 350 projects, at less than 1/40 apiece. Completely illustrated and described to make construction easy. Modern furniture, lamps, garden furniture, games, toys, etc. Sold only in combination with manuals above.

### The DELTAGRAM — the magazine for home craftsmen....

Six times during the year, this information-filled magazine brings a relcome reminder of your thoughdulness. Packed with plans, proj-ects, shop .dess, methods, news. Not included in combination of 17 books. Order expensisly.

. . . Every project, every idea has been worked out carefully in Delta's own shop. And the cost of the books is low. Your gifts of Delta-Craft books will be mailed postpaid with cards bearing your name. . . . So look over your gift list now, and check the home workshop fans. Fill out the coupon below, and send it with your check or money-order today. Don't forget to include a gift for yourself.

to fun, healthful recreation, and home beautification.


Designs . . . en Each Subject!

Projects arranged for quick reference. Hundreds of plans and pictures show "How to do it."

21 Lavely Lamps. Popular designs.

19 Cherming Chairs. Handsome, durable pieces, One Evening Projects, Dandy novelnes, quickly built. Gerden Furniture and Novelties. A swell collection. 40 Fine Tables. The finest of shop projects. Purniture Designs, Desks, beds, wardrobes, etc. Noveltses, Small items. Profitable, interesting. Toys, Games, Playground Equipment, Real money-makers. Small Furniture. Attractive footstools, magazine racks. magazine racks.


Group "B" Set of nine books......



GROUP "E" "New to Plan a Home Workshop".... Fifty-six pages, helpful, practical. Detailed. plans, pictures; guidance in selecting tools, building cabinets, etc. "Muking Money With Delta Tools"; What to make -- to make it - where to sell it, as full-time business or side-line. "Practical Finishing Methods": Scep-by-scep statruc-

tion on any type of housh for any material Staining, polishing, bleaching, varmishing, etc. 64 Duges. Order the

three books



6 big issues



Editor, Della-Craft Publications - The Della also, Co., 53374 to 755mile Act., Miles
I am enclosing check or money-order for
My Name to
Address.
City State State
Bend books to (name)
Address.
City parale sheet for additional orders

# For Men Who Really Know Pipes Koyalton OWNSMAN In the inner circles of pipe devotes quality ranks first - and she password is Royalton: For this superb pipe adds that extra nomething to make a good inbacco tusta better for fine craftmenship." If your dealer is short of Royaltons, pleasur remember that great numbers of these pipes? ere going to men in our fighting forces. WHEREVER BETTER PIPES ARE SOLD

### 28-45. Henry Lantacel & Thomas, Inc., Ocean Ph., M. Y.

# The Seabees Can Do It

(Continued from page 57)

smashed, the controls shot away. To anyone but a Seabee it was not worth scrap iron. A repair shop in the States would have asked two weeks to do the job, yet the Seabees had the shovel rebuilt and operating in two days.


Getting the most out of equipment is a Seabee hobby. On one spot near a Japanese air base, the Seabees built an airfield in record time. Carrying surfacing six miles to the runways, the dump trucks averaged 250 miles per day. Spark plugs were cleaned with blowtorches; air compressors were kept running 23 hours per day, and steam shovels, draglines, and caterpillars worked around the clock. The runway, 6,000 feet long, built across the island with a 16-foot cut through a granite ledge, was finished in 28 days. Ack-ack kept the Japanese dive bombers away until the job was done.

When Seabees were sent to Trinidad their equipment had to be shipped five times, on account of submarines, before it finally arrived. Private contractors were stymied; they said it would take 77 days to finish a job. The Scabees waded in, used their own material, and had the barracks and other buildings up in 27 days. In addition, they completed other unfinished jobs and, for good measure, built themselves a complete theater with stage settings, acenery, and "Earl Carroll" fittings. In another area, when refrigeration units failed to arrive, they improvised two Quonset huts into coolers and saved a huge shipment of fresh meat from spoiling.

Prior to America's entrance into the war, naval bases and other outpost defenses all over the world were being built, under the preparedness and lend-lease programs, by civilian contractors and technicians, and construction gangs composed of American skilled mechanics, electricians, carpenters, welders, plumbers, painters, masons, and engineers. As civilians, however, the workers were often hard to control, and after Pearl Harbor military authorities organized them into a new enlisted arm of Uncle Sam's defense forces.

Credit for the formation of these Construction Battalions, which are commanded by officers of the Navy Civil Engineer Corps, goes to Rear Admiral Moreell. The first regiment was authorized in December, 1941. In a three-week training schedule the recruits absorbed as much military knowledge as could be crammed into them between 6 a.m. and 9:30 p.m. by Marine top sergeants and Navy bosuns' mates and quarter-

(Continued on page 200)



# PROTECT YOUR PRECIOUS MOTOR

 Your automobile motor is precious. It must be watched, protected—its long life insured.

Watch the piston rings, especially. At the first sign of ring failure, install new rings—to save oil and gasoline, and to check cylinder wear.

If you have not seen your motor service man recently, you should do so immediately. He will set up a Protection Program, step by step. He will tell you which symptoms are dangerous, and recommend the remedy.

By this method you can insure the long and economical operation of your precious motor.

HASTINGS MANUFACTORING COMPANY HASTINGS, MICH. Hastings Mig. of Canada, Ltd., Toronto

It's a privilege to buy War Bonds



STEEL-VENT PISTON RINGS

Tough on oil-pumping. Gentle on cylinder walls



fighting men than the pictured scenes of the things he is fighting for . . . from the candles on the dining table, lighted to speed his return, to all the familiar memories of the country he calls home. Send him Pictures

### "Good Pictures"

This 36-page bookint is published by Argus to help solve the problems of exposures, lens, films, etc. Get your copy by sending 25c to Argus, Ann Arber, Michigan, Dept, S.





# Here's <u>already colored</u> wax in HARD-TO-GET COLORS



If you've got a nick or mor to cover in a table top ... or want to bring back the rich, mallow finish on an old piece of cherry, maple, or pine furniture ... or finish a repaired section to match older wood ... here's an assortment of colored waxes all ready to use.



Shinola Wax Shoe Polish in Tan, Brown, Oxblood, and Black, applied and finished as any other wax, is also grand for models, leather, lineleum, while Shinola Tan is swell for autos, Kemember too — Shinola is tops for shoes!

KEEP 'EM Shining With



10

The Best Feeds, I

# SHINOLA

IN ALL COLORS: TAN - BROWN - OXBLOOD - BLACK

# The Seabees Can Do It

(Continued from page 198)

masters. When the grind was over, they could handle all types of weapons from hand grenades to machine guns. Their job was to build—and having built, to be able to defend. They were ready for anything—salvaging ships or building airfields, sea ramps, docks, camps, jungle trails, and bridges, often doing it under fire and always doing it in a hell of a hurry.

The Seabees represent 60 different skilled trades. The poorest-paid Seabee gets \$54 monthly for home service, and \$64.80 overseas. A petty officer gets \$126 monthly at home and \$161 abroad. Fifty percent of the recruits are proving physically acceptable, and training at the \$20,000,000 Camp Endicott, in Rhode Island, does the rest.

Today the scrappy yellow-and-blue Seabee emblem—a bee with a spitting machine gun, a wrench, and a hammer clutched in its feet—is found wherever soldiers, sailors, and Marines are fighting. When the combat troops return home, Seabees will still be on the job, salvaging, building, and repairing the ravages of war. Where today they are building to win the war, tomorrow they will be building to win the peace.

# Letters About Auto Ailments Win Readers Cash Prizes

Atmost every conceivable auto allment from gremlins in the generator to mice on the motor was represented among the scores of entries submitted by readers in our recent contest on unique car troubles. Many of the letters revealed a skill at deductive trouble-shooting worthy of Gus Wilson at his keenest. Here is the list of the winners and their awards.

FIRST PRIZE, \$50 Claude W. LaRue, Chicago, Illinois

SECOND PRIZE, \$25 Clifford Younger, Glendale, California

Third to seventh prizes, \$10 apiece: Carl Wildey, Crown Point, Ind.; Norman Loeber, Van Nuys, Calif.; Lester Standley, Nichols, Conn.; Otto Gruenberger, Milwaukee, Wis.; and Thomas A. Faulkner, St. Paris, Ohio, Eighth to seventeenth prizes, \$5 apiece: D. G. Linton, Toronto, Can.; Lieut, William W. Nivin, Camp Davis, N. C.; Horton Hicka, Ophelm, Mont.; Eugene G. Glick, Akron, Ohio; Frank J. Meinen, Chippewa Falls, Wis.; Richard S. Bennion, Minneapolis, Minn.; Henry Clark, Jamaica, N. Y.; J. W. Grosdidier, San Diego, Calif.; Lynn C. Watson, Birmingham, Ala.; and Raymond A. Klemmer, Twisp, Wash,

# WARTIME ANNOUNCEMENT!

Revolutionary RADIONICS Product of Great Importance

For All Hard of Hearing - their Friends and Families



\$40°

READY TO WEAR
COMPLETE

-WITH RADIONIC TUBES
-CRYSTAL MICROPHONE
AND BATTERIES

. . . Liberal Guarantee

¥

TO PHYSICIANS: A detailed scientific description will be sent upon request Further rechnical details with appear in medical journals.

There are cases in which deficient hearing it caused by a progressive disease and any hearing aid may do harm be giving a false same of security. Therefore we recommend that you cannot your molegist or ear doctor to make sure that your braving deficiency to the type that can be benefited by the use of a heating aid.

7

The Zenith Hearing And can be implicationly by your Zenith franchined Optician or Optionatrist (no home calls or inlicitations).

# Zenith Radio Corporation

E & MCDOMALS.JR.

To: Manpower Authorities, Employers, Physicians, Parents, Teachers and Hard of Hearing

Our country's manpower crisis calls for everyone's maximum efficiency Since I just the hearing of one ear in an accident twenty years ago I have been acutely conscious of the handicaps of the hard of hearing While pioneering in radio I have for some years directed Zenith's research toward development of the best weerable hearing aid that science could produce

My awa company has apent millions the radio industry tens of millions for research. This research has been paid for by scores of millions of purchasers of radio sets.

with this technical knowledge and engineering skill now bring to the bard of hearing a new precision and — the ZENITH RADIONIC an instrument of the highest quality

A hearing aid is essentially a part of a radio receiver—It wires the husan body for sound. It is composed of a crystal appropriate and parts of a radio receiver set reduced to miniature size and manufactured with watch-like precision. For samy years it has seemed to se incredible that the public could bey a complete radio receiver for \$29 or less with which they could hear the words whispered in Europe, Asia, or South America, but people with deficient hearing have paid \$100 to \$200 for a comparably good hearing aid to hear the husan voice across the room

Zenith's facilities and sethods for precision wass production of radio sets, Radionic devices, etc., enable it to bring this superb hearing aid within the teach of ail.

Eye-glazzes like bearing hids today, were once the laxury of the few What the optical companies have done to make the finest apectacles available to everybody at low cost. Zenith is now prepared to do for the hard of hearing — to bring with the aid of modern radionic science a highly perfected hearing aid within the reach of the masses.

ZENITH RADIONIC — low cost buttery upkeep searable hearing and — complete with miniature radio tubes, crystal microphone and butteries — will sent for \$40 — about one-quarter of the price of the better vacuum tube instruments of today, Hereafter no one child or adult need be without a hearing aid because it is too high-priced. There are ten ptilion people of whom over three million are children in our achools, who are hard of hearing

Even if Zenith never makes a dollar at this low price, it is willing to take its pay in the good will of the hard of hearing, their families and their friends. Thus begins a revolution in hearing side --- a revolution to "lower the cost of hearing" within the reach of all

6. F. Olc Donaly S.

President, Zealth Radio Corporation

Write for Fros Descriptive Booklet
ADDRESS DEPT. PS-1, HEARING AID DIVISION
ZENITH RADIO CORPORATION • CHICAGO 39, ILLINOIS



# MAKE THIS A NORTHLAND

Christmas!



- The Let Northland skip help you make this a brighter, happier Christmas . . . a Christmas to remember! They're the overwhelming choice of champions, so whether you're giving or receiving, make sure your choice is Northlands!
- T SEND IO: FOR THE NORTHLAND SKI MANUAL 48 pages , , 62 how-to-do-it illustrations . . . edited by Hannes Schneider . crammed with ski knowledge. Or write for FREE folder, "HOW TO SKL" This offer not good in Canada.

# NORTHLAND SKI MFG. CO.

94 MÉRRIAM PARK, ST. PAUL 4, MINNÉSOTA

★ ★ "The World's Longest Ski Menufocturers" ★ ★



# Electricity for Any Job—Anywhere

ONAN GASOLINE DRIVEN ELECTRIC PLANTS provide electricity in locations where it is not otherwise available, and for amergency and standby service. Thousands doing a winning job in the

> 5 zes from 330 to 33,000 worts, A.C. 50 to 800 cycles, 110 to 660 volts. D.C. 4 to 4000 valts. Also dust A.C. and D.C. ovipul models. Details gladly furnished.

> > D. W. ONAN & SONS

1811 Royalston Ave.,

Minnespolis, Minn.



# ORISTS Wanted

Will you permit us to send you at our risk the Vacu-matic, a device which autoowners everywhere are praising? Install it on your ear. Test it at our risk Unless it trims deliars of your gas hals by saving up to \$2.7 or gasoline consumption, gives more power, quicker pickup and faster acceleration, the test will cost you nothing. Automatic Supercharge Principle

Vacu-matic is entirely different! It operates on the supercharge principle by automatically add-ing a charge of extra organ, drawn free from the outer are into the heart of the gas mixture. It is attraly astronatic and allows the mutor to "breethe" at the correct time opening and closing as required flares up to 10% on gas costs with better meter performance.

Constructed of six parts fined into a single out; adjusted and making at the factory. Ecouy and guick y too telled by any the factory Easily and AGENTS 25 FME FOR INTRODUCING. HERE'S & at should apport by for unquite the feet of the control of the factory of the and protes. Every car, truck tractor owner a prospect. Send name and a ideas row for this more yet aking offer and he wyon can get your Free. The Vecu-matic Co., 7617-880 W. State Street, Warmstone, Wis,

# 1 1 0 - V Q L T S

from DIRECT CURRENT



KATO ENGINEERING CO., 100 Eim St., MANRATO MINN USA





Surpos's Seed Catalog Free-Flowers and Vegetables for your Victory Garden. W. ATLEE SURPEE CO. Hadelphin 32, Pa. or Cliet

to he cure, beatsen, worn spore in thes. m mende shore, reinquets, boots-any-

Sond for

MEND the HOLE for

ST HARDWARD TO So-Lo : 1 to 1 total




a Learn the practical way, by daing, of our of the country's Roget hade schools. Fully equipped to train you to puse toute by probleble war plant john.

A NON PROFIT INSTITUTION backed by a long time leader in the welding field. Individual booths, machines and instruction, Costs you only for materials used, Train

now for this highly emential war work and a promising luture,

Complete HOBART BROTHERS COMPANY TROT, OHIO( Sex P-141 " One Largest Builders of Equipment

# there's a Real Story is the basically improved design of the



# 

Despite its unusually low price, this heavy DURO 16-inch production Metal Cutting Band Saw has many special features not found in machines costing several times as much. It is ideal for cutting tubing, extruded shapes, bar stocks, metal sheets, casting gates, plastics, brake linings, hard rubber, slate, fibre and many other materials. Can be adjusted to obtain standard wood curting speeds by a flip of a lever. Some of its special features include: Heavy machined cast iron trunmon, special roller blade guides which reduce blade crystallization and lessen blade breakage; new design which permits all adjustments to be made from front while saw is in operation; New Departure Ball Bearings; machined dove-tailed ways with adjustable steel gibs; many other advantages. Metal cutting speeds: 236 and 596 R.P.M. Wood-cutting speeds: 2360 and 5960 R.P.M. Available on priorities only.

Send for New DURO Catalog

For full details and prices on the DURO 16" Metal Cutting Band Saw send for latest DURO CATALOG using coupon below, Also lists specifications and prices of complete line of DURO single and multi-spindle Drill Presses, Circular Sawa, Jointers, Routers, Shapers, Grinders, Lathes, Scroll Sawa, Flexible Shaft Units and Portable Electric Drills.

# URO TOOKS

MACHINE DIVISION

ALSO MAKERS OF BUBBO HAND TOOLS

### THE DURG METAL PRODUCTS COMPANY 2649 H. Kildaro Avp., Chicago, Illinois

Centlemen Please send me FREE copy of Intest DURO totalog giving full specifications on new DURO 10' Metal Cutting Band Saw and other DURO Machine Tools

Name

Zone No. . . . . State. . .

## YOU CAN EASILY MAKE

Telescopes—Magnifiers—Photographic Gadgets and HUNDREDS of EXPERIMENTS with

# COST LENSES

Big 10 Page Project and Idea Booklet with all sets describes successful developments points the way to new experiments.

ALL LENSES NEW, finely ground and polished, edgas vary slightly chipped-A SALVAGE BARGAIN!

Set No. 301-N "Our Adverticing Special" 18 Lennes for \$1.60 Postpaid. For making your own powerful TELE-SCOPES, strong magnifiers, photo cells, rifle acope, telephoto lens. DUMMY CAMERA Kodachrome viewer. storeoscopic viewer ground g sea and enlarging focusing aids For experimental optics, copying, ultra close-up shots detachable Reflex View Pipder for 35 mm Camers. and many other uses.

Set No. 305-N "The Gadgetser's Delight" 35 Leases above set plus twenty more expensive lenses increasing your fie d of experiment and gadget making Ad our lenses are neatly packed and marked.

Set No. 210-N "The Experimenter's Dream" 60 Lenson and New Complete 60 Page Societ-510 Postpaid. Contains all the lenses in the above sets p.us 25 others that makes this sensational buy The variety of lenses in this set will anable you to conduct count eas experi-ments and build a wide variety of optical equipment.

### JUST COMPLETED:

50 Page Illustrated Idea Backlet "Fun With Chipped Edge Loncos" Only \$1.00. This beaklet with Lone Set makes a unique gift for the experimentar.

PRISMS: \$1.00—\$1.35—\$2.25 Set of 3 of the above sizes complete \$4,50 Limited Number! Hurry!

EDMUND SALVAGE CO.

27 W. Cliston Ave., P. O. Anduber, N. J.



Weldwood Glue.

Mixed just by adding tap warer, it can be used at once, sets fast (jobs can be lightworked in a few hours) and it makes a permanent bond. Your hardware store or lumber dealer has handy packages of Weldwood Glue in 10c, 25c, 50c and 85c (1 lb.) sizes. Get a can today or send 250 and your dealer's name for a mal 31/2 oz. sample.

# Has Everything!

l. Tremendous Strength. 2. Waterproof, Becterus and Rot Proof. 3. Quick and easy to use. No heating Nowaiting. 4. Economical 6. Applied cold, quick serving 6. Stain-Free. Supply lemeted the to Uncle Sam's war pords.

UNITED STATES PLYWOOD CORPORATION (Weldwood Gine Dept. 12) 103 Park Ave., N.Y. 17, N.Y.


"Makes the pine line the SAFETY line"
















Air leaks . . . below or above the furnace, or in the flue . . . are a frequent cause of fuel waste.

Stop these leaks . . . reduce your fuel bills . . . help to conserve fuel . . . by one application of SMOOTH-ON . . . easily and quickly, without dismantling any parts. The expansive property of SMOOTH-ON tightly fills all openings and makes an iron-hard seal which is not loosened by expansion or contraction

SMOOTH-ON is equally effective for stopping leaks of steam, water or air due to cracks in boilers, heaters, pumps or piping . . . makes low-cost lasting repairs of equipment that you cannot replace because of war-time conditions.

This many-purpose from repair cement also stops leaks in automobile radiators or engine cylinders, and tightens doose fixtures tool handles and hardware. Be sure to buy a can today and be prepared for repair emergencies.

Buy Smooth-On No. 1 in 104 On., 7-on., 1 lb. and larger containers from your dealer or if necessary from us. For your protection, insist on Smooth-On, used by prolessional repair men since 2893

# FREE BOOK

Get your copy of our latest 40 page illustrated handback. Shows how to make repairs quickly, urseemitedly. Just send the couper.

Smooth-On Manufacturing Co., Dept. 58 579 Communipow Ave., Jersey City 4, N.J. Please send the FREE Smooth-On Handbook

Nume

Address

1-44

# Doit with SMOOTH-ON

# Germany's "Fortress Europe"

(Continued from page 53)

they set in uniform rows; they pock the hills and stud the woodlands, four deep here, 10 deep a mile away. Scattered about them are rifle pits, machine-gun nests, and mortar emplacements. And, ever and always, there is the mobile artillery.

Beyond the first line is another span of open country whose every stream bank, hillside, and wooded knoll spouts death, for here again the mobile defense has taken a stand. Here, too, the tank battalions get in their body blooms.

in their body blows.

And now comes the second line, which is an even heavier edition of the first. There are more and stronger tank barriers. More tank traps. More emplacements and heavier guns. More blockhouses, more bunkers. And still heavier artillery. The path through the second line will have to be blasted virtually a yard at a time.

Again that deceptive open country. And,

finally the third and last line.

Here are the massive emplacements, the many-storied individual fortresses, the heaviest artillery, the final word in tank traps and barriers. No shallow ditches here, that merely delay tanks; instead, there are manmade canyons, some of them a hundred yards across, some filled with water like medieval moats, others fitted with nozzles which can cover their floors with flaming oil,

And here are mine fields, building up from the small Tellers to supercharges which can rip the earth like heavy artillery fire. On the heights are massed antiaircraft weapons which can be lowered to deliver awesome waves of devastating fire at ground level. Here, no doubt, are the rocket guns with which the Nazis, like all the other belligerents, have been experimenting—weapons capable of great mobility and frightful destruction.

Place this third line on the defensive side of a river and you have a position that must be hammered into dust before the invaders can get through. And remember that the lines of the Inner Fortress follow the rivers. Along these river valleys are rail lines on which the heaviest weapons of mobile defense can be quickly moved. Some of those lines lead directly into the minor fortresses; some lie just behind, where the big guns can pour their fire over embankments and onto the invader. These big guns include weapons that recall the Big Berthas of World War I. Such guns have been captured on the Russian front,

At this point the attackers may face (Continued on page 206)



# SPLIT-HAIR PRECISION FOR SPLIT-SECOND SHOOTING

When a Tiger Tank is on the rampage and the next shot has to be on the button "or else," there's no time to fiddle with faulty equipment. It bas to be right!

That's why, in thousands of war plants, and in the mobile machine shops of our armed forces, Atlas machine tool precision has won the healthy respect of the men who make and repair our weapons.

Under grueling production schedules Atlas Drill Presses, for example, have drilled and tapped literally billions of holes with an accuracy that is reflected with deadly effect on the battlefield.

For faster production . . . for precision . . . for low cost, Atlas machine tools are making a name for themselves under toughest conditions. Remember Atlas for the time when shop equipment will again be available for nonwar use — for you.



# LAS PRESS CO

KALAMAZOO 13D, MICHIGAN





MILLING MACHINES



SHAPERS





No. GT121—This wotch can go places—stardy, anti-magnetic, precision lested, 15-jewels. Has rad um dial and hands, non-breakable crystal, waterproof strap, sweep second hand and stainless steel back. SHOCK-RESISTANT. #39.75

No. GT328 — Same, 17 jewel, SELF WINDING, SHOCKPROOF

\*59.75

Attractively Boxed Frices include Federal Tox. Postage Prepaid
Write for Free Silustrated Booklet 'GT MAIL ORDERS PROMPTLY FILLED

# BELL WATCH COMPANY

Time and Life Bldg., Rockefeller Center, New York, 29, M. T.

# MOTIO TAPE

# AND THE COLD

New pliable plastic stops leaks, saves fuel. Weatherstrips windows, doors, baseboards caulks casements; makes packing, gaskets.

EASY TO APPLY
Unrolls like ribbon. Just press
into place and it stays put. Does
not erack, chip, dry out or shrink.

About 80 ft. to a roll. At stores or \$1.25 prepaid (\$1.40 west of Rockres).





# STOPS THAT DRIP

A sure cure for condensation drip from tanks, pipes, walls, ceilings, etc. Apply with brush, trowel or spray. At stores or \$1.90 for 1 gal, prepaid (\$2.10 west of Rockies). Free Circular.

J. W. MORTELL CO.

534 Borch St. Washin

# Germany's "Fortress Europe"

(Continued from page 204)

gas—the weapon of ultimate desperation. The invaders, however, will not only have defenses against it; they will be able to return it, and with compound interest.


There will be cities along the way, perhaps in the Fortress line itself; and in today's war the city is a strong point, even a key defense position. The Russians proved that even a city battered to rubble is still not a city captured. In these cities there will be blockhouses and casemates commanding all approaches. Under the streets will be a maze of tunnels and areaways, and set in the pavements will be turtleback turrets with heavy guns. In the lower floors of many buildings will be bunkers, walled with steel and concrete. The buildings may be blown to bits, but the bunkers will still stand, reinforced rather than weakened by the mountains of rubble around them.

This, then, is the path to victory—a road leading from the beaches to and through the fortifications and into the Inner Fortress. Every bombing of Germany's industrial and munitions centers softens it to some degree, for no fortress stands independent of the men and materials behind it. When the big "push" comes, the Fortress walls themselves will quiver under our air attack. But the final, victorious attack must be made on the ground. A road must be blasted and hacked through the enemy's jungle of guns, tanks, and blockhouses, and fighting men must go in and conquer. How it will be done is another story that cannot be told until the Fortress falls. But we do know the magnitude of the job, and we know that it can be done, and will be done.

# Ground Garnets in Plastic Give Nonskid Deck Coating

A viscous plastic fluid, containing ground garnets and capable of being applied to surfaces with a spray gun, has been developed by the Goodyear Research Laboratory, at Akron, Ohio, as a nonskid coating for the decks of our battleships. After being applied, the fluid dries in a few hours to form a fire-resistant layer about 10 times as thick as two or three coats of paint. It adheres well to steel, concrete, or wooden surfaces, and has proved especially successful in providing a sure footing in the areas around a ship's big guns. It is also said to resist the corrosive action of oil and sait as well as washing materials.









Indicator

penell multiplying, proportions dension, extracting roots, etc. Accurate, white composition face. Has standard A. B. C. B. Cl and K scales.

For complete outfit including slide rule 28 page disatrated instruct on both carrying rase send 50c (60c Foreign New "TRIO" 10" Slide Rule, with same all acades as above plus 5 i. and T scales on Reverse of Slide for problems in Trigonometry Outfine all Final Indicator complete instructions \$1.00 May reposited Satisfaction Carrenteed or money rejunded Fee Special Combination (Mer.) Order NOW.

REWIG CO., Box T-143, Crand Central Annex; New York City



from light socker You is bad a thousand uses for the welder around your have garage we have the first a proper of the property of a target property of a target property of a target property of a target property of the prop

# EPSI- OLA HITS THE SPOT

# any days I \$ earn as much as

"I bowl a hary Man Fire actions are and Mary on a least as a Mary on a least as a least as a least a l ha & O. . . . J. H. K. logg W. I. far a . . . . Lie t the 1 Dat September a 1 c 2 2 2 have field 2 of Many We top on a great a keep and a keep a keep a keep a keep and a keep a kee

There are bredreds f to the parties of the to be an executive for the form of the first t

make up to \$2 or \$3 an hour A3; hand aswa, also band and circular saws can be filed. No eye-strain, no experience needed with the FOLEY AUTOMATIC SAW FILER.

mear so much lancer and better with the Foley

FREE PLAN shows how to start this steady can't business now during was time and he ready for the big peace time building boom that is sure to come later. No special prior ty aupit cation required delivery guaranteed, Send coupon today no salesman will call


# FOLEY MANUFACTURING

119-6 Folly Bidg., Minneapolis 13, Minn. Please send PREE PLAN on saw Sing business.

Norme .

Address .





13 accurate model of the famous PT Complete kit includes all littings — Only \$5.

GET THIS SOOK — the only one of its kind. Full of detailed drawings and photographs with instructions for building and rigging thip models. SHIP MODELS ILLUSTRATED

postpord for only \$2.

MARINE WODEL CO., Dopt. P-3, 28 W. 18th St., N.Y.C

Local "Store Route" Plan pays men like you his musey—steady -in wholesale business of your own by cut necessary Rell Visamins to stores of all heads. New low retail price 7 for 15c, opens rust rath field Handle this suitamaker plus 200 other duck profit Items. Many ha loomly advertised No experience needed. Amazing facts PRES. Write TODAY


WORLD'S PRODUCTS CO.

Dept. 83-N



With Our six in. tool steel custors Make mouldings casings drop-leaf tables, grooves heading a joining 1"wide \$1.50 115" \$1.75 Postpaid State size hale, List & folder free-

John A. Sandstrom, Box 517, Stow, H. Y.



# GENERATOR


Por Light or Reavy Work. 30-200 emperes. Complete PLANS 35c Send today and we is include PREE our RIG Cats of LEJAY 800g. Co., 1323 Lejay 800g., Minocopolis, Mion.



# New Designs In

edermize Year Gus! Improve Your Soors! Most durable grips made. Positively unbreakable! For Colt, Smith & Wasson, El-Standard. Origies, Luger & Mausers to a wide choice of beautiful designs in lvory, pearl, walnut, myz, etc. Low prices, CATALOG. Dealers Wanted,

SPORTS, INC. (Mirs.) 2850 % Clark SL, Dout S-1, Chicars, III.



Buy War Savings Bonds and Stamps regularly.

This One RTCD-GGW-OGJH



Refusing smokes and chacolate bars, Trading botteries from the tars, This chieftain made them wonder why, But now they see he's a clever guy.



The garagest You can't buy them as before When it's over there'll be more

### ENGINES IN STOCK



The G. H. Q. ministure gasoline engine that really operates is still available. Over 18,000 sold in the last year, 1/5 H.P. Complete with flywheel and propeller, fuel, 15 accessories and full instructions. Fully bench tested and ready to run. For boats, planes, midget cars, etc. Send only \$1,00-Shipped Collect C.O.D. same day. Send 25c for Catalog of hundreds of hobby Items.

2HQ MOTORS, Dept. SV, 46 East 21 St., New York 18, N. Y

WRITE FOR FOLDER CHICAGO SI, ILL.



Uses Power Take-off any trac-tor. Direct drive. Long stroke. Saws fast. Write for FREE Essy on fuel. Thousands of satisfied users. Dig labor saver. Low in Price. OTTAWA MFG. CO., D101 Forest Ave., OTTAWA, KARSAS

OUR TOOL DATA SHEETS

J. H. WILLIAMS & CO., BUFFALO, N. Y.



Screw

Driver Number 130A

BY "YANKEE" TOOLS

Time saved in the Battle of Production shortens the days to Victory . . . and "Yankee" Fine Mechanics' Tools save time. A minute here and a half-minute there seem unimportant in themselves. Multiplied by the thousands of "Yankee" Tools in service, they total hundreds of man-hours. . . . For nearly half a century, "Yankee" on tools has been the mark of ingenious and dependable performance-of faster and easier work on countless jobs. Safeguard your "Yankee" Tools. They are weapons of war and must be treated right. And when they again become tools of peace, you will find them immediately useful for your post-war needs.

# "YANKEE" TOOLS

make good mechanics better North Bros. Mfg. Co., Phila. 33, U.S.A. Established 1880

Makers, also, of "Yankee-Handyman" Tools

# DRILL PRESS OWNERS!

HERE'S 1 TOOL WITH 5 DISTINCT USES

THE BARRON MULTI-PURPOSE ROTARY WOOD PLANER

PLANES & SURFACES - PANELS & BEADS ROUTE & ERCOVES . RANBETS . TENONS

Converts ANY drill press in-to a time saving, lew cost planer, paneter, tenoner, etc. Surface finishes paneler, benoner, etc. Surface linishes all types of tough grained and knotty surfaces to agate smoothness, Safel Quaranteed harmiess to drill press. Thousands now in use. SOLD ON MONEY BACK QUARANTEE. Full refund on S day trial. Shipped prepaid on receipt of \$7.50—or C.O.D. YOU BIEN NOTHING, Free literature.

BARRON TOOL CO., INC. 370 Architects Ging., Detroit 1, Mich. STEEL TOP AUXILIARY DRILL PRESS TABLE

Has 200 eq. in. assorth working surface. Equipped for shaper and many other important workshap



### FOR SKIING ... AND AFTER

Uncle Sam permits the manufacture of some Base Ski Boote. So take a look for your pair. Good Skiing still Begins with Good Bass Bootal As for war-scarce Weelung, they're worth waiting for if you can't find them now!



# FREE BOOKLET

Write today for illustrated booklet of available Base Outdoor Footwear for men and women.

G. H. BASS & COMPANY 41 Main Street, Wilton, Maine




# WITTEENGINE

A REAL Money Maker

for farm or factory. Uses cheap liquid fuels. Pays for itself out of savings.





MAKE MONEY

Start a wood sawing business — turn

spare timber into cash. Factory prices; cash or terms; FREE Catalog.

WITTE ENGINE WORKS 1600 Oakland Ave. KANSAS CITY 3, MO.



### WORLD'S LOWEST PRICED ADDING MACHIN Vest Pocket Size FREE TRIAL

IDEAL XMAS GIFT. GUARANTEED AC-ONLY \$250 CURATE. Not a toy. Operates with only ONLY \$250 a finger flick. Adds. subtracts. multiplies, divides. Counts up to ten military flows for theelf over and over. SEND NO HIGHLAND ACCOUNTS THE MONEY SEND NO HIGHLAND ACCOUNTS THE MONEY SEND NO HIGHLAND THE SEND NO HIGHLAND NO HIGHLAND THE SEND NO HIGHLAND NO HIGHLAND THE SEND NO HIGHLAND NO HIGHLAND NO HIGHLAND NO HIGHLAND THE SEND NO HIGHLAND NO H

CALCULATOR MACHINE COMPANY (Mfrs.)

DEPT. 438, P. O. BOX 1118

CHICAGO, ILLINOIS

Buy War Savings Bonds and Stamps regularly.

# STEAM MARINE ENGINE



A precision built and engineered single cylinder model angine. Reverse or clutch gear. Automatic oil and water pumps. Scale %" to 1". 11%" x 6%" (not a toy). A counterpart of and oper-

stes at pressures comparable to Modern Marine Construction,

Sand \$2.50 for 11 pages scale drawings,

including baller layout and actual photographs, or 250 - 2 views. including holler, etc. Available rough casting kits, \$12.50, or somi-finished casting kits, \$22.50. Limited number completed and shop tested engines (less -control valves), \$58.50 - order today, STATIONARY ENGINE plans and specifications, \$2.50. Write Model Division, 202 No. Division Ave.

The THOMPSON ENGINEERING CO., Grand Rapids 2, Mich.

# GLIDER BLUEPRINTS



1. UTILITY TRAINER—2 PLACE, 2. PRE-FLIGHT TRAINER. 2. PRIMARY GLIDER. 4. HIGH PER-FORMANCE SOARING GLIDER. Engineered, corries CAA, NR license. Reasonable. Write for free 3-view prints.

CALIFORNIA AERO GLIDER CO., INC. PS-J, 1820 W. 62nd St., Los Angeles 44, Calif.

Amazing BOOK for You

Hardd Hunt wants to send you his hig re-vised No. 14 Catalog. 124 pages of woods to working ideas, 12 pages of rare woods to seduced rulers. UNEASTALER BARGAINS in tomorisal and American woods, supplies, 2-and only 10s to cover pendage and handling.

CRAFTSMAN WOOD SERVICE CO.





### Railroads-Aircraft-Racers MODEL Ship Models-Shap Practice

Devoted to model building, operating, racing exclusively? Numerous construction projects for advanced or beginner. Profusely illustrated, detailed building plane, if sold out at news-dealer or behilf shop, easily publishers.

# for only

MODEL CRAFTEMAN (Dept.P) Tamery, M.J.

# 6 of Burpee's Best-Carret. 5 PACKE Lattuce, Boot, Radish and S Tomato-4 10c-Pkt, of seeds 2) of each, all 5 postpaid for just 10c-send dime today! Burper's Seed Catalog Free.

PHILADELPHIA 32, PA. OF CLINTON, IOWA



HAND MADE, Very best, Lowest prices, Buy direct from Factory and save money, Send name and address for FREE catalog.

17ALIA & P. SOPRANI ACC. MFG. CO.



KLUSTRATED COMIC BOOKLETS for adults (vest pocket size). The kind you like! ] 0 different booklets sent for 50cor 25 assorted for \$1. Shipped prepaid in plain wrapper. No C.O.D. orders. Send Cash, Stamps or Money Order. GRAYNO, Dept. A-121, Box 520, G.P.O., New York.

Often associated with Hardening of the Arteries, a Stroke, Paralysis, Heart Trouble, Kidney Disease, and other grave complications. Resultful treating methods of the Ball Clinic have proven dependable for nearly a quarter of a century. Send for FREE Blood Pressure Book today. No obligation.

BALL CLINIC, Dept. 5160, Excelsior Springs, Mo.

Copylinghead Insulatival

STANDARD BRANDS

Luckies - Chesterfields Camels - Philip Morris Old Golds - Dunhills Pall Mall - Tareyton Kool - Raleigh - Fatima Viceroy - Sheffields Regent - Fleetwood



### PERFECT ARRIVAL GUARANTEED!

Minimum 3 Cartons

Include Postage as follows within 150 miles: · For 3 Cartons, 11c · Add 1c for each additional carton over first 3 Distant orders require extra postage.

SHIPPED SAME DAY ON RECEIPT OF CHECK OR MONEY ORDER

Thousands of satisfied Customers. This is our 24th year in Business.

COMPLETE PRICE FOR

City. Dept. S. 14 Journal Square, Jersey

# SPOTTER **TELESCOPE**



### 20 DAY FREE TRIAL

Ideal for spotting planes, ships triles away. People 500 yards away appear as 100 yards distant 5 miles appear as 1 mile, aPOTTELL YELESCOPE has accentifically ground lens, plastic eye pieces, new-type composition tubes and guaranteed for real performance. Lasy to focus on both moving and antionary objects. 20-DAY FREE TRIAL. Try for 20 days at our right Beturn if not completely satisfied. SEND NO MONEY. Just pay postman \$1.35 plan few cents postate on delivery. Cash orders sent postpoid! Don't woit—production of telescopes may be curtailed as it has been on binoculars. AMERICAN TELESCOPE CO., 7755 2, Haleted, Copt. 5-120, CMCCAGO.

### A HARLEY-DAVIDSON for Me After Victory!

Buy War Bonds NOW -- and own a new Harley-Duvidson after Victory! Two E thrill to greater performance than ever, made possible by the povere tests of exp-time action! Write today for FREE copy of "Enthusiast" magazine filled with autoropule pictures and staries.



14 - 32

3/12

HARLEY-DAYIDSON MOTOR SO., Dept. PS, Milwanker, Wit.

# **Model Builders** 重 Attention! Hen

Thread

Thread Longth

Actual Size V-Plos

Weight, Gram: 31/2 Champion spark plugs for model gas engines give the same dependable performance as their larger counterparts. Sillment sealed. Sillimanite insulator. Alloy needlepoint electrodes for easy starting. One-piece construction,

36 ~ 24

332

14 ~ 32

952

SPARK PLUG COMPANY

JANUARY, 1944

TOLEDO, OHIO

Buy Was Savings Bonds and Stamps regularly.

ANYONE, ANYTIME CAN MAKE PHOTO-COPIES QUICKLY The most USEFUL copying method ever perfected PE-CO PHOTO-COPYER

The accuracy, ease and speed with which A.PE.CO photo-copies are made by anyone, are creating hundreds of new users. This modern, versatile, low-

cost method makes photo-exact copies of anything written, printed, drawn or photographed. Experience proves that A-PE-CO quickly pays for itself.

\$5500

### LEGALLY ACCEPTED PHOTO-COPIES OF


 Letters - Records - Blueprints - Shop Orders • Pictures • Receipts • Drawings • Documents

Same-size copies of anything up to 18" x 22". Eliminates errors. Saves steno-copying, tracing, proofreading. No camera, focusing, film or moving parts. Any employee quickly becomes expert. Lowest investment in equipment. Use on any desk or table. You need A-PE-CO. Let us show you how you can use it to expedite office and shop copying. Immediate delivery. See why thousands are in satisfactory use. Send for A-PE-CO folder-today.

AMERICAN PHOTOCOPY EQUIPMENT CO. 2840 No. Clark St. Dopt. HU-1 Chicago 14, Illinois Representatives in principal cities and Canada,

WITH WAR BONDS FIGHT

# FREE! LATEST, MOST COMPLETE RADIO PARTS CATALOG



It's the most complete, up-to-date BUYING GUIDE available! It consains latest "supply data" on radio and electronic parts available without priority for repair and replacement-plus everything in war training kits, books and equipment! Whatever you need-you'll save time by getting in touch with ALLIED first. Send for this bigfree catalog today.

# RADIO'S FINEST BOOK VALUES Specially prepared to aid radio training in schools

Radio Formules and Data Souk No. 37-752. , 10c Dictionary of Radio Terms No. 37-751...10c

and andustry. Full of valuable data. Send for all six?

Redio Circuit Handbook No. 37-753. . 10c Radio Builders' Handhook No. 37-750. . 10c Simplified Radio Servicing No. 37-755., 10c

Redio Date Hendback No. 37-754. . 25c All Six Books No. 37-799...75c

ALLIED RADIO CORP. 833 W. Jackson, Dept. 7-A-4, Chicago 7

LIED RADIO



South Bend Engine Lathes and Toolroom Lathes are made in five sizes: 9", 10", 13", 14%", and 16" swings, with bed lengths from 3' to 12'. The Turret Lathes are made with 9" and 10" swings. They are fully illustrated and described in Catalog No, 100-C.

Post-war employment and prosperity depend upon quick resumption of normal peace time civilian activities, production, and services. To furnish lathes first to those who will be ready to use them (but cannot qualify for a war-time priority) South Bend Lathe Works now offers a practical post-war priority plan.

To take advantage of this plan, place an order now for the lather you want. No down payment, no deposit is required. Should conditions necessitate, you may cancel the order at any time. All we ask is that it be placed in good faith.

When your order is received, we will issue a numbered Post-war Priority Certificate. As soon as materials and manpower are released for civilian production, South Bend Lathes will be shipped in accordance with the Priority Certificates. Certificate holders will receive the first South Bend Lathes to be thus released, up to 80% of our production. The remaining 20% will be reserved for returning service men who may need lathes.

All standard South Bend Lathes, embodying the improvements developed in meeting exacting war production needs, will be available. No revolutionary models or design changes are to be expected. There will be no price increase—unless material or labor costs, or other conditions beyond our control, require it.

Here is a practical first step in putting your post-war plans into action. Send for Catalog No. 100-C and full information on this plan. Choose the lathes that meet your needs...place an order now, and be sure of earliest possible delivery.

Buy War Bonds New,... Save for Lathes



# SOUTH BEND LATHE WOR

SOUTH BEND 22, INDIANA

ATHE BUILDERS FOR 37 YEARS

POPULAR SCIENCE